



THE ENTERPRISE MIDDLEWARE SOLUTION

BEA eLink for Mainframe SNA

User Guide

BEA eLink for Mainframe SNA 3.1
Document Edition 3.1
June 1999

Copyright

Copyright © 1999 BEA Systems, Inc. All Rights Reserved.

Restricted Rights Legend

This software and documentation is subject to and made available only pursuant to the terms of the BEA Systems License Agreement and may be used or copied only in accordance with the terms of that agreement. It is against the law to copy the software except as specifically allowed in the agreement. This document may not, in whole or in part, be copied photocopied, reproduced, translated, or reduced to any electronic medium or machine readable form without prior consent, in writing, from BEA Systems, Inc.

Use, duplication or disclosure by the U.S. Government is subject to restrictions set forth in the BEA Systems License Agreement and in subparagraph (c)(1) of the Commercial Computer Software-Restricted Rights Clause at FAR 52.227-19; subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.227-7013, subparagraph (d) of the Commercial Computer Software--Licensing clause at NASA FAR supplement 16-52.227-86; or their equivalent.

Information in this document is subject to change without notice and does not represent a commitment on the part of BEA Systems. THE SOFTWARE AND DOCUMENTATION ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND INCLUDING WITHOUT LIMITATION, ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. FURTHER, BEA Systems DOES NOT WARRANT, GUARANTEE, OR MAKE ANY REPRESENTATIONS REGARDING THE USE, OR THE RESULTS OF THE USE, OF THE SOFTWARE OR WRITTEN MATERIAL IN TERMS OF CORRECTNESS, ACCURACY, RELIABILITY, OR OTHERWISE.

Trademarks or Service Marks

BEA and ObjectBroker are registered trademarks of BEA Systems, Inc. BEA Builder, BEA Connect, BEA eLink for Mainframe SNA, BEA Manager, BEA MessageQ, Jolt and M3 are trademarks of BEA Systems, Inc. TUXEDO is a registered trademark in the United States and other countries.

All other company names may be trademarks of the respective companies with which they are associated.

BEA® eLink™ for Mainframe SNA User Guide

Document Edition	Part Number	Date	Software Version
2.0	825-001001-001	July 1998	BEA Connect SNA 2.0
3.0	825-001001-002	April 1999	BEA eLink for Mainframe SNA 3.0
3.1	825-001001-003	June 1999	BEA eLink for Mainframe SNA 3.1

Contents

About This Information Center

Purpose	xvii
Scope	xvii
Who Should Read This Information	xviii
Administrators	xviii
Operators	xviii
Recommended Reading	xviii
How the Information Is Organized	xix
How to Use The Documentation	xix
Online Document Considerations	xx
Opening the information Center in a Web Browser	xx
Printing the PDF File	xx
Printing from a Web Browser	xx
Document Conventions	xxi
Related Documentation	xxii
BEA eLink SNA Documentation	xxii
Product Manuals	xxii
Other Publications	xxii
Contact Information	xxiii
Documentation Support	xxiii
Customer Support	xxiii
North American Support Center	xxiii
European Support Center	xxiv

1. Introducing the BEA eLink SNA System

Features	1-1
Functions	1-2
Supported TUXEDO Platforms	1-3
Supported Host Platforms	1-4

2. Understanding How the Software Works

Overview of Domain Gateways	2-1
The BEA eLink SNA Domain	2-3
The DMINIT and SNACRM Servers	2-5
Other Gateway Servers	2-7

3. Configuring the System

Local Domain Configuration	3-1
Edit the UBBCONFIG File	3-2
Edit the DMCONFIG File	3-2
Prerequisites	3-2
DM_LOCAL_DOMAINS Section	3-2
DM_REMOTE_DOMAINS Section	3-3
DM_SNADOM Section	3-3
DM_SNACRM Section	3-3
DM_SNASTACKS Section	3-4
DM_SNALINKS Section	3-6
DM_LOCAL_SERVICES Section	3-9
DM_REMOTE_SERVICES Section	3-10
Use the dmadm Command Interpreter	3-11
Configuring the DM_SNACRM Section	3-11
Configuring the DM_SNASTACKS Section	3-12
Configuring the DM_SNALINKS Section	3-12

Remote Host Domain Configuration	3-13
Establishing the VTAM Configuration	3-14
Configuring the CICS/ESA LU	3-14
Creating Connections at the Remote Host	3-14
Defining the Session at the Remote Host	3-15
View Connection and Session Status	3-15
Completing Cross-Platform Definitions	3-16
Setting Stack Traces	3-21

4. Verifying the Software

Overview	4-2
Building Your Verification Tests	4-2
Building TUXEDO Executables	4-3
Using the buildserver Utility	4-3
Using the buildclient Utility	4-4
Modifying the UBBCONFIG file	4-4
Enabling Transactional Services	4-4
Executing the tmlodacf Command	4-5
Modifying the DMCONFIG File	4-5
Executing the dmlodacf Command	4-7
Modifying the Environment Files	4-7
Building CICS/ESA Executables	4-10
Choosing the Source Code Language	4-10
Transferring the Source Code to Host	4-11
Translating CICS/ESA Verbs	4-11
Compiling the Translated Source File	4-13
Link-Editing the Compiled Source File	4-15
Configuring the CICS/ESA Application	4-17
Viewing Connection and Session Status	4-23
Running the Sample Application	4-23
Running the Application from a TUXEDO Client	4-24
Running the Application from a CICS/ESA Client	4-24
CICS/ESA Client with CPI-C	4-25
CICS/ESA Client with DPL	4-25

Running the Application from a CICS/VSE Client.....	4-26
CICS/VSE Sample Applications	4-26
Other Considerations	4-26

5. Administering the Application Domain

Administration Facilities	5-1
The dmadm Command Interpreter	5-2
The SNACRM and PU 2.1 Servers	5-3
Starting the PU2.1 Server.....	5-3
Starting the SNACRM	5-3
Using DMINIT	5-4
Specifying the SNACRM as a BEA TUXEDO Server	5-4
Enter the UBBCONFIG Parameters	5-4
Write the Script	5-5
The SNACRM Monitor.....	5-6
Prerequisite for Running the JSNACRM Utility on an NT Platform .	5-6
Running the Java Applet Version.....	5-7
Running the Java Application Version.....	5-11
Activating and De-Activating Links	5-11
Using the crmlkon Command	5-11
Using the crmlkoff Command.....	5-12
Security	5-13
Security Overview	5-13
Where You Specify Security Parameters	5-15
UBBCONFIG File Security Parameters	5-15
DMCONFIG File Security Parameters	5-16
Security Setting Summary.....	5-18
Security Setting Summary Tables	5-20
How To Administer Security.....	5-21
Adding a Userid and Password	5-22
Mapping a Userid	5-22
Removing a Userid's Mapping	5-23
Deleting a Userid and Password.....	5-23
Modifying a Password.....	5-24
Data Translations	5-25

Default Data Translation Rules	5-25
Strings and Numeric Data	5-26
Converting Numeric Data	5-27
Application-to-Host Communications	5-27
Buffers Going To The Remote Host Application	5-28
Buffers Coming From The Remote Host Application	5-30
Data Conversion For DPL Services	5-31
Programming Language String Transformation	5-33
Setting the Switch to Perform String Transformation	5-34
How the Switch Works	5-35
Example	5-36
Code Page Translation Tables	5-36
Specifying a Translation Table	5-37
How the Translation Tables Work	5-39
Example	5-39
General Usage Notes	5-40

6. Programming Considerations

Overview	6-1
APPC/IMS Programming	6-2
CICS/ISC Programming	6-4
About CICS/ISC	6-5
Multi-Region versus Multi-Processor Operations	6-5
ISC Operations	6-6
Asynchronous Processing	6-7
Function Request Shipping	6-7
Transaction Routing	6-7
Distributed Program Link	6-8
Step-by-Step Description: Generic DPL Transaction	6-9
Distributed Transaction Processing	6-10
Step-by-Step Description: Generic DTP Transaction	6-11
CICS/ESA Sync-Levels	6-12
Time-out and Error Handling	6-14

Application-to-Application Programming	6-14
Distributed Program Link (DPL)	6-15
Special Treatment of TRANSID for DPL	6-16
Specifying the Size of a DPL Commarea	6-23
DPL Examples	6-26
Step-by-Step Description: TUXEDO Client Request/Response to CICS/ESA DPL	6-29
Step-by-Step Description: TUXEDO Client Asynchronous Request/Response to CICS/ESA DPL	6-31
Step-by-Step Description: TUXEDO Client Asynchronous Request/Response with No Reply to CICS/ESA DPL	6-33
Step-by-Step Description: CICS/ESA DPL to TUXEDO Request/Response Server	6-35
Step-by-Step Description: CICS/ESA DPL to TUXEDO Request/Response Server, Service in Autonomous Transaction	6-37
Step-by-Step Description: TUXEDO Client Request/Response to CICS/ESA DPL, in Autonomous Transaction	6-39
Step-by-Step Description: Transactional TUXEDO Client Multiple Requests/Responses to CICS/ESA DPL	6-41
Step-by-Step Description: Transactional CICS/ESA DPL to TUXEDO Request/Response Server	6-43
Distributed Transaction Processing (DTP)	6-45
Step-by-Step Description: TUXEDO Client Request/Response to CICS/ESA DTP	6-47
Step-by-Step Description: TUXEDO Client Asynchronous Request/Response to CICS/ESA DTP	6-49
Step-by-Step Description: TUXEDO Client Asynchronous Request/Response with No Reply to CICS/ESA DTP	6-51
Step-by-Step Description: TUXEDO Conversational Client to CICS/ESA DTP, Server Gets Control	6-53
Step-by-Step Description: TUXEDO Conversational Client to CICS/ESA DTP, Client Sends/Receives Data	6-55
Step-by-Step Description: TUXEDO Conversational Client to CICS/ESA DTP, Client Grants Control	6-57
Step-by-Step Description: CICS/ESA DTP to TUXEDO Conversational Server, Client Retains Control	6-59

Step-by-Step Description: CICS/ESA DTP to TUXEDO Conversational Server, Client Relinquishes Control	6-61
Step-by-Step Description: Transactional TUXEDO Client Request/Response to CICS/ESA DTP	6-63
Step-by-Step Description: Transactional TUXEDO Conversational Client to CICS/ESA DTP, Server Gets Control	6-65
Step-by-Step Description: CICS/ESA DTP to Transactional TUXEDO Conversational Server, Host Client Relinquishes Control	6-67
CPI-C Programming	6-69
Step-by-Step Description: TUXEDO Client Request/Response to Host CPI-C	6-71
Step-by-Step Description: TUXEDO Client Asynchronous Request/Response to Host CPI-C	6-73
Step-by-Step Description: TUXEDO Client Asynchronous Request/Response to Host with No Reply	6-75
Step-by-Step Description: TUXEDO Conversational Client to Host CPI-C, Server Gets Control	6-77
Step-by-Step Description: TUXEDO Conversational Client to Host CPI-C, Client Retains Control	6-79
Step-by-Step Description: TUXEDO Conversational Client to Host CPI-C, Client Grants/Gets Control	6-81
Step-by-Step Description: Host CPI-C to TUXEDO Asynchronous Request/Response Server with No Reply	6-83
Step-by-Step Description: Host CPI-C to TUXEDO Server Request/Response	6-85
Step-by-Step Description: Host CPI-C to TUXEDO Conversational Service, Client Retains Control	6-87
Step-by-Step Description: TUXEDO Conversational Service, Client Grants Control	6-89
Step-by-Step Description: Transactional TUXEDO Client Request/Response to Host CPI-C	6-91
Step-by-Step Description: Transactional TUXEDO Conversational Client to Host CPI-C, Server Gets Control	6-93
Step-by-Step Description: Transactional Host CPI-C to TUXEDO Conversational Server, Client Grants Control	6-95
Where to Find Additional Information	6-96

A. Reference Pages

addumap	A-2
addusr	A-4
CRMLOGS	A-6
crmlkoff	A-8
crmlkon	A-10
delumap	A-12
delusr	A-14
DMADM	A-16
dmadmin	A-18
dmconfig	A-38
dmloadcf	A-68
dmunloadcf	A-72
GWADM	A-74
GWSNAX	A-77
modusr	A-80
SNACRM	A-82
xsnacrm	A-87

B. ATMI to CPI-C Function Mapping

C. CPI-C Parameters and Values

D. Error Messages

E. Sample VTAM Configurations

F. Code Page Translation Tables

Glossary

About This Information Center

Purpose

This center provides information about BEA eLink for Mainframe SNA, a BEA TUXEDO multi-domain connectivity product which enables client/server communications between OS390/CICS programs and BEA TUXEDO applications via a Systems Network Architecture (SNA) network.

Scope

This information center explains eLink SNA technical concepts and provides step-by-step procedures for:

- ◆ Installing and configuring eLink SNA platform software
- ◆ Administering the eLink SNA gateway
- ◆ Programming BEA TUXEDO applications for transactional conversations with IBM CICS programs.

Who Should Read This Information

The audience is primarily BEA TUXEDO System application administrators and operators.

Administrators

As the application administrator of a BEA TUXEDO System, you will configure eLink SNA using the DMCONFIG file and its associated *dm* commands. You must have sufficient SNA knowledge to configure the underlying SNA *Stack* so it conforms with definitions created in VTAM and CICS for each remote domain. This document provides information to help you understand the relationship between BEA TUXEDO system configuration settings and SNA-based application configuration concepts.

Successfully linking and establishing conversations between BEA TUXEDO system applications and SNA-based programs requires special coordination. The names and characteristics of SNA resources, configured in the SNA stack, must agree with resources and characteristics defined in VTAM and CICS. This guide includes examples of these relationships.

Typically, remote VTAM and CICS resources are defined by system personnel in a data center where IBM mainframes are located. Therefore, you need to request the remote names of eLink SNA and CICS resources from data center systems personnel and use those names to configure the local SNA stack.

Operators

As an operator of a BEA TUXEDO system, you will use existing skills with the BEA TUXEDO domain administration facility to modify SNA domain configurations and get information about the configuration and run-time environment.

Recommended Reading

You should read the BEA TUXEDO *Product Overview*. Additionally, you should have read and understand the BEA TUXEDO *Domain Guide* and the BEA TUXEDO *Application Development Guide*, which are essential to comprehending the material in this document.

How the Information Is Organized

The *BEA eLink for Mainframe SNA Information Center* is organized as follows:

- ◆ Chapter 1, “Introducing the BEA eLink SNA System”
- ◆ Chapter 2, “Understanding How the Software Works”
- ◆ Chapter 3, “Configuring the System”
- ◆ Chapter 4, “Verifying the Software”
- ◆ Chapter 5, “Administering the Application Domain”
- ◆ Chapter 6, “Programming Considerations”

In addition, the appendixes contain the following information:

- ◆ Appendix A, “Reference Pages” (formerly called man pages)
- ◆ Appendix B, “ATMI to CPI-C Function Mapping”
- ◆ Appendix C, “CPI-C Parameters and Values”
- ◆ Appendix D, “Error Messages”
- ◆ Appendix E, “Sample VTAM Configurations”
- ◆ Appendix F, “Code Page Translation Tables”
- ◆ Glossary

How to Use The Documentation

The Documentation CDROM, included in the package with your product software CDROM, contains both an HTML version of this guide and a PDF version. The HTML version should be viewed as an online browseable document. The PDF version should be used for printing.

Online Document Considerations

This guide is designed primarily as an online, hypertext guide. If you are reading it as a paper publication, to get full use from this guide you should install and access it as an online document. (Information on how to install the online documentation is available in the *BEA eLink for Mainframe SNA Release Notes*.)

Note: The online documentation requires a Web browser that supports HTML 3.0. Netscape Navigator 2.02 or Microsoft Internet Explorer 3.0 or later.

Opening the information Center in a Web Browser

To access the online version of this documentation, open the following HTML file in a Web browser:

`http://(directory path to eLink SNA HTML files)/index.htm`

Printing the PDF File

You must have the Adobe Acrobat Reader to view and print the PDF file. If you do not have this reader, you can obtain it free of charge from the Adobe Systems Incorporated homesite at www.adobe.com. (Please note that the BEA eLink for Mainframe SNA Information Center contains a hot link to this site.)

Printing from a Web Browser

You can print a hard-copy version of this document, one file at a time, from the Web browser. Before you print, make sure that the chapter or appendix you want is displayed and *selected* in your browser. (To select a file, click anywhere inside the frame you want to print. If your browser offers a Print Preview feature, you can use it to verify which file you are about to print.)

Document Conventions

The following documentation conventions are used throughout this manual:

Item	Convention	Example
Arguments	appear in brackets and are formatted in a lowercase monospace font. Optional arguments are formatted in italic font. Predefined arguments are formatted in an uppercase font. Vertical bars separate arguments from which you may choose only one.	<code>{name, 0, value}</code> <code>{ACCTID 2 5000}</code>
Environment variables	are formatted in an initial uppercase font enclosed in angle brackets.	<code><Envfile>=\${APPDIR}</code>
Literals and parameters	are formatted in a monospace font.	<code>class extendSample</code> and the <code>LOCALLU</code> parameter
Programs, applications, files, and subsystem names	are formatted with uppercase font in text, but are in monospace uppercase or lowercase in code examples.	Use the <code>DMCONFIG</code> file and the <code>CLASS LIBRARY</code> . An <code>aix.env</code> file example is included with your product software
User input	are formatted in a monospace font.	Type <code>cd TUXDIR</code>
Glossary terms	are formatted in italics in the printed copy. Online glossary terms are in italics, color, and may be underlined, depending on your browser settings.	<i>Server1</i> is the host name of a BEA eLink server. <i>Server1</i> is the host name of a Jolt server.

Related Documentation

BEA eLink SNA Documentation

The BEA eLink for Mainframe SNA documentation consists of the following items:

- ◆ *BEA eLink for Mainframe SNA Installation Guide*
- ◆ *BEA eLink for Mainframe SNA User Guide*
- ◆ *BEA eLink for Mainframe SNA 3.1 Release Notes*

Product Manuals

- ◆ *TUXEDO Product Overview*
- ◆ *TUXEDO /Domain Guide*
- ◆ *TUXEDO Application Development Guide*
- ◆ *TUXEDO System 6 Reference Manual*
- ◆ *TUXEDO System 6 Programmer's Guide, Volumes 1 and 2*

Other Publications

- ◆ *The TUXEDO System* (Andrade, Carges, Dwyer, Felts)
- ◆ *TUXEDO: An Open Approach to OLTP* (Primatesta)
- ◆ *Building Client/Server Applications Using TUXEDO* (Hall)

Contact Information

Documentation Support

If you have questions or comments on the documentation, you can contact the BEA Information Engineering Group by e-mail at **docsupport@beasys.com**. (For information on how to contact Customer Support, refer to the following section.)

Customer Support

If you have a question you cannot answer using this guide or the *BEA eLink SNA Release Notes*, you can contact BEA Customer Support.

When contacting technical support, be prepared to provide the following information:

- ◆ Your name, e-mail address, phone number, and fax number
- ◆ Your company name and company address
- ◆ Your machine type and authorization codes
- ◆ The name and version of the product you are using
- ◆ A description of the problem and the content of pertinent error messages

North American Support Center

In the USA, you can call Customer Support at **+1.888.BEA.SUPT (+1.888.232.7878)** or **408.570.8070** between 5:00am and 6:00pm Pacific time. Extended Support Customers may call anytime.

You may also send questions to Customer Support by fax to **+1.408.570.8071** or by e-mail to **support@beasys.com**.

European Support Center

In Paris, France, you can call Customer Support at **+08-0-09-05-565 (toll free)** or **+33-1-41-45-7090** Monday through Friday between 9:00am and 6:00pm GMT+1. Extended Support Customers may call anytime.

You may also send questions to Customer Support by fax to **+33-1-41-45-7009** or by e-mail to **support@beasys.fr**.

1 Introducing the BEA eLink SNA System

Features

BEA eLink for Mainframe SNA software provides a bidirectional link enabling BEA TUXEDO and IBM mainframe applications to interact as either a client or server, using a *Customer Information Control System/Extended System Architecture (CICS/ESA) Distributed Program Link (DPL)*, *Information Management System (IMS)* implicit *LU6.2*, or any IBM-supported *Application Program-to-Program Communication (APPC)* or CICS/ESA interface.

BEA eLink SNA version 3.1 offers significant enhancements to prior versions. In summary, these include:

- ◆ With the SNA link on/off function, you can now activate or deactivate SNA communication links
- ◆ With alternate code page translation tables, you have the ability to configure SNA communication links to operate in any of eight European languages plus U.S. English
- ◆ With a command-line switch, you can select improved C-to-COBOL string translation from five TUXEDO-to-host combinations
- ◆ With the improved error messages, you can resolve many problems more easily

Functions

BEA eLink for Mainframe SNA software performs the following functions:

- ◆ It supports the *Application-Transaction Monitor Interface (ATMI)* request/response model. Applications running in local TUXEDO System /T domains can request services in a remote domain. The remote domain is a MVS/CICS region. Applications in the remote domain can request services in a local TUXEDO System domain.
- ◆ It also supports the ATMI conversational model. Applications can establish a conversation between clients and servers in a TUXEDO System /T domain and an MVS/CICS region defined as a remote domain. Either side can initiate the conversation.
- ◆ It performs administration and configuration of a BEA eLink for Mainframe SNA gateway through the DMADM server and DMCONFIG server for a /SNA Domains instantiation.
- ◆ It supports the following typed buffers: FML, FML32, VIEW, VIEW32, X_COMMON, STRING, C_ARRAY, and X_OCTET. All buffer types except C_ARRAY and X_OCTET are converted automatically to and from EBCDIC between TUXEDO and CICS; C_ARRAY and X_OCTET are not converted.
- ◆ It maintains connectivity to multiple *System Network Architecture (SNA)* networks from the local TUXEDO System /T domain.
- ◆ It performs conversion between ASCII and EBCDIC encoding.

Supported TUXEDO Platforms

Table 1-1 lists UNIX-based platforms, NT Windows platforms, and corresponding SNA protocol Stacks supported by BEA eLink for Mainframe SNA 3.1.

Table 1-1 Supported TUXEDO Platforms

Operating System Version	Stack Version	TUXEDO Version	WebLogic Enterprise Version
AIX 5.0	IBM Comm Server 5.0	6.5	4.0
HP-UX 10.20	SNApplus2 V6.0	6.5	4.0
HP-UX 11.00	SNApplus2 V6.0	6.5	4.0
NT 4.0	IBM Comm Server 5.0 and 6.0 for Windows NT	6.5	4.0
Solaris 2.6	DCL SNAP-IX 6.0	6.5	4.0
Solaris 2.6	SUN Link 9.1 ¹	6.5	4.0
Solaris 2.6	Brixton 4.1 ¹	6.5	4.0
Solaris 7	Brixton 4.1 ¹	6.5	None
Solaris 7	DCL SNAP-IX 6.0	6.5	None
Solaris 7	SUN Link 9.1 ¹	6.5	None

1. Solaris users must upgrade to this stack revision level. Sync-level 2 not supported.

Supported Host Platforms

Table 1-2 lists the IBM host platforms supported by BEA eLink for Mainframe SNA 3.1.

Table 1-2 Supported Host Platforms

Vendor	Classification	Product	Version	Comments
IBM	MF/OS	OS390	1.2, 2.4, 2.5, 2.6	Y2K Certified
IBM	MF/OS	VM	2.3	Y2K Certified
IBM	MF/OS	VSE/ESA	2.3	Y2K Certified
IBM	MF/OLTP	CICS/ESA	4.1	for MVS
IBM	MF/OLTP	CICS Transaction Server for OS/390	1.2	for MVS
IBM	MF/OLTP	CICS	2.3	for VSE
IBM	MF/OLTP	IMS/ESA Transaction Manager	5.1 6.1	for MVS
IBM	MF/TCOM	ACF/VTAM	3.4+	for MVS
IBM	MF/TCOM	ACF/NCP	4.3+	for MVS
IBM	MF/TCOM	ACF/VTAM		for VSE
IBM	MF/TCOM	ACF/NCP		for VSE
IBM	MF/OS	OS390	1.2	Y2K Certified

2 Understanding How the Software Works

Overview of Domain Gateways

The BEA Domains gateway architecture grew out of a need for organizations to share services and data among computer applications while enabling application and administrative autonomy within single segments of the business. For example, a bank could have a number of separate applications, such as a loan application, a retail application, and so forth. Each application could span one or more computer nodes and could be administered independently from other applications.

The *Domain*, a separately administered application environment that is interconnected with other domains by gateways, was developed to address this need. To provide a common functional framework for gateways interconnecting individual domains, BEA developed the *Domain Gateway* architecture. This architecture specifies the common functionality and administrative interfaces needed for gateways to perform inter-domain communications. You can find a more detailed discussion of the BEA Domains gateway architecture in *BEA TUXEDO Domain User Guide*.

The BEA eLink family of products provides domain-compliant gateways that permit administration of the remote *Transaction Processing (TP)* system as a foreign domain. The BEA eLink for Mainframe SNA and BEA eLink for Mainframe OSI TP gateways are operating examples.

The Domains Gateway architecture extends the scope of BEA TUXEDO to provide coordinated transaction processing across an enterprise's geographic or organizational boundaries. Within each domain, the administrator determines which local services are available to other specific domains, thus enabling client applications to request those services.

The Domains Gateway architecture is aimed at the BEA TUXEDO application administrator, who makes services in other domains available to application programmers. The existence of applications within distinct domains is, however, totally transparent to the application programmers. They can use BEA TUXEDO programming paradigms to request services offered in other BEA Domains exactly as if they were services offered within the local application.

The BEA TUXEDO application administrator enables remote domains to access a subset of *Local Services*. This subset is called a *Local Domain*. The local domain helps the administrator provide secure "views" of the application.

Furthermore, the administrator can restrict access to local services through an Access Control Lists (ACL). The list designates which remote domains are allowed to issue requests to a particular local service.

Here are common features shared by all BEA Domains-compliant gateways:


- ◆ *X/Open XATMI*. Application programs using BEA TUXEDO can request services from applications running in another domain. Also, remote applications can request services from local servers.
- ◆ *Administration*. BEA Domains-compliant gateways can be booted or shutdown exactly like any other BEA TUXEDO server. Run-time administration is provided, and administrators can dynamically change the configuration to tune the performance of a gateway. Each compliant gateway supports a common set of administrative *Application Programming Interface (API)*, tools, and configuration files.
- ◆ *Multi-domain interaction*. BEA Domains-compliant gateways can inter-operate with multiple domains at the same time.
- ◆ *Transparent multi-network support*. BEA Domains-compliant gateways can communicate with remote domains using different types of networks transparently to the application.

- ◆ *Service names aliases.* This permits the administrators to map service names used by the remote application to service names used by the local application. By using this feature, administrators can easily integrate applications that use different naming schemes.
- ◆ *Data dependent routing.* Administrators can use the configuration capability to define data dependent routing criteria for remote domains. This feature allows the gateway to select a remote domain according to a field value defined in the request (for example, an account number).

The BEA eLink SNA Domain

The eLink SNA domain, shown in Figure 2-1, is the gateway for communications using LU6.2 sessions and conversations to a CICS/ESA region. It adds multi-domain connectivity, bidirectional request/response, and conversations between TUXEDO and SNA-based applications. It provides access to SNA based APPC applications as well as inter-system communication with CICS/ESA. When accessing CICS/ESA systems, the SNA domain acts as a CICS/ESA region, capable of supporting the following sync level 2 functions:

- ◆ Bidirectional synchronous, asynchronous, and conversational service requests
- ◆ Peer support for CICS/ESA and support for multiple remote MVS regions
- ◆ Event monitoring and reporting
- ◆ Both static and dynamic configuration support where allowed by SNA
- ◆ Automatic Data conversion between Unix and Host formats
- ◆ Security through Access Control Lists on the local domain
- ◆ User and password security for CICS/ESA communications

Figure 2-1 BEA TUXEDO System /Domain Architecture

The eLink SNA software enables the TUXEDO System clients and servers to interact with clients and servers in a non-TUXEDO, remote SNA domain. The remote and local domains must support SNA LU6.2 protocols in order to inter-operate. A set of SNA sessions of type LU6.2 over which the local and remote domains communicate are established. When two entities (in this case local and remote domains) communicate via an LU6.2 session, a conversation is allocated to the session. The

gateway and CICS program have exclusive use of the session during the conversation. When the conversation is de-allocated, the session becomes available for use by another client/server pair.


For each client/server communication model, non-conversational or conversational, parallel sessions are allocated for the LU6.2 conversation between the local and remote domains. The behavior of the applications at either end of a conversation depends on the type of client/server communication model in effect for the duration of the LU6.2 conversation. Refer to Chapter 6, “Programming Considerations” for more details about application behavior.

The eLink SNA domain is composed of several elements that can be configured to provide SNA solutions. For the most part, the SNA domain is much like other BEA TUXEDO domain gateways; it uses the DMADM and GWADM servers for administration. With the eLink SNA system, additional servers and processes support peer CICS/ESA connectivity and sync level 2. Figure 2-2 shows each component of the eLink SNA product.

The DMINIT and SNACRM Servers

Additionally, the eLink SNA software provides the DMINIT server, which can be used to start non-BEA TUXEDO servers at gateway group boot time. One such server is the SNA Communication Resource Manager (SNACRM). Both the SNACRM and the SNA PU 2.1 servers must be running before any other servers are booted. Configuring the SNACRM server is explained in the DM_SNACRM Section.

Figure 2-2 BEA eLink for Mainframe SNA Domain Components



Other Gateway Servers

The SNA Domain Gateway (GWSNAX) uses the administrative servers provided with BEA TUXEDO software for domain and gateway configuration and administration. These are the Domain Administration Server (DMADM) and Gateway Administration Server (GWADM). Specific information about configuring the various sections of the SNA Domain Gateway can be found in the following:

- ◆ Chapter 3, “Configuring the System”
- ◆ The `dmconfig` file description found in Appendix A, “Reference Pages,” located in the back of this guide.
- ◆ *BEA TUXEDO/Domain Guide*

3 Configuring the System

This chapter is divided into two parts: Local Domain Configuration and Remote Host Domain Configuration.

Local Domain Configuration

There are four aspects to configuring a BEA eLink for Mainframe SNA local domain:

- ◆ Edit the UBBCONFIG File to define the eLink SNA administrative and gateway servers to the BEA TUXEDO system. Use this method to establish a new gateway configuration or modify an existing one. Also, you can specify the SNA Communications Resource Manager (SNACRM) process as a TUXEDO server.
- ◆ Edit the DMCONFIG File and process it with the `dmloadcf` utility. Use this method to establish a new gateway configuration.
- ◆ Use the `dmadmin` Command Interpreter. This gives you access to the binary `BDMCONFIG` file. Use this method to change an existing gateway configuration. Refer to Appendix A, “Reference Pages,” for more information about the `dmadmin` command.
- ◆ Perform a cold start on the eLink SNA domain after making changes to the `DM_SNACRM` Section, `DM_SNASTACKS` Section, or `DM_SNALINKS` Section. If you do not cold start the eLink SNA domain, an error occurs on domain start-up indicating cold start required for the configuration change.

Edit the UBBCONFIG File

Refer to the *BEA TUXEDO Reference Manual* for general and detailed information about this subject.

Edit the DMCONFIG File

The configuration specified in the DMCONFIG file controls much of the operation of the eLink SNA gateway. A sample of this file is provided in the installation directory of your eLink SNA product software.

Note: Because eLink SNA may be installed on a variety of platforms, the procedures in this section make only general references to command entries. Many steps show UNIX command examples. Be sure to use the proper syntax for your platform when making command-line entries.

Prerequisites

The eLink SNA product software must be installed and accessible to your text editor. You must have file permission to access the `install` directory and modify the sample DMCONFIG file. In addition, the following prerequisites must be met to successfully complete the editing procedure:

- ◆ The `$TUXDIR/udataobj/DMTYPE` file defining the valid domain types must exist (see `dmloadcf` in Appendix A, “Reference Pages,” for more information).
- ◆ The effective user identifier of the person running `dmloadcf` must match the UID in the `RESOURCES` section of the TUXCONFIG file (refer to `dmloadcf` in Appendix A, “Reference Pages,” for more information).

The following paragraphs describe the significant parameters within specific sections of the DMCONFIG file.

DM_LOCAL_DOMAINS Section

In this section, the value for the `TYPE` parameter distinguishes this gateway from other gateway types. Currently, `SNAX` replaces the value `SNADOM` used in previous releases. The parameter entry takes the form:

```
TYPE={SNAX | OSITP | TDOMAIN}
```

Select the value `TYPE=SNAX` for this entry.

DM_REMOTE_DOMAINS Section

In this section, the value for the `TYPE` parameter indicates that the remote domain communicates using the SNA protocol. The parameter entry takes the form:

```
TYPE={SNAX | OSITP | TDOMAIN}
```

Select the value `TYPE=SNAX` for this entry.

DM_SNADOM Section

This section has been replaced with the following sections, each of which is described in subsequent paragraphs:

- ◆ `DM_SNACRM` section
- ◆ `DM_SNASTACKS` section
- ◆ `DM_SNA_LINKS` section

Note: Any changes to the `DM_SNACRM`, `DM_SNASTACKS`, or `DM_SNA_LINKS` sections require a cold start for the eLink SNA domain. If you do not cold start the SNA domain, an error will occur on domain start-up indicating cold start required for the configuration change.

DM_SNACRM Section

The `DM_SNACRM` section provides three keywords used to identify the `SNACRM` that provides ATMI transaction semantics among a given domain and its partners. Entries have the general form:

```
<SNA CommunicationsResourceManagerName> parameters
```

Where `<SNA CommunicationsResourceManagerName>` is the locally known name of this `SNACRM` definition to be used when referencing this `SNACRM` in subsequent sections. This name is an ASCII string 1-30 characters in length. The parameters are the keyword/value pairs that makeup the definition. All keywords are required for a valid `SNACRM` definition. Keywords can be in any order.

LDOM <LocalDomainName> (Required)

LDOM associates this SNACRM with a defined local domain. <LocalDomainName> is the reference to an entry in the `DM_LOCAL_DOMAINS` section. This name is an ASCII string 1 to 30 characters in length. This parameter is required. This parameter has no default.

SNACRMADDR <HexSocketAddress> (Required)

SNACRMADDR provides the socket address the domain gateway will use to communicate with the SNACRM. If the SNACRM is started independently of the domain gateway, this address must be used on the SNACRM command line. This parameter is required. This parameter must contain an even number of hex characters. This parameter has no default.

<HexSocketAddress> is a TCP/IP address using the `sockaddr_in` format of `family,port,address`:

```
<0xFFFFPPPPAAAAAAA> or //hostname:port_addr
```

Where:

- ◆ FFFF is the hex value of the protocol family, always 0x0002 for the INET family.
- ◆ PPPP is the hex value of an unused TCP/IP port
- ◆ AAAAAAA is the hex value of the IP address for the machine running the SNACRM

Therefore if the SNACRM was running on a machine named `myhost` with an IP address of 206.189.43.13, and you wanted to use port 6000 for the SNACRM, then SNACRMADDR would be:

```
0x00021770CEBD2B0D or //myhost:6000
```

DM_SNASTACKS Section

The `DM_SNASTACKS` section provides five keywords which identify the third party SNA stack that should be used for connections established between a given domain and it's partners. Entries have the general form:

```
<StackReference> parameters
```

Where *<StackReference>* is the locally known name of this stack definition to be used when referencing this stack in subsequent sections. This name is an ASCII string 1-30 characters in length. The parameters are the keyword/value pairs that make up the definition. Keywords can be in any order. All keywords are required for a valid stack definition.

LOCALLU *<LocalLUAlias>* (Required)

LOCALLU provides a reference to an LU alias defined in the third party SNA stack. *<LocalLUAlias>* is the name used to identify the local LU definition as specified by the third party SNA stack configuration. This is a name that represents the end node for an LU6.2 connection. The value for this parameter is an ASCII string, 1-8 characters in length. This parameter is required. This parameter has no default. The third party SNA stack will require a corresponding definition for a local LU.

LTPNAME *<LocalTransactionProgramName>* (Required)

LTPNAME identifies the inbound transaction programs which will be serviced by any SNACRM using this stack definition. *<LocalTransactionProgramName>* is the name used to identify inbound transaction programs for which an attach will be accepted. The only useful value is an asterisk. This indicates all inbound attaches will be accepted. This parameter is required. This parameter has no default. Partial TP names are not supported. The third party SNA stack will require a corresponding definition for inbound TP names.

SNACRM *<SNACommunicationsResourceMangerName>* (Required)

SNACRM provides a name to which the associated SNACRM definition is referenced. *<SNACommunicationsResourceMangerName>* is the name used to associate the DM_SNACRM definition with this DM_SNASTACKS entry. The value for this parameter is an ASCII string, 1-30 characters in length. This parameter is required. This parameter has no default.

STACKPARMS *<parameters required for third party sna stack>* (Required)

STACKPARMS provides a method for the domain gateway to pass any required parameters to the third party SNA stack. The *<parameters required for third party sna stack>* is an ASCII string, 1-128 characters in length. Currently, the only value used is the TCP/IP hostname for the machine running the third party SNA stack. This parameter is required. This parameter has no default.

STACKTYPE={brx41 | hp51 | hp60 | ibm50 | ibm60 | spx60 | sun91}

This option is used to indicate which vender SNA stack is being used. It is also used to determine the names of specific eLink SNA system libraries. Because of this, it is essential that the value of this option be coded correctly. These values are mapped to the equivalent eLink SNA system library.

DM_SNALINKS Section

This section defines the SNA Link information required by domains of type SNA.

STACKREF = string (Required)

This required parameter defines the stack that will be used for establishment of this link. The `STACKREF` string is the tag that was used in the corresponding definition established in the `DM_SNASTACKS` section.

RDOM=name

Each link defines a connection between a BEA TUXEDO System application domain and a remote system connected with an SNA network. The remote system is, in BEA TUXEDO terms, a remote domain. The `RDOM` option associates the link with a remote domain. This remote domain must have been configured with the `TYPE=SNAX` option. The `RDOM` name should match a `RDOM` value previously identified in the `DM_REMOTE_DOMAINS` section.

LSYSID=name

`LSYSID` is the four-character identifier for this link. This should match the connection ID in the CICS/ESA resource definition used by a partner CICS/ESA to communicate to the `SNACRM` across this link. If you are using the macro definition, this is a four-character name on the `SYSIDNT` option of the `DFHTCT` macro.

RSYSID=name

`RSYSID` is the four-character remote sysid of the partner. Typically it is the sysid of a CICS/ESA region, but could also be the subsystem ID of an IMS control region. This parameter must match the actual sysid of the remote partner. This name is the `SYSIDNT` of the `DFHSIT` or the value in the CICS/ESA start-up overrides

RLUNAME=name (Required)

The `RLUNAME` value represents an alias known to the third party SNA stack that resolves to a VTAM `netname` for the remote application. This would most likely be the VTAM `applid` for a CICS/ESA region, however it could also be an APPC/MVS LU defined for use with IMS. The value must be unique within the SNA network. The value *name* should be 1-8 characters. This parameter is required. This parameter has no default. The third party stack configuration requires a matching definition.

MODENAME=name (Required)

`MODENAME` is VTAM mode entry defined to the third-party SNA stack. For a CICS/ESA link, this must be compatible with the session definition or profile entry for the corresponding connection. For an IMS connection, this must be compatible with the `DLOGMOD` entry on the LU definition used to access the IMS scheduler. The value *name* should be 1-8 ASCII characters. This parameter is required. This parameter must match the third-party SNA stack configuration and must be compatible with the corresponding entries defined to VTAM and/or CICS/ESA.

SECURITY={LOCAL, IDENTIFY, VERIFY, PERSISTENT, MIXIDPE}

`SECURITY` specifies the security setting in CICS/ESA connection resource definition. It identifies the level of security enforced under CICS/ESA by the external security manager. Legal values are `LOCAL`, `IDENTIFY`, `VERIFY`, `PERSISTENT` or `MIXIDPE`. The default setting is `LOCAL`. `PERSISTENT` and `MIXIDPE` identify the setting in the remote connection definition, but are identical to the `VERIFY` option in this release of eLink SNA.

MAXSESS=number

This number represents the maximum number of sessions that can be concurrently acquired on this link. It must be greater than or equal to four, and less than or equal to the maximum number of sessions that can be configured by the SNA stack. The actual number of concurrent sessions is determined by both system configurations to be the lowest maximum number of sessions allowed by either system.

MINWIN=number

This minimum number of contention winners. Typically, this value is half the MAXSESS value. This number added to all CICS/ESA session definition winner numbers for the connection should be equal to the MAXSESS value.

MAXSYNCLVL={0, 1, 2}

This represents the maximum sync-level conversation that can be supported on this link. The default is sync-level 2. If the installation is not licensed for sync-level 2, this parameter must be set to 0 or 1 for the link to be established. Transaction support is only available at sync-level 2.

Sync-level 0

A value of zero (0) means this link is non-transactional. No synchronization is maintained. This can be used for sending and receiving messages from IMS via the APPC/MVS transparency interface.

Sync-level 1

Allows Sync-level 0 capabilities as well as support for SYNCONRETURN *Distributed Program Link (DPL)* with CICS/ESA systems (outbound ATMI `tpcall()` requests with `TPNOTRAN`).

Sync-level 2

Supports all sync-level 0 and sync-level 1 features for systems able to exchange logs and compare states. In addition, full syncpoint synchronization at sync-level 2 is supported.

Also supports:

Full transaction coordination and recovery between BEA TUXEDO and CICS/MVS systems. This includes transaction support between BEA TUXEDO services and CICS APPC applications as well as DPL.

Outbound ATMI `tpcall()` as a DPL request with full two phase commit transaction semantics using `tpcommit()`.

Outbound ATMI `tpconnect()` as APPC or CPI-C *Distributed Transaction Processing (DTP)* with full commit transaction semantics using `tpbegin()` and `tpcommit()`.

Inbound EXEC CICS LINK requests with full two phase commit transaction semantics using Prepare, Rollback, and Syncpoint verbs.

Inbound APPC or CPI-C conversations with full two phase commit transaction semantics using Prepare, Rollback, and Syncpoint verbs.

Caution: If you set `MAXSYNCLVL=2` or make no entry for this parameter (that is, accept the default) without having installed the eLink SNA software licensed for that level, the system configuration automatically reverts to sync-level 1 and an error message is sent to the error log. To clear that error message, you must either reset the `MAXSYNCLVL` parameter to an appropriate value or purchase and install the correct software.

`STARTTYPE={auto|cold}`

This option sets the recovery mode for transactional links. When set to `AUTO`, the system restarts using configuration and link data recovered from the transaction log. When set to `COLD`, the system uses configuration data taken from the current `DMCONFIG` file and loses any in-flight link data. Changing `DMCONFIG` file parameters and performing a `AUTO` start results in a message warning that changed parameters are ignored until the next cold start. To force a cold start and disregard the `STARTTYPE` setting, delete the `SNA*LOG` files in `$APPDIR`.

DM_LOCAL_SERVICES Section

`RNAME=name` (Required)

The `RNAME` option is the local-service name imported from a remote CICS/ESA region. This name is used by the `SNACRM` to select a local service.

When the `RNAME` specifies an alternate mirror transaction identifier for explicit attachment for inbound DPL requests, it must be a combination of the alternate mirror `TRANSID` and a CICS/ESA program name in the following format:

`RNAME=AAAA:BBBBBBBB`

where:

`AAAA`

is a 1-4 character alternate mirror `TRANSID`.

`BBBBBBBB`

is a 1-8 character CICS/ESA program name.

The colon is required to indicate the TRANSID/program name combination. The TRANSID must be composed of acceptable CICS/ESA characters:

A-Za-z0-9\$@#. /-_%&Qç?! | " = , ; < >

Refer to “Special Treatment of TRANSID for DPL” in Section 6.

DM_REMOTE_SERVICES Section

FUNCTION={APPC | DPL}

The FUNCTION option has been added to allow outbound TUXEDO service requests to map to APPC transaction programs or CICS/ESA programs. The default value APPC indicates the remote service is a transaction program that may or may not be running under CICS/ESA. The DPL value indicates the remote service maps to a program running under CICS/ESA.

RNAME=name

The RNAME option is the name of the host TP_NAME. For non-CICS/ESA systems, this name can be up to 64 characters in length. For CICS/ESA systems, this name is the transaction ID for FUNCTION=APPC and the program name for FUNCTION=DPL requests. CICS/ESA trans-id names cannot exceed four characters and CICS/ESA program names cannot exceed eight characters. The RNAME option must observe these requirements.

When the RNAME specifies an alternate mirror transaction identifier for explicit attachment to outbound DPL requests, it must be a combination of the alternate mirror TRANSID and an advertised remote CICS/ESA program name in the following format:

RNAME=AAAA:BBBBBBBB

where:

AAAA

is a 1-4 character alternate mirror TRANSID

BBBBBBBB

is a 1-8 character CICS/ESA program name.

The colon is required to indicate the TRANSID/program name combination. The TRANSID must be composed of acceptable CICS/ESA characters:

A-Za-z0-9\$@#./-_%&Qç?!| " = , ; < >

Refer to “Special Treatment of TRANSID for DPL” in Section 6.

Use the dmadmin Command Interpreter

The `dmadmin` command is an interactive command interpreter for the administration of domain gateway groups defined for a particular BEA TUXEDO System/T application. The `dmadmin` command enters configuration mode when you execute it with the `-c` option, or when you use the `config` subcommand. In this mode, `dmadmin` performs run-time updates to the BDMCONFIG file. You can use any text editor available on your platform to make `dmadmin -c` changes.

This subsection provides quick references to changes you can make to eLink SNA-related sections of the DMCONFIG file. Refer to Appendix A, “Reference Pages,” for details about using the `dmadmin` command.

Note: The DM_SNA section has been replaced with the DM_SNALINKS, DM_SNASTACKS, and DM_SNACRM sections.

Configuring the DM_SNACRM Section

Table 3-1 lists the fields in the DM_SNACRM section which you may need to update for your configuration.

Table 3-1 DM_SNACRM Field Updates

Field Identifier	Field Type	Update	Notes
TA_LDOM	string	NoGW	
TA_SNACRMADDR	hex-string	NoGW	

Configuring the DM_SNASTACKS Section

Table 3-2 lists the fields in the DM_SNASTACKS section which you may need to update for your configuration.

Table 3-2 DM_SNASTACKS Field Updates

Field Identifier	Field Type	Update	Notes
TA_SNACRM	string	NoGW	
TA_STACKTYPE	string	Yes	brx41 hp51 hp60 ibm50 ibm60 sun91 spx60
TA_LOCALLU	numeric	Yes	Local SYSID
TA_LTPNAME	string		wildcard for local tpname
TA_STACKPARMS	string		Parameters for vender stack

Configuring the DM_SNALINKS Section

Table 3-3 lists the fields in the DM_SNALINKS section which you may need to update for your configuration.

Table 3-3 DM_SNALINKS Field Updates

Field Identifier	Field Type	Update	Notes
TA_STACKREF	string	NoGW	
TA_RDOM	string	Yes	Key
TA_LSYSID	numeric	Yes	Local SYSID
TA_RSYSID	string	NoGW	Remote SYSID
TA_RLUNAME	string	NoGW	as known to VTAM
TA_MODENAME	string	NoGW	for the sessions
TA_SECURITY	string	NoGW	LOCAL, IDENTIFY, VERIFY, PERSISTENT, MIXIDPE

Table 3-3 DM_SNALINKS Field Updates

Field Identifier	Field Type	Update	Notes
TA_STARTTYPE	string	NoGW	Auto Cold
TA_MAXSESS	numeric		Maximum number of concurrent APPC sessions
TA_MINWIN	numeric	NoGW	Minimum contention winners
TA_MAXSYNCLVL	numeric	NoGW	Maximum conversation sync level for link

Remote Host Domain Configuration

You must ensure the CICS/ESA remote domain is prepared to conduct operations with the BEA TUXEDO local domain. This includes:

- ◆ Establishing the VTAM Configuration
- ◆ Configuring the CICS/ESA LU (Logical Unit)
 - ◆ Creating Connections at the Remote Host
 - ◆ Defining the Session at the Remote Host
- ◆ Completing Cross-Platform Definitions
- ◆ Setting Stack Traces

Note: Any samples provided illustrate a starting point for configuring your system and do not represent all possibilities. The samples represent one way a mainframe can be configured to work in an APPN LAN environment.

Establishing the VTAM Configuration

If your eLink SNA system is used in a *Virtual Telecommunications Access Method (VTAM)* environment, you must ensure the host configuration supports it. Refer to Appendix E, “Sample VTAM Configurations,” for some examples based on the requirements for BEA eLink for Mainframe SNA to be used in a VTAM environment with an Ethernet LAN and an APPN mainframe system.

Configuring the CICS/ESA LU

Before you can connect to the remote stack, the LU configuration must be established. This entails creating connection definitions, creating session definitions, and installing resource definitions.

Creating Connections at the Remote Host

If it is not already in place, you must work with the mainframe support personnel to create a remote connection definition file. When placed on the remote host, the definition provides a connection with the BEA TUXEDO local domain. It corresponds to the LSYSID in the local domain’s DMCONFIG file. The following is an example of a connection definition file:

```
DEFINE CONNECTION(BEA)          GROUP(BEACONN)
DE(CONNECT SNA EXAMPLE RDO CONNECTION)
ACCESSMETHOD(VTAM)             PROTOCOL(APPC)
NETNAME(**VTAM NETWORK NAME OF REMOTE SYSTEM**)
ATTACHSEC(LOCAL)               AUTOCONNECT(NO)
```

To install the sample connection definition, put it in on the host in a separate group which does not contain existing connection. Use the CEDAS INSTALL command, for example:

```
CEDAS INSTALL I GROUP(BEACONN)
```

Defining the Session at the Remote Host

If it is not already in place, you must work with the mainframe support personnel to create a session definition. When placed on the remote host, it defines the logical links by which the BEA TUXEDO local domain communicates with the remote host. The following is an example of a session definition:

```
DEFINE SESSION ( BEATEST )          GROUP ( BEACONN )
      CONNECTION ( BEA )
      DE ( CONNECT SNA EXAMPLE RDO SESSION )
      PROTOCOL ( APPC )              AUTOCONNECT ( YES )
      MODENAME ( **MODE** )          MAXIMUM ( **SESSNBR** , **WINNER** )
```

AUTOCONNECT indicates how the activation of the session is to be negotiated. YES enables the CICS/ESA host to negotiate its own winner sessions when a conversation is allocated.

The MODENAME can be either a CICS/ESA-supplied mode name, such as SMSNA100, or with your own defined mode name. If another set of session definitions exist for the BEA connection, this mode name must be unique among all sets defined to the connection. The mode name corresponds to the VTAM LOGMODE name.

The MAXIMUM option defines the total number of sessions in the set and the total number of winner sessions. The total number of winner sessions must include those for the host and the remote stack. The WINNER number plus the remote WINNER number should equal the SESSNBR. The local SESSNBR must equal the remote SESSNBR,

View Connection and Session Status

Once you have installed group definitions, you can view the status of connections and sessions using the following CICS/ESA system commands:

```
CEMT I CONN(BEA)                  **view the status of the connection
CEMT I NET(**Netname**)            **View the status of the sessions
CEMT I MODENAME(**MODE**)          **View the status of the mode
```

Completing Cross-Platform Definitions

It is important to communicate with the administrator of the CICS/ESA remote domain to obtain key parameters in the VTAM definition that must be included in the SNA stack configuration, as well as in other configuration files in the eLink SNA local domain.

Before installing eLink SNA software, please examine Table 3-4 for a summary of cross-platform definitions. Consult with the VTAM system administrator to obtain the value indicated in the Name column and make the corresponding entries shown in the Needed In column.

Table 3-4 Summary of Cross-Platform Definitions

Item	Name	Originates In	Needed In
1.	SNA Network ID (e.g., SNANET1) and VTAM Host ID (e.g., VTAMHOST)	VTAM configuration	Brixton-based Stack Configuration: ¹ Example: CP NQ_CP_NAME=SNANET1.SPARC1 DLC RMTNQ_CP_NAME=SNANET1.VTAMHOST LU NQ_LU_NAME=SNANET1.L0P0024A PTNR_LU NQ_LU_NAME=SNANET1.CICSSYN SNAP-IX based Stack Configuration: ² Example: fgcp_name=SNANET1.SPARC1 adj_cp_name=SNANET1VTAMHOST fgplu_name=SNANET1.CICSSYN

Table 3-4 Summary of Cross-Platform Definitions

Item	Name	Originates In	Needed In
2.	Mode Name (e.g.,SNA62)	VTAM-MODEENT definition	<p>CICS Sessions Definition: Example: MODENAME(SNA62)</p> <p>Brixton-based Stack Configuration: ¹ Example: CP NQ_CP_NAME=SNANET1.SPARC1 DLC RMTNQ_CP_NAME=SNANET1.VTAMHOST LU NQ_LU_NAME=SNANET1.L0P0024A PTNR_LU NQ_LU_NAME=SNANET1.CICSSYN</p> <p>SNAP-IX based Stack Configuration: ² Example: fgcp_name=SNANET1.SPARC1 adj_cp_name=SNANET1VTAMHOST fgplu_name=SNANET1.CICSSYN</p> <p>TUXEDO Domain Configuration: Example: DM_SNA_LINKS MODENAME="SNA62"</p>
3.	Control Point Name CPNAME (e.g.,SPARC1)	VTAM-PU definition	<p>Brixton-based Stack Configuration: ¹ Example: CP NQ_CP_NAME=SNANET1.SPARC1 DLC RMTNQ_CP_NAME=SNANET1.VTAMHOST LU NQ_LU_NAME=SNANET1.L0P0024A PTNR_LU NQ_LU_NAME=SNANET1.CICSSYNSNAP-IX</p> <p>based Stack Configuration: ² Example: fgcp_name=SNANET1.SPARC1 adj_cp_name=SNANET1VTAMHOST fgplu_name=SNANET1.CICSSYN</p>

Table 3-4 Summary of Cross-Platform Definitions

Item	Name	Originates In	Needed In
4.	Local LU Name (e.g., L0F0024A)	VTAM-LU definition	<p>CICS CONNECTION definition: Example: NETNAME(L0F0024A)</p> <p>Brixton-based Stack Configuration: ¹ Example: CP NQ_CP_NAME=SNANET1.SPARC1 DLC RMTNQ_CP_NAME=SNANET1.VTAMHOST LU NQ_LU_NAME=SNANET1.L0P0024A PTNR_LU NQ_LU_NAME=SNANET1.CICSSYN</p> <p>SNAP-IX based Stack Configuration: ² Example: fgcp_name=SNANET1.SPARC1 adj_cp_name=SNANET1.VTAMHOST fgplu_name=SNANET1.CICSSYN</p> <p>TUXEDO Domain Configuration: Example: DM_SNA_STACKS LOCALLU="L0F0024A"</p>
5.	CICS LU Name (e.g., CICSSYN)	VTAM-LU definition	<p>Brixton-based Stack Configuration: ¹ Example: CP NQ_CP_NAME=SNANET1.SPARC1 DLC RMTNQ_CP_NAME=SNANET1.VTAMHOST LU NQ_LU_NAME=SNANET1.L0P0024A PTNR_LU NQ_LU_NAME=SNANET1.CICSSYN</p> <p>SNAP-IX based Stack Configuration: ² Example: fgcp_name=SNANET1.SPARC1 adj_cp_name=SNANET1.VTAMHOST fgplu_name=SNANET1.CICSSYN</p> <p>TUXEDO Domain Configuration: Example: DM_SNA_LINKS RLUNAME="CICSSYN"</p>

Table 3-4 Summary of Cross-Platform Definitions

Item	Name	Originates In	Needed In
6.	Terminal Identifier (e.g.,05DF0024)	VTAM (IDNUM+IDBLK)	Brixton-based Stack Configuration: ¹ Example: CP NQ_CP_NAME=SNANET1.SPARC1 DLC RMTNQ_CP_NAME=SNANET1.VTAMHOST LU NQ_LU_NAME=SNANET1.L0P0024A PTNR_LU NQ_LU_NAME=SNANET1.CICSSYN SNAP-IX based Stack Configuration: ² Example: fgcp_name=SNANET1.SPARC1 adj_cp_name=SNANET1.VTAMHOST fgplu_name=SNANET1.CICSSYN
7.	Local Network Device (e.g.,/dev/tr)	UNIX Configuration	Brixton-based Stack Configuration: ¹ Example: CP NQ_CP_NAME=SNANET1.SPARC1 DLC RMTNQ_CP_NAME=SNANET1.VTAMHOST LU NQ_LU_NAME=SNANET1.L0P0024A PTNR_LU NQ_LU_NAME=SNANET1.CICSSYN
8.	Local MAC Address (token ring only)	Token ring address of Host	Brixton-based Stack Configuration: ¹ Example: CP NQ_CP_NAME=SNANET1.SPARC1 DLC RMTNQ_CP_NAME=SNANET1.VTAMHOST LU NQ_LU_NAME=SNANET1.L0P0024A PTNR_LU NQ_LU_NAME=SNANET1.CICSSYN

Table 3-4 Summary of Cross-Platform Definitions

Item	Name	Originates In	Needed In
9.	Remote MAC Address (token ring only)	Token ring address of local machine	Brixton-based Stack Configuration: ¹ Example: CP NQ_CP_NAME=SNANET1.SPARC1 DLC RMTNQ_CP_NAME=SNANET1.VTAMHOST LU NQ_LU_NAME=SNANET1.L0P0024A PTNR_LU NQ_LU_NAME=SNANET1.CICSSYN SNAP-IX based Stack Configuration: ² Example: fgcp_name=SNANET1.SPARC1 adj_cp_name=SNANET1.VTAMHOST fgplu_name=SNANET1.CICSSYN
10.	LAN Speed (e.g.,4MBs)	Speed of token ring network	Brixton-based Stack Configuration: ¹ Example: CP NQ_CP_NAME=SNANET1.SPARC1 DLC RMTNQ_CP_NAME=SNANET1.VTAMHOST LU NQ_LU_NAME=SNANET1.L0P0024A PTNR_LU NQ_LU_NAME=SNANET1.CICSSYN
11.	SDLC parameters (line protocol)	VTAM-line definition	Brixton-based Stack Configuration: ¹ Example: CP NQ_CP_NAME=SNANET1.SPARC1 DLC RMTNQ_CP_NAME=SNANET1.VTAMHOST LU NQ_LU_NAME=SNANET1.L0P0024A PTNR_LU NQ_LU_NAME=SNANET1.CICSSYN
12.	Partner Definition (e.g.,TUXPART1)	CICS/ESA	Mainframe Client Application: (e.g., COBOL with embedded CPI-C to route CICS to appropriate LU for BEA eLink for Mainframe SNA) COBOL Example: MOVE 'TUXPART1' TO SYM-DEST-NAME CALL 'CMINIT' USING CONVERSATION-ID SYM-DEST-NAME, CM_RETCODE END-CALL

Table 3-4 Summary of Cross-Platform Definitions

Item	Name	Originates In	Needed In
13.	Set LU definition so maximum sync-level allowed corresponds to DMCONFIG entry: DM_SNA_LINKS MAXSYNCLVL	Stacks	Brixton-based Stack Configuration: ¹ Example: CP NQ_CP_NAME=SNANET1.SPARC1 DLC RMTNQ_CP_NAME=SNANET1.VTAMHOST LU NQ_LU_NAME=SNANET1.L0P0024A PTNR_LU NQ_LU_NAME=SNANET1.CICSSYN SNAP-IX based Stack Configuration: ² Example: fgcp_name=SNANET1.SPARC1 adj_cp_name=SNANET1.VTAMHOST fgplu_name=SNANET1.CICSSYN
14.	Map all incoming conversations to BEA eLink for Mainframe SNA gateway (make sure TPs have all privileges available, e.g., CNOS, syncpoint if licensed, service conversations, etc.).	Stacks	Brixton-based Stack Configuration: ¹ Example: CP NQ_CP_NAME=SNANET1.SPARC1 DLC RMTNQ_CP_NAME=SNANET1.VTAMHOST LU NQ_LU_NAME=SNANET1.L0P0024A PTNR_LU NQ_LU_NAME=SNANET1.CICSSYN SNAP-IX based Stack Configuration: ² Example: fgcp_name=SNANET1.SPARC1 adj_cp_name=SNANET1.VTAMHOST fgplu_name=SNANET1.CICSSYN
15.	CICS Transaction IDs (e.g.,TOUP)	CICS/ESA	TUXEDO Domain Configuration: Example: DM_REMOTE_SERVICES

1. Brixton-based stack = SunLink
2. SNAP-IX based stack = SNAPplus2, IBM CS/AIX, or SNAP-IX for Solaris

Setting Stack Traces

Consult the vendor publications for instructions on how to set up stack tracing.

4 Verifying the Software

After installing and configuring the BEA eLink for Mainframe SNA product software, it is important to verify the operational integrity of the environment. To do this, you run a sample application on a simple server in client/server transaction scenarios. This process employs programs available in your product software libraries.

Note: Before running the sample application, you must configure the eLink SNA gateway environment, start the Physical Unit (PU), start the SNACRM, and start the BEA TUXEDO system. Refer to “Configuring the System,” and “Administering the Application Domain,” for details.

This section covers the following topics:

- ◆ Overview
- ◆ Building Your Verification Tests
 - ◆ Building TUXEDO Executables
 - ◆ Building CICS/ESA Executables
- ◆ Running the Sample Application
 - ◆ Running the Application from a TUXEDO Client
 - ◆ Running the Application from a CICS/ESA Client
 - ◆ Running the Application from a CICS/VSE Client

Overview

The sample applications are located in the eLink SNA simple server library (`simpapp`). The simple server passes a string from the client to the server.

The CICS/ESA programs may run as either DTP or DPL processes, and as either servers or clients. In addition, the simple server may run in either transactional or non-transactional mode. In the transactional mode, these scenarios verify that the sync-level 2 protocol is established between the two application environments.

When the client runs as a BEA TUXEDO client, the server runs as a CICS/ESA host. You enter a text string in lower-case letters with command arguments. The CICS/ESA server converts the lower-case letters to upper-case letters and re-displays the text string.

When the client runs as a CICS/ESA client, the server runs as a BEA TUXEDO server. Again, you enter a text string in lower-case letters. The BEA TUXEDO server converts the text string into a mirror image and displays the string as reversed letters.

Note: The verification process is intended for the CICS/ESA environment only, that is, between BEA TUXEDO applications and CICS/ESA applications. If your BEA TUXEDO applications operate in other environments, you must create your own verification process.

Building Your Verification Tests

You must build the verification test to run in two domains, the BEA TUXEDO local domain and the CICS/ESA remote domain. The executables in each domain are different. The following subsections discuss how to build these executables.

Building TUXEDO Executables

Use the following checklist to complete this process:

1. Modify the name of the simple server in the `UBBCONFIG` file provided.
2. Execute the `tmloadcf` command to compile the `UBBCONFIG` file.
3. Modify the required local and remote definitions in the `DMCONFIG` file provided.
4. Execute the `dmloadcf` command to compile the `DMCONFIG` file.
5. Modify the `apps.env` and `<machine>.env` environment files (optional).
6. Use the `buildserver` utility to build a server load module.
7. Use the `buildclient` utility to build a client load module.

Using the `buildserver` Utility

Use the BEA TUXEDO `buildserver` utility to build the `mirrorsrv` server load module from the source file `mirrorsrv.c` provided. The source file contains two service entries, `MIRROR` and `DOUBLEMIRROR`, which will be advertised by the `mirrorsrv` server.

When executed, the `MIRROR` service receives a text string from the client, reverses the letters, and displays a mirror image of the input text string.

When executed, the `DOUBLEMIRROR` service receives a text string from the client, reverses the letters, and concatenates the reversed string to the forward image of the string.

This is an example of a command entry to invoke the `buildserver` utility:

```
buildserver -o mirrorsrv -f mirrorsrv.c -s MIRROR,DOUBLEMIRROR
```

(Refer to the BEA TUXEDO *Reference Manual* for option descriptions.)

Using the buildclient Utility

Use the BEA TUXEDO `buildclient` utility to build a client load module from the source file `toupclt` provided. When executed, the load module sends a lower-case text string to the server, which converts it to uppercase in several modes, causing different server scenarios to execute. (Refer to the *BEA TUXEDO Reference Manual* for option descriptions.)

For example:

```
buildclient -o toupclt -f toupclt.c
```

Modifying the UBBCONFIG file

Include the name of the BEA TUXEDO simple server in the UBBCONFIG file.

```
GROUPS
GROUP3          LMID=sna  GRPNO=3

SERVERS
mirrorsrv       SRVGRP=GROUP3  SRVID=1  RQADDR=MIRR1  REPLYQ=Y

SERVICES
MIRROR
```

Enabling Transactional Services

If you plan to run the transactional version of the verification process, enable the `TLOGDEVICE` comment in the Machine section. This must point to a valid DTP transaction log. To run transaction examples, create the DTP transaction log named on the UBBCONFIG `TLOGDEVICE`. Create the log with the TUXEDO bulletin modification interpreter `tmadmin`. (Refer to the *BEA TUXEDO Reference Manual* for more details.)

The application server `GROUP3` in the Groups section must point to a valid transaction manager server. For example:

```
GROUPS
GROUP3          LMID=sna GRPNO=3 TMSNAME=tsttms

SERVERS
mirrorsrv       SRVGRP=GROUP3 SRVID=1 RQADDR=MIRRL1 REPLYQ=Y

SERVICES
MIRROR
```

Executing the tmloadcf Command

Execute the BEA TUXEDO `tmloadcf` command to parse the `UBBCONFIG` file and create a binary version of the file. (Refer to the BEA TUXEDO *Reference Manual* for more details.)

For example:

```
tmloadcf UBBCONFIG
```

Respond to the prompts as the command executes.

Modifying the DMCONFIG File

The `DMCONFIG` file must contain both local and remote definitions for the simple server.

Note: A sample `DMCONFIG` file is included with the simple server.

Listing 4-1 Sample DMCONFIG File

```
DM_LOCAL_SERVICES
#The Tuxedo reverse string server
MIRROR          LDOM="simpsnad"
                CONV=N
                RNAME="MIRRORSEV"
                INBUFTYPE="STRING"
                OUTBUFTYPE="STRING"
DOUBLEMIRROR
                CONV=N
                RNAME="MIRRDPLS"
                INBUFTYPE="STRING"
                OUTBUFTYPE="STRING"
DM_REMOTE_SERVICES
#The CICS upper-case DTP and DPL servers
```

```
SIMPDPL      AUTOTRAN=N
              LDOM="simpsnad"
              RDOM=SNAG1
              CONV=N
              RNAME="TOUPDPLS"
              INBUFTYPE="STRING"
              OUTPBUTYPE="STRING"
              FUNCTION="DPL"
SIMPDTP      AUTOTRAN=N
              LDOM="simpsnad"
              RDOM=SNAG1
              CONV=N
              RNAME="DTPS"
              INBUFTYPE="STRING"
              OUTPBUTYPE="STRING"
              FUNCTION="APPC"
```

In the preceding DMCONFIG file example, both instances of the LDOM name correspond to the SNA domain name in the DM_LOCAL_DOMAINS section. The server is a request/response server.

In the DM_LOCAL_SERVICES section, the RNAME="MIRRORserv" and RNAME="MIRRDPLS" values are the names passed from the CICS/ESA environment. MIRROR and DOUBLEMIRROR refer to the advertised services provided by the mirrorsrv server named in the UBBCONFIG file. The CONV=N definition indicates the protocol that is observed by the SNA domain, although the CICS/ESA client does not perform a TUXEDO ATMI tpcall.

In the DM_REMOTE_SERVICES section, the RNAME value identifies what is invoked in the CICS/ESA domain. For the *Distributed Program Link (DPL)* request, the RNAME equals the name of the *program* called (or for alternate mirror transaction identifiers, a TRANSID/program name combination). For the *Distributed Transaction Processing (DTP)* request, the RNAME equals the name of the *transaction id*.

If you want to run transactional verification tests, you must enter a link definition MAXSYNCLVL=2 in the DM_SNALINKS section. If you want to run non-transactional DPL tests only, you must enter MAXSYNCLVL=1.

Executing the dmloadcf Command

Execute the BEA TUXEDO `dmloadcf` command to parse the `DMCONFIG` file and create a binary version of the file. (Refer to the *BEA TUXEDO Reference Manual* for more details.)

For example:

```
dmloadcf DMCNFIG
```

Respond to the prompts as the command executes.

Modifying the Environment Files

Two types of files are provided with your eLink SNA product software which can be used to define the application and/or machine environments for verification testing. If their equivalents do not already exist, it is recommended you modify the files provided and make them available to your system. The files are `apps.env` and `<machine>.env`.

The `apps.env` File

Modify the `apps.env` file and include it with the `ENVFILE` parameter in the `MACHINES` section of the `UBBCONFIG` file. The `apps.env` file looks like this:

Listing 4-2 The apps.env File

```
#=====
# apps.env
#     Environment macros for tuxedo application testing.
#
# See also
#     See $(TOP)/Makefile for more information.
#
# @(#)SNA Devel apps/simpsna app.env 1.4 98/03/03 15:42:30
# Copyright 1997, BEA Systems, Inc., all rights reserved.
#-----
APPDIR=<Your application directory here>
TUXCONFIG=<Your Tux configuration here>
BDMCONFIG=<Your Domain configuration here>
TUXDIR=<Your Tuxedo directory here>
FLDTBLDIR32=<Your Tuxedo directory here>/lib
FIELDTBLS32=fmb.def
```

The <Machine>.env Files

Modify the <machine>.env file that is appropriate for your system:

- ◆ aix.env
- ◆ hpux.env
- ◆ solaris.env
- ◆ ntenv.bat

Each of these files is executable. Once you have modified the appropriate file for your system, execute it to export the machine environment variables. The files look like this:

Listing 4-3 The aix.env File

```
#=====
# aix.env
#      Environment macros for AIX testing.
#
# See also
#      See $(TOP)/Makefile for more information.
#
# @(#)SNA Devel apps/simpsna aix.env 1.2 98/02/23 12:39:36
# Copyright 1997, BEA Systems, Inc., all rights reserved.
#-----
export APPDIR=<Your application directory bin here>
export TUXCONFIG=<Your tuxedo configuration qualified name here>
export BDMCONFIG=<Your tuxedo domain configuration qualified name
here>
export TUXDIR=<Your tuxedo product directory here>
export STACK=<Your stack product library here>
#example STACK=/opt/SUNWappc or /opt/sna/lib
export FLDTBLDIR32=$TUXDIR/lib
export FIELDTBLS32=fmb.def
export PATH=$APPDIR:$TUXDIR/bin:$PATH
export LIBPATH=$TUXDIR/lib:$LIBPATH:$STACK
```

Listing 4-4 The hpux.env File

```

#=====
# hpux.env
#     Environment macros for HP-UX testing.
#
# See also
#     See $(TOP)/Makefile for more information.
#
# @(#)SNA Devel apps/simpsna hpux.env 1.3 98/02/23 12:38:34
# Copyright 1997, BEA Systems, Inc., all rights reserved.
#-----
export APPDIR=<Your application directory bin here>
export TUXCONFIG=<Your tuxedo configuration qualified name here>
export BDMCONFIG=<Your tuxedo domain configuration qualified name
here>
export TUXDIR=<Your tuxedo product directory here>
export STACK=<Your stack product library here>
#example STACK=/opt/sna/lib
export PATH=$APPDIR:$TUXDIR/bin:$PATH
export SHLIB_PATH=$APPDIR:$TUXDIR/lib:$SHLIB_PATH:$STACK

```

Listing 4-5 The solaris.env File

```

#=====
# solaris.env
#     Environment macros for SOLARIS testing.
#
# See also
#     See $(TOP)/Makefile for more information.
#
# @(#)SNA Devel apps/simpsna solaris.env 1.3 98/02/23 12:39:05
# Copyright 1997, BEA Systems, Inc., all rights reserved.
#-----
export APPDIR=<Your application directory bin here>
export TUXCONFIG=<Your tuxedo configuration qualified name here>
export BDMCONFIG=<Your tuxedo domain configuration qualified name
here>
export TUXDIR=<Your tuxedo product directory here>
export STACK=<Your stack product library here>
#example STACK=/opt/SUNWappc

```

```
export FLDTBLDIR32=$TUXDIR/lib
export FIELDTBLS32=fmb.def
export PATH=$APPDIR:$TUXDIR/bin:$PATH
export LD_LIBRARY_PATH=$TUXDIR/lib:$LD_LIBRARY_PATH:$STACK
```

Building CICS/ESA Executables

Use the following checklist to complete this process:

1. Choose either COBOL or C source.
2. Transfer source from SNA install directory to the PDS.
3. Translate CICS/ESA verbs.
4. Compile the translated source file.
5. Link-edit the compiled source file.
6. Configure the CICS/ESA application (similar to CICS LU configuration).
7. View the connection, session, or mode status.

Choosing the Source Code Language

The CICS/ESA sample programs used for verification are unloaded during the installation of your BEA eLink for Mainframe SNA product software. These programs are available in two languages, COBOL and C. You must choose which language is used to build the CICS/ESA executable object code. (Your choice might be affected by the type of compiler available on your MVS host.)

You can identify the sample program names by their suffixes:

- ◆ `TOUPDTPS.c` is the C language program name
- ◆ `TOUPDTPS.cbl` is the COBOL language program name (requires a compiler that accepts COBOL II verbs)

Although the structures of the sample programs are different, they both perform the same function. The BEA TUXEDO executable program that you build communicates with either.

Transferring the Source Code to Host

Transfer the source code to the host by the method you prefer, for example FTP (File Transfer Program). The destination could be sequential dataset or a PDS. Table 4-1 lists the source code files provided for UNIX and MVS platforms. The UNIX filename extensions suggest the type of destination libraries into which the source code may be transferred.

Table 4-1 Source Code Filenames

UNIX Filename	MVS Member Name
BEACONN.RDO	BEACONN
BEASNA.RDO	BEASNA
MIRRDPLC.<c> <cbl>	MIRRDPLC
MIRRDTPC.<c> <cbl>	MIRRDTPC
TOUPDPLS.<c> <cbl>	TOUPDPLS
TOUPDTPS.<c> <cbl>	TOUPDTPS

Translating CICS/ESA Verbs

This step translates the EXEC CICS verbs into program CALL statements of the form required by the selected source language. The source is read from the SYSIN dataset. The translated source program is written to the SYSPUNCH dataset. The translator listing is written to the SYSPRINT dataset.

Different translator modules are provided for different source languages. There are also language-specific parameters for the translation step. (Refer to the *IBM CICS/ESA Application Programming Guide* for additional translation options that might apply to your environment.)

The translator modules are installed in the CICS/ESA load datasets. This is indicated in the following examples by the CICSxxx.SDFHLOAD entry, where xxx is the CICS/ESA release number.

COBOL Language Translator Example

The translator module name in the following example is `DFHECP1$`. The parameter `COBOL2` indicates that a source module containing COBOL II verbs is to be translated.

Listing 4-6 COBOL Language Translator Example

```
//TRN EXEC PGM=DFHECP1$,  
//      PARM='COBOL2,NOS,CICS',REGION=256K  
//STEPLIB DD DSN=CICSXXX.SDFHLOAD,DISP=SHR  
//SYSIN DD DSN=YOUR.PDS(pgmname),DISP=SHR  
//SYSPRINT DD SYSOUT=*  
//SYSPUNCH DD DSN=&&SYSCIN,  
//          DISP=(,PASS),UNIT=SYSDA,  
//          DCP=BLKSIZE=400  
//          SPACE=(400,(400,100))
```

C Language Translator example

The translator module name in Listing 4-7 is `DFHEDP1$`. The parameter `C` indicates that a source module containing C verbs is to be translated.

Listing 4-7 C Language Translator Example

```
//TRN EXEC PGM=DFHEDP1$,  
//      PARM='C,NOS,CICS',REGION=256K  
//STEPLIB DD DSN=CICSXXX.SDFHLOAD,DISP=SHR  
//SYSIN DD DSN=YOUR.PDS(pgmname),DISP=SHR  
//SYSPRINT DD SYSOUT=*,  
//SYSPUNCH DD DSN=&&SYSCIN,  
//          DISP=(,PASS),UNIT=SYSDA,  
//          DCB=BLKSIZE=400  
//          SPACE=(400,(400,100))
```

Compiling the Translated Source File

The next step is to compile the translated source file &&SYSCIN. This step generates the following program modules in preparation for the link-edit step:

- ◆ TOUPDPLS (CICS server DPL module)
- ◆ TOUPDTPS (CICS server DTP module using CICS APIs)
- ◆ MIRRDPLC (CICS client DPL module)
- ◆ MIRRDTPC (CICS client DTP module using CPI-C verbs)

COBOL Compiler Example

Listing 4-8 shows a COBOL compiler example.

Listing 4-8 COBOL Compiler Example

```
//COB EXEC PGM=IGYCRCTL,REGION=GM,
//      PARM='NODYNAM,RENT,RES,APOST,MAP,XREF'
//STEPLIB DD DSN=SYS2.COB2.COB2COMP,DISP=SHR
//SYSLIB DD DSN=CICSXXX.SDFCOB,DISP=SHR
//SYSPRINT DD SYSOUT=*
//SYSIN DD DSN=&&SYSCIN,DISP=(OLD,DELETE)
//SYSLIN DD DSN=&&LOADSET,DISP=(MOD,PASS),
//      UNIT=&WORK,SPACE=(400,(20,20))
//SYSUT1 DD UNIT=WORK,SPACE=(460,(350,100))
//SYSUT2 DD UNIT=WORK,SPACE=(460,350,100))
//SYSUT3 DD UNIT=WORK,SPACE=(460,(350,100))
//SYSUT4 DD UNIT=&WORK,SPACE=(460,(350,100))
//SYSUT5 DD UNIT=&WORK,SPACE=(460,(350,100))
//SYSUT6 DD UNIT=&WORK,SPACE=(460,(350,100))
//SYSUT7 DD UNIT=&WORK,SPACE=(460,(350,100))
```

C Compiler Example

Compile and pre-link your C language source. The BEA eLink SNA installation library contains C language compiler examples. Listing 4-9 shows a C/MVS compiler example.

In this example, the external storage variables must be re-entrant in the load module for the CICS/ESA environment. Additionally, the C language source contains long variable and function names. The pre-link step must be run to resolve the long names and create reentrant variables from the compiled object. Perform the pre-link step, use the RENT option in the compile program, and use the compile output in the link-edit step.

Listing 4-9 C/MVS Compiler Example

```
//*-----
//* COMPILE STEP:
//*-----
//COMPILE EXEC PGM=CB310,REGION=2M,COND=(7,LT,TRN),
//      PARM=('OPT(1),LONGNAME,RENT,SOURCE')
//STEPLIB DD DSN=SYS1.SCEERUN,DISP=SHR
//      DD DSN=SYS1.SCBC3CMP,DISP=SHR
//SYMSGS DD DSN=SYS1.SCBC3MSG(EDCMSGE),DISP=SHR
//SYSIN DD DSN=&&SYSCIN,DISP=SHR **FROM TRN STEP
```

```
//SYSLIB      DD DSN=SYS1.SCEEH.H,DISP=SHR
//           DD DSN=SYS1.SCEEH.SYS.H,DISP=SHR
//           DD DSN=CICSxxx.SDFHC370,DISP=SHR**CPIC
//           REQUIRED**
//SYSLIN      DD DSN=PLNKSET,UNIT=VIO,
//           DISP=(MOD,PASS),SPACE=(TRK,(3,3)),
//           DCP=(RECFM=FB,LRECL=80,BLKSIZE=SYSLBLK)
//SYSPRINT    DD SYSOUT=*
//SYSOUT      DD SYSOUT=*
//SYSCPRT     DD SYSOUT=*
//SYSUT1      DD UNIT=VIO,SPACE=(32000,(30,30)),
//           DCB=(RECFM=FB,LRECL=80,BLKSIZE=3200
//SYSUT4      DD UNIT=VIO,SPACE=(32000,(30,30)),
//           DCB=(RECFM=FB,LRECL=80,BLKSIZE=3200
//SYSUT5      DD UNIT=VIO,SPACE=(32000,(30,30)),
//           DCB=(RECFM=FB,LRECL=80,BLKSIZE=12800
//SYSUT6      DD UNIT=VIO,SPACE=(32000,(30,30)),
//           DCB=(RECFM=FB,LRECL=80,BLKSIZE=12800
//SYSUT7      DD UNIT=VIO,SPACE=(32000,(30,30)),
//           DCB=(RECFM=FB,LRECL=80,BLKSIZE=12800
//SYSUT8      DD UNIT=VIO,SPACE=(32000,(30,30)),
//           DCB=(RECFM=FB,LRECL=80,BLKSIZE=12800
//SYSUT9      DD UNIT=VIO,SPACE=(32000,(30,30)),
//           DCB=(RECFM=FB,LRECL=137,BLKSIZE=882
//SYSUT10     DD SYSOUT=*
//           DCB=(RECFM=FB,LRECL=80,BLKSIZE=3200
//SYSUT14     DD UNIT=VIO,SPACE=(32000,(30,30)),
//           DCB=(RECFM=FB,LRECL=80,BLKSIZE=128007
//PLKED EXEC  PGM=EDCPRLK,COND=((7,LT,C),(7,LT,TRN)),
//           PARM=,REGION=2M
//STEPLIB     DD DSN=SYS1.SCEERUN,DISP=SHR
//SYSMMSG     DD DSN=SYS1.SCEEMSGP(EDCPMSG),DISP=SHR
//SYSLIB      DD DSN=LE370HLQ..SCEECP,DISP=SHR
//           DD DUMMY
//SYSIN       DD DSN=PLNKSET,DISP=(MOD,PASS)
//SYSMOD      DD DSN=LOADSET,DISP=(,PASS),
//           DCB=(RECFM=FB,LRECL=80,BLKSIZE=3200)
//SYSOUT      DD SYSOUT=*
//SYSPRINT    DD SYSOUT+*
```

Link-Editing the Compiled Source File

The next step is to take the compiled source and create the executable object. You should load the resulting object module into the application library that is concatenated with the CICS/ESA region datasets.

In the following COBOL and C program examples, `SYSLIN` is the name of the file containing the compiled source concatenated with other necessary executables, including interfaces for the CICS API verbs, interfaces for CPI-C verbs, and interfaces for SAA resource recovery verbs (sync-level 2).

In Listing 4-10, the module is linked as re-entrant and marked with 31-bit mode addressability. This is required for the module `MIRRDTPC` which performs CPI-C and SAA Resource/Recovery requests.

You must change the `NAME` to that of the executable being generated.

Listing 4-10 COBOL Link-Edit Sample for TOUPDPLS, TOUPDTPS, and MIRRDPLC

```
//LKED      EXEC PGM=IEWL,      * ** LINKAGE EDITOR **
//          PARM=AMODE=31,RENT,
//          REGION=512K//SYSPRINT DD SYSOUT=*
//SYSLIN     DD DSN=&&LOADSET,DISP=(OLD,DELETE)
//          DD *
INCLUDE SYSLIB(DFHECI)
ORDER DFHECI
NAME xxxxxxxx(R)
/*
//SYSLIB     DD DSN=CICSxxx.SDFHLOAD,DISP=SHR
//          DD DSN=CICSxxx.SDFHCOB,DISP=SHR
//          DD DSN=SYS1.SCEELKED,DISP=SHR
//          DD DSN=SYS1.SIGYCOMP,DISP=SHR
//SYSLMOD    DD DSN=application.loadlib,DISP=(SHR,PASS)
//SYSUT1     DD UNIT=VIOD,SPACE=(1024,(50,20))
//
```

Listing 4-11 COBOL Link-Edit Sample for MIRRDTPC

```
//LKED      EXEC PGM=IEWL,      * ** LINKAGE EDITOR **
//          PARM=AMODE=31,RENT,
//          REGION=512K//SYSPRINT DD SYSOUT=*
//SYSLIN     DD DSN=&&LOADSET,DISP=(OLD,DELETE)
//          DD *
INCLUDE SYSLIB(DFHECI)
INCLUDE SYSLIB(DFHCPLC)
INCLUDE SYSLIB(DFHCPLRR)
ORDER DFHECI
```

```

NAME xxxxxxxx(R)
/*
//SYSLIB      DD DSN=CICSxxx.SDFHLOAD,DISP=SHR
//            DD DSN=CICSxxx.SDFHCOB,DISP=SHR
//            DD DSN=SYS1.SCEELKED,DISP=SHR
//            DD DSN=SYS1.SIGYCOMP,DISP=SHR
//SYSLMOD     DD DSN=application.loadlib(xxxxxxxx),DISP=(SHR,PASS)
//SYSUT1      DD UNIT=VIOD,SPACE=(1024,(50,20))
//

```

Listing 4-12 C Link-Edit Sample

```

//LKED        EXEC PGM=HEWL,REGION=4M,
//            PARM='AMODE=31,RENT,
//            COND=((7,LT,C),(7,LT,PLKED),(7,LT,TRN))
//SYSLIB      DD DSN=CICSxxx.SDFHLOAD,DISP=SHR
//            DD DSN=SYS1.SCEELKED,DISP=SHR
//SYSLIN      DD DSN=&&LOADSET,DISP=(OLD,DELETE)
//            DD *INCLUDE SYSLIB(DFHELII)
//                INCLUDE SYSLIB(DFHCPLC)
//                INCLUDE SYSLIB(DFHCPLRR)NAME xxxxxxxx(R)
//
/*
//SYSLMOD     DD DSN=application.loadlib(xxxxxxxx),DISP=SHR
//SYSUT1      DD UNIT=VIOD,SPACE=(1024,(50,20))
//SYSPRINT    DD SYSOUT=*

```

Configuring the CICS/ESA Application

Your installed eLink SNA software contains two sample files that can be used to configure the CICS application:

- ◆ The **BEACONN** file contains the CICS/ESA configuration parameters to the host system. These include connection definitions and session definitions.
- ◆ The **BEASNA** file contains the application definitions that enable you to perform the installation verification in the CICS/ESA environment. These definitions are required to run the installation verification. They include the program definitions, transaction definitions, and for the CPI-C example, the partner definition.

Caution: The BEACONN file should only be added to the CICS/ESA System Definition (CSD) file if no definitions currently exist. Check with your system administrator.

One method of adding the files is to use the batch utility program DFHCSDUP. Listing 4-13 is an example of the *Job Control Language (JCL)* statements you can use to invoke DFHCSDUP as a batch program to add the BEASNA file:

Listing 4-13 JCL Example for Invoking DFHCSDUP

```
//YOURJOB JOB accounting info,name,MSGLEVEL=1
//STEP1 EXEC PGM=DFHCSDUP,REGION=512K,
//          PARM='CSD(READWRITE),PAGESIZE(60),NOCOMPAT'
//STEPLIB DD DSN=CICSxxx.SDFHLOAD,DISP=SHR
//DFHCSD DD UNIT=SYSDA,DISP=SHR,DSN=CICSxxx.DFHCSD
//SYSPRINT DD SYSOUT=A
//SYSIN DD DSN=YOUR.PDS(BEASNA),DISP=SHR
```

The definitions in the sample member use a eLink SNA *Resource Definition Online (RDO)* Group name. You may want to add these definitions to an existing RDO group, or you might consider adding them to your CICS/ESA start-up list if you plan to use them often. (This automatically installs the group on start-up of the CICS/ESA region.) To add the groups to the start-up list, un-comment the following statements in the sample RDO.

```
ADD GROUP(BEACONN) LIST(**YOURLIST**)
ADD GROUP(BEASNA) LIST(**YOURLIST**)
```

To manually install the groups after start-up of the CICS/ESA region, issue the following commands from a CICS/ESA terminal session.

```
CEDA I GROUP(BEACONN)
CEDA I GROUP(BEASNA)
```

BEACONN File: Connection definition

The BEACONN file includes a sample connection definition.

Note: The sample connection definition achieves the minimum requirements for a connection over which the installation verification can be executed. Do not rely on it to provide optimal performance. Consult the *CICS/ESA Resource Definition Guide* for information about adding options not included in the sample.

The name of the sample connection definition is BEA, located under the installation group name BEACONN. It looks like this:

Listing 4-14 Sample Connection Definition in BEACONN File

```
DEFINE CONNECTION(BEA)          GROUP(BEACONN)
DE(CONNECT SNA EXAMPLE RDO CONNECTION)
ACCESSMETHOD(VTAM)              PROTOCOL(APPC)
NETNAME(LUHP10A)
ATTACHSEC(LOCAL)                AUTOCONNECT(NO)
```

The `NETNAME` option must be changed to the LU name of the remote system as known by VTAM. The `ATTACHSEC` option indicates the level of attach-time user security required for the connection. `LOCAL` is the simplest security. The authorization of the user is taken to be that of the link itself, relying on the authorization validation provided by the remote security utility. `AUTOCONNECT` indicates when the connection is acquired. `NO` is required. This means that CICS does not attempt to bind sessions when the connection is established by the stack.

Note: It is required that the eLink SNA software acquire the connection and negotiate the bind when the eLink SNA software starts up.

To install the sample connection definition, put it in on the host in a separate group which does not contain existing connection. Use the `CEDA INSTALL` command, for example:

```
CEDA INSTALL GROUP(BEACONN)
```

BEACONN File: Session Definition

The BEACONN file also includes a sample session definition. When placed on the remote host, it defines the logical links by which the BEA TUXEDO local domain communicates with the remote host.

The name of the sample session definition is `BEATEST`, located under the installation group name `BEACONN`. It looks like this:

Listing 4-15 Sample Session Definition in BEACONN File

```
DEFINE SESSION(BEATEST)      GROUP(BEACONN)
      CONNECTION(BEA)
      DE(CONNECT SNA EXAMPLE RDO SESSION)
      PROTOCOL(APPC)          AUTOCONNECT(YES)
      MODENAME(**SMSNA100**)  MAXIMUM(**6**, **3**)
```

`AUTOCONNECT` indicates how the activation of the session is to be negotiated. `YES` enables the CICS/ESA host to negotiate its own winner sessions when the connection is bound. (Remember that it is required that the eLink SNA software acquire the connection instead of the CICS/ESA host. However, when the stack acquires the connection, it can only bind the number of sessions identified as its winners. Setting the `AUTOCONNECT` parameter to `YES` causes the host to bind winner sessions immediately when the connection is acquired. Otherwise, the host's outbound clients must wait for winner sessions to bind.)

Replace `**MODE**` with either a CICS/ESA-supplied mode name, such as `SMSNA100`, or with your own defined mode name. If another set of session definitions exist for the BEA connection, this mode name must be unique among all sets defined to the connection. The mode name corresponds to the VTAM `LOGMODE` name.

The `MAXIMUM` option defines the total number of sessions in the set and the total number of contention winner sessions. To verify the installation, the total number of winner sessions must include those for the host and the remote stack. The installation verification process allows both sides to execute as the client. The total number of local contention winner sessions plus remote contention winner sessions must equal the number of sessions. The local number of sessions must equal the remote number of sessions.

BEASNA File: Program Definition

The BEASNA file includes a sample program definition, shown in Listing 4-16. Replace the `LANGUAGE` variable `**LANG**` in the sample with either `C` or `COBOL` to identify the source type you have selected for the sample application.

Listing 4-16 Sample Program Definitions in BEASNA File

```
DEFINE PROGRAM(MIRRDPLC)      GROUP(BEASNA)
      DE(CONNECT SNA EXAMPLE CICS DPL CLIENT (MIRROR STRING))
      LANGUAGE(**LANG**)      DATALLOCATION(ANY)

DEFINE PROGRAM(MIRRDTPC)      GROUP(BEASNA)
      DE(CONNECT SNA EXAMPLE CICS DTP CLIENT (MIRROR STRING))
      LANGUAGE(**LANG**)      DATALLOCATION(ANY)

DEFINE PROGRAM(TOUPDTPS)      GROUP(BEASNA)
      DE(CONNECT SNA EXAMPLE CICS DTP SERVER (TOUPPER STRING))
      LANGUAGE(**LANG**)      DATALLOCATION(ANY)

DEFINE PROGRAM(TOUPDPLS)      GROUP(BEASNA)
      DE(CONNECT SNA EXAMPLE CICS DPL SERVER (TOUPPER STRING))
      LANGUAGE(**LANG**)      DATALLOCATION(ANY)
```

BEASNA File: Remote Program Definition

The BEASNA file also contains a sample remote program definition, shown in Listing 4-17. The program definition is used by the CICS DPL client to identify the remote system and service for the DPL request. Replace the REMOTESYSTEM variable ****CONNECTION ID**** in the sample with the name of the connection for the remote LU.

Listing 4-17 Sample Remote Program Definition in BEASNA File

```
DEFINE PROGRAM(MIRRDPLS)      GROUP(BEASNA)
      DE(CONNECT SNA EXAMPLE DPL REMOTE PROGRAM DEFINITION)
      LANGUAGE(C)              DATALLOCATION(ANY)
      REMOTESYSTEM(**CONNECTION ID**) REMOTENAME(MIRRDPLS)
```

BEASNA File: Transaction Definition

The BEASNA file also contains a sample transaction definition, shown in Listing 4-18.

Listing 4-18 Sample Transaction Definitions in BEASNA File

```

DEFINE TRANSACTION(DTPS      GROUP(BEASNA)
                DE(CONNECT SNA EXAMPLE CICS DTP SERVER)
                TASKDATALOC(ANY)      PROGRAM(TOUPDTPS)

DEFINE TRANSACTION(H1PL)     GROUP(BEASNA)
                DE(CONNECT SNA EXAMPLE CICS DPL CLIENT - SYNCLEVEL 1)
                TASKDATALOC(ANY)      PROGRAM(MIRRDPLC)

DEFINE TRANSACTION(H2PL)     GROUP(BEASNA)
                DE(CONNECT SNA EXAMPLE CICS DTP CLIENT - SYNCLEVEL 2)
                TASKDATALOC(ANY)      PROGRAM(MIRRDPLC)

DEFINE TRANSACTION(H0TP)     GROUP(BEASNA)
                DE(CONNECT SNA EXAMPLE CICS DPL CLIENT - SYNCLEVEL 0)
                TASKDATALOC(ANY)      PROGRAM(MIRRDTPC)

DEFINE TRANSACTION(H2TP)     GROUP(BEASNA)
                DE(CONNECT SNA EXAMPLE CICS DTP CLIENT - SYNCLEVEL 2)
                TASKDATALOC(ANY)      PROGRAM(MIRRDTPC)

```

BEASNA File: Partner Definition

The sample CICS/ESA client MIRRDTPC contains CPI-C verbs. The partner resource definition contains the CPI-C side information needed to allocate a conversation with the TUXEDO server. It contains the information about the remote LU and transaction program.

As shown in Listing 4-19, the `TPNAME` parameter identifies the transaction program that is invoked in the remote system. In this case, the name correlates to the `RNAME` value in the `DM_LOCAL_SERVICES` section of the `DMCONFIG` file. The `RNAME` there must match the `TPNAME` in the partner definition. (Notice in the sample `DMCONFIG` configuration file that a local service definition `MIRROR` exists. The `RNAME` in that definition matches the `TPNAME` in the sample partner definition.)

The profile resource definition can define conversation attributes, in particular `MODENAME`. In the sample, the `PROFILE` parameter can be replaced with a valid profile resource definition. The default profile name for the parameter is `DFHCICSA`. `DFHCICSA` is a CICS-delivered profile.

Use the `NETNAME` specified in the Connection definition of the remote LU (refer to “Creating Connections at the Remote Host”).

Listing 4-19 Sample Partner Definition in BEASNA File

```

DEFINE PARTNER(MIRRDTPS)      GROUP(BEASNA)
DE(CONNECT SNA EXAMPLE CICS DTP CLIENT USING CPIC VERBS
TPNAME(MIRRORSEV)           PROFILE(**DFHCICSA**)
NETNAME(**NETWORK NAME**)

```

Viewing Connection and Session Status

Once you have made the verification group definitions, you can view the status of connections and sessions using the following CICS/ESA system commands:

```

CEMT I CONN(BEA)              **view the status of the connection
CEMT I NET(**Netname**)       **View the status of the sessions
CEMT I MODENAME(**MODE**)     **View the status of the mode

```

Running the Sample Application

Now you are ready to validate the eLink SNA installation by running the sample application. At this stage, you should have completed the following prerequisites:

- ◆ Installed the BEA eLink for Mainframe SNA software
- ◆ Configured the BEA TUXEDO and eLink SNA local domains
- ◆ Configured the CICS/ESA remote domain
- ◆ Initialized the stack processes
- ◆ Booted the servers

The sample application contains several scenarios. When the client runs as a BEA TUXEDO client, the server runs as a CICS/ESA host. When the client runs as a CICS/ESA client, the server runs as a BEA TUXEDO server.

Running the Application from a TUXEDO Client

In this scenario, the `toupc1t` client performs a `tpcall` to the CICS/ESA host server. The server converts the text string you enter from lower-case to upper-case letters. The client may be run in transactional or non-transactional mode. The CICS/ESA server may be run as a DTP or DPL program

For example, enter the following command:

```
toupc1t -s 0 -t DTP "hello world"
```

where:

`-s (0|2)`

Application Sync-Level.

0 = none (default)

2 = Transactional.

`-t (DPL|DTP)`

Remote Server Program.

DPL = Distributed Program Link (default)

DTP = Distributed Transaction Program

`-h`

Help

“ “

Lowercase text string of up to 1915 characters.

If the BEA TUXEDO client successfully executes the command, it displays the text string in upper-case letters, for example:

```
"HELLO WORLD"
```

Running the Application from a CICS/ESA Client

The following paragraphs depict two scenarios for running the application from a CICS/ESA client.

CICS/ESA Client with CPI-C

In this scenario, the CICS/ESA client sends a text string to the eLink SNA simple server. The string is re-displayed on the client's screen in reverse order.

Enter either of the following commands:

H0TP <string>

H2TP <string>

where:

H0TP = CPI-C Application Sync-Level 0

H2TP = CPI-C Application Sync-Level 2

<string> is a text string up to 1915 characters long.

If the CICS/ESA client successfully completes the transaction, it displays the text string in reverse order, for example:

You enter:

H0TP "HELLO WORLD"

The system returns:

"DLROW OLLEH"

CICS/ESA Client with DPL

Two transactions are available to execute the same program for the DPL sample. One is a simple request/response with the required sync-level 1, the other is a transactional request/response with sync-level 2.

Enter either of the following commands:

H1PL <string>

H2PL <string>

where:

H1PL = DPL Application Sync-Level 1

H2PL = DPL Application Sync-Level 2

`<string>` is a text string up to 955 characters long.

If the CICS/ESA client successfully completes the transaction, it displays a reverse (or mirror) image of the text string concatenated to the input text string, for example:

You enter:

```
H1PL "HELLO WORLD"
```

The system returns:

```
"HELLO WORLD : DLROW OLLEH"
```

Running the Application from a CICS/VSE Client

The CICS/VSE sample applications are virtually identical to the CICS/ESA sample applications, except the file names have the `.vse` extension. The same scenarios for running the sample applications apply for both client categories. Other noteworthy differences are that minor syntax changes have been made in the sample applications to accommodate the CICS/VSE operating system and that CICS/VSE does not support a CPI-C interface.

CICS/VSE Sample Applications

The following is a list of the CICS/VSE sample applications:

- ◆ BEASNA.RDO.VSE
- ◆ MIRRDPLC.c.VSE
- ◆ TOUPDPLS.c.VSE
- ◆ TOUPDTPS.c.VSE
- ◆ TOUPDTPS.cbl.VSE

Other Considerations

Some FTP operations may result in mis-translation of C-language special characters. It may be necessary for you to edit the source file(s) and correct the mis-translations of brackets [] and parallel bar | | characters.

CSMI and CVMI use profile DFHCICST with the attribute INBFMH = NO. When using DTP transactions, you are required to set INBFMH = ALL; otherwise an ABEND AXFQ occurs.

CICS/VSE transactions should be defined with the security attribute RSLC=NO; otherwise an EIBRCODE (NOTAUTH) is returned to the client.

5 Administering the Application Domain

The topics in this section cover activities an administrator performs to maintain BEA eLink for Mainframe SNA applications. More details about these activities can be found in BEA TUXEDO documentation. Before attempting the activities, it is essential that you become familiar with BEA TUXEDO configuration procedures.

This section covers the following administration topics:

- ◆ Administration Facilities
- ◆ Security
- ◆ Data Translations
- ◆ General Usage Notes

Administration Facilities

The administrative interface for eLink SNA software has two components:

- ◆ The interface to the eLink SNA stack administration and configuration, which is dependent on the stack provider and thus cannot be covered in this guide. Refer to vendor publications for the stack(s) used in your environment.

- ◆ The interface to the administration and configuration of the BEA TUXEDO System portion of an eLink SNA application, which is provided by the command `dmadmin`, other shell-level commands, and by screens of the BEA TUXEDO *Graphical Administrative Interface*.

This subsection covers the following topics:

- ◆ The `dmadmin` Command Interpreter
- ◆ The SNACRM and PU 2.1 Servers
- ◆ The SNACRM Monitor
- ◆ Activating and De-Activating Links

The `dmadmin` Command Interpreter

The `dmadmin` interactive command interpreter is used for the administration of domain gateway groups defined for a BEA TUXEDO System/T application. It can operate in two modes, administration mode and configuration mode. Configuration mode allows you to change a configuration while the application is running. The `dmadmin` description in Appendix A, “Reference Pages,” of this guide has been edited to include material and new subcommands that apply specifically to the eLink SNA gateway.

Note: The following four `dmadmin` commands are not applicable to eLink SNA because transactions, in the BEA TUXEDO System sense, are not supported:

- ◆ `dsdmlog`
- ◆ `forgettrans`
- ◆ `indmlog`
- ◆ `printtrans`

New subcommands have been added to `dmadmin` to support the entry of userids and passwords in the domain security table. These new commands can be entered only as subcommands of `dmadmin`:

- ◆ `addumap [options]`
- ◆ `addusr (addu) [options]`
- ◆ `delumap [options]`

◆ `delusr (delu) [options]`

◆ `modusr (modu) [options]`

The reference pages for these subcommands and other /Domain commands have been modified for the eLink SNA product. Use Appendix A, “Reference Pages,” in preference to similar pages in the *BEA TUXEDO Reference Manual*.

The SNACRM and PU 2.1 Servers

The SNA Communications Resource Manager (SNACRM) is a server that communicates directly with the PU 2.1 server to provide SNA connectivity. These servers can be started manually or via the DMINIT server. In either case, the PU 2.1 server must always be started before the SNACRM. Both servers must be started before starting the associated SNA Domain gateway.

Starting the PU2.1 Server

Please refer to SNACRM in Appendix A, “Reference Pages,” of this guide for information about starting the PU2.1 server.

Starting the SNACRM

You can manually start the SNACRM from the command line or during `tmboot` with the DMINIT server. Before starting the SNACRM, you should specify it as a BEA TUXEDO server (refer to “Specifying the SNACRM as a BEA TUXEDO Server”). You can either start all SNACRM processes with a single DMINIT process or individually start each one with a DMINIT server that is defined to each gateway server group.

When you start SNACRM from the UNIX command line, the SNACRM Command Line Console puts its prompt in this window, and if exited, shuts down all of the active links. When started from DMINIT, the console is redirected to the null device. In this case, you can use the `xsnacrm` command to monitor the console and enable/disable tracing of SNACRM and the SNA stack.

Please refer to SNACRM in Appendix A, “Reference Pages,” of this guide for more detailed information.

Using DMINIT

Please refer to `SNACRM` in Appendix A, “Reference Pages,” of this guide for information about using `DMINIT`.

Specifying the `SNACRM` as a BEA TUXEDO Server

You should specify the `SNACRM` as a BEA TUXEDO server. This is recommended for all platforms because it ensures that start-up and shut-down of the `SNACRM` is controlled by the BEA TUXEDO commands `tmboot` and `tmshutdown`. To do this, you must enter parameters defining the `SNACRM` as a server in the `UBBCONFIG` file, then provide a script to perform the startup and shutdown of the specific group that contains the server.

Note: This is required if eLink SNA software is installed on a Windows NT platform or if it is used with the BEA TAP for IBM CICS system.

Enter the `UBBCONFIG` Parameters

To specify the `SNACRM` as a BEA TUXEDO server, provide the equivalent `UBBCONFIG` parameters shown in the example in Figure 5-1.

Figure 5-1 Example UBBCONFIG File Entries Specifying SNACRM as BEA TUXEDO Server

*GROUPS		*SERVERS	
SNAGRP	LMID=mysys GRPNO=4	DEFAULT:	CLOPT = "-A"
		DMADM	SRVGRP=LOCGRP SRVID=14
LOCGRP	LMID=mysys BRPNO=5	GWADM	SRVGRP=SNAGRP SRVID=14 REPLYQ=Y RESTART=N GRACE=0
		SNACRM	SRVGRP=SNAGRP SRVID=15 CLOPT="-A--//dalhps2:4452 SNAGRP" RESTART=Y RCMD=rstsnagrp GRACE=120 MAXGEN=2
		GWSNAX	SRVGRP=SNAGRP SRVID=16 RQADDR="SNADOM" REPLYQ=N RESTART=Y RCMD=rstsnagrp GRACE=120 MAXGEN=2

Write the Script

The executable script `rstsnagrp` should reside in the `APPDIR` and contain the following lines:

```
# Filename = rstsnagrp
tmshutdown -g SNAGRP
tmboot -g SNAGRP
```

The SNACRM Monitor

You can use the SNACRM monitor to set trace levels for a selected SNACRM and the associated APPC stacks. You also can observe link activity and display trace status, link status, and link statistics.

Note: The SNACRM monitor does not show trace data. This data is captured in a file under the /APPCDIR directory. Please contact BEA Customer Support for help in locating the trace file(s) and interpreting them.

The BEA eLink for Mainframe SNA product software includes two utilities which launch and execute the SNACRM monitor. The `xsnacrm` utility is designed for UNIX platforms and requires Motif libraries. The `jsnacrm` utility is designed for Windows NT platforms and supplies both a Java-based application and an applet.

The following discussion relates to the Windows NT-based SNACRM monitor only. Refer to `xsnacrm` in Appendix A, “Reference Pages,” for detailed information about the UNIX-based SNACRM monitor.

The BEA eLink for Mainframe SNA software CDROM contains the following files related to the `jsnacrm` utility:

- ◆ `bealogo.gif`
- ◆ `jsnacrm.html`
- ◆ `jsnacrm.jar`
- ◆ `moncrm.jar`
- ◆ `moncrm.x509`

Prerequisite for Running the JSNACRM Utility on an NT Platform

The `jsnacrm` utility is written in Java as both an application and an applet. The application launches and executes like any other Java application and can be set up so it is accessible from the Windows desktop. The applet launches and executes from a network browser, either Netscape Communicator 4.0x or Internet Explorer 4.0x.

In order to run both the application and the applet, you must first have the Java Development Kit (JDK) 1.1 installed on your system. You can download this kit from the following internet location:

<http://java.sun.com/products/jdk/1.1>

Running the Java Applet Version

The following paragraphs describe how to set up and run the Java applet version of the JSNACRM utility.

PREREQUISITES for RUNNING the JAVA APPLET VERSION

You must have either Netscape Communicator 4.0x or Internet Explorer 4.0x installed on your NT Windows system. You also must have the Java plug-in installed on your system. You can download this plug-in from the following internet location:

`http://java.sun.com/products/plugin`

Note: If the Java plug-in is not already installed on your system, when you attempt to open the `jsnacrm.html` file, the program prompts you for an automatic download of the plug-in by the browser.

Next, you must set up your system to accept code signed by the identity “moncrm.” To do this, perform the following steps:

1. Create the identity `moncrm` in your JDK 1.1 identity database. By entering the parameter `true`, you establish `moncrm` to be a trusted identity.
`jvakey -c moncrm true`
2. Import the `moncrm` certificate into your identity database. To associate the certificate with the identity, use the nickname `moncrm` as the first argument to the `jvakey` command.

`jvakey -ic moncrm %TUXDIR%\bin\moncrm.x509`

STARTING the JAVA APPLET

To start the Java applet in an existing browser, open the file:

`<tuxedo-path>\bin\jsnacrm.html`

To build a shortcut to start the Java applet using a separate instance of your network browser, enter the following command:

`<browser-pathname> %TUXDIR%\bin\jsnacrm.html`

RUNNING the JAVA APPLET VERSION

Set up your applet version to monitor either a local or a remote SNACRM. To do this, you make selections on the Java(TM) Plug-in Properties control panel. This control panel is automatically downloaded with the plug-in and is initiated from the Windows Start Programs pop-up menu. Refer to on-line documentation about the control panel at the following internet location:

`http://java.sun.com/products/plugin/1.1.1/docs`

Once the Monitor screen displays (Figure 5-2), you enter in the field at the top of the screen the address of the SNACRM you want to monitor.

To monitor a local SNACRM, select Applet Host from the Network access drop-down menu. Type the following in the Enter SNACRM Address panel:

`//localhost:port`

where:

`localhost`

Explicitly specifies the local host.

`port`

Specifies the port number of the SNACRM on the local host.

To monitor a remote SNACRM, select Unrestricted from the Network access drop down menu. Type the following in the Enter SNACRM Address panel:

`//remotehostname:address`

where:

`remotehostname`

Specifies the remote host.

`address`


Specifies the network address of the SNACRM on the remote host.

The GUI contains two screen areas that require user entry and four screen areas that display information about the SNACRM being monitored. Status messages are displayed at the bottom of the screen. The GUI screen functions are listed in Table 5-1 and shown in Figure 5-2.

Table 5-1 SNACRM Monitor Screen Functions

Display Section	Function
SNACRM Address	This is where you enter the address of the SNACRM to be monitored.
Selected SNACRM	Displays the name of the SNACRM at the address entered in the address field.
Trace Status	Displays the currently selected trace options.
Trace Options	<ul style="list-style-type: none"> ◆ Stop CRM Trace disables SNACRM tracing and closes the trace file, if it exists. ◆ Set Minimum CRM Trace establishes tracing of only major events. This level is sufficient only to determine the sequence of application conversations. ◆ Set Medium CRM Trace establishes minimum tracing plus tracing of all I/O buffers. ◆ Set Maximum CRM Trace establishes medium tracing plus tracing of all APPC verbs. ◆ Start APPC Stack Trace establishes tracing of the APPC stack. Generally shows the parameters and results of all API calls. Depending on the stack being used, other options such as vendor-specified environment variables also may have to be activated. May be selected along with any of the previous Trace Options. ◆ Stop APPC Stack Trace disables APPC stack trace, if established.
Link Status	Displays the current status of all remote links for the selected SNACRM. (Text may be scrolled.)
Link Statistics	Displays the current statistics for all remote links for the selected SNACRM. (Text may be scrolled.)
Message Line	Displays messages showing the either the results of automatic connection attempts or commands issued to change the trace options.

Figure 5-2 The SNACRM Monitor Running as an Applet on a Network Browser



Running the Java Application Version

The Java application version displays and operates identically to the applet version. Refer to screen definitions and functions discussed under “Running the Java Applet Version.”

To build a shortcut to start the Java application version, perform the following steps:

1. Enter the command:

```
java -classpath %ClassPath%;jsnacrm.jar jsnacrm
```

2. Start the application in the directory %TUXDIR%\bin so it can find its files.

To run from a command window, perform the following steps:

1. Change directory to %TUXDIR%\bin.

2. Enter the command:

```
java -classpath %ClassPath%;jsnacrm.jar jsnacrm
```

Activating and De-Activating Links

The eLink SNA gateway software provides a command line tool you can use to activate and de-activate links that have been defined in the DM_SNALINKS section of the DMCONFIG file. This tool consists of two commands and their associated parameters: `crmlkon` and `crmlkoff`.

Note: If a link to a remote host is de-activated and re-activated by the host, the eLink SNA software normally re-establishes the link automatically. If this does not occur, you can use the `crmlkon` command to re-establish the link.

Using the `crmlkon` Command

You can start one or more SNA links with this command. Use the following syntax:

```
crmlkon {-n} {hostname:port} {-v} {-i} {h} {linkname}...
```

where:

- n
indicates that the parameters immediately following are the hostname and port of the machine running the SNACRM where the linkname is located.
 - hostname:port
specifies the IP host name and port of the machine running the SNACRM where the linkname is located.
 - v
specifies that this command displays verbose output.
 - i
causes the command to ignore errors and attempt to start all links specified on the command line.
 - h
invokes a help screen which shows the syntax usage for this command.
 - linkname
specifies the link name(s) to start.
- Note:** There is no notification that the link(s) started with the `crmlkon` command are activated. Use the SNACRM monitor to verify a link is active. Refer to “The SNACRM Monitor.”

Using the `crmlkoff` Command

You can stop one or more SNA links with this command. Use the following syntax:

```
crmlkoff {-n} {hostname:port} {-v} {-I} {-h} {linkname}...
```

where:

- n
indicates that the parameters immediately following are the hostname and port of the machine running the SNACRM where the linkname is located. This is required.
- hostname:port
specifies the IP host name and port of the machine running the SNACRM where the linkname is located.
- v
specifies that this command displays verbose output.

- I** causes the command to ignore errors and attempt to stop all links specified on the command line.
- h** invokes a help screen which shows the syntax usage for this command.
- linkname** specifies the link name(s) to start.
- Note:** There is no notification that the link(s) stopped with the `crmlkoff` command are de-activated. Use the SNACRM monitor to verify a link is not active. Refer to “The SNACRM Monitor.”

Security

This subsection covers the following topics:

- ◆ Security Overview
- ◆ Where You Specify Security Parameters
- ◆ How To Administer Security

Security Overview


In order for any security checking to occur, the BEA TUXEDO Local Domain and the Host System must have security mechanisms in place. For the Local Domain, this is the Authorization Server. For the Host System, this is the External Security Manager. Figure 5-3 shows these elements.

There are four sections in two BEA TUXEDO configuration files in which you specify parameters bearing on Local Domain security. The two configuration files are DMCONFIG and UBBCONFIG.

Userid and password mapping between the Local Domain and the Host System also bears on security. There are five `DMADMIN` subcommands which you use to enter userids and passwords, set up mappings, remove mappings, remove userids and passwords, and modify passwords.

Caution: Mixed environment security is more complex than depicted in Figure 5-3. A domain without an operational security mechanism in place accepts all transaction requests by treating userids as “trusted users.” Refer to BEA TUXEDO documentation for more detailed information about domain security.

Figure 5-3 BEA eLink for Mainframe SNA Security Elements



Where You Specify Security Parameters

The configuration sections where security is specified are:

- ◆ `RESOURCES` section of the `UBBCONFIG` file
- ◆ `DM_LOCAL_DOMAINS` section of the `DMCONFIG` file
- ◆ `DM_SNALINKS` section of the `DMCONFIG` file
- ◆ `DM_ACCESS_CONTROL` section of the `DMCONFIG` file

UBBCONFIG File Security Parameters

The `RESOURCES` section in this file contains a `SECURITY` parameter which works in conjunction with the `SECURITY` parameter in the `DMCONFIG` file to establish how eLink SNA controls access to the BEA TUXEDO local domain. This parameter takes the form:

```
SECURITY = {value}
```

where `value` is:

`NONE`

No security is enforced (default)

`APP_PW`

Requires password authorization for BEA TUXEDO clients and administrative tools to connect to the local application.

`USER_AUTH`

Same as `APP_PW`, but additional authorization is required on a per-user basis.

`ACL`

Same as `USER_AUTH`, but additional access-control checks are done on service names, queue names, and event names. If no *Access Control Lists (ACL)* exists for a given name, access is granted.

`MANDATORY_ACL`

Same as `ACL`, but if no `ACL` exists for a given name, access is denied.

In most cases, the `UBBCONFIG` file has already been configured and you don't need to establish the `SECURITY` parameter settings, but examining this file enables you to ascertain how eLink SNA enforces security.

If this parameter is set to `NONE`, no security is enforced. If set to `APP_PW`, the local BEA TUXEDO domain's Authorization Server prompts for the application password. If set to `USER_AUTH`, `ACL`, or `MANDATORY_ACL`, the qualified security is enforced as specified.

DMCONFIG File Security Parameters

Three sections in the DMCNFIG file contain parameters affecting eLink SNA control of access to the BEA TUXEDO local domain:

- ◆ `DM_LOCAL_DOMAINS` section contains a `SECURITY` parameter which specifies the type of security enforced for the BEA TUXEDO local domain.
- ◆ `DM_SNALINKS` section contains a `SECURITY` parameter which records the security in effect for the host system.
- ◆ `DM_ACCESS_CONTROL` section contains local access control lists used by the BEA TUXEDO local domain to associate local resources with host systems permitted to have access to them.

Caution: Do not delete the DMCNFIG binary file before running the `dmlloadcf` command. Tables of remote users, remote passwords, and remote mappings are stored in this file. If deleted, all security information must be re-entered.

DM_LOCAL_DOMAINS section

The `SECURITY` parameter settings in this section work in conjunction with the `SECURITY` parameter in the `RESOURCES` section of the BEA TUXEDO local domain's UBBCONFIG file to establish how eLink SNA controls access to the BEA TUXEDO local domain. The parameter takes the form:

```
SECURITY = {value}
```

where `value` is:

`NONE`

No security is enforced.

`APP_PW`

No security is enforced.

`DM_USER_PW`

User and password security is enforced.

If this parameter is set to `NONE` or `APP_PW`, the local domain takes no action with regard to security. If this parameter is set to `DM_USR_PW`, the local domain enforces security according to the setting in the `UBBCONFIG` file (refer to “UBBCONFIG File Security Parameters”).

DM_SNALINKS section

This section of the `DMCONFIG` file is dedicated to eLink SNA parameters. It records the security in effect for the host system. It correlates to the values set for the `ATTACHSEC` parameter in the connection resource definition. In the following parameter definition, *remote* refers to the TUXEDO domain and *local* refers to the host system. The parameter takes the form:

```
SECURITY_TYPE = {value}
```

where `value` is:

LOCAL

Specifies that a user identifier is not to be supplied by the remote system. `LOCAL` is the default value.

IDENTIFY

Specifies that a user identifier is expected on every attach request. All remote users of a system must be identified to the remote external security manager.

VERIFY

Attaches a userid and valid password to the remote region. The userid and password are controlled by the region's external security manager.

PERSISTENT

Not fully supported. Functions the same as `VERIFY`.

MIXIDPE

Not fully supported. Functions the same as `VERIFY`.

The values `LOCAL` and `IDENTIFY` are roughly equivalent to `NONE` and `APP_PW` for the `SECURITY` parameter in the `DMCONFIG` file.

DM_ACCESS_CONTROL section

This section contains local *Access Control Lists (ACL)* used by the BEA TUXEDO local domain to restrict access by remote regions to local resources. (Refer to “Security Administration” in the *BEA TUXEDO Administrator’s Guide*.) Each entry consists of an `ACL_NAME` resource identifier along with a list of required parameters designating remote domains permitted to access the resource. If no entry exists for a local service, the service is accessible to all remote domains.

Security Setting Summary

The domain administrator can add or delete users from the domain security table in two ways: first, through data entry panels in the TUXEDO System administration Graphical Administrative Interface; second, by using the `dmadmin` command.

The combined settings of the `SECURITY` parameters in the `UBBCONFIG` and the `DMCONFIG` files have the following effects:

- ◆ When the `DM_LOCAL_DOMAINS` Security parameter is set to `NONE` or `APP_PW`, no action is taken by the eLink SNA gateway with regard to security.
- ◆ However, when the `UBBCONFIG` file Security parameter is set to `APP_PW`, the application password is validated by an `AUTHSVC` when clients join the application. The `AUTHSVC` is provided by the user application.

If security is to be enforced by both the local domain and the host system for each request inbound from the host system to the local domain, the following settings must be made:

- ◆ The `UBBCONFIG` file `SECURITY` parameter must be set to one of `USER_AUTH`, `ACL`, or `MANDATORY_ACL`;
- ◆ The `DMCONFIG` file `DM_LOCAL_DOMAINS` section `SECURITY` parameter must be set to `DM_USER_PW`
- ◆ The `DM_SNALINKS` `SECURITY` parameter must be set to `IDENTIFY` or `VERIFY`.

(Refer to Table 5-2 for a summary of the file settings required to achieve different security combinations for inbound requests from the host system.)

If security is to be enforced by both the local domain and the host system for each request outbound from the local domain, the following settings must be made:

- ◆ UBBCONFIG file SECURITY parameter must be set to one of USER_AUTH, ACL, or MANDATORY_ACL
- ◆ the DMCONFIG file DM_LOCAL_DOMAINS section SECURITY parameter must be set to DM_USER_PW
- ◆ and the DM_SNALINKS SECURITY parameter must be set to IDENTIFY or VERIFY

(Refer to Table 5-3 for a summary of the file settings required to achieve different security combinations for outbound requests from the local domain.)

For a request sent to the host system, the local principal userid is located in the domain security table and the associated remote userid, or userid and password, are put into the conversation start-up request before being sent over the LU6.2 conversation. (This occurs if SECURITY is set to IDENTIFY or VERIFY in the DM_SNALINKS section of the DMCONFIG file.)

For requests sent from the host system, the local domain extracts the remote userid, or userid and password, from the conversation start-up request and checks the domain security table. That table contains pairs of local principal userids and remote userids, maintained on a service-by-service basis. The remote userid is mapped to the local principal userid. The local principal userid and password are used for further Access Control List (ACL) checking, as specified in the UBBCONFIG file.

When a request is received from the host system, the local domain checks the DMCONFIG file ACL for the local service to see if requests from the remote domain are permitted. If the DMCONFIG file does not contain an ACL for the local service, the service is accessible to all requests.

Therefore, if the ATTACHSEC level for the connection definition in the host system is Identify or Verify, the DMCONFIG SECURITY parameter must be set to DM_USER_PW so that a userid and a password are sent on the conversation start-up requests.

Security Setting Summary Tables

Table 5-2 shows settings for the `SECURITY` parameters in the `UBBCONFIG` and `DMCONFIG` files required to achieve local domain and host system security combinations for inbound requests.

Note: Security setting combinations other than those shown in the tables will have unpredictable results.

Table 5-2 Security Setting Summary (Inbound Requests from Host System)

SECURITY COMBINATION		SETTINGS IN UBBCONFIG FILE	SETTINGS IN DM_LOCAL_DOMAINS SECTION of DMCONFIG FILE	SETTINGS IN DM_SNALINKS SECTION of DMCONFIG FILE	OUTBOUND USERID and PASSWORD ACTIVITY (UID/PW)
LOCAL DOMAIN	HOST SYSTEM				
NO	NO	SECURITY = NONE or APP_PW	SECURITY = NONE or APP_W	SECURITY= LOCAL	Not Applicable
YES	NO	SECURITY = USER_AUTH, ACL, or MANDATORY_ACL	SECURITY = NONE or APP_PW	SECURITY = LOCAL	Not Applicable
NO	YES	SECURITY = NONE or APP_PW	SECURITY = DM_USER_PW	SECURITY = IDENTIFY or VERIFY	INVALID
YES	YES	SECURITY = USER_AUTH, ACL, or MANDATORY_ACL	SECURITY = DM_USER_PW	SECURITY = IDENTIFY or VERIFY	UID or UID+PW checked by Host System

Table 5-3 shows settings for the `SECURITY` parameters in the `UBBCONFIG` and `DMCONFIG` files required to achieve local domain and host system security combinations for outbound requests.

Note: Security setting combinations other than those shown in the tables will have unpredictable results.

Table 5-3 Security Setting Summary (Outbound Requests from Local Domain)

SECURITY COMBINATION		SETTINGS IN UBBCONFIG FILE	SETTINGS IN DM_LOCAL_DOMAINS SECTION of DMCONFIG FILE	SETTINGS IN DM_SNALINKS SECTION of DMCONFIG FILE	INBOUND USERID and PASSWORD ACTIVITY (UID/PW)
LOCAL DOMAIN	HOST SYSTEM				
NO	NO	SECURITY = NONE or APP_PW	SECURITY = NONE or APP_W	SECURITY= LOCAL	Not Applicable
YES	NO	SECURITY = USER_AUTH, ACL, or MANDATORY_ACL	SECURITY = NONE or APP_PW	SECURITY = LOCAL	INVALID
NO	YES	SECURITY = NONE or APP_PW	SECURITY = DM_USER_PW	SECURITY = IDENTIFY or VERIFY	UID or UID+PW from Host System ignored
YES	YES	SECURITY = USER_AUTH, ACL, or MANDATORY_ACL	SECURITY = DM_USER_PW	SECURITY = IDENTIFY or VERIFY	UID or UID+PW checked by Local Domain

How To Administer Security

After setting up and/or checking the security settings for the BEA TUXEDO domain and the host system, you must relate the security information in both domains to each other. To do this, use the `addusr` and `addumap` subcommands provided with the `dmadmin` command interpreter.

Once the user security information in both domains is mapped, you can perform administration on the affected security files in each domain. To do this, use the `delumap`, `modusr`, and `delusr` subcommands.

The following paragraphs discuss how you enter these commands. Refer to Appendix A, “Reference Pages,” for detailed information about each subcommand.

Adding a Userid and Password

Use the `addusr` subcommand to add a BEA TUXEDO local domain's userid and password to the remote CICS/ESA domain's user and password file. Enter the following command:

```
addusr {-d} local_domain_id {-R} remote_domain_id {-u}  
remote_userid
```

where:

`-d`

Specifies the name of the local domain with which the userid and password are associated.

`-R`

Specifies the name of the remote domain to which the userid and password are to be added.

`-u`

Specifies the user name to be added. Enter the user's password when prompted.

Mapping a Userid

Use the `addumap` subcommand to map a local domain principal userid number to a remote domain user name. The userid must be added before it can be mapped (refer to "Adding a Userid and Password"). Enter the following command:

```
addumap {-d} local_domain_id {-R} remote_domain_id  
{-p} local_principal_userid {-u} remote_userid
```

where:

`-d`

Specifies the name of the local domain with which the userid is associated.

`-R`

Specifies the name of the remote domain to which the userid is mapped.

`-p`

Specifies the local principal userid number defined in the ACL.

-u
Specifies the remote user name as defined in the security application of the remote domain.

Removing a Userid's Mapping

Use the `delumap` subcommand to remove the mapping for a local domain principal userid to a remote domain user name. Enter the following command:

```
delumap {-d} local_domain_id {-R} remote_domain_id  
{-p} local_principal_userid {-u} remote_userid
```

where:

-d
Specifies the name of the local domain with which the userid is associated.

-R
Specifies the name of the remote domain to which the userid is mapped.

-p
Specifies the local principal userid number defined in the ACL.

-u
Specifies the remote user name as defined in the security application of the remote domain.

Deleting a Userid and Password

Use the `delusr` subcommand to remove a local BEA TUXEDO domain's user ID and password from the CICS/ESA remote domain's user and password file. The mapping for a userid must be removed before the userid can be removed (refer to "Removing a Userid's Mapping"). Enter the following command:

```
delusr {-d} local_domain_id {-R} remote_domain_id {-u}  
remote_userid
```

where:

-d
Specifies the name of the local domain with which the userid and password are associated.

- R Specifies the name of the remote domain from which the userid and password are to be deleted.
- u Specifies the user name to be deleted. Enter the user's password when prompted.

Modifying a Password

Use the `modusr` subcommand to modify a local BEA TUXEDO domain user's password recorded in a CICS/ESA remote domain's user and password file. Enter the following command:

```
modusr {-d} local_domain_id {-R} remote_domain_id {-u}  
remote_userid
```

where:

- d Specifies the name of the local domain with which the userid and password are associated.
- R Specifies the name of the remote domain in which the userid and password are to be modified.
- u Specifies the user name to be modified. Enter the user's password when prompted.

Data Translations

This section discusses the following aspects of data translation:

- ◆ Default Data Translation Rules
- ◆ Application-to-Host Communications
- ◆ Programming Language String Transformation
- ◆ Code Page Translation Tables

Default Data Translation Rules

The following subsections provide suggestions to help you develop VIEW definitions for input and output buffers and records. It also explains how string data and numeric data are treated by default in the eLink SNA environment.

If you do not specify string transformation (please refer to “Programming Language String Transformation”), the rules in Table 5-4 apply.

Table 5-4 Default Data Translation Rules

Field Type	Translation Rules
CARRAY	Passed without translation as sequences of bytes.
STRING and CHAR	Translated from ASCII to EBCDIC (If needed. Refer to “Programming Language String Transformation.”)
SHORT	Translated to S9(4)COMP
LONG	Translated to S9(9)COMP
FLOAT	Translated to COMP-1
DOUBLE	Translated to COMP-2

Note: BEA TUXEDO provides a field type named `dec_t` that supports decimal values within VIEWs. The gateway translates these fields into machine independent representations of packed decimals. For example, `dec_t(m,n)` becomes `S9(2*m-(n+1))V9(n) COMP-3`. Therefore, a decimal field with a size of 8,5 corresponds to `S9(10)V9(5) COMP-3`.

The translation rules between C and IBM/310 data types are listed in the following table.

Table 5-5 Data Translation Rules between C and IBM/370 Data Types

Remote Data Type	Description	View Field Type/Length
PIC X(n)	Alpha-numeric Characters	string / n
PIC X	Single Alpha-numeric Character	char
PIC X(n)	Raw Bytes	carray / n
PIC X	Single Numeric Byte	carray / 1
PIC S9(4) COMP	32-bit Integer	short
PIC S9(9) COMP	64-bit Integer	long
COMP-1	Single-precision Floating Point	float
COMP-2	Double-precision Floating Point	double
PIC S9((m+(n+1))/2)V9(n) COMP-3	Packed Decimal	dec_t / m,n

Strings and Numeric Data

When you create VIEW definitions for input and output records that are used by CICS/ESA applications, do not specify an extra position for the terminating NULL characters that are used in string fields.

For example, when a CICS/ESA application program expects 10 characters in an input record, specify 10 for that field, not 10 plus 1.

Note: Although eLink SNA software does not require strings to be null-terminated, it respects null termination. When the gateway software detects a null (zero) character within a string, it does not process any subsequent characters. To pass full 8-bit data that contains embedded null values, use a CARRAY type field or buffer.

The character set translations performed by eLink SNA are fully localizable, in accordance with the X/Open XPG Portability Guides. ASCII and EBCDIC translations are loaded from message files. Refer to “Programming Language String Transformation” for more information.

The eLink SNA software contains default behaviors which should meet the requirements of most English-language applications. However, you may find it necessary to customize tables. Refer to “Code Page Translation Tables” for more information.

Converting Numeric Data

You can convert numeric data into different data types easily, as long as you specify enough range in the intermediate and destination types to handle the maximum value needed.

For example, you can convert an FML field of double into a packed decimal field on the remote target system by specifying an appropriate `dec_t` type VIEW element.

In addition, you can convert numeric values into strings, vice versa. For example, while FML buffers do not directly support the `dec_t` type, you can place decimal values in string fields and map these to `dec_t` fields within VIEW definitions.

Application-to-Host Communications

Like other domain gateways, the eLink SNA gateway uses the BEA TUXEDO *Typed Buffer* to transmit and receive data. When communication is between an eLink SNA application and a remote host region, there are some special considerations.

Since the remote host application does not understand the typed buffer, the BEA TUXEDO application must communicate with the host application by using an aggregate data type known as a *record*. A record is a flat data area defined by a template that describes the data type and length of each field in the record.

The typed buffer must be represented to the host application as a record and the record must be represented to the BEA TUXEDO application as a typed buffer. In addition, string data must be in EBCDIC format for the host region and in ASCII format for the BEA TUXEDO application.

The data may be manipulated into the correct format by the BEA TUXEDO application or remote host application, or it may be formatted prior to transmission by the eLink SNA gateway. The service definitions in the DM_LOCAL_SERVICES and the DM_REMOTE_SERVICES section of the DMCONFIG file provide parameters to describe the typed buffer/record combination required for successful communications between the applications. These parameters are `INBUFTYPE` and `OUTBUFTYPE`.

The parameter definitions are made from the perspective of the receiver of the buffer, the BEA TUXEDO application which receives a typed buffer, or the remote host application which receives record data. That is, `INBUFTYPE` is used to format a typed buffer into a record for the remote host application; `OUTBUFTYPE` is used to format a host record into a typed buffer for the BEA TUXEDO application.

Buffers Going To The Remote Host Application

The BEA TUXEDO application buffer is a typed buffer that must be communicated to the remote host as a record containing aggregate data fields. The eLink SNA gateway looks at the service definition to determine what, if any, conversion must be applied to the data buffer. The service definition uses the `INBUFTYPE` in both the DM_LOCAL_SERVICES and DM_REMOTE_SERVICES section of the DMCONFIG file to describe the type of buffer manipulation.

INBUFTYPE Parameter Definition

`INBUFTYPE = type:subtype`

In this parameter definition, `type` must be one of the designated BEA TUXEDO typed buffers described in the following subsections.

The `subtype` value names a view and is required for certain BEA TUXEDO typed buffers.

Only one `type:subtype` may be entered for the `INBUFTYPE` parameter.

Data Conversion for STRING Typed Buffer

The null terminated string is converted to EBCDIC. The null character is part of the converted record.

Data Conversion for X_OCTET/CARRAY Typed Buffers

No data conversion is performed on these typed buffers. The BEA TUXEDO application or remote host application performs all conversion of data fields in the record. This includes all numeric and EBCDIC conversions.

These typed buffers are used when a data record cannot be described or converted using one of the other *strong* typed buffers. *Strong* means that eLink SNA can understand all data fields and perform the required data conversions.

These typed buffers are also options when the remote service expects many styles of data aggregation (multiple record types). The `INBUFTYPE` parameter is limited to one `type:subtype`.

Data Conversion for VIEW/VIEW32/X_C_TYPE/X_COMMON Typed Buffers

A subtype is required for these typed buffers. The subtype is the name of the view that describes the remote host record. The BEA TUXEDO buffer is converted from a C structure to the record, including EBCDIC conversion, using the compiled VIEW file. By default, the record is a COBOL structure, mapped by the remote host application using a COBOL copybook.

Data Conversion for FML/FML32 Typed Buffers

A subtype is required for these typed buffers. The subtype is the name of the view that describes the remote host record. The data in the typed buffer is *Field Manipulation Language (FML)* data. The eLink SNA converts the buffer to a record described by the view; this includes EBCDIC conversion.

The BEA TUXEDO buffer is converted from an FML typed buffer to a C structure using the subtype compiled VIEW file. The C structure is then converted to the record using the same subtype compiled VIEW file. By default, the record is a COBOL structure that is mapped by the remote host application using a COBOL copybook

Buffers Coming From The Remote Host Application

An aggregate data type known as a record is received from the remote host application. The record must be converted to a BEA TUXEDO typed buffer by eLink SNA before it is passed to the BEA TUXEDO application. eLink SNA looks at the service definition to determine what, if any, conversion must be applied to the host data buffer. The service definition uses the `OUTBUFTYPE` in both the `DM_LOCAL_SERVICES` and `DM_REMOTE_SERVICES` section of the `DMCONFIG` file to describe the host record, and how to convert the record to the BEA TUXEDO typed buffer.

OUTBUFTYPE Parameter Definition

`OUTBUFTYPE=type:subtype`

In this parameter definition, `type` must be one of the designated BEA TUXEDO typed buffers described in the following subsections. The `type` not only determines the typed buffer, but also describes the host record.

The `subtype` value names a view and is required for certain BEA TUXEDO typed buffers.

Only one `type:subtype` may be entered for the `OUTBUFTYPE` parameter.

Data Conversion for STRING Typed Buffer

The null terminated string is converted to ASCII. The converted string is moved to a BEA TUXEDO STRING typed buffer.

Data Conversion for X_OCTET/CARRAY Typed Buffers

No data conversion is performed on these typed buffers. The remote host application or the BEA TUXEDO application converts the data fields in the record. This includes all numeric and ASCII conversions.

These typed buffers are used when the data record cannot be described or converted using one of the other *strong* type buffers. *Strong* means eLink SNA can understand all data fields and perform the required data conversion.

These typed buffers are also options when the remote service expects many styles of data aggregation (multiple record types). The `OUTBUFTYPE` parameter is limited to one `type:subtype`.

Data Conversion for VIEW/VIEW32/X_C_TYPE/X_COMMON Typed Buffers

A subtype is required for these typed buffers. The subtype is the name of the view that describes the remote host record. The remote host record is converted to a BEA TUXEDO typed buffer. The compiled VIEW file is used to perform the data and ASCII conversion on the host record. By default, the host record is a COBOL data aggregate and the converted typed buffer is mapped by the BEA TUXEDO application using a C structure.

Data Conversion for FML/FML32 Typed Buffers

A subtype is required for these typed buffers. The subtype is the name of the view that describes the remote host record. The host record is converted to an FML buffer that is passed to the BEA TUXEDO application.

By default, the host record is a COBOL record aggregate data type. The data is converted to a C structure, including ASCII conversion, using the compiled VIEW file. This data is then converted to an FML buffer using the field definitions associated with the VIEW.

Data Conversion For DPL Services

The eLink SNA system supports remote CICS services as *Distributed Program Link (DPL)* programs, as described in “Introducing the BEA eLink SNA System.” The DPL support is performed as if the BEA TUXEDO service is a peer CICS/ESA service.

In a DPL program, the application is protected from all *Distributed Transaction Processing (DTP)*. The DPL application is a request/response service, with all data communication performed by the passing of a COMMAREA.

A basic DPL request API looks like this:

```
EXEC CICS LINK  
  
    PROGRAM ( )  
    DATALENGTH ( )  
    LENGTH ( )  
    COMMAREA ( )
```

In the preceding example, the requester sends the `COMMAREA` of `DATALength` size and the receiving application receives the `COMMAREA` data contents in a buffer the size of `Length`. The `DATALength` size might be smaller than the `Length` size, but the requester expects and receives the response in the original `COMMAREA` buffer the size of `Length`.

The difference between a DPL program and a BEA TUXEDO service is that a receiving BEA TUXEDO service can resize a reply buffer, while the DPL program expects a reply buffer of a designated size. Also, a BEA TUXEDO requester can receive a resized buffer in a buffer different from the original reply buffer.

eLink SNA performs the manipulation described in the following subsections to smoothly adjust to the requirements of both types of applications.

DPL Requests Originating From A TUXEDO Application

The eLink SNA software must determine what size `COMMAREA` the remote DPL service is expecting because there is no corresponding `Length` parameter on a BEA TUXEDO request.

To determine the `Length` value for a DPL request, the software uses the larger potential size of the `INBUFTYPE` or the `OUTBUFTYPE` parameter definitions, as described in Table 5-6.

The remote DPL application receives a buffer of `Length` size and returns a buffer of `Length` size.

Table 5-6 DPL Request Length Calculation

INBUFTYPE or OUTBUFTYPE	LENGTH CALCULATION
STRING/X_OCTET/ CARRAY	For these typed buffers, only the <code>INBUFTYPE</code> parameter definition is used to determine the <code>Length</code> .
VIEW/VIEW32/ X_COMMON/ X_C_TYPE	<code>Length</code> is the maximum size of the <code>VIEW</code> file. This calculation takes in the potential size of both the C structure and the target record.
FML/FML32	The maximum size of the <code>VIEW</code> file. This calculation takes in the potential size of both the C structure, and the target record. The length of the FML buffer is not taken into account.

If no `LENGTH` can be determined, then the largest value allowed by the CICS application is allocated. Refer to the “General Usage Notes” section.

DPL Requests Originating From a CICS DPL

The eLink SNA software receives a `LENGTH` value and `COMMAREA` data of `DATALLENGTH` size from the requesting CICS DPL. The software allocates a buffer of `LENGTH` size and moves the `COMMAREA` data into this buffer before performing the conversions.

Programming Language String Transformation

When considering the interaction between TUXEDO and host applications, you must attend to the programming languages in which the applications are written. A character string is represented differently in the COBOL language than in the C language and associated TUXEDO VIEW buffer. This is shown in Listing 5-1, which demonstrates the three ways that the same two strings are coded (`string1` and `string2`).

Listing 5-1 Three Representations of Strings

C Structure:

```
struct text
{
    char    rbufsize[5];
    char    testnum[2];
    char    sendnum;
    char    sysid[4];
    char    textfld[10];
    char    string1[10];
    char    string2[16];
};
```

VIEW text

#type	cname	fbname	count	flag	size	null
char	rbufsize	-	5	-	-	-
char	testnum	-	2	-	-	-
char	sendnum	-	1	-	-	-
char	sysid	-	4	-	-	-
char	textfld	-	10	-	-	-
string	string1	-	1	-	10	-

```
string          string2          -          1          -          16          -
END
```

COBOL Record

```
01  TEXT.
    05  RBUFSIZE  PIC X(5) .
    05  TEXTNUM   PIC X(2) .
    05  SENDNUM   PIC X.
    05  SYSID     PIC X(4) .
    05  STRING1   PIC X(9) .
    05  STRING2   PIC X(15) .
```

The listing shows that, in the C structure and VIEW buffer, the sizes of `string1` and `string2` are represented as 10 and 16 characters, respectively. However, in the COBOL record, the sizes are 9 and 15 characters, respectively. This incompatibility can cause code misalignment between C and COBOL programs if not anticipated in the source code.

To avoid such incompatibilities, the eLink SNA gateway provides a software switch to control the mapping of string data between C and COBOL applications. This switch enables you to automatically compensate for the differences in null termination and padding characteristics of the two languages.

Note: The switch operates on string fields in TUXEDO VIEW buffers only. STRING buffers are not affected by this switch.

Setting the Switch to Perform String Transformation

To set the switch, use the `CLOPT` parameter when you configure the gateway server definition in the `UBBCONFIG` file. If you set the `-t` option of the `CLOPT` parameter to one of the values listed in Table 5-7, the gateway performs the corresponding string transformation. Use the following syntax format:

```
CLOPT="-- -t {number}"
```

where:

`CLOPT`

specifies the TUXEDO parameter which enables you to provide command-line options in a server definition.

- marks the end of system-recognized arguments and the start of arguments passed to a subroutine within the server. This option is required if you supply application-specific arguments, such as the `-t` option, to the server.
- `-t` is the eLink SNA option to establish C-to-COBOL string transformation.
- `number` indicates the type of string transformation the gateway performs (see Table 5-7).
- Note:** If you do not set the `-t` option of the `CLOPT` parameter in your server definition, by default the eLink SNA gateway performs no string transformation.

Table 5-7 C to COBOL String Transformation

CLOPT -t Parameter Value	TUXEDO Application Language	Host Application Language
Not Set	No string transformation established	
1	C	COBOL
2	COBOL	C
3	C	C
4	COBOL	COBOL

How the Switch Works

Option value 1:

For outbound messages to the host, C string fields are converted to COBOL string fields. All available characters, up to the defined length of the string and beginning with the null character, are converted to spaces and the length of the field is reduced by one.

For inbound messages from the host, COBOL string fields are converted to C string fields, trailing blanks are converted to null characters (zero value) and the length of the field is increased by one.

Option value 2:

For outbound messages to the host, COBOL string fields are converted to C string fields, trailing blanks are converted to null characters (zero value) and the length of the field is increased by one.

For inbound messages from the host, C string fields are converted to COBOL string fields. All available characters, up to the defined length of the string and beginning with the null character, are converted to spaces and the length of the field is reduced by one.

Option values 3 and 4:

No string transformations are made between programs written in compatible languages.

Example

The following is an example of a server definition using the switch to establish string transformations between a TUXEDO application written in C and a host application written in COBOL.

```
*SERVERS
```


```
GWSNAX SRVGRP=GROUP1 SRVID=5 CLOPT="-A -- -t 1"
```

Code Page Translation Tables

The eLink SNA software includes translation tables which enable conversions between ASCII character sets and EBCDIC character sets. This gives you 12 standardized tables to facilitate operations between TUXEDO applications using the Latin-1 ASCII code set (CP-00819) and host applications using a national language code set.

Note: Code Page Translation Tables are not supported for WebLogic Enterprise 4.0.

Each translation table consists of two mapping tables, one for outbound conversions (TUXEDO to host) and one for inbound conversions (host to TUXEDO). You do not have to specify the direction of a translation. All you have to determine is the national language in which the host application is written. Figure 5-4 illustrates code page translation.

Figure 5-4 eLink SNA Code Page Translation

The figure demonstrates how a TUXEDO application using the Latin-1 ASCII code page CP-00819 character set operates with a host application using German EBCDIC code page CP-00273. The eLink SNA translation table 00819x00273 provides both the inbound and outbound conversions.

Specifying a Translation Table

To designate the translation table for your applications, make an entry in the TUXEDO DMCONFIG file definition for each remote domain. Use the CODEPAGE parameter with the following format:

```
*DM_LOCAL_DOMAINS
{ldom} TYPE={type}

*DM_REMOTE_DOMAINS
{rdom} TYPE={type} CODEPAGE={cpname}
```

where:

`ldom`

is used to identify the local domain. `ldom` must be unique across both local and remote domains.

`type`

is used for grouping local and remote domains into classes. `TYPE` can be set to one of the following values: `TDOMAIN`, `OSITP` or `SNAX`.

`rdom`

is used to identify a remote domain. `rdom` must be unique across both local and remote domains.

`cpname`

is used to identify the translation table for the remote domain, from Table 5-8.

Note: The DMCONFIG file entries in the previous format description are intended for example only. All required entries are not shown. Refer to `dmconfig` in Appendix A for complete syntax requirements.

Table 5-8 lists the translation tables provided with eLink SNA software.

Table 5-8 eLink SNA Code Page Translation Tables

Country	File Name	ASCII Code Set	EBCDIC Code Set
TUXEDO default ¹	TUXEDO	TUXEDO-ASCII	TUXEDO-EBCDIC
United States	00819x00037	CP-00819 ²	CP-00037
Great Britain	00819x00285	CP-00819	CP-00285
France	00819x00297	CP-00819	CP-00297
Portugal	00819x00860	CP-00819	CP-00860
Spain	00819x00284	CP-00819	CP-00284
Belgium	00819x00500	CP-00819	CP-00500
Germany	00819x00273	CP-00819	CP-00273
Finland	00819x00278	CP-00819	CP-00278
Sweden	00819x00278	CP-00819	CP-00278

Latin-1	00819x01047	CP-00819	CP-01047
Latin-2	00912x00870	CP-00912	CP-00870

1. The default TUXEDO ASCII and EBCDIC code pages are slightly different than CP-00819 and CP-00037.
2. CP-00819 is exactly equivalent to ISO-8859-1 (also called Latin-1 ASCII), and is used as the ASCII code page in all of the countries listed in this table.

How the Translation Tables Work

The eLink SNA translation tables are based on IBM-defined code sets. At start up, the eLink SNA gateway loads a translation table for each remote domain.

You can modify any of the tables to suit your application translation needs, except the default TUXEDO tables, which are hard-coded. Refer to Appendix F, “Code Page Translation Tables” for detailed table contents. You must restart the gateway to change any translation table definitions.

Note: Replicas of the default TUXEDO translation tables are included with your product software. These are provided for you to modify, if desired. They are not the actual default tables. You cannot modify the default TUXEDO tables.

The eLink SNA translation tables are located in the following sub-directory:

`$TUXDIR/udataobj/codepage`

If no `CODEPAGE` specification is made for a remote domain, the eLink SNA software uses the TUXEDO default translation tables. If the software cannot find the translation table file, it generates a message `2241:ERROR Unable to access codepage table with a reason code` and the gateway fails to start. (Refer to this message in Appendix D, “Error Messages” for explanations of the reason codes.) If the software cannot read the translation table file, it generates an `Invalid or Corrupt` message and the gateway fails to start. If the software cannot read a translation table file because of access permission, it generates a `Permission Denied` message and the gateway fails to start.

Example

Listing 5-2 depicts entries defining one local domain (CIXA) and two remote domains (CISA and IMSA). In all cases, it is assumed that the local domain uses ASCII code page CP-00819. In the example, the two remote domains use the German and French EBCDIC code pages CP-00273 and CP-00297, respectively.

Listing 5-2 Code Page Definition Example

```
# DMCONFIG  
  
*DM_LOCAL_DOMAINS  
  
CIXA TYPE=SNAX  
  
*DM_REMOTE_DOMAINS  
  
CISA TYPE=SNAX CODEPAGE=00819X00273  
  
IMSA TYPE=SNAX CODEPAGE=00819X00297
```

The eLink SNA translation table 00819x00273 is based on the IBM defined code set CP-00819 for ASCII and the German EBCDIC code page CP-00273. The eLink SNA translation table 00819x00273 is based on the IBM defined code set CP-00819 for ASCII and the French EBCDIC code page CP-00297.

General Usage Notes

The current size limit of remote host messages is limited to approximately 32K bytes. Any conversions resulting in records larger than 32756 bytes are not supported.

6 Programming Considerations

This section covers the following topics:

- ◆ Overview
- ◆ APPC/IMS Programming
- ◆ CICS/ISC Programming
- ◆ Application-to-Application Programming

Overview

This chapter is intended for application programmers who implement and integrate BEA TUXEDO and host enterprise applications using *Application Program-to-Program Communication (APPC)*. Although primarily oriented toward BEA TUXEDO application developers, it is also useful for non-TUXEDO application developers seeking to understand the relationship between the environments.

BEA eLink for Mainframe SNA software gives BEA TUXEDO applications access to host APPC programs acting as servers. At the same time, APPC applications can act as clients and access BEA TUXEDO system services. Because the client and server programs must be written for separate and very different environments, eLink SNA allows the applications to be written using native programming facilities:

- ◆ The application programmer in a BEA TUXEDO environment uses the familiar *Application-Transaction Monitor Interface (ATMI)* primitives in the application code. Service requests can be made to the eLink SNA Domain gateway just as they would be made to any other BEA TUXEDO system server or gateway.
- ◆ The application programmer in the CICS/ESA environment can use CICS APPC API verbs. In addition, the programmer can use *Distributed Program Link (DPL)* techniques as either a client or server.
- ◆ The application programmer in the APPC environment can use *Customer Information Control System/Extended System Architecture (CICS/ESA)* verbs for SNA-based applications.
- ◆ The application programmer in the *Information Management System (IMS)* environment can use implicit IMS verbs.

Programmers in each environment can continue to use the tools with which they are familiar to develop application software. It is not important that a programmer be well versed in the programming facilities of the other environments. What is important, however, is proper coordination between the applications running in each environment.

This chapter explains the various options offered by the eLink SNA domain and illustrates the most effective ways to implement these options.

APPC/IMS Programming

The eLink SNA system supports non-transactional IMS servers using either the implicit APPC support for IMS or the explicit APPC interface using APPC/MVS calls from a user application.

Implicit APPC is similar and more convenient than the CICS/ESA DPL. Any IMS program that gets from and puts messages to the IMS message queue can be used without change as either a client or server.

Note: BEA eLink for Mainframe SNA does not currently support CONFIRM and SYNCPOINT IMS operations. When specifying synchronization levels for IMS operations, you must use MAXSYNCLVL=0 (none) in the DM_SNALINKS section of the DMCONFIG file. That is the default.

To use the implicit APPC capabilities of IMS, you must modify the APPCM file in the SYS1.PARMLIB library provided with your eLink SNA software. The configuration parameters in this file associate the LU with the IMS scheduler. You must identify the LU representing the application name used by eLink SNA to access the IMS region and the IMS system ID which provides scheduling for inbound requests. It is important to discuss with mainframe support personnel the changes you make to the APPCM file.

In Listing 6-1, the VTAM application major node is designated to be MVSLU01 and the scheduling facility is designated to be the IMS control region IVP4.

Listing 6-1 APPCM File in SYS1.PARMLIB Library (Example Only)

```

SYS1.PARMLIB (APPCMxx)

LUADD ACBNAME(MVSLU01) BASE TPDATA(SYS1.APPCTP),
SCHED( IVP4),
SIDEINFO DATASET(SYS1.APPCSI)

SYS1.VTAMLST(MVSLU01)

MVSLU01 APPL  ACBNAME=MVSLU01,          ACBNAME FOR APPC          C
              APPC=YES,                  C
              AUTOSSES=3,                 C
              DDRAINL=NALLOW,             C
              DLOGMOD=APPCHOST,            C
              DMINWNL=3,                  C
              DMINWNR=3,                  C
              DRESPL=NALLOW,              C
              DSESLIM=6,                  C
              LMDENT=19,                   C
              MODETAB=APPCTAB,             C
              PARSESS=YES,                 C
              SECACPT=CONV,                C
              SRBEXIT=YES,                 C
              VPACING=1

```

The job which starts the IMS subsystem should have the APPC parameter set to Y. The example in Listing 6-2 illustrates such a job, but is not intended to be used under actual conditions. Use your own custom job for starting IMS.

Listing 6-2 IMS Subsystem Start Job (Example Only)

```
) IVP51F41 EXEC,PROC=IMSFP,TIME=(1440),,
      AGN=IVP,                AGN NAME
      SOUT='*',              SYSOUT CLASS
      MBR=DFSIVAG,           PROGRAM NAME
      PSB=DFSIVPG,          PSB      NAME
      NBA=06,                INITIAL FAST PATH DB BUFFERS
      OBA=05,                SECONDARY FAST PATH DB BUFFERS
      TLIM=10,              IFP TERMINATION LIMIT
      SOD=,                  SPIN-OFF DUMP CLASS
      IMSID=IVP4,           IMSID OF IMS CONTROL REGION
      APPC=Y,               ENABLE IMPLICIT APPC
      PREINIT=DC            PROCLIB DFSINTXX MEMBER
```

CICS/ISC Programming

This subsection covers the following topics:

- ◆ About CICS/ISC
- ◆ Multi-Region versus Multi-Processor Operations
- ◆ ISC Operations
- ◆ Time-out and Error Handling

About CICS/ISC

The CICS/ESA Intersystem Communications (ISC) facility permits multiple independent CICS/ESA systems, normally executing on different hosts and possibly different computing platforms, to cooperate while performing various computing tasks.

CICS/ESA defines a set of five distinct services with ISC as a common foundation:

- ◆ Asynchronous Processing (AP)
- ◆ Function Request Shipping (FRS)
- ◆ Transaction Routing (TR)
- ◆ Distributed Program Link (DPL)
- ◆ Distributed Transaction Processing (DTP)

The first four ISC services are categorized as *implicit*. These services are not used directly by user-written CICS/ESA applications, but are employed indirectly and automatically by the CICS/ESA system on behalf of them. The services are supported between peer CICS/ESA systems; for example, between two mainframe CICS/ESA systems connected by an ISC link. Currently, eLink SNA software supports DPL for BEA TUXEDO.

DTP, on the other hand, is an *explicit* service that can be used by CICS/ESA applications to cooperatively distribute business functionality. The eLink SNA software supports DTP services between peer CICS/ESA systems, as well as between CICS/ESA systems and non-CICS/ESA systems (for example, a DTP application conversing with an APPC/MVS application). The eLink SNA software also supports DTP for BEA TUXEDO ATMI applications.

Multi-Region versus Multi-Processor Operations

CICS/ESA applications may also use another form of intersystem communication, called Multi-Region Operation (MRO). MRO is typically used to improve the performance of a CICS/ESA system by partitioning it into multiple, physically distinct regions.

MRO can be compared to a BEA TUXEDO Multi-Processor (MP) environment. In a two-platform MP application domain, the first platform might be dedicated to handle terminal and workstation clients, and the second platform might be dedicated to handle the application logic and file services. In a similar MRO configuration, all terminals might be placed in one CICS/ESA region (called a terminal-owning region), and applications and data stores might be placed in another CICS/ESA region (called an application-owning or file-owning region).

The biggest difference between this MP environment and the MRO configuration is that the MP environment spans multiple platforms, whereas the MRO configuration resides on a single host.

The eLink SNA software does not relate directly to the MRO single platform nature. However, it does support ISC operations.

ISC Operations

The ISC facility provides a mechanism for multiple CICS/ESA systems operating on different host computers to communicate with each other, but ISC is more than a simple communications mechanism. It implements a well-defined set of protocols by which connected CICS/ESA systems cooperate in the execution of recoverable, distributed units of work. This important concept is fundamental to understanding the relationship between connected CICS/ESA systems.

IBM's Systems Network Architecture (SNA) defines the protocols for communications between IBM systems in a multi-system environment. ISC is an implementation of a specific SNA protocol known as Advanced Program-to-Program Communications (APPC, also referred to as LU TYPE 6.2 or LU 6.2).

The ISC for APPC is not a strict implementation of the SNA architecture specification. In particular, CICS/ESA makes use of special Function Management Headers (FMH) which are not part of the SNA architecture specification. Other deviations are documented in the *IBM Distributed Transaction Programming Guide*.

Although ISC can be used to connect CICS/ESA systems residing on a single host computer, ISC is normally used to connect CICS/ESA systems which reside on physically-distinct host computers. Furthermore, systems which are geographically separated may be connected.

IBM's Advanced Communication Facility / Virtual Telecommunications Access Method (AFC/VTAM) is used to define and implement a logical connection between two CICS/ESA systems. Using the VTAM facilities, CICS/ESA systems establish one or more concurrent sessions for communications. Each session supports one logical conversation between the two systems. These logical conversations carry the inter-system traffic associated with the various ISC functions.

Similar to BEA TUXEDO conversational service requests, LU 6.2 is a half-duplex protocol; that is, session traffic can flow in only one direction at a time. The session partners are responsible for coordinating their use of the session such that when one is sending, the other is receiving. Both session partners cannot send (or receive) at the same time.

Asynchronous Processing

This ISC service allows an application to start a transaction on a remote system. Unlike DPL and Function Request Shipping, the calling application does not wait for the remote task to complete. The calling transaction initiates an asynchronous process with the CICS/ESA interval START command. Information can be passed to the back-end transaction in the FROM option of the START COMMAND. The back-end transaction can then issue a RETRIEVE command to get this data. The transaction can be defined as remote, indicating the system on which the transaction is to be run, or the remote system can be named explicitly in the SYSID option of the START command.

Function Request Shipping

Remote resources, such as VSAM files, DLI requests, Transient Data Queues, and Temporary Storage Queues can be made available to a local application. The application is not necessarily aware that the requested resource is on another CICS/ESA region. Files and Queues are defined as remote with system administration utilities, but could optionally be specified as remote using the SYSID option of the resource request command.

Transaction Routing

Transaction routing provides a terminal connected to a CICS/ESA region with the ability to run a transaction on another CICS/ESA region in a fashion transparent to the terminal user. A transaction can be defined as a remote transaction in the system initialization table. This definition indicates on which remote system the transaction is to run.

Distributed Program Link


Distributed Program Link (DPL) allows a CICS/ESA program to call (link to) another CICS/ESA program located on a remote system. This is a synchronous process; control does not return to the calling program until the called program has finished executing. See Figure 6-1 for a generic example of the DPL process.

In most cases, DPL is completely transparent to both the calling and called programs. An application program is not aware that it is calling a program located on a remote system.

The remote program is minimally constrained. It can access files and databases, as well as link to other programs, but it cannot perform terminal I/O. Also, it does not provide recovery and restart of CICS/ESA-controlled resources, such as files and databases; implicit support is provided automatically by the CICS/ESA system.

Note: If a client sends a data buffer to a remote CICS/ESA system as part of a DPL and no data is modified, the remote system returns no data and the length is zero.

Figure 6-1 Generic DPL Transaction




Step-by-Step Description: Generic DPL Transaction

1. CICS/ESA transaction TRN1, executing on CICS/ESA System A, issues an EXEC CICS LINK to program PRG002, which resides on CICS/ESA System B. TRN1 “waits” while the LINK request is processed.
2. The LINK implementation internally initiates a special mirror transaction on system B, using an APPC conversation.
3. The mirror transaction runs the system program DFHMIR. It starts the user program PRG0002 and passes any input data to it. The mirror program uses APPC verbs to pass data to and from the user program.
4. Upon completion, PRG0002 returns control to the mirror program which sends any return data back to PGM0001. PGM001 continues execution and may invoke multiple DPL requests using the same conversation and mirror program task.
5. The conversation with the mirror program remains active and available to PGM0001 until a SYNCPOINT is issued. The conversation is used to coordinate the SYNCPOINT processing and is deallocated when the SYNCPOINT is complete.

Distributed Transaction Processing

Distributed Transaction Processing (DTP) is the only ISC services that provides for direct, application-to-application communications. DTP takes place between two conversation partners, both of which are normally user-written CICS/ESA applications. One conversation partner initiates a conversation with a counterpart on a remote system, and must explicitly identify the remote system. The conversation partner on the remote system must accept the requested conversation. Using the full capabilities of ISC, DTP applications send and receive application-defined data streams and engage in a series of application-defined interactions. See Figure 6-2 for a generic example of the DTP process.

Figure 6-2 Generic DTP Transaction



Step-by-Step Description: Generic DTP Transaction

1. Transaction TRN1, invokes program PGM0001 executing on CICS/ESA System A.
2. Program PGM0001 initiates (requests) a conversation with transaction TRN2, located on CICS/ESA System B, which in turn, invokes program PGM0002.
3. Transaction TRN2, executing on CICS/ESA System B, invokes program PGM0002.
4. Program PGM0001 sends data to program PGM0002, then relinquishes control to PGM0002.
5. Program PGM0002 sends data to PGM0001, perhaps the response to the previous request. PGM0001 receives the data sent by PGM0002.
6. PGM0001 and PGM0002 synchronize the data, acknowledge the conversation, and end the conversation.

DTP offers the best of two worlds. On one hand, it provides support for completely customized application protocol semantics. On the other hand, it allows the applications to select the desired level of support for resource recovery and restart:

- ◆ At sync-level 0, the conversation partners elect to forego CICS/ESA system-assisted synchronization altogether.
- ◆ At sync-level 1, the conversation partners can exchange special synchronization verbs as an aid in maintaining synchronization.
- ◆ At sync-level 2, the CICS/ESA system provides full recovery and restart of all controlled resources, such as files and databases. More specifically, a task can initiate tasks on other systems and the collection of tasks can be synchronized into a common unit of work. If there is a failure in any of the tasks, the entire collection can be rolled back.

Note: It is important to understand that, by definition, ISC operates only at sync-level 2.

DTP conversations are LUTYPE 6.2 conversations. They are a half-duplex form of data exchange between two transactions. It is half-duplex because only one side of the conversation can send data at a time. A conversation is initiated by the application using the *Application Program-to-Program Communication (APPC)* protocol. Because of this, the application must be coded to respect the various conversation states. These states are documented in the *IBM CICS/ESA Intercommunication Guide* and identify which APPC verbs are legal at the various stages of a conversation. LUTYPE 6.2 conversations can be mapped or unmapped conversations.

Unmapped or base-level conversation support is the minimum support level required for LUTYPE 6.2 product implementation. Mapped conversations are at a higher level than base conversations and do not require the application to be aware of the SNA data stream format. The state transitions are less restrictive and the command set is more robust. In addition to this, the application has access to CICS/ESA data areas to determine the status of the conversation and the results of certain APPC commands.

CICS/ESA Sync-Levels

In general, the synchronization level determines the cooperation between communicating partners needed to coordinate changes to their respective resources (such as files and databases). It also defines specific protocol flows required to support a requested synchronization level. The APPC architecture defines three distinct levels of synchronization. These three levels are Level 0, Level 1, and Level 2 (corresponding to the SNA-defined levels of NONE, CONFIRM, and SYNCPOINT, respectively).

Level 0 (NONE)

No synchronization at the protocol level is provided. This level is used when synchronization is not required or supported. This is very similar to non-transactional TUXEDO System service requests.

Level 1 (CONFIRM)

This level supports the exchange of private, application-level, synchronization requests between conversing partners. These partners, or applications, are totally responsible for defining and executing the synchronization process to ensure the integrity of all resources. The CICS/ESA system is not involved in the synchronization process at this level. There is no confirm capability in the TUXEDO System. Any CICS/ESA application attempting to initiate a sync-level 1 operation with TUXEDO causes an error condition.

Level 2 (SYNCPOINT)

At this level, the CICS/ESA system is fully involved in the synchronization process and provides complete, automatic support of sync-pointing, including rollback. The CICS/ESA system defines and coordinates the synchronization process and is responsible for ensuring the integrity of all CICS/ESA-managed resources.

In the case of DTP, the communicating applications participate in the synchronization process and are responsible for the management and integrity of any non-CICS/ESA resources to which they gain access.

Because DTP takes place between two application-level conversation partners, it may operate at any of the three defined synchronization levels. In other words, the conversation partners are permitted to specify the desired level of synchronization and participate in the synchronization process only to the extent specified.

If the user DTP conversation is at sync-level 0 or 1, the CICS/ESA system does not propagate sync-points from one system to another via the conversation. Thus the user can explicitly suspend CICS/ESA *ACID Properties*. A DTP conversation at sync-level 2 causes a CICS/ESA system to propagate sync-points automatically via the conversation as well as via subordinate conversations.

DPL can also operate at sync-level 1, in which case the user is responsible for maintaining the ACID properties. Sync-level 1 DPL conversations usually occur because one or both of the systems are incapable of operating at sync-level 2. The eLink SNA software can support DPL requests at both sync-levels 1 and 2, and can support DTP conversations at sync-levels 0 and 1.

Time-out and Error Handling

The /Domain's global timer is used to determine excessive time for a service request. If a time-out occurs, a FAILURE indication is raised and `tperrno` is set to `TPETIME`. The domain gateway cleans up any resources allocated to the failed communication.

The eLink SNA software sets `tperrno` values when an error occurs. Appendix B, "ATMI to CPI-C Function Mapping," describes the CPI-C return codes and their mapping to ATMI return codes.

Refer to Appendix D, "Error Messages," for error code listings.

Application-to-Application Programming

This section provides *Transaction* scenarios for the following programming environments supported by eLink SNA:

- ◆ Distributed Program Link (DPL)
- ◆ Distributed Transaction Processing (DTP)
- ◆ CPI-C Programming

Caution: The scenarios in this section demonstrate how TUXEDO ATMI calls relate to CICS/ESA programming structures. They are intended neither for use in developing application code, nor for the replacement of existing application code. The use of any of these examples in actual situations may have unpredictable results.

Distributed Program Link (DPL)

Using the eLink SNA gateway, BEA TUXEDO applications can make ATMI service calls to invoke programs running in a remote CICS/ESA DPL environment. CICS/ESA programs can in turn use the `EXEC CICS LINK` command to invoke user-defined BEA TUXEDO services. This feature is available to either new or existing CICS/ESA programs and BEA TUXEDO applications. DPL can only be used by BEA TUXEDO application domains connected to a CICS/ESA system.

Consider the program issuing the distributed link request or ATMI service request to be the *Client* program. Consider the executing remote program or service to be the *Server* program. The client does not have to be aware of the server's location.

BEA TUXEDO programs can use both the request/response and conversational models to invoke programs on the host. (However, request/response models are preferred.)

Local and remote services are defined with the `FUNCTION=DPL` option in the `DM_LOCAL_SERVICES` and `DM_REMOTE_SERVICES` section in the `DMCONFIG` file, indicating that the DPL ISC function is invoked.

Host DPL requests, in turn, can also be compared to BEA TUXEDO services using either call model. The request/response model is very similar to DPL. The conversational model, although supported in DTP, is less efficient and programmatically more complex than the request/response model. It is recommended that you use a DTP model when invoking conversational transactions.

It is also recommended you use a DPL model when invoking the same request/response or conversational request multiple times in a single transaction. With DPL, ISC starts a long-running mirror transaction to the CICS/ESA DPL server, enabling the server to process each of the requests over the same conversation. With DTP, each of the requests establishes a separate conversation with the server and the conversation remains outstanding until the transaction is committed.

Special Treatment of TRANSID for DPL

The eLink SNA software employs a special feature that enables BEA TUXEDO clients to invoke CICS/ESA server programs and, conversely, CICS/ESA client programs to invoke BEA TUXEDO services. Based on the IBM CICS/ESA *mirror transaction*, this feature facilitates DPL requests to/from a remote region. The feature is called *Mirror Transaction Identifier Support* and it involves special treatment of the transaction ID (TRANSID) that is part of every DPL request.

This subsection discusses DPL fundamentals related to this feature and describes how eLink SNA software does the following:

- ◆ Processes DPL requests by implicitly attaching a TRANSID to outbound requests only
- ◆ Processes both inbound and outbound requests by allowing you to explicitly attach a TRANSID to the requests

CICS/ESA Fundamentals Relating to Alternate Mirror TRANSID

In the CICS/ESA context, DPL requests are treated as mirror transactions, which include attachment of the server program to the requestor's TRANSID. Two scenarios are possible: implicit attachment (default) and explicit attachment.

When a server program receives a DPL request from a remote region, the *mirror task* services the request. The task attaches the request to a mirror transaction, typically CVMI for SYNCONRETURN requests or CSMI for transactional requests. The mirror task then attaches the appropriate mirror transaction to the requestor's TRANSID, found in the requestor's EIBTRNID field. This is implicit attachment (default).

Note: Implicit attachment of alternate mirror transaction identifier is not supported for inbound DPL requests to BEA TUXEDO services.

The other scenario is explicit attachment. The DPL requestor names the TRANSID that should be attached to the request instead of the default CSMI or CVMI.

For outbound requests from BEA TUXEDO domains to remote CICS/ESA regions, this TRANSID can be included in the API command (tpcall). The TRANSID must be defined in the program resource definition for the destination region and it must point to the mirror task DFHMIRS.


For inbound requests from a remote CICS/ESA region to a local BEA TUXEDO domain, the `TRANSID` is paired with a `PROGRAM` name to explicitly name an advertised service.

Implicit Attachment of `TRANSID`

Figure 6-3 depicts an implicit attachment using the requestor's `TRANSID`. The outbound `tpcall` invokes a service from the remote CICS/ESA region, but does not explicitly name a `TRANSID`. Instead, the `TRANSID` of the requestor is passed to the region as an invoking `TRANSID`. The mirror transaction (CSMI or CVMI) is attached and starts the mirror program, which attaches the requestor's `TRANSID` found in its `EIBTRNID` field. The mirror task then calls the application program.

Note: The eLink SNA software does not support implicit attachment of `TRANSID` to inbound requests for BEA TUXEDO services.

Figure 6-3 Implicit Attachment of TRANSID (Outbound Requests Only)



1. The BEA TUXEDO service makes a request to the service TRN1DATA, which is advertised as a remote service in the DMCONFIG file. It is a DPL request to a program named SVC1 in the CICS/ESA region.
2. The first four characters of the remote service tag name (TRN1) are extracted and passed to the CICS/ESA region as the invoking TRANSID. No CICS/ESA resource definition for the TRANSID is required in the region.
3. The mirror transaction CSMI is attached in the CICS/ESA region, starting the mirror program DFHMIRS. The program performs the DTP requests for the service.
4. The mirror program now attaches the invoking TRANSID (TRN1) and then invokes the application service program SVC1. The program can interrogate the EIBTRNID field to find this value.

Explicit Attachment of TRANSID

Explicit attachment names the TRANSID to be attached instead of the default mirror transaction, CSMI or CVMI. The client might use the explicit method for the following reasons:

- ◆ The system administrator wants to restrict the use of a specific TRANSID, or impose scheduling constraints on the transaction itself.
- ◆ The remote server might base its response on the value specified in the EIBTRNID field, thus causing possible unexpected results when the implicit method is used.
- ◆ The request might be forwarded to another remote CICS/ESA region before the mirror program is invoked, thus bypassing attachment of the TRANSID.

Explicit attachment can be used for both outbound and inbound DPL requests. You can specify the TRANSID in the API command or in the RNAME parameter for the service definition in the DMCONFIG file.

The following example shows how to provide a TRANSID in the API command:

```
EXEC CICS LINK PROGRAM("SERVICE1")
      SYSID("AIX1")
      TRANSID("TRN1")
```

A TRANSID for an outbound DPL request is specified in the DM_REMOTE_SERVICES section of the DMCONFIG file. Conversely, a TRANSID for an inbound DPL request is specified in the DM_LOCAL_SERVICES section. The format for the TRANSID and server name in the DMCONFIG file entry is as follows:

```
RNAME=AAAA:BBBBBBBB
```

where:

AAAA

is a 1-4 character alternate mirror TRANSID

BBBBBBBB

is a 1-8 character CICS/ESA program name.

The colon is required to indicate the TRANSID/program name combination. The TRANSID must be composed of acceptable CICS/ESA characters:

```
A-Za-z0-9$@#./-_%&Q?;!|"',;<>
```


The following paragraphs discuss explicit attachment of `TRANSID` to both outbound requests for remote CICS/ESA services and to inbound requests for BEA TUXEDO services.

Outbound Requests

Figure 6-4 depicts the explicit attachment of the `TRANSID` to an outbound request for services in a remote CICS/ESA region. The `TRANSID` can be provided in the `API` command or in the remote-service definition in the `DMCONFIG` file. The `RNAME` value in the `DMCONFIG` file is used to create the alternate mirror ID and invoke the remote server.

The request passes the transaction ID of the mirror transaction to the remote CICS/ESA region. This transaction ID is defined in the remote region and must point to the mirror program `DFHMIRS`. When the mirror program invokes the application program, the transaction ID is passed to the program in the `EIBTRNID` field.

Figure 6-4 Explicit Attachment of TRANSID for Outbound Requests




1. The BEA TUXEDO program makes a service request for `SERVICE1`, which is advertised as a remote service in the DMCONFIG file. The `FUNCTION` option indicates the remote service is invoked as a DPL.
2. The request extracts `TRN1` as an alternate mirror transaction ID for the remote region, along with the remote program name `SERVICE1`.
3. The `TRN1` ID is attached instead of the default mirror transaction, `CSMI` or `CVMI`. The `TRN1` ID must be defined as a transaction resource in the remote region and must point to the mirror transaction program `DFHMIRS`.
4. The mirror program `DFHMIRS` calls the server application program, passing the `TRN1` ID in the `EIBTRNID` field.

Inbound Requests

Figure 6-5 depicts the explicit attachment of the `TRANSID` to inbound request for services in a BEA TUXEDO local domain. The `TRANSID` can be provided in the API command or in the local-service definition in the `DMCONFIG` file. The `TRANSID` named in the API command or in the requested program name must exactly match an `RNAME` in the `DM_LOCAL_SERVICES` section of the `DMCONFIG` file.

Figure 6-5 Explicit Attachment of TRANSID for Inbound Requests



1. The CICS/ESA program makes a request to `INSVC1`, which is a local BEA TUXEDO service. The `SYSID` and `PROGRAM` values in the request identify the local system and the name of the local service. The `TRANSID` option indicates the mirror transaction to be initiated.

2. The `PROGRAM` and mirror `TRANSID` are extracted from the DPL request. These are used to find an exact `RNAME` match in the `DM_LOCAL_SERVICES` section of the `DMCONFIG` file.
3. The service `SERVICE1`, which is advertised locally in the BEA TUXEDO application, is initiated.

Explicit Attachment Usage Notes

You must enter the alternate mirror transaction and remote server name as `RNAME` values in both the `DM_LOCAL_SERVICES` and `DM_REMOTE_SERVICES` sections of the `DMCONFIG` file, using the format shown previously in the “Inbound Requests” section.

For outbound requests to a CICS/ESA server, the `RNAME` value in the `DMCONFIG` file is used to create the alternate mirror ID and invoke the remote server.

For inbound requests, the `TRANSID` named in the API command or in the `PROGRAM` definition is used along with the requested program name to exactly match an `RNAME` associated with a local service entry.

Note: If an `RNAME` is not found with both the transaction ID and the `PROGRAM` name, an error is returned to the CICS/ESA client.

Do not insert trailing spaces between the `TRANSID` and colon in the `RNAME` option. The eLink SNA software automatically discards trailing spaces before attempting to match `RNAME` values.

If the specified `TRANSID/PROGRAM` combination in a service name (either local or remote) is not a DPL, eLink SNA software returns an error which is not detected until run time.

Specifying the Size of a DPL Commarea

To translate a TUXEDO ATMI request to an EXEC CICS LINK request, the eLink SNA gateway uses the `INBUFTYPE` and `OUTBUFTYPE` of the remote service to create the `COMMAREA` for the DPL program.

For each remote service defined in the `DMCONFIG` file `REMOTE_SERVICES` section, `INBUFTYPE` is a description of the data that the service receives (the format of the request) and `OUTBUFTYPE` is a description of the data that the service sends as a response.

When a DPL program is invoked, it receives the request data in a COMMAREA. When the program completes, it returns this same COMMAREA to the program that invoked it. The DPL program cannot change the size of the COMMAREA; therefore, the COMMAREA must be large enough to hold both the request and the reply.

Before the gateway invokes a DPL program, it uses the INBUFTYPE and OUTBUFTYPE to calculate this size. Because CARRAY and STRING do not have sizes associated with them, the maximum size is used (4096 bytes).

Note: You cannot specify a response buffer in a `tpcall` or a `tpacall` for the purpose of sizing a COMMAREA. The gateway is unaware of the size of the response buffer that is specified in the `tpcall`, and in `tpacall`, the response buffer is not specified until the reply is retrieved with `tpgetreply`.

The best approach is to use VIEW types as the INBUFTYPE and OUTBUFTYPE of DPL programs. This allows the size of the request and response to be described in exact detail. Refer to the examples below:

Listing 6-3 Example of DMCONFIG File Entry Specifying VIEWS to Size the COMMAREA

```
*DM_REMOTE_SERVICES  
  
SIMPDPDV AUTOTRAN=N  
  
    LDOM="simpsnad"  
  
    RDOM=SIMPSNAG  
  
    CONV=N  
  
    RNAME="TOUPDPLS"  
  
    INBUFTYPE="VIEW:reqstr"  
  
    OUTBUFTYPE="VIEW:respstr"  
  
    FUNCTION="DPL"
```

The following listing shows the corresponding view descriptions:

Listing 6-4 Descriptions of VIEWS for Sizing COMMAREA

```
VIEW reqstr
```

#TYPE	CNAME	FBNAME	COUNT	FLAG	SIZE	NULL
string	reqstring	-	1	-	20	" "

```
END
```

```
VIEW respstr
```

#TYPE	CNAME	FBNAME	COUNT	FLAG	SIZE	NULL
string	respstring	-	1	-	50	" "

```
END
```

The following listing shows the code used for a client that requests the SIMPDPLV application:

Listing 6-5 Program Using Views to Size COMMAREA

```
/* Include header file generated by views -n myviews.v */  
  
#include "myviews.h"  
  
sendbuf = (struct reqstr *) tmalloc("VIEW", "reqstr", sizeof(struct  
reqstr));  
  
rcvbuf = (struct respstr *) tmalloc("VIEW", "respstr",  
sizeof(struct respstr));  
  
tpcall("SIMPDPV", (char *) sendbuf, 0, (char **) &rcvbuf, &rcvlen,  
(long)0);
```

In the previous examples, the two VIEWS describe a request string of length 20 and a response string of length 50; therefore, the COMMAREA created can hold a string of 50 characters.


DPL Examples

The examples in this section represent a few of the many programming scenarios available for using DPL and BEA TUXEDO service invocations. These examples employ the most natural and efficient approaches.

Note: To run *Transaction* client/server scenarios, the eLink SNA software must be licensed for sync-level 2 operations.

(This page intentionally blank.)


Figure 6-6 TUXEDO Client Request/Response to CICS/ESA DPL



Step-by-Step Description: TUXEDO Client Request/Response to CICS/ESA DPL

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpcall` for `SIMPDPL`, which is advertised in the `DM_REMOTE_SERVICES` section of the `DMCONFIG` file.
3. Host mirror transaction starts `TOUPDPLS` program and passes `idata` buffer contents for processing.
4. The `TOUPDPLS` program processes data.
5. The CICS/ESA server returns the `commarea` into the client's `odata` buffer.


Figure 6-7 TUXEDO Client Asynchronous Request/Response to CICS/ESA DPL



Step-by-Step Description: TUXEDO Client Asynchronous Request/Response to CICS/ESA DPL

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpacall` for `SIMPDPL`, which is advertised in the `DM_REMOTE_SERVICES` section of `DMCONFIG` file.
3. Host mirror transaction starts `TOUPDPLS` program and passes `idata` buffer contents for processing.
4. The `TOUPDPLS` program processes data.
5. The CICS/ESA system returns the `commarea` into the client's `tpgetreply` `odata` buffer.


Figure 6-8 TUXEDO Client Asynchronous Request/Response with No Reply to CICS/ESA DPL



Step-by-Step Description: TUXEDO Client Asynchronous Request/Response with No Reply to CICS/ESA DPL

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpacall` for `SIMPDPPL`, which is advertised in the `DM_REMOTE_SERVICES` section of `DMCONFIG` file. The `toupsrv` service uses `TPNOREPLY` to specify that no reply is expected.
3. Host mirror transaction starts `TOUPDPLS` program and passes `idata` buffer contents for processing.
4. The `TOUPDPLS` program processes data.


Figure 6-9 CICS/ESA DPL to TUXEDO Request/Response Server



Step-by-Step Description: CICS/ESA DPL to TUXEDO Request/Response Server

1. User-entered `HOPL` invokes `MIRRDPLC` program.
2. The `EXEC CICS LINK` command causes the advertised service mapped to `MIRRDPLS` (in the `DM_LOCAL_SERVICES` section of the `DMCONFIG` file) to execute.
3. The `MIRROR` service processes the data received in the service `TPSVCINFO` data buffer from the `EXEC CICS LINK`.
4. The `tpreturn` call returns the data into the `COMM-AREA` buffer.


Figure 6-10 CICS/ESA DPL to TUXEDO Request/Response Server, Service in Autonomous Transaction



Step-by-Step Description: CICS/ESA DPL to TUXEDO Request/Response Server, Service in Autonomous Transaction

1. User-entered `H0PL` invokes `MIRRDPLC` program.
2. The `EXEC CICS LINK` command causes the advertised service mapped to `MIRRDPLS` (in the `DM_LOCAL_SERVICES` section of the `DMCONFIG` file) to execute. The `SYNCONRETURN` option indicates that the invoked service will not participate in the CICS/ESA transaction.
3. The `MIRROR` service request `tpbegin` incorporates all further operations in a transaction.
4. The `MIRROR` service processes the data.
5. The `tpcommit` indicates the end of the transaction; all updates performed within the service transaction are to be committed.
6. The `tpreturn` call returns the data into the `commarea` buffer.
7. The `EXEC CICS SYNCPOINT` is an explicit commit request. All updated resources in the CICS/ESA transaction are committed.


Figure 6-11 TUXEDO Client Request/Response to CICS/ESA DPL, in Autonomous Transaction



Step-by-Step Description: TUXEDO Client Request/Response to CICS/ESA DPL, in Autonomous Transaction

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpbegin` to start the transaction.
3. The `toupsrv` service issues `tpcall` for `SIMPDPL`, which is advertised in the `DM_REMOTE_SERVICES` section of the `DMCONFIG` file. The `TPNOTRAN` parameter indicates the CICS/ESA application does not participate in the service transaction.
4. Host mirror transaction starts `TOUPDPLS` program and passes `idata` buffer contents for processing.
5. The `TOUPDPLS` program processes data.
6. The `EXEC CICS SYNCPOINT` is an explicit commit request. All updated resources in the CICS/ESA transaction are committed.
7. The CICS/ESA server returns the `commarea` into the client's `odata` buffer.
8. The `toupsrv` service `tpcommit` request signals the successful completion of the transaction, causing a commit of its own updated resources.


Figure 6-12 Transactional TUXEDO Client Multiple Requests/Responses to CICS/ESA DPL



Step-by-Step Description: Transactional TUXEDO Client Multiple Requests/Responses to CICS/ESA DPL

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpbegin` to start the transaction.
3. The `toupsrv` service issues `tpcall` for `SIMPDPL`, which is advertised in the `DM_REMOTE_SERVICES` section of the `DMCONFIG` file. The `tpcall` is requested multiple times within the same transaction.
4. Host mirror transaction starts `TOUPDPLS` program and passes `idata` buffer contents for processing. The host mirror transaction remains as a long-running task to service all further requests on the transaction.
5. The `TOUPDPLS` program processes data.
6. The CICS/ESA system returns the `commarea` into the client's `odata` buffer.
7. Step 3 through Step 6 are repeated until the `toupsrv` service loop end conditions are met.
8. The `tpcommit` request indicates the successful completion of the transaction, causing a commit of its own resources and the resources held by the host mirror transaction.

Figure 6-13 Transactional CICS/ESA DPL to TUXEDO Request/Response Server



Step-by-Step Description: Transactional CICS/ESA DPL to TUXEDO Request/Response Server

1. User-entered `H2PL` invokes `MIRRDPLC` program.
2. The `EXEC CICS LINK` command causes the advertised service mapped to `MIRRDPLS` (in the `DM_LOCAL_SERVICES` section of the `DMCONFIG` file) to execute. The invoked service participates in the CICS/ESA transaction.
3. The `MIRROR` service processes the data.
4. The `tpreturn` call returns the data into the `commarea` buffer.
5. The `EXEC CICS SYNCPOINT` is an explicit commit request indicating a successful end of the conversation. All updated resources in the transaction are committed.

(This page intentionally blank.)

Distributed Transaction Processing (DTP)

The following examples represent a few programming scenarios for using DTP and BEA TUXEDO service invocations.

The recommended method of performing DTP services is to use BEA TUXEDO conversational services instead of request/response services. The conversational service enables a client and a server to communicate as needed over the eLink SNA session conversation.


Although it is most suited for the DPL environment, the `tpcall` is used in the examples for a request/response to a DTP server.

It is recommended you use a DPL model when invoking multiple request/response calls in a single transaction. With DPL, a long-running mirror transaction to the CICS/ESA DPL server is started, enabling the server to process each of the requests over the same conversation. With DTP, each of the ATMI requests will establish a separate conversation; the conversation remains outstanding until the transaction is committed.

The examples in this section represent a few of the many programming scenarios available for using DTP and BEA TUXEDO service invocations. These examples employ the most natural and efficient approaches.

Note: To run *transactional* client/server scenarios, the eLink SNA software must be licensed for sync-level 2 operations.


Figure 6-14 TUXEDO Client Request/Response to CICS/ESA DTP



Step-by-Step Description: TUXEDO Client Request/Response to CICS/ESA DTP

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpcall` for `SIMPDTP`, which is advertised in the `DM_REMOTE_SERVICES` section of `DMCONFIG` file.
3. User transaction `DTPS` starts `TOUPDTPS` program.
4. It is recommended you save the `eibtrmid` to a program variable. This value may be used to identify the specific conversation in your CICS/ESA APPC verbs.
5. The `EXEC CICS RECEIVE` command receives the `idata` buffer contents for processing.
6. The `TOUPDTPS` program processes data.
7. The `EXEC CICS SEND` command returns the `OUT-BUFFER` contents into the clients `odata` buffer. `LAST` indicates the conversation is finished. `WAIT` suspends processing until the data has successfully been received.


Figure 6-15 TUXEDO Client Asynchronous Request/Response to CICS/ESA DTP



Step-by-Step Description: TUXEDO Client Asynchronous Request/Response to CICS/ESA DTP

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpacall` for `SIMPDTP`, which is advertised in the `DM_REMOTE_SERVICES` section of the `DMCONFIG` file.
3. User transaction `DTPS` starts `TOUPDTPS` program.
4. It is recommended you save the `EIBTRMID` to a program variable. This value may be used to identify the specific conversation in your CICS/ESA `APPC` verbs.
5. The `EXEC CICS RECEIVE` command receives the `idata` buffer contents for processing.
6. The `TOUPDTPS` program processes data.
7. The `EXEC CICS SEND` command returns the `OUT-BUFFER` contents into the clients `tpgetreply odata` buffer. `LAST` indicates the conversation is finished. `WAIT` suspends processing until the data has successfully been received.


Figure 6-16 TUXEDO Client Asynchronous Request/Response with No Reply to CICS/ESA DTP



Step-by-Step Description: TUXEDO Client Asynchronous Request/Response with No Reply to CICS/ESA DTP

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpacall` with a `TPNOREPLY` request for `SIMPDTP`, which is advertised in the `DM_REMOTE_SERVICES` section of `DMCONFIG` file.
3. User transaction `DTPS` starts `TOUPDTPS` program.
4. It is recommended you save the `EIBTRMID` to a program variable. This value may be used to identify the specific conversation on your CICS/ESA APPC verbs.
5. The `EXEC CICS RECEIVE` command receives the `idata` buffer contents for processing.
6. The `TOUPDTPS` program processes data.


Figure 6-17 TUXEDO Conversational Client to CICS/ESA DTP, Server Gets Control



Step-by-Step Description: TUXEDO Conversational Client to CICS/ESA DTP, Server Gets Control

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpconnect` for `SIMPDTP`, which is advertised in the `DM_REMOTE_SERVICES` section of `DMCONFIG` file. The `TPRECVONLY` flag indicates the server gets control and the first conversation verb `toupsrv` can issue is `tprecv`. Data is sent on the `tpconnect` in the `idata` buffer.
3. User transaction `DTPS` starts `TOUPDTPS` program.
4. It is recommended you save the `EIBTRMID` to a program variable. This value may be used to identify the specific conversation on your CICS/ESA `APPC` verbs.
5. The `EXEC CICS RECEIVE` command receives the `idata` buffer contents for processing.
6. The `TOUPDTPS` program processes data.
7. The `EXEC CICS SEND` command returns the `OUT-BUFFER` contents into the clients `tprecv odata` buffer. `WAIT` suspends processing in `TOUPDTPS` until the data has successfully been received. `LAST` indicates the conversation is finished and is communicated to the `tprecv` as `TPEV_SVCSUCC`.


Figure 6-18 TUXEDO Conversational Client to CICS/ESA DTP, Client Sends/Receives Data



Step-by-Step Description: TUXEDO Conversational Client to CICS/ESA DTP, Client Sends/Receives Data

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpconnect` for `SIMPDTP`, which is advertised in the `DM_REMOTE_SERVICES` section of `DMCONFIG` file. The `TPSENDONLY` indicates the client retains control and continues to send data. Data is sent on the `tpconnect` in the `idata` buffer.
3. User transaction DTPS starts `TOUPDTPS` program.
4. It is recommended you save the `EIBTRMID` to a program variable. This value may be used to identify the specific conversation on your CICS/ESA APPC verbs.
5. The `EXEC CICS RECEIVE` command receives the `tpconnect idata` buffer contents for processing.
6. The `TOUPDTPS` program processes data.
7. The `EXEC CICS RECEIVE` command receives the `tpsend idata` contents into the server's `IN-BUFFER`.
8. The server processes the data.
9. The `EXEC CICS SEND WAIT LAST` returns `OUT-BUFFER` data in the `tprecv odata` buffer, along with notification that the conversation is over.


Figure 6-19 TUXEDO Conversational Client to CICS/ESA DTP, Client Grants Control



Step-by-Step Description: TUXEDO Conversational Client to CICS/ESA DTP, Client Grants Control

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpconnect` for `SIMPDTP`, which is advertised in the `DM_REMOTE_SERVICES` section of `DMCONFIG` file. The `TPRECVONLY` indicates the server gets control and the first conversation verb `toupsrv` can issue is `tprecv`.
3. User transaction DTPS starts `TOUPDTPS` program.
4. It is recommended you save the `EIBTRMID` to a program variable. This value may be used to identify the specific conversation on your CICS/ESA APPC verbs.
5. The `EXEC CICS RECEIVE` command receives a `send state` indicator from the `tpconnect` `TPRECVONLY` flag. No data is received into the `INBUFFER`.
6. The `EXEC CICS SEND` command returns the `OUT-BUFFER` contents into the clients `tprecv odata` buffer. The `EXEC CICS SEND` command relinquishes control to the client by using the `INVITE` option. This is communicated to the `tprecv` as `TPEV_SENDOONLY`.
7. The `EXEC CICS RECEIVE` command receives the `tpsend idata` contents into the server's `IN-BUFFER`, along with notification that the server has relinquished control.
8. The `EXEC CICS RETURN` ends the conversation, communicated to the `tprecv` as `TPEV_SVCSUCC`.


Figure 6-20 CICS/ESA DTP to TUXEDO Conversational Server, Client Retains Control



Step-by-Step Description: CICS/ESA DTP to TUXEDO Conversational Server, Client Retains Control

1. User-entered `H0TP` invokes `MIRRDTPC` program.
2. The `EXEC CICS ALLOCATE` acquires a session to the remote BEA TUXEDO domain.
3. Save the conversation ID returned in `EIBRSRCE` to a program variable. This value is used to identify the specific conversation in your CICS/ESA APPC verbs.
4. The `EXEC CICS CONNECT PROCESS` command initiates the advertised service mapped to `MIRROR` in the `DM_LOCAL_SERVICES` section of the `DMCONFIG` file.
5. Execute the `EXEC CICS SEND` command to send the contents of the `OUT-BUFFER` to the BEA TUXEDO service in the `tpsvcinfol->data` buffer. The contents might be sent immediately.
6. The `EXEC CICS SEND INVITE WAIT` command sends `out-buff` contents into the `tprecv odata` buffer. The `INVITE` parameter relinquishes control of the conversation, seen as a `TPEV_SENDOONLY` in the `reevent` parameter on the `tprecv` command. The data is sent immediately, along with the data from the previous `SEND` operation.
7. The BEA TUXEDO service processes data.
8. The CICS/ESA server processes data.
9. The TUXEDO `tpreturn` data returns data to the `EXEC CICS RECEIVE`, along with notification that the conversation completed successfully.


Figure 6-21 CICS/ESA DTP to TUXEDO Conversational Server, Client Relinquishes Control



Step-by-Step Description: CICS/ESA DTP to TUXEDO Conversational Server, Client Relinquishes Control

1. User-entered HOTP invokes MIRRDTPC program.
2. The EXEC CICS ALLOCATE acquires a session to the remote BEA TUXEDO domain.
3. Save the conversation ID returned in EIBRSRCE to a program variable. This value is used to identify the specific conversation in your CICS/ESA APPC verbs.
4. The EXEC CICS CONNECT PROCESS command initiates the advertised service mapped to MIRROR in the DM_LOCAL_SERVICES section of the DMCONFIG file.
5. The EXEC CICS SEND command relinquishes control with the INVITE WAIT option.
6. The EXEC CICS RECEIVE command receives the tpsend idata buffer contents into the IN-BUFFER.
7. The tpretturn request tears down the conversation and indicates on the EXEC CICS RECEIVE that the conversation is over.

Figure 6-22 Transactional TUXEDO Client Request/Response to CICS/ESA DTPS




Step-by-Step Description: Transactional TUXEDO Client Request/Response to CICS/ESA DTP

Note: This is not the recommended method of performing a DTP transactional service. Please refer to the transactional DPL using request/response for the recommended method.

1. TUXEDO client `toupclt` invokes `toupsrv` service. (Note that each `tpcall` made in the program must be bookended with a `tpbegin` and a `tpcommit`.)
2. The service issues `tpbegin` to start a transaction.
3. The `toupsrv` service issues `tpcall` for `SIMPDTP`, which is advertised in the `DM_REMOTE_SERVICES` section of the `DMCONFIG` file.
4. User transaction `DTPS` starts `TOUPDTPS` program.
5. Save the `EIBTRMID` to a program variable. This value is used to identify the specific conversation on your CICS/ESA APPC verbs.
6. The `EXEC CICS RECEIVE` command receives the `idata` buffer contents for processing.
7. The `TOUPDTPS` program processes data.
8. The `EXEC CICS SEND` command returns the `OUT-BUUFER` contents into the clients `odata` buffer. `CONFIRM` indicates the conversation is finished. `INVITE` allows the client to respond with a `COMMIT` request.
9. The `toupsrv` service issues `tpcommit` to end the transaction. The `COMMIT` is received on the `EXEC CICS RECEIVE` verb and the server issues `EXEC CICS RETURN` to commit the resources, terminate the transaction, and free the outstanding conversation.


Figure 6-23 Transactional TUXEDO Conversational Client to CICS/ESA DTPS, Server Gets Control



Step-by-Step Description: Transactional TUXEDO Conversational Client to CICS/ESA DTP, Server Gets Control

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpbegin` to start the transaction.
3. The `toupsrv` service issues `tpconnect` for `SIMPDTP`, which is advertised in the `DM_REMOTE_SERVICES` section of `DMCONFIG` file. The `TPRECVONLY` indicates the server gains control and the first conversation verb `toupsrv` can issue is `tprecv`. Data is sent on the `tpconnect` in the `idata` buffer.
4. User transaction `DTPS` starts `TOUPDTPS` program.
5. It is recommended you save the `EIBTRMID` to a program variable. This value may be used to identify the specific conversation on your CICS/ESA APPC verbs.
6. The `EXEC CICS RECEIVE` command receives the `idata` buffer contents for processing.
7. The `TOUPDTPS` program processes data.
8. The `EXEC CICS SEND` command returns the `OUT-BUFFER` contents into the clients `tprecv odata` buffer. `CONFIRM` indicates that the conversation is finished and is communicated to the `tprecv` as `TPEV_SVCSUCC`. `INVITE` enables the client to respond with a `COMMIT` request.
9. The `toupsrv` service issues `tpcommit` to end the transaction. The `COMMIT` is received on the `EXEC CICS RECEIVE` verb and the server issues `EXEC CICS RETURN` to commit the resources, terminate the transaction, and free the outstanding conversation.

Figure 6-24 Transactional CICS/ESA DTP to TUXEDO Conversational Server, Host Client Relinquishes Control



Step-by-Step Description: CICS/ESA DTP to Transactional TUXEDO Conversational Server, Host Client Relinquishes Control

1. User-entered H2TP invokes MIRRDTPC program.
2. The EXEC CICS ALLOCATE acquires a session to the remote BEA TUXEDO domain.
3. Save the conversation ID returned in EIBRSRCE to a program variable. This value is used to identify the specific conversation on your CICS/ESA APPC verbs.
4. The EXEC CICS CONNECT PROCESS command initiates the advertised service mapped to MIRRDTPS. The SYNCLEVEL(2) parameter indicates the inclusion of the TUXEDO service in the CICS/ESA transaction.
5. The EXEC CICS SEND INVITE WAIT command causes the client to immediately relinquish control to the BEA TUXEDO server. This is communicated to the service in TPSVCINFO as TPSENDONLY. No data is sent to the server on this request.
6. The EXEC CICS RECEIVE command receives the tpsend idata buffer contents into the IN-BUFFER. The EXEC CICS RECEIVE command receives a confirm request indicating the conversation should be terminated.
7. The EXEC CICS ISSUE CONFIRMATION verb responds positively to the confirm request.
8. The EXEC CICS SYNCPOINT is an explicit commit request to end the conversation and update all resources in the transaction.
9. The EXEC CICS FREE verb explicitly frees the outstanding conversation.

(This page intentionally blank.)

CPI-C Programming

The Common Programming Interface for Communications (CPI-C) is an implementation choice for program-to-program communications. The reason that CPI-C may be used over other implementations is that CPI-C defines a single programming interface to the underlying network protocols across many different programming languages and environments.

Also, you can use the CPI Resource Recovery interface to provide a consistent interface to system services that allow your programs to coordinate data exchange and updates of databases and resources.

The examples in this section show the protocol exchanges between the local BEA TUXEDO and remote host application program. With BEA TUXEDO, the type of ATMI service request determines the nature of the client/server communication model. For requests initiated by the host application, the configuration information for the local service determines the protocol exchanges on the conversation.

The recommended method of performing APPC services is to use BEA TUXEDO conversational services instead of request/response services. The conversational service enables a client and a server to communicate as needed over the eLink SNA session conversation.


Although it is most suited for the DPL environment, the `tpcall` is used in the examples for a request/response to an APPC server.

It is recommended you use a DPL model when invoking multiple request/response calls in a single transaction. With DPL, a long-running mirror transaction to the CICS/ESA DPL server is started, enabling the server to process each of the requests over the same conversation. With APPC, each of the ATMI requests will establish a separate conversation; the conversation remains outstanding until the transaction is committed.

The examples in this section represent a few of the many programming scenarios available for using CPI-C and BEA TUXEDO service invocations. These examples employ the most natural and efficient approaches.

Note: To run *transactional* client/server scenarios or the CPI Resource Recovery interface, the eLink SNA software must be licensed for sync-level 2 operations.


Figure 6-25 TUXEDO Client Request/Response to Host CPI-C



Step-by-Step Description: TUXEDO Client Request/Response to Host CPI-C

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpcall` for `SIMPCPIC`, which is advertised in the `DM_REMOTE_SERVICES` section of the `DMCONFIG` file.
3. The remote service with the `tpname` `TPNCPIC` invokes `TOUPCPIC` program.
4. The server accepts the conversation with the `cmaccp` call. The conversation id returned on the request in `convid` is used for all other requests on this conversation.
5. The `cmrcv` request receives the `idata` buffer contents for processing
6. The `TOUPCPIC` program processes data.
7. The `cmsst` request prepares the next send request by setting the send type to `CM_SEND_AND_DEALLOCATE`.
8. The `cmsend` request returns the `obuffer` contents into the client `odata` buffer. The buffer is flushed, and the conversation ended.


Figure 6-26 TUXEDO Client Asynchronous Request/Response to Host CPI-C



Step-by-Step Description: TUXEDO Client Asynchronous Request/Response to Host CPI-C

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpacall` for `SIMPCPIC`, which is advertised in the `DM_REMOTE_SERVICES` section of the `DMCONFIG` file.
3. The remote service with `tpname` `TPNCPIC` invokes `TOUPCPIC` program.
4. The server accepts the conversation with the `cmaccp` call. The conversation id returned on the request in `convid` is used for all other requests on this conversation.
5. The `cmrcv` request receives the `idata` buffer contents for processing.
6. The `TOUPCPIC` program processes data.
7. The `cmsend` command returns the `obuffer` contents into the client `tpgetreply odata` buffer. The data may not be immediately sent to the `tpgetreply odata` buffer on this request.
8. The `cmdeal` flushes the data to the client, and indicates the conversation is finished.


Figure 6-27 TUXEDO Client Asynchronous Request/Response to Host CPI-C with No Reply



Step-by-Step Description: TUXEDO Client Asynchronous Request/Response to Host with No Reply

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpacall` with a `TPNOREPLY` request for `SIMPCPIC`, which is advertised in the `DM_REMOTE_SERVICES` section of the `DMCONFIG` file.
3. The remote service with `tpname` `TPNPCPIC` invokes `TOUPCPIC` program.
4. The server accepts the conversation with the `cmaccp` call. The conversation id returned on the request in `convid` is used for all other requests on this conversation.
5. The `cmrcv` request receives the `idata` buffer contents for processing, and notification that the conversation has ended with the return code value of `CM_DEALLOCATED_NORMAL`.
6. The `TOUPCPIC` program processes data.


Figure 6-28 TUXEDO Conversational Client to Host CPI-C, Server Gets Control



Step-by-Step Description: TUXEDO Conversational Client to Host CPI-C, Server Gets Control

1. TUXEDO client invokes `toupsrv` service
2. The `toupsrv` service issues `tpconnect` for `SIMPCPIC`, which is advertised in the `DM_REMOTE_SERVICES` section of the `DMCONFIG` file. The `TPRECVONLY` indicates the server gains control and the first conversation verb the `toupsrv` can issue is `tprecv`. Data is sent on the `tpconnect` in the `idata` buffer.
3. The remote service with `tpname` `TPNCPIC` invokes `TOUPCPIC` program.
4. The server accepts the conversation with the `cmaccp` call. The conversation ID returned on the request in `convid` is used for all other requests on this conversation.
5. The `cmrcv` request receives the `idata` buffer contents for processing.
6. The `TOUPCPIC` program processes data
7. The `cmsst` request prepares the next send request by setting the send type to `CM_SEND_AND_FLUSH`.
8. The `cmsend` command returns the `obuffer` contents into the client `tprecv` `odata` buffer. The data is immediately flushed on the send request.
9. The `cmdeal` request ends the conversation.


Figure 6-29 TUXEDO Conversational Client To Host CPI-C, Client Retains Control



Step-by-Step Description: TUXEDO Conversational Client to Host CPI-C, Client Retains Control

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpconnect` for `SIMPCPIC`, which is advertised in the `DM_REMOTE_SERVICES` section of the `DMCONFIG` file. The `TPSENDONLY` indicates the client retains control and continues to send data. No data is sent with the `tpconnect`.
3. The remote service with `tpname` `TPNCPIC` invokes `TOUPCPIC` program.
4. The server accepts the conversation with the `cmaccp` call. The conversation id returned on the request in `convid` is used for all other requests on this conversation.
5. The `cmrcv` request receives the `tpsend idata` buffer contents for processing. The conversation is relinquished with the `TPRECVONLY` flag.
6. The `TOUPCPIC` program processes data.
7. The `cmsend` returns a response in the `tprecv idata` buffer, along with notification from the `cmdeal` command that the conversation is over. The `cmdeal` flushes the data buffer and the `tprecv reevent` parameter is set to `TPEV_SUCCESS`.


Figure 6-30 TUXEDO Conversational Client to Host CPI-C, Client Grants/gets Control



Step-by-Step Description: TUXEDO Conversational Client to Host CPI-C, Client Grants/Gets Control

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpconnect` for `SIMPCPIC`, which is advertised in the `DM_REMOTE_SERVICES` section of the `DMCONFIG` file. The `TPRECVONLY` indicates the server gains control and the first conversation verb the `toupsrv` can issue is `tprecv`.
3. The remote service with `tpname` `TPNCPIC` invokes `TOUPCPIC` program.
4. The server accepts the conversation with the `cmaccp` request. The conversation id returned on the request in `convid` is used for all other requests on this conversation.
5. The `cmrcv` request receives the indicator that control has been granted to the server.
6. The `cmsend` request returns its `obuffer` contents into the first client `tprecv` `odata` buffer. The data may not immediately be sent.
7. The `cmsend` request returns its `obuffer` contents into the second client `tprecv` `odata` buffer. The data may not immediately be sent.
8. The `cmptr` request flushes the data to the client, and grants control to the client.
9. The `cmrcv` request receives the `tpsend` `idata` buffer contents for processing. The `TPRECVONLY` is passed to the `tprecv`, relinquishing control of the conversation.
10. The `cmdeal` indicates a successful completion of the conversation to the `tprecv`; no data is passed.


Figure 6-31 Host CPI-C to TUXEDO Asynchronous Request/Response Server with No Reply



Step-by-Step Description: Host CPI-C to TUXEDO Asynchronous Request/Response Server with No Reply

1. The CPI-C application program `MIRRCPI-C` is invoked using environment start-up specifications.
2. The `MIRRCPI-C` client requests `cminit` to establish conversation attributes and receive a conversation ID that will be used on all other requests on this conversation. The remote server and service are named in the CPI-C side information entry `MIRRSIDE`.
3. The `cmallc` request initiates the advertised service mapped to `MIRRORSERV` in the `DM_LOCAL_SERVICES` section of the `DMCONFIG` file.
4. The `cmsend` request sends the contents of `obuffer` to the TUXEDO service in the `tpsvcinfc->data` buffer.
5. The `cmdeal` request flushes the data, and indicates the conversation is finished with the `TPNOREPLY` in the `tpsvcinfc->flag` field.
6. The service completes with the `tpreturn`.


Figure 6-32 Host CPI-C to TUXEDO Server Request/Response



Step-by-Step Description: HOST CPI-C to TUXEDO Server Request/Response

1. The CPI-C application program MIRRPCIC is invoked using environment start-up specifications.
2. The MIRRPCIC client requests `cminit` to establish conversation attributes and receive a conversation id that will be used on all other requests on this conversation. The remote server and service are named in the CPI-C side information entry `MIRRSIDE`.
3. The `cmallc` request initiates the advertised service mapped to `MIRRORserv` in the `DM_LOCAL_SERVICES` section of the `DMCONFIG` file.
4. The `cmsst` request prepares the next send request by setting the send type to `CM_SEND_AND_PREP_TO_RECEIVE`.
5. The `cmsend` request immediately sends the contents of `obuffer` to the TUXEDO service in the `tpsvcin` info->data buffer and relinquishes control to the `mirror` service.
6. The `cmrcv` request receives the contents of the `odata` returned on the TUXEDO `tpreturn` service, and notification that the conversation has ended with the return code value of `CM_DEALLOCATED_NORMAL`.


Figure 6-33 Host CPI-C to TUXEDO Conversational Service, Client Retains Control



Step-by-Step Description: Host CPI-C to TUXEDO Conversational Service, Client Retains Control

1. The CPI-C application program MIRRCPIC is invoked using environment start-up specifications.
2. The MIRRCPIC client requests `cminit` to establish conversation attributes and receive a conversation id that will be used on all other requests on this conversation. The remote server and service are named in the CPI-C side information entry `MIRRSIDE`.
3. The `cmallc` request initiates the advertised service mapped to `MIRRORSEV` in the `DM_LOCAL_SERVICES` section of the `DMCONFIG` file.
4. The `cmsend` request sends the contents of `obuffer` to the TUXEDO service in the `tpsvcininfo->data` buffer.
5. The `cmdeal` request flushes the data and ends the conversation, as indicated by `TPNOREPLY` in the `tpsvcininfo->flag` field.


Figure 6-34 Host CPI-C TUXEDO to Conversational Service, Client Grants Control



Step-by-Step Description: TUXEDO Conversational Service, Client Grants Control

1. The CPI-C application program `MIRRCPI` is invoked using environment start-up specifications.
2. The `MIRRCPI` client requests `cminit` to establish conversation attributes and receive a conversation ID that will be used on all other requests on this conversation. The remote server and service are named in the CPI-C side information entry `MIRRSIDE`.
3. The `cmailc` request initiates the advertised service mapped to `MIRROR` in the `DM_LOCAL_SERVICES` section of the `DMCONFIG` file.
4. The `cmptr` relinquishes control of the conversation to the TUXEDO service indicated as `TPSENDONLY` in the `tpsvcin` info->flag field. No data is passed in the `tpsvcin` info->data field.
5. The `cmrcv` receives the contents of the `tpsend` odata into the `ibuffer`. The end of the conversation is passed from the `tpreturn` service as return code value `CM_DEALLOCATED_NORMAL`.


Figure 6-35 Transactional TUXEDO Client Request/Response to Host CPI-C



Step-by-Step Description: Transactional TUXEDO Client Request/Response to Host CPI-C

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpbegin` to start the transaction.
3. The `toupsrv` service issues `tpcall` for `SIMPCPIC`, which is advertised in the `DM_REMOTE_SERVICES` section of the `DMCONFIG` file. Data is sent from the `idata` buffer on the `tpconnect`.
4. The remote service with `tpname` `TPNCPIC` invokes `TOUPCPIC` program.
5. The server accepts the conversation with the `cmaccp` call. The conversation ID returned on the request in `convid` is used for all other requests during this conversation.
6. The `cmrcv` request receives the `idata` buffer contents for processing.
7. The `cmsst` and `cmsptr` prepare the next send request by setting the send type to `CM_SEND_AND_PREP_TO_RECEIVE` and by setting the prepare-to-receive type to `CM_PREP_TO_RECEIVE_CONFIRM`.
8. The `cmsend` request immediately returns the `obuffer` contents into the client's `odata` buffer. The server relinquishes control to the server and indicates the end of the conversation with the `CONFIRM` request.
9. The `toupsrv` issues the `tpcommit` to successfully complete the transaction and commit all updated resources. The `cmrcv` request receives the commit request, and responds explicitly to the request with the SAA Resource/Recovery commit call `srrcmit`. The conversation is ended after the successful commit exchange.


Figure 6-36 Transactional TUXEDO Conversational Client to Host CPI-C, Server Gets Control



Step-by-Step Description: Transactional TUXEDO Conversational Client to Host CPI-C, Server Gets Control

1. TUXEDO client invokes `toupsrv` service.
2. The `toupsrv` service issues `tpbegin` to start the transaction.
3. The `toupsrv` service issues a `tpconnect` service request for `SIMPCPIC`, which is advertised in the `DM_REMOTE_SERVICES` section of the `DMCONFIG` file. Data is sent in the `idata` buffer on the `tpconnect`.
4. The remote service with `tpname` `TPNCPIC` invokes `TOUPCPIC` program.
5. The server accepts the conversation with the `cmaccp` call. The conversation ID returned on the request in `convid` is used for all other requests during this conversation.
6. The `cmrcv` request receives the `idata` buffer contents sent on the `tpconnect` for processing.
7. The `TOUPCPIC` program processes the data.
8. The `cmsend` returns the `obuffer` contents into the client's `tprecv odata` buffer. The buffer contents may not be sent immediately.
9. The `cmsptr` prepares the prepare-to-receive request with `CM_PREP_TO_RECEIVE_CONFIRM`. The `cmptr` request with `CONFIRM` indicates that the conversation is finished and is communicated to the `tprecv` as `TPEV_SVCSUCC`.
10. The `toupsrv` issues the `tpcommit` to successfully complete the transaction and commit all updated resources. The `cmrcv` request receives the commit request and responds explicitly to the request with the SAA Resource/Recovery commit call `srremit`. The conversation is ended after the successful commit exchange.

Figure 6-37 Transactional Host CPI-C to TUXEDO Conversational Server, Client Grants Control



Step-by-Step Description: Transactional Host CPI-C to TUXEDO Conversational Server, Client Grants Control

1. The CPI-C application program `MIRRCPIC` is invoked using environment start-up specifications.
2. The `MIRRCPIC` client requests `cminit` to establish conversation attributes and receive a conversation ID that will be used on all other requests on this conversation. The remote server and service are named in the CPI-C side information entry `MIRRSIDE`.
3. The `cmssl` sets the conversation attributes to sync-level 2 with `CM_SYNCPOINT`. This allows the TUXEDO service to participate in the transaction.
4. The `cmalloc` request initiates the advertised service mapped to `MIRRORSERV` in the `DM_LOCAL_SERVICES` section of the `DMCONFIG` file.
5. The `MIRRCPIC` causes the client to relinquish control to the TUXEDO server with a prepare-to-receive request. The `cmsptr` sets the prepare-to-receive type to `CM_RECEIVE_AND_FLUSH`. The `cmptr` request immediately relinquishes control.
6. The `MIRROR` service sends the data contents of the `odata` buffer to the `cmrcv` `ibuffer`. The `cmrcv` receives a confirm request from the server indicating the conversation should be terminated.
7. The client replies positively to the confirm request with `cmcfmd`.
8. The `MIRRCPIC` client prepares to free the conversation with the `cmdeal` request. The conversation in `CM_DEALLOCATE_SYNC_LEVEL` commits all updated resources in the transaction and waits for the SAA resource recovery verb, `srrcmit`. After the `commit` sequence has completed, the conversation terminates.

Where to Find Additional Information

Additional information on the subject of CICS/ESA Intersystem Communications may be found in the following IBM publications:

- ◆ *CICS/ESA Intercommunication Guide*, IBM publication No. SC33-0657
- ◆ *CICS/ESA Distributed Transaction Programming Guide*, IBM publication No. SC33-00783
- ◆ *CICS/ESA Recovery and Restart Guide*, IBM publication No. SC33-0658

A Reference Pages

This appendix covers the following reference pages, formerly called man pages:

- ◆ addumap
- ◆ addusr
- ◆ CRMLOGS
- ◆ crmlkoff
- ◆ crmlkon
- ◆ xsnacrm
- ◆ delumap
- ◆ delusr
- ◆ DMADM
- ◆ dmadmin
- ◆ dmconfig
- ◆ dmloadcf
- ◆ dmunloadcf
- ◆ GWADM
- ◆ GWSNAX
- ◆ modusr
- ◆ SNACRM
- ◆ xsnacrm

addumap

Add a local-to-remote mapping for a local/remote domain pair

Synopsis

```
DMCONFIG=dmconfig runs under dmadmin
addumap -d local domain ID -R remote domain ID
-p local principal name -u remote username
```

Description

addumap can only be executed as a subcommand of dmadmin(1). The purpose of this page is to describe options for the subcommand and to show examples.

The subcommand allows the administrator to add local-to-remote user mappings for a local/remote domain pair.

Mappings are defined to be inbound, outbound or both when the application is using /SNA Domain gateways and SECURITY is set to USER_AUTH, ACL, or MANDATORY ACL in the ubbconfig file and SECURITY is set to DM_PW or USER_PW in the DMCNFIG file.

The following options are available:

-d *local domain ID*

This is the name of the local domain gateway with which the ids and passwords are associated. This is the same ID as the one used when creating the domain definitions either in the DMCNFIG file or through the Graphical Administrative Interface.

-R *remote domain ID*

This is the name of the remote domain gateway with which the ids and passwords are associated. This is the same ID as the one used when creating the domain definitions either in the DMCNFIG file or through the Graphical Administrative Interface.

-p *local principal*

The user identification number. The *local principal* must be defined in the ACL user file and must be unique within the list of existing identifiers for the application.

`-u remote username`

The remote user name as defined in the ACL security application (for example, RACF) of the remote domain.

Before running this subcommand the application must be configured using either the Graphical Administrative Interface or `tmloadcf(1)` and `dmloadcf(1)`. `dmadmin addumap` may be run on any active node.

Portability

This subcommand is available on the latest version of TUXEDO, as documented for this release of BEA eLink for Mainframe SNA.

Diagnostics

The `dmadmin addumap` subcommand exits with a return code of 0 upon successful completion.

Example

```
addumap -d ldom -R cics -p tuxusr -u cicsusr  
/*maps principal tuxusr with  
remote user cicsusr */
```

See Also

`dmadmin(1)`, `delumap(5)`

addusr

Add a user to the remote domain user and password file

Synopsis

```
DMCONFIG=dmconfig  
addusr -d local domain ID -R remote domain ID -u remote username  
[-w ]
```

Description

addusr can only be executed as a subcommand of dmadmin(1). The purpose of this page is to describe options for the subcommand and to show an example.

The subcommand allows the administrator to add remote usernames and passwords to the remote domain remote user and password table. If -w is not specified, the user is prompted for a password.

The table entries created are used for passing remote user names and passwords to remote SNA domains when the application is using /SNA Domain gateways and SECURITY is set to USER_AUTH, ACL, or MANDATORY ACL in the ubbconfig file and SECURITY is set to DM_PW or USER_PW in the DMCONFIG file.

The following options are available:

-d *local domain ID*

This is the name of the local domain gateway with which the ids and passwords are associated. This is the same ID as the one used when creating the domain definitions either in the DMCONFIG file or through the Graphical Administrative Interface.

-R *remote domain ID*

This is the name of the remote domain gateway with which the ids and passwords are associated. This is the same ID as the one used when creating the domain definitions either in the DMCONFIG file or through the Graphical Administrative Interface.

-u *remote username*

The remote user name to be added.

-w

Do not prompt for password.

Before running this subcommand the application must be configured using either the Graphical Administrative Interface or `tmloadcf(1)` and `dmloadcf(1)`. `dmadmin addusr` may be run on any active node.

Portability

This subcommand is available on the latest version of TUXEDO, as documented for this release of BEA eLink for Mainframe SNA.

Diagnostics

The `dmadmin addusr` subcommand exits with a return code of 0 upon successful completion.

Examples

```
addusr -d tux -R cics -u cicsusr /*adds remote user cicsusr to
                                cics domain's user and
                                password file. The
                                administrator is prompted for
                                a password*/
```

See Also

`delusr(5)`, `modusr(5)`

CRMLOGS

Displays the content and state of the SNA Communications Resource Manager (SNACRM) log files.

Synopsis

```
CRMLOGS <group> [<crm name>]
```

Description

You can use the CRMLOGS command to display the contents and state of the two SNARCM log files. RSTRTLOG is the transaction state log used during the recovery process and the BLOBLOG log stores session and link information. Deleting the log files require a cold start for each link involved.

CRMLOGS requires the following parameters:

<i>group</i>	SNA domain group name (required)
<i>crm name</i>	SNACRM name (default SNARCM)

Diagnostics

CRMLOGS exits with a return code of 0 upon successful completion.

Examples

To display the RSTRTLOG log file for group2, type:

```
CRMLOGS GROUP2 SNARCM.GROUP2.RSTRTLOG
```

To display the BLOBLOG log file for group1, type:

```
CRMLOGS GROUP1 SNARCM.GROUP1.BLOBLOG
```

See Also

SNACRM and `xsnacrm`

crmlkoff

Stop one or more named SNACRM links.

Synopsis

```
crmlkoff -n<hostname:port> [-v -i -h] <linkname> ...
```

Description

`crmlkoff` stops all of the SNACRM links named on the command line. This is useful if one or more individual links need to be stopped after the SNACRM server booted. It can be used from any machine located on the same TCP/IP network as the machine running the SNACRM server. It can be used in a script and will return zero if the command could be sent to the target SNACRM. It will return one if the command could not be sent to the target SNACRM.

`-n`

names the machine and port running the SNACRM server.

`-v`

specifies verbose. Normally the command will not produce any messages, facilitating use in a script.

`-i`

ignores errors. When specifying multiple links, any error encountered when issuing SNACRM commands will cause `crmlkoff` to stop processing links and return. Errors can be ignored for individual links, and processing continued with the next named link.

`<linkname>`

names the link to be stopped. This is the `*DM_SNALINKS` entry in the `DMCONFIG` which defines this link. Multiple link names can be specified.

Portability

`crmlkoff` is supported as a TUXEDO-supplied administrative tool on all platforms supporting an eLink SNA SNACRM.

Example

To stop links `link1` and `cicstest` owned by the SNACRM running on `mach` at port 5000:

```
crmlkoff -n mach:5000 link1 cicstest
```

Diagnostics

`crmlkoff` only checks the syntax of the command. Separate facilities, either `xsnacrm` or mainframe based facilities must be used to determine if the link actually became inactive. If the command could not be successfully sent to the SNACRM `crmlkoff` prints an error message, if in verbose mode, and exits with error code 1. Upon successful completion, `crmlkoff` exits with exit code 0.

See Also

`crmlkon(1)`, `xsnacrm(1)`

TUXEDO /Domain User Guide

crmlkon

Start one or more named SNACRM links.

Synopsis

```
crmlkon -n<hostname:port> [-v -i -h] <linkname> ...
```

Description

`crmlkon` starts all of the SNACRM links named on the command line. This is useful if one or more individual links failed to start when the SNACRM server booted. It can be used from any machine located on the same TCP/IP network as the machine running the SNACRM server. It can be used in a script and will return zero if the command could be sent to the target SNACRM. It will return one if the command could not be sent to the target SNACRM.

`-n`
names the machine and port running the SNACRM server.

`-v`
specifies verbose. Normally the command will not produce any messages, facilitating use in a script.

`-i`
ignores errors. When specifying multiple links, any error encountered when issuing SNACRM commands will cause `crmlkon` to stop processing links and return. Errors can be ignored for individual links, and processing continued with the next named link.

`<linkname>`
names the link to be started. This is the `*DM_SNALINKS` entry in the `DMCONFIG` which defines this link. Multiple link names can be specified.

Portability

`crmlkon` is supported as a TUXEDO-supplied administrative tool on all platforms supporting an eLink SNA SNACRM.

Example

To start links `link2` and `cicstest` owned by the SNACRM running on `mach1` at port 5000:

```
crmlkon -n mach1:5000 link2 cicstest
```

Diagnostics

`crmlkon` only checks the syntax of the command. Separate facilities, either `xsnacrm` or mainframe based facilities must be used to determine if the link actually became active. If the command could not be successfully sent to the SNACRM `crmlkon` prints an error message, if in verbose mode, and exits with error code 1. Upon successful completion, `crmlkon` exits with exit code 0.

See Also

`crmlkon(1)`, `xsnacrm(1)`

delumap

Delete a local-to-remote mapping for a local/remote domain pair

Synopsis

```
DMCONFIG=dmconfig  
delumap -d local domain ID -R remote domain ID  
-p local principal name -u remote username
```

Description

delumap can only be executed as a subcommand of dmadm(1). The purpose of this page is to describe options for the subcommand and to show examples.

The subcommand allows the administrator to delete local-to-remote user mappings for a local/remote domain pair.

Mappings are defined to be inbound, outbound or both when the application is using /SNA Domain gateways and SECURITY is set to USER_AUTH, ACL, or MANDATORY ACL in the ubbconfig file and SECURITY is set to DM_PW or USER_PW in the DMCNFIG file.

The following options are available:

-d *local domain ID*

This is the name of the local domain gateway with which the ids and passwords are associated. This is the same ID as the one used when creating the domain definitions either in the DMCNFIG file or through the Graphical Administrative Interface.

-R *remote domain ID*

This is the name of the remote domain gateway with which the ids and passwords are associated. This is the same ID as the one used when creating the domain definitions either in the DMCNFIG file or through the Graphical Administrative Interface.

-p *local principal*

The user identification number. The *local principal* must be defined in the ACL user file and must be unique within the list of existing identifiers for the application.

`-u remote username`

The remote user name as defined in the ACL security application (for example, RACF) of the remote domain. Space is a valid remote username.

Before running this subcommand the application must be configured using either the Graphical Administrative Interface or `tmloadcf(1)` and `dmloadcf(1)`. `dmadmin delumap` may be run on any active node.

Portability

This subcommand is available on the latest version of TUXEDO, as documented for this release of BEA eLink for Mainframe SNA.

Diagnostics

The `dmadmin delumap` subcommand exits with a return code of 0 upon successful completion.

Example

```
delumap -d ldom -R cics -p tuxusr -u cicsusr
/*deletes the mapping of principal
tuxusr with remote user cicsusr */
```

See Also

`dmadmin(1)`, `addumap(5)`

delusr

Delete a user from the remote domain user and password file

Synopsis

```
DMCONFIG=dmconfig  
delusr -d local domain -R remote domain -u remote username
```

Description

`delusr` can only be executed as a subcommand of `dmadmin(1)`. The purpose of this page is to describe options for the subcommand and to show an example.

The subcommand allows the administrator to remove remote usernames and passwords from the remote domain remote user and password table.

Once the entries are deleted they can no longer be used for mapping remote user names and passwords to local user names and passwords when the application is using /SNA Domain gateways and SECURITY is set to USER_AUTH, ACL, or MANDATORY ACL in the `ubbconfig` file and SECURITY is set to DM_USER_PW in the `DMCONFIG` file.

The following options are available:

`-d local domain ID`

This is the name of the local domain gateway with which the ids and passwords are associated. This is the same ID as the one used when creating the domain definitions either in the `DMCONFIG` file or through the Graphical Administrative Interface.

`-R remote domain ID`

This is the name of the remote domain gateway with which the ids and passwords are associated. This is the same ID as the one used when creating the domain definitions either in the `DMCONFIG` file or through the Graphical Administrative Interface.

`-u remote username`

The remote user name to be deleted.

Before running this subcommand the application must be configured using either the Graphical Administrative Interface or `tmloadcf(1)` and `dmloadcf(1)`. `dmadmin delusr` may be run on any active node.

Portability

This subcommand is available on the latest version of TUXEDO, as documented for this release of BEA eLink for Mainframe SNA.

Diagnostics

The `dmadmin delusr` subcommand exits with a return code of 0 upon successful completion.

Examples

```
delusr -d tux -R cics -u cicsusr /*deletes remote user cicsusr to
                                cics domain users. The
                                administrator is prompted for a
                                password*/
```

See Also

`addusr(5)`, `modusr(5)`

DMADM

/Domain administrative server

Synopsis

```
DMADM SRVGRP = "identifier"  
SRVID = "number"  
REPLYQ = "N"
```

Description

The /DOMAIN administrative server (DMADM) is a TUXEDO-supplied server that provides run-time access to the BDMCONFIG file. When DMADM is booted the BDMCONFIG environment variable should be set to the pathname of the file containing the binary version of the DMCONFIG file.

DMADM is described in the SERVERS section of the UBBCONFIG file as a server running within a group, e.g., DMADMGRP. There should be only one instance of the DMADM running in this group and it must not have a reply queue (REPLYQ must be set to "N").

The following server parameters can also be specified for the DMADM server in the SERVERS section: SEQUENCE, ENVFILE, MAXGEN, GRACE, RESTART, RQPERM and SYSTEM_ACCESS.

Portability

DMADM is supported as a TUXEDO-supplied server on UNIX System and Windows NT operating systems.

Examples

The following example illustrates the definition of the administrative server and a gateway group in the UBBCONFIG file.

```
#
*GROUPS
DMADMGRP  LMID=mach1  GRPNO=1
gwgrp     LMID=mach1  GRPNO=2
#
*SERVERS
DMADM SRVGRP="DMADMGRP" SRVID=1001 REPLYQ=N RESTART=Y GRACE=0
GWADM SRVGRP="gwgrp"    SRVID=1002 REPLYQ=N RESTART=Y GRACE=0
GWSNAX SRVGRP="gwgrp"   SRVID=1003 RQADDR="gwgrp" REPLYQ=N
RESTART=N MIN=1 MAX=1
```

See Also

dmadmin(1), tmboot(1), dmconfig(5), GWADM(5), servopts(5), ubbconfig(5)

TUXEDO /Domain User Guide
TUXEDO Administrator's Guide

dmadmin

TUXEDO System/T Domain Administration Command Interpreter

Synopsis

```
dmadmin [-c]
```

Description

The `dmadmin` interactive command interpreter is used for the administration of domain gateway groups defined for a particular TUXEDO System/T application. The interpreter can operate in two modes: administration mode and configuration mode.

The `dmadmin` command interpreter enters *administration* mode when called with no parameters. This is the default. In this mode, `dmadmin` can be run on any active node (excluding workstations) within an active application. Application administrators can use this mode to obtain or change parameters on any active domain gateway group. Application administrators may also use this mode to create, destroy, or re-initialize the DMTLOG for a particular local domain. In this case, the domain gateway group associated with that local domain must not be active, and `dmadmin` must be run on the machine assigned to the corresponding gateway group.

The `dmadmin` command interpreter enters *configuration* mode when it is invoked with the `-c` option or when the `config` subcommand is invoked. Application administrators can use this mode to update or add new configuration information to the binary version of the domain configuration file (BDMCONFIG).

The `dmadmin` command interpreter requires the use of the DOMAIN administrative server (DMADM) for the administration of the BDMCONFIG file and the gateway administrative server (GWADM) for the re-configuration of active DOMAIN gateway groups (there is one GWADM per gateway group).

Administration Mode Commands

Once `dmadmin` has been invoked, commands may be entered at the prompt (“>”) according to the following syntax:

```
command [arguments]
```

Several commonly occurring arguments can be given default values via the default command. Commands that accept parameters set via the default command check default to see if a value has been set. If no value is set, an error message is returned.

Once set, a default value remains in effect until the session is ended, unless changed by another default command. Defaults may be overridden by entering an explicit value on the command line, or reset by entering the value “*”. The effect of an override lasts for a single instance of the command.

Output from dmadmin commands is paginated according to the pagination command in use (see the paginate subcommand below).

Commands may be entered either by their full name or their abbreviation (shown in parentheses) followed by any appropriate arguments. Arguments appearing in square brackets, [], are optional; those in curly braces, { }, indicate a selection from mutually exclusive options. Note that for many commands *local_domain_name* is a required argument, but note also that it can be set with the default command.

The following commands are available in administration mode:

`addumap [options]`

Add local user mappings to remote user mappings for a local/remote domain pair. Mappings are defined to be inbound, outbound or both. See the `addumap(5)` reference page for an explanation of the available options and for examples.

`addusr (addu) [options]`

Add remote usernames and passwords to the remote user and password tables of a remote domain. See the `addusr(5)` reference page for an explanation of the available options and for examples.

`advertise (adv) -d local_domain_name [{ -all | service}]`

Advertise all remote services provided by the named local domain or the specified remote service.

`audit (audit) -d local_domain_name [{off | on}]`

Activate (on) or deactivate (off) the audit trace for the named local domain. If no option is given, then the current setting will be toggled between the values on and off, and the new setting will be printed. The initial setting is off.

`chbktme (chbt) -d local_domain_name -t bktme`

Change the blocking timeout for a particular local domain.

`config (config)`

Enter configuration mode. Commands issued in this mode follow the conventions defined in the section “Configuration Mode Commands” (see below).

`crdmlog (crdlg) -d local_domain_name`

Create the domain transaction log for the named local domain on the current machine (that is, the machine where `dmadmin` is running). The command uses the parameters specified in the `DMCONFIG` file. This command fails if the named local domain is active on the current machine or if the log already exists.

`default (d) [-d local_domain_name]`

Set the corresponding argument to be the default local domain. Defaults may be reset by specifying “*” as an argument.

If the `default` command is entered with no arguments, the current default values are printed.

`delumap [options]`

Delete local to remote user mappings for a local/remote domain pair. See the `delumap(5)` reference page for an explanation of the available options and for examples.

`delusr (delu) [options]`

Delete remote usernames and passwords from the remote user and password tables of a remote domain. See the `delusr(5)` reference page for an explanation of the available options and for examples.

`dsdmlog (dsdlg) -d local_domain_name [-y]`

Destroy the domain transaction log for the named local domain on the current machine (that is, the machine where `dmadmin` is running). An error is returned if a `DMTLOG` is not defined for this local domain, if the local domain is active, or if outstanding transaction records exist in the log. The term outstanding transactions means that a global transaction has been committed but an end-of-transaction has not yet been written. This command prompts for confirmation before proceeding unless the `-y` option is specified. `dsdmlog` is not supported for `/SNA Domain`.

`echo (e) [{off | on}]`

Echo input command lines when set to `on`. If no option is given, then the current setting is toggled, and the new setting is printed. The initial setting is `off`.

`forgettrans (ft) -d local_domain_name [-t tran_id]`

Forget one or all heuristic log records for the named local domain. If the transaction identifier *tran_id* is specified, then only the heuristic log record for that transaction will be forgotten. The transaction identifier *tran_id* can be obtained from the `printtrans` command or from the ULOG file.

`forgettrans` is not supported for /SNA Domain.

`help (h) [command]`

Print help messages. If *command* is specified, the abbreviation, arguments, and description for that command are printed. Omitting all arguments causes the syntax of all commands to be displayed.

`indmlog (indlg) -d local_domain_name [-y]`

Re-initialize the domain transaction log for the named local domain on the current machine (that is, the machine where `dmadmin` is running). An error is returned if a DMTLOG is not defined for this local domain, if the local domain is active, or if outstanding transaction records exist in the log. The term outstanding transactions means that a global transaction has been committed but an end-of-transaction has not yet been written. The command prompts for confirmation before proceeding unless the `-y` option is specified. `indmlog` is not supported for /SNA Domain.

`modusr (modu) [options]`

Change remote passwords in the password tables of a remote domain. See the `modusr(5)` reference page for an explanation of the available options and for examples.

`paginate (page) [{off | on}]`

Paginate output. If no option is given, then the current setting will be toggled, and the new setting is printed. The initial setting is on, unless either standard input or standard output is a non-tty device. Pagination may only be turned on when both standard input and standard output are tty devices. The shell environment variable `PAGER` may be used to override the default command used for paging output. The default paging command is the indigenous one to the native operating system environment, for example, the command `pg` is the default on UNIX System operating environments.

`passwd (passwd) [-r] local_domain_name remote_domain_name`

Prompts the administrator for new passwords for the specified local and remote domains. The `-r` option specifies that existing passwords and new passwords should be encrypted using a new key generated by the system. The password is truncated after at most eight characters.

`printdomain (pd) -d local_domain_name`

Print information about the named local domain. Information printed includes connected remote domains, global information shared by the gateway processes, and additional information that is dependent on the domain type instantiation.

`printstats (stats) -d local_domain_name`

Print statistical and performance information gathered by the named local domain. The information printed is dependent on the domain gateway type.

`printtrans (pt) -d local_domain_name`

Print transaction information for the named local domain. `printtrans` is not supported for /SNA Domain.

`quit (q)`

Terminate the session.

`resume (res) -d local_domain_name [{ -all | service}]`

Resume processing of the specified service or for all remote services handled by the named local domain.

`stats (stats) -d local_domain_name [{ off | on | reset }]`

Activate (*on*), deactivate (*off*), or reset (*reset*) statistics gathering for the named local domain. If no option is given, then the current setting will be toggled between the values *on* and *off*, and the new setting will be printed. The initial setting is *off*.

`suspend (susp) -d local_domain_name [{ -all | service}]`

Suspend one or all remote services for the named local domain.

`unadvertise (unadv) -d local_domain_name [{ -all | service}]`

Unadvertise one or all remote services for the named local domain.

`verbose (v) [{off | on}]`

Produce output in verbose mode. If no option is given, then the current setting will be toggled, and the new setting is printed. The initial setting is *off*.

`! shellcommand`

Escape to shell and execute *shellcommand*.

`!!`

Repeat previous shell command.

[*text*]

Lines beginning with "#" are comment lines and are ignored.

<CR>

Repeat the last command.

Configuration Mode Commands

The `dmadmin` command enters configuration mode when executed with the `-c` option or when the `config` subcommand is used. In this mode, `dmadmin` allows run-time updates to the `BDMCONFIG` file. `dmadmin` manages a buffer that contains input field values to be added or retrieved, and displays output field values and status after each operation completes. The user can update the input buffer using any available text editor.

The `dmadmin` command first prompts for the desired section followed by a prompt for the desired operation.

The prompt for the section is as follows:

Sections:

- | | |
|-------------------|--------------------|
| 1) LOCAL_DOMAINS | 2) REMOTE_DOMAINS |
| 3) LOCAL_SERVICES | 4) REMOTE_SERVICES |
| 5) ROUTING | 6) ACCESS_CONTROL |
| 7) PASSWORDS | 8) TDOMAIN |
| 9) OSITP | 10) SNA |
| 11) QUIT | |

Enter Section [1]:

The number of the default section appears in square brackets at the end of the prompt. You can accept the default by pressing `RETURN` or `ENTER`. To select another section enter its number, then press `RETURN` or `ENTER`.

`dmadmin` then prompts for the desired operation.

Operations:

- | | |
|----------------|-----------|
| 1) FIRST | 2) NEXT |
| 3) RETRIEVE | 4) ADD |
| 5) UPDATE | 6) DELETE |
| 7) NEW_SECTION | 8) QUIT |

Enter Operation [1]:

The number of the default operation is printed in square brackets at the end of the prompt. Pressing `RETURN` or `ENTER` selects this option. To select another operation enter its number, then press `RETURN` or `ENTER`.

The currently supported operations are:

1. FIRST

Retrieve the first record from the specified section. No key fields are needed (they are ignored if in the input buffer).

2. NEXT

Retrieve the next record from the specified section, based on the key fields in the input buffer.

3. RETRIEVE

Retrieve the indicated record from the specified section by key field(s) (see fields description below).

4. ADD

Add the indicated record in the specified section. Any fields not specified (unless required) take their default values as specified in `dmconfig(5)`. The current value for all fields is returned in the output buffer. This operation can only be done by the System/T administrator.

5. UPDATE

Update the record specified in the input buffer in the selected section. Any fields not specified in the input buffer remain unchanged. The current value for all fields is returned in the input buffer. This operation can only be done by the System/T administrator.

6. DELETE

Delete the record specified in the input buffer from the selected section. This operation can only be done by the System/T administrator.

7. NEW SECTION

Clear the input buffer (all fields are deleted). After this operation, `dmadmin` immediately prompts for the section again.

8. QUIT

Exit the program gracefully (`dmadmin` is terminated). A value of `q` for any prompt also exits the program.

For configuration operations, the effective user identifier must match the System/T administrator user identifier (`UID`) for the machine on which this program is executed. When a record is updated or added, all default values and validations used by `dmloadcf(1)` are enforced.

`dmadmin` then prompts whether or not to edit the input buffer.

Enter editor to add/modify fields [n]?

Entering a value of `y` will put the input buffer into a temporary file and execute the text editor. The environment variable `EDITOR` is used to determine which editor to be used; the default is “`ed`”. The input format is in field name/field value pairs and is described in the `CONFIGURATION INPUT FORMAT` section below. The field names associated with each `DMCONFIG` section are listed in tables in the subsections below. The semantics of the fields and associated ranges, default values, restrictions, etc., are described in `dmconfig(5)`. In most cases, the field name is the same as the `KEYWORD` in the `DMCONFIG` file, prefixed with “`TA_`”. When the user completes editing the input buffer, `dmadmin` reads it. If more than one line occurs for a particular field name, the first occurrence is used and other occurrences are ignored. If any errors occur, a syntax error will be printed and `dmadmin` prompts whether or not to correct the problem.

Enter editor to correct?

If the problem is not corrected (response `n`), then the input buffer will contain no fields. Otherwise, the editor is executed again.

Finally, `dmadmin` asks if the operation should be done.

Perform operation [y]?

When the operation completes, `dmadmin` prints the return value as in

Return value `TAOK`

followed by the output buffer fields. The process then begins again with a prompt for the section. All output buffer fields are available in the input buffer unless the buffer is cleared.

Entering break at any time restarts the interaction at the prompt for the section.

When “`QUIT`” is selected, `dmadmin` prompts for authorization to create a backup ASCII version of the configuration:

Unload `BDMCONFIG` file into ASCII backup [y]?

If a backup is selected, `dmadmin` prompts for the file name.

Backup filename [`DMCONFIG`]?

On success, `dmadmin` indicates that a backup was created, otherwise an error is printed.

Configuration Input Format

Input packets consist of lines formatted as follows:

```
fldname<tabs>fldval
```

The field name is separated from the field value by one or more tabs (or spaces).

Lengthy field values can be continued on the next line by having the continuation line begin with one or more tabs (which are dropped when read back into `dmadmin`).

Empty lines consisting of a single newline character are ignored.

To enter an unprintable character in the field value or to start a field value with a tab, use a backslash followed by the two-character hexadecimal representation of the desired character (see ASCII(5) in a UNIX reference manual). A space, for example, can be entered in the input data as `\20`. A backslash can be entered using two backslash characters. `dmadmin` recognizes all input in this format, but its greatest usefulness is for non-printing characters.

Configuration Limitations

The following are general limitations of the dynamic domain re-configuration capability:

- ◆ Values for key fields (as indicated in the following sections) may not be modified. Key fields can be modified, when the system is down, by reloading the configuration file.
- ◆ Dynamic deletions cannot be applied when local domains are active (the corresponding gateway group is running).

Restrictions for Configuration Field Identifiers/Updates

The following sections describe, for each `DMCONFIG` section, what the field identifiers are for each `DMCONFIG` field, what the field type of the identifier is, and when the field can be updated. All applicable field values are returned with the retrieval operations. Fields that are allowed and/or required for adding a record are described in `dmconfig(5)`. Fields indicated below as *key* are key fields that are used to uniquely identify a record within section. These key fields are required to be in the input buffer when updates are done and are not allowed to be updated dynamically. The `Update` column indicates when a field can be updated. The possible values are:

Yes

Can be updated at any time.

NoGW

Cannot be updated dynamically while the gateway group representing the local domain is running.

No

Cannot be updated dynamically while at least one gateway group is running.

Configuring the DM_LOCAL_DOMAINS Section

The following table lists the fields in the DM_LOCAL_DOMAINS section.

Table A-1 DM_LOCAL_DOMAINS SECTION

Field Identifier	Field Type	Update	Notes
TA_LDOM	string	NoGW	key
TA_AUDITLOG	string	Yes	
TA_BLOCKTIME	numeric	Yes	
TA_DOMAINID	string	NoGW	
TA_DMTLOGDEV	string	NoGW	
TA_DMTLOGNAME	string	NoGW	
TA_DMTLOGSIZE	numeric	NoGW	
TA_GWGRP	string	NoGW	
TA_MAXDATALEN	numeric	Yes	
TA_MAXRDOM	numeric	Yes	
TA_MAXRDTRAN	numeric	NoGW	
TA_MAXTRAN	numeric	NoGW	
TA_SECURITY	string	Yes	format: {NONE APP_PW DM_PW}
TA_TYPE	string	NoGW	format: {TDOMAIN OSITP SNA}

Configuring the DM_REMOTE_DOMAINS Section

The following table lists the fields in the DM_REMOTE_DOMAINS section.

Table A-2 DM_REMOTE_DOMAINS SECTION

Field Identifier	Field Type	Update	Notes
TA_RDOM	string	No	key
TA_DOMAINID	string	No	
TA_TYPE	string	No	format: {TDOMAIN OSITP SNA }
TA_CODEPAGE	string	No	CODEPAGE filename

Configuring the DM_TDOMAIN Section

The DM_TDOMAIN section contains the network addressing parameters required by TDOMAIN type domains. The following lists the fields in this section:

Table A-3 DM_TDOMAIN SECTION

Field Identifier	Field Type	Update	Notes
TA_LDOM or TA_RDOM	string	No/NoGW	key
TA_NWADDR	string	No/NoGW	ASCII format (no embedded NULL characters)

If the domain identifier (TA_LDOM) is a local domain identifier, then the TA_NWADDR field can be updated if the gateway group representing that local domain is not running.

Configuring the DM_OSITP Section

The DM_OSITP section contains the network addressing parameters required by OSITP type domains. The following lists the fields in this section:

Table A-4 DM_OSITP SECTION

Field Identifier	Field Type	Update	Notes
TA_LDOM or TA_RDOM	string	No/NoGW	key
TA_APT	string	No/NoGW	
TA_AEQ	string	No/NoGW	
TA_AET	string	No/NoGW	
TA_ACN	string	No/NoGW	
TA_APID	string	No/NoGW	
TA_AEID	string	No/NoGW	
TA_PROFILE	string	No/NoGW	

If the domain identifier (TA_LDOM) is a local domain identifier, then the other fields in this table can be updated if the gateway group representing that local domain is not running.

Configuring the DM_LOCAL_SERVICES Section

The following table lists the fields in the DM_LOCAL_SERVICES section.

Table A-5 DM_LOCAL_SERVICES SECTION

Field Identifier	Field Type	Update	Notes
TA_SERVICENAME	string	No	key
TA_LDOM	string	Yes	
TA_RNAME	string	Yes	
TA_ACLNAME	string	Yes	
TA_BUFTYPE	string	Yes	
TA_BUFSTYPE	string	Yes	

Table A-5 DM_LOCAL_SERVICES SECTION

Field Identifier	Field Type	Update	Notes
TA_OBUFTYPE	string	Yes	
TA_OBUFSTYPE	string	Yes	

Configuring the DM_REMOTE_SERVICES Section

The following table lists the fields in the DM_REMOTE_SERVICES section.

Table A-6 DM_REMOTE_SERVICES SECTION

Field Identifier	Field Type	Update	Notes
TA_SERVICENAME	string	No	key
TA_RDOM	string	No	key
TA_LDOM	string	No	key
TA_RNAME	string	Yes	
TA_CONV	string	NoGW	format: { Y N }
TA_BUFTYPE	string	Yes	
TA_BUFSTYPE	string	Yes	
TA_OBUFTYPE	string	Yes	
TA_OBUFSTYPE	string	Yes	
TA_ROUTINGNAME	string	Yes	
TA_TRANTIME	numeric	Yes	
TA_FUNCTION	string	No	

Configuring the DM_ROUTING Section

The following table lists the fields in the DM_ROUTING section.

Table A-7 DM_ROUTING SECTION

Field Identifier	Field Type	Update	Notes
TA_ROUTINGNAME	string	No	key
TA_FIELD	string	Yes	
TA_RANGE	string	Yes	
TA_BUFTYPE	string	Yes	

Configuring the DM_ACCESS_CONTROL Section

The following table lists the fields in the DM_ACCESS_CONTROL section.

Table A-8 DM_ACCESS_CONTROL SECTION

Field Identifier	Field Type	Update	Notes
TA_ACLNAME	string	No	key
TA_RDOM	string	Yes	

Configuring the DM_PASSWORDS Section

The following table lists the fields in the DM_PASSWORDS section.

Table A-9 DM_PASSWORDS SECTION

Field Identifier	Field Type	Update	Notes
TA_LDOM	string	No	key
TA_RDOM	string	No	key
TA_LPWD	string	Yes	format: { Y N U }
TA_RPWD	string	Yes	format: { Y N U }

The TA_LPWD and TA_RPWD show the existence of a defined password for the local and/or the remote domain. Passwords are not displayed. If an UPDATE operation is selected, the value of the corresponding field must be set to U. The program will then prompt with echo turned off for the corresponding passwords.

Diagnostics in Configuration Mode

dmadmin fails if it cannot allocate an FML typed buffer, if it cannot determine the /etc/passwd entry for the user, or if it cannot reset the environment variables FIELDTBLS or FLDTBLDIR.

The return value printed by dmadmin after each operation completes indicates the status of the requested operation. There are three classes of return values.

The following return values indicate a problem with permissions or a TUXEDO System/T communications error. They indicate that the operation did not complete successfully.

[TAEPERM]

The calling process specified an ADD, UPDATE, or DELETE operation but it is not running as the System/T administrator. Update operations must be run by the administrator (that is, the user specified in the UID attribute of the RESOURCES section of the TUXCONFIG file).

[TAESYSTEM]

A TUXEDO System/T error has occurred. The exact nature of the error is written to userlog(3).

[TAEOS]

An operating system error has occurred.

[TAETIME]

A blocking timeout occurred. The input buffer is not updated so no information is returned for retrieval operations. The status of update operations can be checked by doing a retrieval on the record that was being updated.

The following return values indicate a problem in doing the operation itself and generally are semantic problems with the application data in the input buffer. The string field TA_STATUS will be set in the output buffer and will contain short text describing the problem. The string field TA_BADFLDNAME will be set to the field name for the field containing the value that caused the problem (assuming the error can be attributed to a single field).

[TAECONFIG]

An error occurred while reading the BDMCONFIG file.

[TAEDUPLICATE]

The operation attempted to add a duplicate record.

[TAEINCONSIS]

A field value or set of field values are inconsistently specified.

[TAENOTFOUND]

The record specified for the operation was not found.

[TAENOSPACE]

The operation attempted to do an update but there was not enough space in the BDMCONFIG file.

[TAERANGE]

A field value is out of range or is invalid.

[TAEREQUIRED]

A field value is required but not present.

[TAESIZE]

A field value for a string field is too long.

[TAEUPDATE]

The operation attempted to do an update that is not allowed.

The following return values indicate that the operation was successful.

[TAOK]

The operation succeeded. No updates were done to the BDMCONFIG file.

[TAUPDATED]

The operation succeeded. Updates were made to the BDMCONFIG file.

When using `dmunloadcf` to print entries in the configuration, optional field values are not printed if they are not set (for strings) or 0 (for integers). These fields will always appear in the output buffer when using `dmadmin`. In this way, it makes it easier for the administrator to retrieve an entry and update a field that previously was not set. The entry will have the field name followed by a tab but no field value.

Configuration Example

In the following example, `dmadmin` is used to add a new remote domain. For illustration purposes, `ed` is used for the editor.

```
$ EDITOR=ed dmadmin
> config
Sections:
    1) LOCAL_DOMAINS          2) REMOTE_DOMAINS
    3) LOCAL_SERVICES         4) REMOTE_SERVICES
    5) ROUTING                 6) ACCESS_CONTROL
    7) PASSWORDS              8) TDOMAIN
    9) OSITP                  10) SNA
    11) QUIT
Enter Section [1]: 2
Operations:
    1) FIRST                   2) NEXT
    3) RETRIEVE                4) ADD
    5) UPDATE                  6) DELETE
    7) NEW_SECTION             8) QUIT
Enter Operation [1]: 4
Enter editor to add/modify fields [n]? y
a
TA_RDOM                       B05
TA_DOMAINID                   BA.BANK05
TA_TYPE                       TDOMAIN
w
53
q
Perform operation [y]? <return>
Return value TAUPDATED
Buffer contents:
TA_OPERATION                   4
TA_SECTION                     2
TA_DOMAINID                   BA.BANK05
TA_RDOM                       B05
TA_TYPE                       TDOMAIN
TA_STATUS                     Update completed successfully
Operations:
    1) FIRST                   2) NEXT
    3) RETRIEVE                4) ADD
    5) UPDATE                  6) DELETE
    7) NEW_SECTION             8) QUIT
Enter Operation [4]: 7
Sections:
    1) LOCAL_DOMAINS          2) REMOTE_DOMAINS
    3) LOCAL_SERVICES         4) REMOTE_SERVICES
    5) ROUTING                 6) ACCESS_CONTROL
```

```

        7) PASSWORDS                8) TDOMAIN
        9) OSITP                    10) QUIT
Enter Section [1]: 8
Operations:
        1) FIRST                    2) NEXT
        3) RETRIEVE                4) ADD
        5) UPDATE                  6) DELETE
        7) NEW_SECTION              8) QUIT
Enter Operation [6]: 4
Enter editor to add/modify fields [n]? y
a
TA_RDOM                            B05
TA_NWADDR                          0x00020401c0066d05
w
55
q
Perform operation [y]? <return>
Return value TAUPDATED
Buffer contents:
TA_OPERATION                        4
TA_SECTION                          8
TA_RDOM                            B05
TA_NWADDR                          0x00020401c0066d05
TA_STATUS                          Update completed successfully
Operations:
        1) FIRST                    2) NEXT
        3) RETRIEVE                4) ADD
        5) UPDATE                  6) DELETE
        7) NEW_SECTION              8) QUIT
Enter Operation [4]: 8
> quit
The dmadmin program ends.

```

Security

If dmadmin is run with the application administrator's UID, it assumes a trusted user and Security is bypassed. If dmadmin is run with another user ID, and if the security option is enabled in the TUXCONFIG file, then the corresponding application password is required to start the dmadmin program. If standard input is a terminal, then dmadmin will prompt the user for the password with echo turned off. If standard input is not a terminal, the password is retrieved from the environment variable, APP_PW. If this environment variable is not specified and an application password is required, then dmadmin will fail to start.

When running with another user ID (other than the UID of the administrator) only a limited set of commands is available.

Environment Variables

The `dmadmin` command resets the `FIELDTBLS` and `FLDTBLDIR` environment variables to pick up the `${TUXDIR}/udataobj/dmadmin` field table. Hence, the `TUXDIR` environment variable should be set correctly.

If the application requires security and the standard input to `dmadmin` is not from a terminal, then the `APP_PW` environment variable must be set to the corresponding application password.

The `TUXCONFIG` environment variable should be set to the pathname of the TUXEDO System/T configuration file.

General Diagnostics

If the `dmadmin` command is entered before the system has been booted, the following message is displayed:

```
No bulletin board exists. Only logging commands are available.
```

`dmadmin` then prompts for the corresponding commands.

If an incorrect application password is entered or is not available to a shell script through the environment, then a log message is generated, the following message is displayed, and the command terminates:

```
Invalid password entered.
```

Interoperability

`dmadmin` for /SNA must be installed on TUXEDO System/T R6.4. Other nodes in the same domain with an R6.4 gateway may be TUXEDO System/T R4.2.2 or later.

Portability

This command interpreter is supported as a TUXEDO System/T-supplied administrative tool on UNIX and Windows NT operating systems.

See Also

`dmloadcf(1)`, `tmadmin(1)`, `dmconfig(5)`, `DMADM(5)`, `addusr(5)`, `delusr(5)`

TUXEDO /Domain User Guide

dmconfig

TUXEDO System/T ASCII domain configuration file

Description

`dmconfig` is the ASCII version of a TUXEDO System/Domain domain configuration file; it is also referred to by its environmental variable name: `DMCONFIG`. The `dmconfig` file is parsed and loaded into a binary version by the `dmloadcf(1)` utility. The binary configuration file, called the `BDMCONFIG` file, contains information used by domain gateways to initialize the context required for communications with other domains. `dmadmin(1)` uses the binary file (or a copy of it) in its monitoring activity. There will be one `BDMCONFIG` file for each TUXEDO System/Domain application that uses the /Domain feature.

A `DMCONFIG` file, and its binary `BDMCONFIG` counterpart, are analogous to the `UBBCONFIG` and `TUXCONFIG` files of a non-/Domain System/T application. The `DMCONFIG` file extends the definition of a non-/Domain System/T application so that the application becomes a domain.

Definitions

A TUXEDO System/Domain Application is defined as the environment described in a single `TUXCONFIG` file. A System/T Application can communicate with another System/T Application or with another TP Application via a domain gateway group. In “TUXEDO System/Domain” terms, an Application is the same as a TP Domain.

A Gateway Group is a collection of domain gateway processes that provide communication services with a specific type of TP Domain.

A Domain Gateway is a TUXEDO System/Domain process that relays requests and replies to another TP Domain.

A Local Domain characterizes a part of the application (set or subset of services) that is made available to other domains. A Local Domain is always represented by a Domain Gateway Group, and both terms are used as synonyms.

A Remote Domain is a remote application that is accessed through a Gateway Group. The remote application may be another TUXEDO System/Domain application or an application running under another TP system.

A `Remote Service` is a service provided by a remote domain that is made available to the local application through a Gateway Group.

A `Local Service` is a service of a local domain that is made available to remote domains through a Gateway Group.

Configuration File Format

The format of a domain configuration file is as follows:

- ◆ The file is made up of eight possible specification sections. Lines beginning with an asterisk (*) indicate the beginning of a specification section. Each such line contains the name of the section immediately following the *. Allowable section names are: `DM_LOCAL_DOMAINS`, `DM_REMOTE_DOMAINS`, `DM_SNACRM`, `DM_SNASTACKS`, `DM_SNALINKS`, `DM_LOCAL_SERVICES`, `DM_REMOTE_SERVICES`, `DM_ROUTING`, `DM_ACCESS_CONTROL`, `DM_OSITP`, and `DM_TDOMAIN`. The `DM_LOCAL_DOMAINS` section must precede the `DM_REMOTE_DOMAINS` /.
- ◆ Parameters are generally specified by: `KEYWORD = value`. This sets `KEYWORD` to `value`. Valid keywords are described below within each section. `KEYWORDS` are reserved; they can not be used as `values` unless they are quoted.

Lines beginning with the reserved word, `DEFAULT:`, contain parameter specifications that apply to any lines that follow them in the section in which they appear. Default specifications can be used in all sections. They can appear more than once in the same section. The format for these lines is:

```
DEFAULT: [ KEYWORD1 = value1 [ KEYWORD2 = value2 [...]]]
```

The values set on this line remain in effect until reset by another `DEFAULT:` line, or until the end of the section is reached. These values can also be overridden on non-`DEFAULT:` lines by placing the optional parameter setting on the line. If on a non-`DEFAULT:` line, the parameter setting is valid for that line only; lines that follow revert to the default setting. If `DEFAULT:` appears on a line by itself, all previously set defaults are cleared and their values revert to the system defaults.

If a value is *numeric*, standard C notation is used to denote the base (that is, 0x prefix for base 16 (hexadecimal), 0 prefix for base 8 (octal), and no prefix for base 10 (decimal)). The range of values acceptable for a numeric parameter are given under the description of that parameter.

If a value is an *identifier*, standard C rules are used. An *identifier* must start with an alphabetic character or underscore and contain only alphanumeric

characters or underscores. The maximum allowable length of an identifier is 30 (not including the terminating null). An identifier cannot be the same as any *KEYWORD*.

A value that is neither an integer number or an identifier must be enclosed in double quotes. Certain special characters can be escaped inside a string using a backslash. “\\” translates to a single backslash. “\”\”” translates to a double quote. “\n” translates to a newline. “\t” translates to a tab. “\f” translates to a form feed. “\x” (where ‘x’ is any character other than one of the previously mentioned special characters) translates to ‘x’.

- ◆ Input fields are separated by at least one space (or tab) character.
- ◆ “#” introduces a comment. A newline ends a comment.
- ◆ Blank lines and comments are ignored.
- ◆ Comments can be freely attached to the end of any line.
- ◆ Lines are continued by placing at least one tab after the newline. Comments can not be continued.

VERSION=*string_value*

where *string_value* can be any value. The field is not checked by the software; it is provided simply as a place where the customer can enter a string that may have some documentation value to the application.

The DM_LOCAL_DOMAINS Section

This section identifies local domains and their associated gateway groups. The section must have an entry for each gateway group (Local Domain). Each entry specifies the parameters required for the domain gateway processes running in that group.

Entries have the form:

LDOM required parameters [optional parameters]

where *LDOM* is an *identifier* value used to name each local domain. *LDOM* must be unique within a particular configuration. As you will see in the description of the DM_LOCAL_SERVICES section, *LDOM* is the identifier that connects local services with a particular gateway group.

The following are the required parameters:

`GWGRP = identifier`

specifies the name of the gateway server group (the name provided in the TUXCONFIG file) representing this local domain. There is a one-to-one relationship between a *DOMAINID* (see below) and the name of the gateway server group, that is, each GWGRP must have its own, unique DOMAINID.

`TYPE = identifier`

is used for grouping local domain into classes. TYPE can be set to one of the following values: TDOMAIN, OSITP or SNAX. The TDOMAIN value indicates that this local domain can only communicate with another TUXEDO System/Domain. The OSITP value indicates that this local domain communicates with another TP Domain via the OSI-TP protocol. The SNA value indicates that this local domain communicates with an MVS/CICS region via the LU6.2 protocol. Domain types must be defined in the \$TUXDIR/udataobj/DMTYPE file.

`DOMAINID = string`

is used to identify the local domain. DOMAINID must be unique across both local and remote domains. The value of *string* can be a sequence of characters (for example, "BA.CENTRAL01"), or a sequence of hexadecimal digits preceded by "0x" (for example, "0x0002FF98C0000B9D6"). DOMAINID must be 32 octets or fewer in length. If the value is a string, it must be 32 characters or fewer (counting the trailing null).

`DMTLOGDEV = string`

specifies the TUXEDO filesystem that contains the Domain transaction log (DMTLOG) for this machine. The DMTLOG is stored as a TUXEDO System VTOC table on the device. If this parameter is not specified (and it should not be specified if TYPE=SNADOM), the domain gateway group is not allowed to process requests in transaction mode. Local domains running on the same machine can share the same DMTLOGDEV filesystem, but each local domain must have its own log (a table in the DMTLOGDEV) named as specified by the DMTLOGNAME keyword (see below).

Optional parameters describe resources and limits used in the operation of domain gateways:

`AUDITLOG = string`

specifies the name of the audit log file for this local domain. The audit log feature is activated from the `dmadmin(1)` command and records all the operations within this local domain. If the audit log feature is active and this parameter is not specified, the file `DMmmddy.LOG` (where `mm`=month, `dd`=day, and `yy`=year) is created in the directory specified by the `$APPDIR`

environment variable or the APPDIR keyword of the MACHINES section of the TUXCONFIG file.

`BLOCKTIME = numeric`

specifies the maximum wait time allowed for a blocking call. The value sets a multiplier of the SCANUNIT parameters specified in the TUXCONFIG file. The value `SCANUNIT * BLOCKTIME` must be greater than or equal to SCANUNIT and less than 32,768 seconds. If this parameter is not specified, the default value is set to the value of the BLOCKTIME parameter specified in the TUXCONFIG file. A time-out always implies a failure of the affected request. Notice that the time-out specified for transactions in the TUXCONFIG will always be used when the request is issued within a transaction.

`DMTLOGNAME = identifier`

specifies the name of the domain transaction log for this domain. This name must be unique when the same DMTLOGDEV is used for several local domains. If not specified, the default is the string “DMTLOG”. The name must be 30 characters or less. Since transactions are not support for /SNA Domain, this parameter has no meaning when `TYPE=SNADOM`.

`DMTLOGSIZE = numeric`

specifies the numeric size, in pages, of the Domain transaction log for this machine. It must be greater than 0 and less than the amount of available space on the TUXEDO filesystem. If not specified, the default is 100 pages. Since transactions are not support for /SNA Domain, this parameter has no meaning when `TYPE=SNADOM`.

`MAXDATALEN = numeric`

specifies a maximum amount of data (in bytes) that can be sent to or from any services advertised by this local domain. There is no limit if this parameter is not specified.

`MAXRDOM = numeric`

specifies the maximum number of connections (or dialogues if the domain is of type *OSITP*) allowed per gateway. There is no limit if this parameter is not specified.

`MAXRDTRAN = numeric`

specifies the maximum number of domains that can be involved in a transaction. It must be greater than 0 and less than 32,768. If not specified, the default is 16. Since transactions are not support for /SNA Domain, this parameter has no meaning when `TYPE=SNADOM`.

`MAXTRAN = numeric`

specifies the maximum number of simultaneous global transactions allowed on this local domain. It must be greater than or equal to 0 and less than or equal to the `MAXGTT` parameter specified in the `TUXCONFIG` file. If not specified, the default is the value of `MAXGTT`.

`MAXSENDLEN = numeric`

specifies the maximum length (in bytes) of messages sent or received by this local domain. If this parameter is set all messages sent or received will be broken up into packets of no more than `MAXSENDLEN` bytes. There is no limit if this parameter is not specified.

`SECURITY = value`

specifies the type of application security to be enforced. The following description applies to security in an /SNA Domain.

The combined settings of the `SECURITY` parameters in the `UBBCONFIG` and the `DMCONFIG` files have the following effects:

- ◆ When the `DM_LOCAL_DOMAINS` Security parameter is set to `NONE` or `APP_PW`, no action is taken by the eLink SNA gateway with regard to security.
- ◆ However, when the `UBBCONFIG` file Security parameter is set to `APP_PW`, the application password is validated by an `AUTHSVC` when clients join the application. The `AUTHSVC` is provided by the user application.

If security is to be enforced by both the local domain and the host system for each request outbound from the local domain, the following settings must be made:

- ◆ `UBBCONFIG` file Security parameter must be set to one of: `USER_AUTH`, `ACL`, or `MANDATORY_ACL`
- ◆ `DMCONFIG` file `DM_LOCAL_DOMAINS` section Security parameter must be set to `DM_USER_PW`
- ◆ `DM_SNALINKS` Security parameter must be set to `IDENTIFY` or `VERIFY`.

If security is to be enforced by both the local domain and the host system for each request inbound from the host system to the local domain, the following settings must be made:

- ◆ `UBBCONFIG` file Security parameter must be set to one of: `USER_AUTH`, `ACL`, or `MANDATORY_ACL`

- ◆ DMCONFIG file DM_LOCAL_DOMAINS section Security parameter must be set to DM_USER_PW
- ◆ DM_SNALINKS Security parameter must be set to IDENTIFY or VERIFY.

For a request sent to the host system, the local principal userid is located in the domain security table and the associated remote userid, or userid and password, are put into the conversation start-up request before being sent over the LU6.2 conversation. (This occurs if SECURITY is set to IDENTIFY or VERIFY in the DM_SNALINKS section of the DMCONFIG file.)

For requests sent from the host system, the local domain extracts the remote userid, or userid and password, from the conversation start-up request and checks the domain security table. That table contains pairs of local principal userids and remote userids, maintained on a service-by-service basis. The remote userid is mapped to the local principal userid. The local principal userid and password are used for further Access Control List (ACL) checking, as specified in the UBBCONFIG file.

When a request is received from the host system, the local domain checks the DMCONFIG file ACL for the local service to see if requests from the remote domain are permitted. If the DMCONFIG file does not contain an ACL for the local service, the service is accessible to all requests.

Therefore, if the ATTACHSEC level for the connection definition in the host system is *Identify* or *Verify*, the DMCONFIG SECURITY parameter must be set to DM_USER_PW so that a userid and a password are sent on the conversation start-up requests.

The DM_REMOTE_DOMAINS Section

This section identifies the known set of remote domains and their characteristics.

Entries have the form:

RDOM required parameters [optional parameters]

where *RDOM* is an *identifier* value used to identify each remote domain known to this configuration. *RDOM* must be unique within the configuration.

The following parameters are required:

TYPE = *identifier*

is used for grouping remote domain into classes. TYPE can be set to one of the following values: TDOMAIN, OSITP or SNAX. The TDOMAIN value indicates

that this remote domain can only communicate with another TUXEDO System/Domain Domain. The `OSITP` value indicates that this remote domain communicates with another TP domain via the OSI-TP protocol. The `SNAX` value indicates that this remote domain communicates with an MVS/CICS region via the LU6.2 protocol.

`DOMAINID = string`

is used to identify a remote domain. `DOMAINID` must be 32 octets or fewer in length. If the value is a string, it must be 32 characters or fewer (counting the trailing null). `DOMAINID` must be unique across remote domains. The value of *string* can be a sequence of characters or a sequence of hexadecimal digits preceded by “0x”.

The following parameter is optional:

`CODEPAGE = table identifier`

is used to designate a bidirectional translation table for ASCII to EBCDIC conversion between a local TUXEDO application and a remote mainframe application. The table identifier describes a file containing a translation table. The name of the file, located in the `$TUXDIR/udata/jobj/codepage` directory, is a composite of the code page numbers used for the translation, for example:

`CODEPAGE=00819x00297`

designates the translation table for converting ASCII CP-00819 characters to French EBCDIC CP-00297 characters, and vice versa. The translation tables can be modified. Refer to Appendix F, “Code Page Translation Tables,” for complete character listings.

The DM_TDOMAIN Section

This section defines the addressing information required by domains of type `TDOMAIN`. This section should have an entry per local domain if requests from remote domains to local services are accepted on that local domain (gateway group), and an entry per remote domain accessible by the defined local domains.

Entries have the form:

`DOM` required parameters [optional parameters]

where *DOM* is an *identifier* value used to identify either a local domain (*LDOM*) or a remote domain (*RDOM*) in the *DM_LOCAL_DOMAINS* section or in the *DM_REMOTE_DOMAINS* section. The *DOM* identifier must match a previously defined *LDOM* in the *DM_LOCAL_DOMAINS* sections or *RDOM* in the *DM_REMOTE_DOMAINS* section.

The following parameter is required:

NWADDR = *string*

This parameter specifies the network address used by a local or a remote domain to accept connections from other TUXEDO System/Domain Domains. If *string* has the form '*0xhex-digits*', it must contain an even number of valid hexadecimal digits.

The following parameter is optional:

NWIDLETIME = *numeric*

This parameter specifies the maximum time allowed for a connection to be idle (that is, unused). When this time is reached, the idle connection is terminated. The numeric value represents a time in minutes. If this keyword is not specified, then idle connections will be maintained until the gateway handling the connection is shutdown.

Notice that multiple entries for a particular domain may be defined in this table. Multiple addresses specified for a remote domain mean that the first address (the first entry in the table for the remote domain) should be used to establish the connection and the other addresses should be used as back-up addresses in case of failure of the connection setup to the first address. Multiple addresses specified for a local domain mean that multiple listening ports are available on the same or different types of networks.

The *DM_OSITP* Section

This section defines the addressing information required by domains of type *OSITP*. This section should have one entry per gateway group (local domain), and one entry per remote domain of type *OSITP*.

Entries have the form:

DOM required parameters [optional parameters]

where *DOM* is an *identifier* value used to identify a local domain (LDM) or a remote domain (RDM) in the DM_LOCAL_DOMAINS section or in the DM_REMOTE_DOMAINS section. The *DOM* identifier must match a previously defined *LDM* in the DM_LOCAL_DOMAINS sections or *RDM* in the DM_REMOTE_DOMAINS section.

The following are required parameters:

APT = *string*

This parameter specifies an OSI Application Process Title (APT). An APT may be a name (i.e., the Directory Name of an Application Process Title) or an object identifier (i.e., a sequence of integer values separated by periods).

AEQ = *string*

This parameter specifies an OSI Application Entity Qualifier (AEQ). An AEQ may be a name (i.e., the relative distinguished name of a particular Application Entity) or an integer (i.e., if the APT is an object identifier).

The following are optional parameters:

AET = *string*

This parameter specifies an OSI Application Entity Title (AET). An AET is formed from an Application Process Title (APT) and an Application Entity Qualifier (AEQ), i.e. in ASN.1 AET is defined as a SEQUENCE { APT, AEQ } where APT and AET are of type ANY. Three main formats are accepted for the value of *string*:

encoded string

This is a single value as a hexadecimal octet string which a represents a valid BER encoding of the AET, e.g. AET = "0x06062B80CE0F0107".

{object identifier}, {integer}

The first element represents the APT defined as an object identifier (i.e., a sequence of integer values separated by periods) and the second element represents an AEQ defined as an integer constant, e.g., AET = "{1.3.15.0.3},{1}".

{string}, {string}

This format allows the APT and the AEQ to be defined as string constants, e.g., AET = "{BA.CENTRAL01},{TUXEDO}".

ACN = {*XATMI* | *UDT*}

This parameter specifies the object identifier of the Application Context Name (ACN) used by this domain. Current allowed application contexts are: the *XATMI*-ASE (*XATMI*) and the *UDT*-ASE (*UDT*). If this parameter is not specified, the ACN is set to the object identifier of the *XATMI*-ASE Application Context.

APID = *integer*

This parameter specifies an OSI Application Process Invocation Identifier (APID).

AEID = *integer*

This parameter specifies an OSI Application Entity Invocation Identifier (AEID).

PROFILE = *identifier*

This parameter specifies the OSI TP profile used by this domain and is used to determine the required OSI TP functional units. PROFILE can be set to one of the following values: ATP11, ATP21, ATP31, ATP12, ATP22, and ATP32. The UDT ASE application context allows the use of any of these profiles. The XATMI-ASE application context only allows profiles ATP11, ATP21 and ATP31. Profiles ATP11, ATP21 and ATP31 use the Dialogue, Polarized Control and Handshake functional units. Profiles ATP12, ATP22 and ATP32 use the Dialogue, Shared Control, and Handshake functional units. Profiles ATP11 and ATP12 do not use OSI TP transactions (the Commit functional unit is not used). Profiles ATP21 and ATP22 require the Commit, Unchained Transactions, and Recovery functional units. Profiles ATP31 and ATP32 require the Commit, Chained Transactions, and Recovery functional units. By default, the ATP21 profile is always selected.

URCH = *string*

This parameter specifies the user portion of the OSITP Recovery Context Handle. It may be required by the XAP-TP provider in order to perform recovery of distributed transactions after a communications line or system failure.

The DM_SNACRM Section

The DM_SNACRM section provides three (3) keywords used to identify the SNA Communications Resource Manager that will provide ATMI transaction semantics between a given domain and its partners. Entries have the general form:

<SNA CommunicationsResourceManagerName> parameters

Where <SNA CommunicationsResourceManagerName> is the locally known name of this SNACRM definition to be used when referencing this SNACRM in subsequent sections. This name is an ASCII string 1 to 30 characters in length. The parameters are the keyword/value pairs that makeup the definition. All keywords are required for a valid SNACRM definition. Keywords can be in any order.

LDOM <LocalDomainName>

LDOM associates this SNACRM with a defined local domain.

<LocalDomainName> is the reference to an entry in the DM_LOCAL_DOMAINS section. This name is an ASCII string 1 to 30 characters in length. This parameter is required. This parameter has no default.

SNACRMADDR <HexSocketAddress> or <host:port>

SNACRMADDR provides the socket address the eLink SNA gateway uses to communicate with the SNACRM. If the SNACRM is started independent of the gateway, this address must be used on the SNACRM command line.

<HexSocketAddress> is a TCP/IP address using the sockaddr_in format of family,port,address:

<0xFFFFPPPPAAAAAAA>

where:

FFFF

is the hex value of the protocol family, always 0x0002 for the INET family.

PPPP

is the hex value of an unused TCP/IP port

AAAAAAA

is the hex value of the IP address for the machine running the SNACRM

Therefore if the SNACRM was running on a machine with an IP address of 206.189.43.13, and we wanted to use port 6000 for the SNACRM then SNACMADDR would be:

```
0x00021770CEBD2B0D
```

This parameter is required. This parameter must contain an even number of hex characters. This parameter has no default.

The DM_SNASTACKS Section

The DM_SNASTACKS section provides five (5) keywords which identify the third party SNA stack that should be used for connections established between a given domain and it's partners. Entries have the general form:

<StackReference> parameters

Where *<StackReference>* is the locally known name of this stack definition to be used when referencing this stack in subsequent sections. This name is an ASCII string 1 to 30 characters in length. The parameters are the keyword/value pairs that makeup the definition. All keywords are required for a valid stack definition. Keywords can be in any order.

LOCALLU *<LocalLUAlias>*

LOCALLU provides a reference to an LU alias defined in the third party SNA stack. *<LocalLUAlias>* is the name used to identify the local LU definition as specified by the third party SNA stack configuration. This is a name that represents the end node for an LU6.2 connection. The value for this parameter is an ASCII string, 1 to 64 characters in length. This parameter is required. This parameter has no default. The third party SNA stack will require a corresponding definition for a local LU.

LTPNAME *<LocalTransactionProgramName>*

LTPNAME identifies the inbound transaction programs which will be serviced by any SNACRM using this stack definition.

<LocalTransactionProgramName> is the name used to identify inbound transaction programs for which an attach will be accepted. The only useful value is an asterisk. This indicates all inbound attaches will be accepted. This parameter is required. This parameter has no default. Partial TP names are not supported. The third party SNA stack will require a corresponding definition for inbound TP names.

SNACRM <SNACommunicationsResourceMangerName>

SNACRM provides a name by which to reference the associated SNACRM definition. <SNACommunicationsResourceMangerName> is the name used to associate the DM_SNACRM definition with this DM_SNASTACKS entry. The value for this parameter is an ASCII string, 1 to 32 characters in length. This parameter is required. This parameter has no default.

STACKPARMS <parameters required for third party sna stack>

STACKPARMS provides a method for the domain gateway to pass any required parameters to the third party SNA stack. <parameters required for third party sna stack> is an ASCII string, 1 to 128 characters in length. Currently, the only value used is the TCP/IP hostname for the machine running the third party SNA stack. This parameter is required. This parameter has no default.

STACKTYPE={brx41 | hp51 | hp60 | hp61 | ibm50 | ibm60 | spx60 | sun91}

This option is used to indicate which vendor SNA stack is being used. It is also used to determine the name of specific BEA eLink for Mainframe SNA system libraries. It is essential that the value of this option be coded correctly. These values are mapped to the equivalent BEA eLink for Mainframe SNA system library.

The DM_SNALINKS Section

This section defines the SNA Link information required by domains of type SNA.

Entries have the form:

LINK parameters

Where *LINK* is an *identifier* value used to identify a connection between a local domain (LDM) and a remote domain (RDM). The *RDM* identifier must match a previously defined *RDM* in the DM_REMOTE_DOMAINS section.

The following parameters are available:

STACKREF = *string*

This required parameter defines the stack that will be used for establishment of this link. The STACKREF string is the tag that was used in a previous definition established in the DM_SNASTACKS section.

RDM = *string*

The RDM string should match a previous RDM definition in the DM_REMOTE_DOMAINS section.

LSYSID = <Connection ID of remote (CICS) region>

LSYSID is the 4 character identifier that is to be used for this link. This should match the connection ID used by a partner CICS to communicate to the SNACRM across this link.

RSYSID = <SYSID of remote (CICS) region>

RSYSID is the 4 character remote sysid of the partner. Typically it is the sysid of a CICS region, but could also be the subsystem id of an IMS control region. This parameter should match the actual sysid of the remote partner.

RLUNAME = <Alias of APPLID for remote region>

The RLUNAME value represents an alias known to the third party SNA stack that resolves to a VTAM netname for the remote application. This would most likely be the VTAM applid for a CICS region, however it could also be an APPC/MVS LU defined for use with IMS. The value must be unique within the SNA network. *string* should be from 1 to 8 characters. This parameter is required. This parameter has no default. The third party stack configuration requires a matching definition.

MODENAME = <Mode name VTAM mode entry>

MODENAME is VTAM mode entry, defined to the third party SNA stack, to be used for this link. For a CICS link this must be compatible with the RDO session definition for the corresponding connection. For an IMS connection this must be compatible with the DLOGMOD entry on the LU definition used to access the IMS scheduler. *string* should be from 1 to 8 ASCII characters. This parameter is required. This parameter must match the third party SNA stack configuration and must be compatible with the corresponding entries defined to VTAM and/or CICS.

SECURITY = *string*

SECURITY_TYPE specifies the security setting in CICS/RACF or partner. Legal values are LOCAL, IDENTIFY, VERIFY, PERSISTENT or MIXIDPE. *string* should be from 1 to 10 characters. The default setting is LOCAL.

MAXSESS = number

MAXSESS is the maximum number of parallel sessions that can be started on this link. MAXSESS must be greater than or equal to four.

MINWIN = number

The minimum number of contention winners. This value is typically half the MAXSESS value.

MAXSYNCLVL = number

This value represents the maximum transaction synchronization level that can be supported over this link.

A value of zero (0) means this link is non-transactional. No synchronization will be maintained. This level can be used for sending and receiving messages from IMS via the APPC/MVS transparency interface. The default sync-level is sync-level 0.

A value of one (1) means this link will support everything supported with zero (0), in addition to:

- Outbound ATMI tpcall() as a CICS distributed program link request with the semantics of SYNCONRETURN.

- Inbound EXEC CICS LINK requests with the semantics of SYNCONRETURN. The program name must match the RNAME on the local service definition and the SYSID must match the LSYSID for the link.

A value of two (2) means this link will support everything supported with zero (0) and one (1) for partners able to exchange logs and compare states, in addition to:

- The exchange logs and compare states function with a partner CICS.

- Outbound ATMI tpcall() as a CICS distributed program link request with full two phase commit transaction semantics using tpcommit().

- Outbound ATMI tpconnect() as APPC or CPIC distributed transaction processing with full two phase commit transaction semantics using tpcommit().

- Inbound EXEC CICS LINK requests with full two phase commit transaction semantics using Prepare Rollback and Syncpoint verbs.

- Inbound APPC or CPIC conversations with full two phase commit transaction semantics using Prepare Rollback and Syncpoint verbs.

The partner must be able to negotiate a CICS style exchange logs and compare states for successful initialization of a sync-level 2 link.

If the installation is not licensed for sync-level 2, this parameter must be set to 0 or 1 for the link to be established. Transaction support is only available at sync-level 2. Distributed Program Link can be accessed as SYNCONRETURN, that is, not transactional if the link sync-level is 1.

Caution: If you set MAXSYNCLVL=2 or make no entry for this parameter (that is, accept the default) without having installed the eLink SNA software licensed for that level, the system configuration automatically reverts to Sync-level 1 and an error message is sent to the error log. To clear that error message, you must either reset the MAXSYNCLVL parameter to an appropriate value or purchase and install the correct software.

STARTTYPE = {auto | cold}

This option sets the recovery mode for transactional links. When set to AUTO, the system restarts using configuration and link data recovered from the in-flight transaction log. When set to COLD, the system uses configuration data taken from the current dmconfig file and loses any in-flight link data. Changing dmconfig file parameters and performing an AUTO start results in a message warning that changed parameters are ignored until the next cold start. To force a cold start and disregard the STARTTYPE setting, delete the SNA*LOG files in \$APPDIR.

The DM_ACCESS_CONTROL Section

This section specifies the access control lists used by local domain. Lines in this section are of the form:

```
ACL_NAME    required parameters
```

where *ACL_NAME* is a (*identifier*) name used to identify a particular access control list; it must be 15 characters or less in length.

Required parameters are:

```
ACLIST = identifier [, identifier]
```

where an ACLIST is composed of one or more remote domain names (RDOM) separated by commas. The wildcard character (*) can be used to specify that all the remote domains defined in the DM_REMOTE_DOMAINS section can access a local domain.

The DM_LOCAL_SERVICES Section

This section provides information on the services exported by each local domain. This section is optional and if it is not specified then all local domains defined in the DM_LOCAL_DOMAINS section accept requests to all of the services advertised by the TUXEDO System/Domain application. If this section is defined then it should be used to restrict the set of local services that can be requested from a remote domain.

Lines within this section have the form:

service [optional parameters]

where *service* is the (*identifier*) local name of the exported service, and it must be 1-15 characters in length. This name corresponds to a name advertised by one or more servers running with the local TUXEDO System/Domain application. Notice that exported services inherit the default or special properties specified for the service in an entry in the SERVICES section of the TUXCONFIG file. Some of these parameters are: LOAD, PRIO, AUTOTRAN, ROUTING, BUFTYPE, and TRANTIME.

Optional parameters are:

ACL = *identifier*

specifies the name of the access control list (ACL) to be used by the local domain to restrict requests made to this service by remote domains. The name of the ACL is defined in the DM_ACCESS_CONTROL section. If this parameter is not specified then access control will not be performed for requests to this service.

API = ATMI

specifies the API used by the local service. Currently the only supported value is ATMI. This parameter is required.

CONV = { Y | N }

specifies whether (Y) or not (N) the local service is a conversational service. The default value is N.

LDOM = *identifier*

specifies the name identifying the local domain exporting this service. If this keyword is not specified, then the first local domain entry in the DM_LOCAL_DOMAINS section accepts requests for this local service.

INBUFTYPE = *type[:subtype]*

restricts the buffer type naming space of data types accepted by this service to a single buffer type. This parameter should be defined when the service is going to be used from an OSITP type gateway that uses the UDT ASE Application Context. For /SNA Domain buffer types, see the discussion in the DM_REMOTE_SERVICES section below.

`OUTBUFTYPE = type[:subtype]`

restricts the buffer type naming space of data types returned by this service to a single buffer type. This parameter should be defined when the service is going to be used from an `OSITP` type gateway that uses the UDT ASE Application Context. The `FML` buffer type cannot be used for `OSITP` type gateways. For `/SNA Domain` buffer types, see the discussion in the `DM_REMOTE_SERVICES` section below.

`RNAME = string`

The `RNAME` option is the local-service name imported from a remote CICS/ESA region. This name is used by the `SNACRM` to select a local service.

When the `RNAME` specifies an alternate mirror transaction identifier for explicit attachment for inbound DPL requests, it must be a combination of the alternate mirror `TRANSID` and a CICS/ESA program name in the following format:

`RNAME=AAAA:BBBBBBBB`

where:

`AAAA`

is a 1-4 character alternate mirror `TRANSID`

`BBBBBBBB`

is a 1-8 character CICS/ESA program name.

The colon is required to indicate the `TRANSID`/program name combination. The `TRANSID` must be composed of acceptable CICS/ESA characters:

`A-Za-z0-9$@#. /-_%&Qç?! | " = , ; < >`

The `DM_REMOTE_SERVICES` Section

This section provides information on services “imported” and available on remote domains. Lines within this `DM_REMOTE_SERVICES` section have the form:

`service` [optional parameters]

where `service` is the (*identifier*) name used by the local TUXEDO System/Domain application for a particular remote service. Remote services are associated with a particular remote domain.

Optional Parameters are:

AUTOTRAN = { Y | N }

specifies whether or not a transaction should automatically be started if a request message is received that is not already in transaction mode. The default is N.

BLOCKTIME = *numeric*

specifies the maximum wait time allowed for a reply to this remote service. The value sets a multiplier of the SCANUNIT parameters specified in the TUXCONFIG file. The value SCANUNIT * BLOCKTIME must be greater than or equal to SCANUNIT and less than 32,768 seconds. A time-out always implies a failure of the affected transaction or request.

CONV = { Y | N }

specifies whether (Y) or not (N) the remote service is a conversational service. The default value is N.

FUNCTION = {APPC|DPL}

enables outbound Tuxedo service requests to map to APPC transaction programs or CICS programs. The default value APPC indicates the remote service is a transaction program that may or may not be running under CICS. The DPL value indicates the remote service maps to a program running under CICS.

LDOM = *identifier*

specifies the name of a local domain in charge of routing requests to this remote service. The gateway group associated with the local domain advertises *service* in the TUXEDO System/Domain Bulletin Board. If this parameter is not specified then all the local domains will be able to accept requests to this remote service. The service request will be then redirected to a remote domain of the same type (see RDOM keyword below).

LOAD = *integer*

specifies that the remote service imposes a load of integer units. The value of LOAD can be between 1 and 32767 inclusive. If not specified, the default is 50. A higher number indicates a greater load.

INBUFTYPE = *type[:subtype]*

restricts the buffer type naming space of data types accepted by this service to a single buffer type. This parameter should be defined when the service is going to be used from an OSITP type gateway that uses the UDT ASE Application Context. The FML buffer type cannot be used for OSITP type gateways.

OUTBUFTYPE = *type[:subtype]*

restricts the buffer type naming space of data types returned by this service to a single buffer type. This parameter should be defined when the service is going to be used from an OSITP type gateway that uses the UDT ASE Application Context. The FML buffer type cannot be used for OSITP type gateways.

PRIO = integer

specifies the dequeuing priority of service requests to this remote service. The value of PRIO must be greater than 0 and less than or equal to 100, with 100 being the highest priority. The default is 50.

RDOM = *identifier*

specifies the name of the remote domain responsible for the actual execution of this service. If this parameter is not specified and a routing criteria (see below ROUTING keyword) is not specified, then the local domain assumes that any remote domain of the same type accepts this service and it selects a known domain (a domain to which a connection already exists) or remote domain from the \DM_REMOTE_DOMAINS section.

RNAME = *string*

specifies the actual service name expected by the remote domain. If this parameter is not specified, the remote service name is the same as the name specified in *service*.

The RNAME option is the name of the host TP_NAME. For non-CICS systems, this name can be up to 64 characters in length. For CICS systems, this name is the trans-id name for APPC-defined requests and the program name for DPL requests. CICS trans-id names cannot exceed four characters and CICS program names cannot exceed eight characters. The RNAME option must observe these requirements.

When the RNAME specifies an alternate mirror transaction identifier for explicit attachment to outbound DPL requests, it must be a combination of the alternate mirror TRANSID and an advertised remote CICS/ESA program name in the following format:

RNAME=AAA:BBBBBBBB

where:

AAA

is a 1-4 character alternate mirror TRANSID

BBBBBBBB

is a 1-8 character CICS/ESA program name.

The colon is required to indicate the TRANSID/program name combination. The TRANSID must be composed of acceptable characters recognized in CICS/ESA identifiers:

A-Za-z0-9\$@#./-_%&Qç?!| " = , ; < >

ROUTING = *identifier*

when more than one remote domain offers the same service, a local domain can perform data dependent routing if this optional parameter is specified. The *identifier* specifies the name of the routing criteria used for this data dependent routing. If not specified, data dependent routing is not done for this service. *identifier* must be 15 characters or less in length. If multiple entries exist for the same service name but with different RDOM parameters, the ROUTING parameter should be the same for all of these entries.

TRANTIME = *integer*

specifies the default time-out value in seconds for a transaction automatically started for the associated service. The value must be greater than or equal to 0 and less than 2147483648. The default is 30 seconds. A value of 0 implies the maximum time-out value for the machine.

The DM_ROUTING Section

This section provides information for data dependent routing of /T Domain service requests using FML, VIEW, X_C_TYPE, and X_COMMON typed buffers. Lines within the DM_ROUTING section have the form:

CRITERION_NAME required parameters

where *CRITERION_NAME* is the (*identifier*) name of the routing entry that was specified on the services entry. *CRITERION_NAME* must be 15 characters or less in length.

Required parameters are:

FIELD = *identifier*

specifies the name of the routing field. It must be 30 characters or less. This field is assumed to be a field name that is identified in an FML field table (for FML buffers) or an FML view table (for VIEW, X_C_TYPE, or X_COMMON buffers). The FLDTBLDIR and FIELDTBLS environment variables are used to

locate FML field tables, and the VIEWDIR and VIEWFILES environment variables are used to locate FML view tables.

`RANGES = string`
specifies the ranges and associated remote domain names (RDOM) for the routing field. *string* must be enclosed in double quotes. The format of *string* is a comma-separated ordered list of range/RDOM pairs (see EXAMPLES below).

A range is either a single value (signed numeric value or character string in single quotes), or a range of the form “lower - upper” (where lower and upper are both signed numeric values or character strings in single quotes). Note that “lower” must be less than or equal to “upper”. To embed a single quote in a character string value (as in O’Brien, for example), it must be preceded by two backslashes (‘O’Brien’). The value MIN can be used to indicate the minimum value for the data type of the associated FIELD; for strings and arrays, it is the null string; for character fields, it is 0; for numeric values, it is the minimum numeric value that can be stored in the field. The value MAX can be used to indicate the maximum value for the data type of the associated FIELD; for strings and arrays, it is effectively an unlimited string of octal-255 characters; for a character field, it is a single octal-255 character; for numeric values, it is the maximum numeric value that can be stored in the field. Thus, “MIN - -5” is all numbers less than or equal to -5 and “6 - MAX” is all numbers greater than or equal to 6. The meta-character “*” (wild-card) in the position of a range indicates any values not covered by the other ranges previously seen in the entry; only one wild-card range is allowed per entry and it should be last (ranges following it will be ignored).

The routing field can be of any data type supported in FML. A numeric routing field must have numeric range values and a string routing field must have string range values.

String range values for string, array, and character field types must be placed inside a pair of single quotes and can not be preceded by a sign. Short and long integer values are a string of digits, optionally preceded by a plus or minus sign. Floating point numbers are of the form accepted by the C compiler or `atof()`: an optional sign, then a string of digits optionally containing a decimal point, then an optional e or E followed by an optional sign or space, followed by an integer.

When a field value matches a range, the associated RDOM value specifies the remote domain to which the request should be routed. A RDOM value of “*”

indicates that the request can go to any remote domain known by the gateway group.

Within a range/RDOM pair, the range is separated from the RDOM by a “:”.

```
BUFTYPE = ~type1[:subtype1[,subtype2 . . . ]][;type2[:subtype3[, . . . ]]] . . . ~
```

is a list of types and subtypes of data buffers for which this routing entry is valid. The types are restricted to be either FML, VIEW, X_C_TYPE, or X_COMMON. No subtype can be specified for type FML and subtypes are required for the other types (“*” is not allowed). Duplicate type/subtype pairs can not be specified for the same routing criterion name; more than one routing entry can have the same criterion name as long as the type/subtype pairs are unique. This parameter is required. If multiple buffer types are specified for a single routing entry, the data types of the routing field for each buffer type must be the same.

If the field value is not set (for FML buffers), or does not match any specific range and a wild-card range has not been specified, an error is returned to the application process that requested the execution of the remote service.

Files

The BDMCONFIG environment variable is used to find the BDMCONFIG configuration file.

Example 1

The following configuration file defines a 5-site domain configuration. The example shows 4 Bank Branch domains communicating with a Central Bank Branch. Three of the Bank Branches run within other TUXEDO System/Domain domains. The fourth Branch runs under the control of another TP Domain and OSI-TP is used in the communication with that domain.

```
# TUXEDO DOMAIN CONFIGURATION FILE FOR THE CENTRAL BANK
#
#
*DM_LOCAL_DOMAINS
# <local domain name> <Gateway Group name> <domain type> <domain
id> <log device>
#                               [<audit log>] [<blocktime>]
#                               [<log name>] [<log offset>] [<log size>]
#                               [<maxrdom>] [<maxrdtran>] [<maxtran>]
```

```
#                                [<maxdatalen>] [<security>]
#                                [<tuxconfig>] [<tuxoffset>]
#
#
DEFAULT: SECURITY = NONE

c01    GWGRP = bankg1
        TYPE = TDOMAIN
        DOMAINID = "BA.CENTRAL01"
        DMTLOGDEV = "/usr/apps/bank/DMTLOG"
        DMTLOGNAME = "DMTLG_C01"

c02    GWGRP = bankg2
        TYPE = OSITP
        DOMAINID = "BA.CENTRAL01"
        DMTLOGDEV = "/usr/apps/bank/DMTLOG"
        DMTLOGNAME = "DMTLG_C02"
        URCH = "ABCD"

#
*DM_REMOTE_DOMAINS
#<remote domain name> <domain type> <domain id>
#
b01    TYPE = TDOMAIN
        DOMAINID = "BA.BANK01"

b02    TYPE = TDOMAIN
        DOMAINID = "BA.BANK02"

b03    TYPE = TDOMAIN
        DOMAINID = "BA.BANK03"

b04    TYPE = OSITP
        DOMAINID = "BA.BANK04"
        URCH = "ABCD"

*DM_TDOMAIN
#
# <local or remote domain name>    <network address>
#
# Local network addresses
c01    NWADDR = "0x0002ff98c00b9d6d"
c01    NWADDR = "newyork01.65432"
# Remote network addresses
b01    NWADDR = "0x00020401c00b6d05"
b02    NWADDR = "dallas.65432"
b03    NWADDR = "0x00021094c00b6d9c"

*DM_OSITP
#
#<local or remote domain name> <apt> <aeq>
```

```

#                                     [<aet>] [<acn>] [<apid>] [<aeid>]
#                                     [<profile>]
#
c02      APT = "BA.CENTRAL01"
          AEQ = "TUXEDO.R.4.2.1"
          AET = "{1.3.15.0.3},{1}"
          ACN = "XATMI"

b04      APT = "BA.BANK04"
          AEQ = "TUXEDO.R.4.2.1"
          AET = "{1.3.15.0.4},{1}"
          ACN = "XATMI"

*DM_LOCAL_SERVICES
#<service_name>  [<Local Domain name>] [<access control>]
#               [<exported svcname>]
#               [<inbuftype>] [<outbuftype>]
#
open_act      ACL = branch
close_act     ACL = branch
credit
debit
balance
loan          LDOM = c02          ACL = loans

*DM_REMOTE_SERVICES
#<service_name>  [<Remote domain name>] [<local domain name>]
#               [<remote svcname>] [<routing>] [<conv>] [<trantime>]
#               [<inbuftype>] [<outbuftype>]
#
tlr_add      LDOM = c01  ROUTING = ACCOUNT
tlr_bal      LDOM = c01  ROUTING = ACCOUNT
tlr_add      RDOM = b04  LDOM = c02  RNAME = "TPSU002"
tlr_bal      RDOM = b04  LDOM = c02  RNAME = "TPSU003"

*DM_ROUTING
# <routing criteria> <field> <typed buffer> <ranges>
#
ACCOUNT FIELD = branchid  BUFTYPE = "VIEW:account"
RANGES = "MIN - 1000:b01, 1001-3000:b02, *:b03"

*DM_ACCESS_CONTROL
#<acl name>      <Remote domain list>
#
branch  ACLIST = b01, b02, b03
loans   ACLIST = b04

```

Example 2

This example shows the TUXEDO System/Domain Configuration file required at one of the Bank Branches (BANK01).

```
#
#TUXEDO DOMAIN CONFIGURATION FILE FOR A BANK BRANCH
#
#
*DM_LOCAL_DOMAINS
#
b01      GWGRP = auth
         TYPE = TDOMAIN
         DOMAINID = "BA.BANK01"
         DMTLOGDEV = "/usr/apps/bank/DMTLOG"

*DM_REMOTE_DOMAINS
#
c01      TYPE = TDOMAIN
         DOMAINID = "BA.CENTRAL01"

*DM_TDOMAIN
#
b01      NWADDR = "0x00021094c00b689c"
c01      NWADDR = "0x0002ff98c00b9d6d"
*DM_LOCAL_SERVICES
#
tlr_add      ACL = central
tlr_bal      ACL = central

*DM_REMOTE_SERVICES
#
OPA001      RNAME = "open_act"
CLA001      RNAME = "close_act"
CRD001      RNAME = "credit"
DBT001      RNAME = "debit"
BAL001      RNAME = "balance"

DM_ACCESS_CONTROL
#
central      ACLIST = c01
```

Example 3

This example shows the configuration file entries for an eLink SNA application:

```
#=====
# DMCONFIG
```

```

#      Application Domain Gateway Test Configuration
#
# See also
#      See $(TOP)/Makefile for more information.
#
# @(#)SNA Devel apps/simpsna DMCONFIG 1.6 98/03/03 15:35:29
# Copyright 1997, BEA Systems, Inc., all rights reserved.
#-----

*DM_LOCAL_DOMAINS
simpsnad
    GWGRP=GROUP2
    TYPE=SNAX
    DOMAINID="simpsnad"
    BLOB_SHM_SIZE=1000000
    DMTLOGDEV=<your TUXEDO filesystem device and name for
    DMTLOG>

#example DMTLOGDEV="/home/me/bin/DMTLOG"

*DM_REMOTE_DOMAINS

SIMPSNAG TYPE=SNAX DOMAINID="SIMPSNAG"

*DM_SNACRM

simpcrm      SNACRMADDR=<your Host Socket Listen Address>
              LDOM="simpsnad"

#example SNACRMADDR="0x00021770cfbd2b0d" INET family 0x0002 port
6000 host 207.189.43.13 or SNACRMADDR=//207.189.43.13:6000

*DM_SNASTACKS

simpstk
    SNACRM="simpcrm"
    STACKTYPE=<SNACRM Stack Library Named Token>
    LOCALLU=<Local LU definition specified in
    stack product>
    LTPNAME="*"
    STACKPARMS=<Parameters passed to Stack
    Product>

#example STACKTYPE="HP51"
#      LOCALLU="HPTTEST"
#      STACKPARMS="testhp"  Name of the host machine

*DM_SNALINKS

```

```
simplk1    STACKREF="simpstk"
           RDOM="SIMPSNAG"
           LSYID=<Connection ID of remote (CICS)
           region>
           RSYID=<SYSID of remote (CICS) region>
           RLUNAME=<Alias of Applid for remote region>
           MODENAME=<Mode name VTAM mode entry>
           SECURITY="LOCAL"
           STARTTYPE="COLD"
           MAXSESS=<Total Session number>
           MINWIN=<Session Local Winners>
           MAXSYNCLVL=<0|1|2 Maximum Syncpoint Level>

#example LSYID="BEA"
#       RSYID="TEST"
#       RLUNAME="CICSTEST"
#       MODENAME="SMSNA100"
#       MAXSESS=10
#       MINWIN=5
#       MAXSYNCLVL=2

*DM_LOCAL_SERVICES

MIRROR LDOM="simpsnad"
      CONV=N
      RNAME="MIRRORSERV"
      INBUFTYPE="STRING"
      OUTBUFTYPE="STRING"
      API="ATMI"

*DM_REMOTE_SERVICES

SIMPDPDPL AUTOTRAN=N
        LDOM="simpsnad"
        RDOM=SIMPSNAG
        CONV=N
        RNAME="TOUPDPLS"
        INBUFTYPE="STRING"
        OUTBUFTYPE="STRING"
        API="ATMI"
        FUNCTION="DPL"

SIMPDPDTP AUTOTRAN=N
        LDOM="simpsnad"
        RDOM=SIMPSNAG
        CONV=N
        RNAME="DTPS"
        INBUFTYPE="STRING"
        OUTBUFTYPE="STRING"
```

```
API="ATMI "  
FUNCTION="APPC "
```

See Also

```
build_dgw(1), dmadm(1), tmboot(1), tmshutdown(1), dmloadcf(1),  
dmunloadcf(1)
```

```
dmgwopts(5), GWADM(5), DMADM(5)
```

TUXEDO /Domain User Guide

TUXEDO Administrator's Guide

TUXEDO Programmer's Guide

dmloadcf

Parse a DMCONFIG file and load binary BDMCONFIG configuration file

Synopsis

```
dmloadcf [-c] [-n] [-y] [-b blocks] {dmconfig_file | - }
```

Description

`dmloadcf` reads a file or the standard input that is in DMCONFIG syntax, checks the syntax, and optionally loads a binary BDMCONFIG configuration file. The BDMCONFIG environment variable points to the path name of the BDMCONFIG file where the information should be stored.

`dmloadcf` prints an error message if it finds any required section of the DMCONFIG file missing. If a syntax error is found while parsing the input file, `dmloadcf` exits without performing any updates to the BDMCONFIG file.

`dmloadcf` requires the existence of the `$TUXDIR/udataobj/DMTYPE` file. This file defines the valid domain types. If this file does not exist, `dmloadcf` exits without performing any updates to the BDMCONFIG file.

The effective user identifier of the person running `dmloadcf` must match the UID in the RESOURCES section of the TUXCONFIG file.

The `-c` option to `dmloadcf` causes the program to print minimum IPC resources needed for each local domain (gateway group) in this configuration. The BDMCONFIG file is not updated.

The `-n` option to `dmloadcf` causes the program to do only syntax checking of the ASCII DMCONFIG file without actually updating the BDMCONFIG file.

After syntax checking, `dmloadcf` checks to see if the file pointed to by BDMCONFIG exists, is a valid TUXEDO System file system, and contains BDMCONFIG tables. If these conditions are not true, the user is prompted to create and initialize the file with

```
Initialize BDMCONFIG file: path [y, q]?
```

where *path* is the complete file name of the BDMCONFIG file. Prompting is suppressed if the standard input or output are not terminals, or if the `-y` option is specified on the command line. Any response other than “y” or “Y” will cause `dmloadcf` to exit without creating the configuration file.

If the BDMCONFIG file is not properly initialized, and the user has given the go-ahead, `dmloadcf` creates the TUXEDO file system and then creates the BDMCONFIG tables. If the `-b` option is specified on the command line, its argument is used as the number of blocks for the device when creating the TUXEDO file system. If the value of the `-b` option is large enough to hold the new BDMCONFIG tables, `dmloadcf` will use the specified value to create the new file system; otherwise, `dmloadcf` will print an error message and exit. If the `-b` option is not specified, `dmloadcf` will create a new file system large enough to hold the BDMCONFIG tables. The `-b` option is ignored if the file system already exists. The `-b` option is highly recommended if BDMCONFIG is a raw device (that has not been initialized) and should be set to the number of blocks on the raw device. The `-b` option is not recommended if BDMCONFIG is a regular UNIX file.

If the BDMCONFIG file is determined to already have been initialized, `dmloadcf` ensures that the local domain described by that BDMCONFIG file is not running. If a local domain is running, `dmloadcf` prints an error message and exits. Otherwise, `dmloadcf`, to confirm that the file should be overwritten, prompts the user with:

```
"Really overwrite BDMCONFIG file [y, q]?"
```

Prompting is suppressed if the standard input or output are not a terminal or if the `-y` option is specified on the command line. Any response other than “y” or “Y” will cause `dmloadcf` to exit without overwriting the file.

If the `SECURITY` parameter is specified in the `RESOURCES` section of the `TUXCONFIG` file, then `dmloadcf` will flush the standard input, turn off terminal echo and prompt the user for an application password as follows:

```
Enter Application Password?
```

The password is truncated to 8 characters. The option to load the ASCII `DMCONFIG` file via the standard input (rather than a file) cannot be used when this `SECURITY` parameter is turned on. If the standard input is not a terminal, that is, if the user cannot be prompted for a password (as with a `here` file, for example), then the environment variable `APP_PW` is accessed to set the application password. If the environment variable `APP_PW` is not set with the standard input not a terminal, then `dmloadcf` will print an error message, generate a log message and fail to load the BDMCONFIG file.

Assuming no errors, and if all checks have passed, `dmloadcf` loads the `DMCONFIG` file into the `BDMCONFIG` file. It will overwrite all existing information found in the `BDMCONFIG` tables.

Portability

This command is supported as a TUXEDO-supplied administrative tool on UNIX and Windows NT operating systems.

Environment Variables

The environment variable `APP_PW` must be set for applications that require security (the `SECURITY` parameter in the `TUXCONFIG` file is set to `APP_PW`) and `dmloadcf` is run with something other than a terminal as the standard input.

The `BDMCONFIG` environment variable should point to the `BDMCONFIG` file.

Examples

The following example shows how a binary configuration file is loaded from the `bank.dmconfig` ASCII file. The `BDMCONFIG` device is created (or re-initialized) with 2000 blocks:

```
dmloadcf -b 2000 -y bank.dmconfig
```

Diagnostics

If an error is detected in the input, the offending line is printed to standard error along with a message indicating the problem. If a syntax error is found in the `DMCONFIG` file or the system is currently running, no information is updated in the `BDMCONFIG` file and `dmloadcf` exits with exit code 1.

If `dmloadcf` is run on an active node, the following error message is displayed:

```
*** dmloadcf cannot run on an active node ***
```

If `dmloadcf` is run by a person whose effective user identifier doesn't match the `UID` specified in the `TUXCONFIG` file, the following error message is displayed:

```
*** UID is not effective user ID ***
```

Upon successful completion, `dmloadcf` exits with exit code 0. If the `BDMCONFIG` file is updated, a `userlog` message is generated to record this event.

See Also

`dmunloadcf(1)`, `dmconfig(5)`, `ubbconfig(5)`

TUXEDO /Domain User Guide

TUXEDO Administrator's Guide

dmunloadcf

Unload binary BDMCONFIG domain configuration file

Synopsis

`dmunloadcf`

Description

`dmunloadcf` translates the BDMCONFIG configuration file from the binary representation into ASCII. This translation is useful for transporting the file in a compact way between machines with different byte ordering and backing up a copy of the file in a compact form for reliability. The ASCII format is the same as is described in `dmconfig(5)`.

`dmunloadcf` reads values from the BDMCONFIG file pointed to by the BDMCONFIG environment variable and writes them to its standard output.

Portability

This command is supported as a TUXEDO-supplied administrative tool on UNIX and Windows NT operating systems.

Examples

To unload the configuration in `/usr/tuxedo/BDMCONFIG` into the file `bdmconfig.backup`:

```
BDMCONFIG=/usr/tuxedo/BDMCONFIG dmunloadcf > bdmconfig.backup
```

Diagnostics

`dmunloadcf` checks that the file pointed to by the BDMCONFIG environment variable exists, is a valid TUXEDO file system, and contains BDMCONFIG tables. If any of these conditions is not met, `dmunloadcf` prints an error message and exits with error code 1. Upon successful completion, `dmunloadcf` exits with exit code 0.

See Also

`dmloadcf(1)`, `dmconfig(5)`

TUXEDO /Domain User Guide

GWADM

/Domain gateway administrative server

Synopsis

```
GWADM SRVGRP = "identifier" SRVID = "number" REPLYQ = "N"  
CLOPT = "-A -- [-a { on | off } ] [-s services ]  
[-t { on | off } ]"
```

Description

The gateway administrative server (GWADM) is a TUXEDO-supplied server that provides administrative functions for a /Domain gateway group.

GWADM should be defined in the SERVERS section of the UBBCONFIG file as a server running within a particular gateway group, that is, SRVGRP must be set to the corresponding GRPNAME tag specified in the GROUPS section. The SVRID parameter is also required and its value must consider the maximum number of gateways allowed within the gateway group.

There should be only one instance of a GWADM per /Domain gateway group, and it should NOT be part of the MSSQ defined for the gateways associated with the group. Also, GWADM should have the REPLYQ attribute set to N.

The CLOPT option is a string of command line options that is passed to the GWADM when it is booted. This string has the following format:

```
CLOPT="-A -- <gateway group runtime parameters>"
```

The following runtime parameters are recognized for a gateway group:

`-a { on | off }`

This option turns *off* or *on* the audit log feature for this local domain. The default is *off*. The `dmadmin` program can be used to change this setting while the gateway group is running (see `dmadmin(1)`).

`-s services`

Specifies the remote *services* that should be initially offered by the domain gateway. The specifications for these services are found in the DMCONFIG file. For example, the specification

```
-s x,y,z
```

implies that the gateway should initially advertise remote services `x`, `y`, and `z`. Spaces are not allowed between commas and the `-s` option may appear several times.

```
-t { on | off }
```

This option turns `off` or `on` the statistics gathering feature for the local domain. The default is `off`. The `dmadmin` program can be used to change this setting while the gateway group is running (see `dmadmin(1)`).

The GWADM server must be booted before the corresponding gateways.

Portability

This server is supported on TUXEDO-supplied servers, using UNIX System and Windows NT operating systems.

Interoperability

The initial release of /SNA Domain can only be installed on a node running TUXEDO Release 6.4.

Examples

The following example illustrates the definition of the administrative server in the UBBCONFIG file.

```
#
*GROUPS
DMADMGRP  GRPNO=1
gwgrp    GRPNO=2
#
*SERVERS
DMADM SRVGRP="DMADMGRP" SRVID=1001 REPLYQ=N RESTART=Y GRACE=0
GWADM SRVGRP="gwgrp" SRVID=1002 REPLYQ=N RESTART=Y GRACE=0
      CLOPT="-A -- -a on -t on"
SNACRM SRVGRP="gwgrp" SRVID=1003 CLOPT="-A--//host:6000 gwgrp"
GWSNAX SRVGRP="gwgrp" SRVID=1004 RQADDR="gwgrp" REPLYQ=N
```

See Also

`dmadmin(1)`, `tmboot(1)`

`dmconfig(5)`, `DMADM(5)`, `servopts(5)`, `ubbconfig(5)`

TUXEDO /Domain User Guide

TUXEDO Administrator's Guide

GWSNAX

This is the gateway server process for eLink SNA.

Synopsis

```
GWSNAX SRVGRP = "identifier" SRVID = "number" REPLYQ = "N"  
      CLOPT = "-A -- [-t { number } ]"
```

Description

The GWSNAX server provides TUXEDO functions for an eLink SNA gateway group.

GWSNAX should be defined in the SERVERS section of the UBBCONFIG file as a server running within a particular gateway group, that is, SRVGRP must be set to the corresponding GRPNAME tag specified in the GROUPS section. The SVRID parameter is also required and its value must consider the maximum number of gateways allowed within the gateway group. The GWSNAX definition must not precede its associated SNACRM server definition in the UBBCONFIG file.

There should be only one instance of a GWSNAX per eLink SNA gateway group, and it should NOT be part of the MSSQ defined for the gateways associated with the group.

The CLOPT option is a string of command line options that is passed to the GWSNAX when it is booted. This string has the following format:

```
CLOPT="-A -- <gateway runtime parameters>"
```

The following runtime parameters are recognized for a gateway:

- t { number }
This option indicates the type of character string transformation the gateway performs. Refer to the following table for values.

Table A-10 C to COBOL String Transformation

CLOPT -t Parameter Value	TUXEDO Application Language	Host Application Language
Not Set	No string transformation established	

Table A-10 C to COBOL String Transformation

CLOPT -t Parameter Value	TUXEDO Application Language	Host Application Language
1	C	COBOL
2	COBOL	C
3	C	C
4	COBOL	COBOL

Portability

Refer to Table 1-1 for a complete listing of compatible operating systems.

Interoperability

Refer to Table 1-1 for a complete listing of supported platforms.

Examples

The following example illustrates the definition of the administrative server in the UBBCONFIG file.

```
#
*GROUPS
DMADMGRP GRPNO=1
gwgrp    GRPNO=2
#
*SERVERS
DMADM SRVGRP="DMADMGRP" SRVID=1001 REPLYQ=N RESTART=Y GRACE=0
GWADM SRVGRP="gwgrp" SRVID=1002 REPLYQ=N RESTART=Y GRACE=0
      CLOPT="-A -- -a on -t on"
SNACRM SRVGRP="gwgrp" SRVID=1003 CLOPT="-A--//host:6000 gwgrp"
GWSNAX SRVGRP="gwgrp" SRVID=1004 RQADDR="gwgrp" REPLYQ=N
      CLOPT="-- -t 1"
```

See Also

`dmadmin(1)`, `tmboot(1)`

`dmconfig(5)`, `DMADM(5)`, `servopts(5)`, `ubbconfig(5)`

TUXEDO /Domain User Guide

TUXEDO Administrator's Guide

modusr

Modify a remote user password

Synopsis

```
DMCONFIG=dmconfig  
modusr -d local domain ID -R remote domain ID -u remote username
```

Description

`modusr` can only be executed as a subcommand of `dmadmin(1)`. The purpose of this page is to describe options for the subcommand and to show an example.

The subcommand allows the administrator to modify passwords in the remote password table. The administrator is prompted for the remote password.

The table entries modified are used for passing remote user names and passwords to remote SNA domains when the application is using /SNA Domain gateways and SECURITY is set to USER_AUTH, ACL, or MANDATORY ACL in the `ubbconfig` file and SECURITY is set to DM_USER_PW in the `DMCONFIG` file.

The following options are available:

`-d local domain ID`

This is the name of the local domain gateway with which the ids and passwords are associated. This is the same ID as the one used when creating the domain definitions either in the `DMCONFIG` file or through the Graphical Administrative Interface.

`-R remote domain ID`

This is the name of the remote domain gateway with which the ids and passwords are associated. This is the same ID as the one used when creating the domain definitions either in the `DMCONFIG` file or through the Graphical Administrative Interface.

`-u remote username`

The remote user whose password is being modified.

Before running this subcommand the application must be configured using either the Graphical Administrative Interface or `tmloadcf(1)` and `dmloadcf(1)`. `dmadmin modusr` may be run on any active node.

Portability

This subcommand is available on the latest version of TUXEDO, as documented for this release of BEA eLink for Mainframe SNA.

Diagnostics

The `dmadmin modusr` subcommand exits with a return code of 0 upon successful completion.

Examples

```
modusr -d tux -R cics -u cicsusr /*modifies remote user's password  
                                sent to CICS. The administrator  
                                is prompted for the password*/
```

See Also

`delusr(5)`, `addusr(5)`

SNACRM

Launches the SNA Communications Resource Manager.

Synopsis

```
SNARCM [ -t 0|1|2|3 ] [-s] [-o]] <addr> <group>
```

Description

SNACRM provides all of the Sync-Level 2 logic for an eLink SNA gateway and directly communicates with the PU2.1 server.

On a UNIX platform, you can manually start SNACRM from the command line or during `tmboot` with the DMINIT server. On a Microsoft NT platform, you must start the SNACRM as a BEA TUXEDO server.

Note: In most cases, it is recommended that you start the SNACRM as a TUXEDO server. Please refer to “Specifying the SNACRM as a BEA TUXEDO Server,” in Chapter 5.

On a UNIX platform, you can either start all SNACRM processes with a single DMINIT process or individually start each one with a DMINIT server that is defined to each gateway server group.

When you start SNACRM from the UNIX command line, the SNACRM Command Line Console puts its prompt in the window, and if exited, shuts down all of the active links. When started from DMINIT, the console is redirected to the null device.

When using TMADMIN to start and stop servers by group ID, include the DMINIT server in the same group so that SNARCM can be restarted with its corresponding SNA Domain Gateway.

You must configure one SNACRM for each eLink SNA gateway, as well as configuring one stack for each SNACRM definition. Each stack can manage one or more SNA links, which is equivalent to a TUXEDO remote domain.

SNACRM has two types of log files stored in \$APPDIR, RSTRTLOG and BLOBLOG. RSTRTLOG is the transaction state log used during the recovery process, while the BLOBLOG log stores session and link information. Deleting the log files require a cold start for each link involved. You can use the CRMLOGS command to display the contents and state of the SNACRM log files.

Trace Options

When initiating the SNACRM from the UNIX command line or via the DMINIT server, you can specify any of the following trace levels:

- ◆ 0—No tracing. Setting this level effectively disables SNACRM tracing and closes the trace file, if there is one. If tracing is subsequently restarted, a new file is created with an incremented numerical suffix.
- ◆ 1—Minimum tracing. At this level, SNACRM traces only major events and is sufficient only to determine the sequence of application conversations.
- ◆ 2—Medium tracing. At this level, SNACRM also traces all I/O buffers.
- ◆ 3—Maximum tracing. At this level, SNACRM also traces all APPC verbs.

The APPC Protocol Stack API trace is either enabled or disabled. If enabled, it generally shows the parameters and results of all API calls. Depending on the stack being used, other options (such as vendor-specified environment variables) may have to be activated for SNACRM to enable the trace.

Note: When specifying the SNACRM as a server on a Microsoft NT platform, you can establish the above trace levels in the CLOPT parameter for the server definition in the UBBCONFIG file. Refer to BEA TUXEDO publications for information about the CLOPT parameter.

General Options

The following parameters apply to this command:

`-s`

APPC Stack API trace (default none)

`addr`

Socket listening address (required)

0x<16 hex chars> or //host:port (Note: Only the port is significant.)

group

eLink SNA Gateway Group Name (required)

Note: Do not use the `-o` and `-a` parameters for the `SNACRM` command.

Environment Variables

You must set the following environment variables before starting the `SNARCM` from the UNIX command line, starting it as a BEA TUXEDO server, or by using a `DMINIT` server:

- ◆ `FIEDLTBLS32` must contain `fmb.def`
- ◆ `FLDTBLDIR32` must contain `$TUXDIR/lib`
- ◆ `APPDIR` must be set to the application directory

Configuring `DM_SNACRM`

This section describes the `DM_SNACRM` section in `DMCONFIG` that pertains to the SNA Communications Resource Manager, and contains the network addressing parameters required by eLink SNA domains. It specifies the field identifiers for each `DMCONFIG` field, what the field type of the identifier is, and when the it can be updated. All applicable field values are returned with the retrieval operations. Fields that are allowed and/or required for adding a record are described in `dmconfig(5)`. Fields indicated below as *key* are key fields used to uniquely identify a record within a section. These fields are required to be in the input buffer when updates are done and are not allowed to be dynamically updated. The `Update` column indicates when a field can be updated. The possible values are:

Yes

Can be updated at any time.

NoGW

Cannot be dynamically updated while the gateway group representing the local domain is running.

No

Cannot be dynamically updated while at least one gateway group is running.

The following table lists the fields in this section:

Table A-11 DM_SNACRM SECTION

Field Identifier	Field Type	Update	Notes
LDOM	string	No/NoGW	Associates this SNACRM with a defined local domain definition.
SNACRMADDR (required)	string	No/NoGW	Provides the socket of the domain gateway. The hex format for this option is <code>//<hostname>:<port></code> where: <i>hostname</i> is the name of the host machine where the stack is located. <i>port</i> is the TCP/IP port number of the local machine.

Portability

Refer to Table 1-1, “Supported Platforms” for a list of operating systems and stacks supporting SNACRM:

Interoperability

SNACRM is interactive with the following:

- ◆ CICS 3.3 or higher
- ◆ IMS 4.1 or higher
- ◆ MVS 5.22 9510 or higher
- ◆ OS/390 1.2 or higher
- ◆ VTAM for MVS/ESA, version 4.3 or higher

Diagnostics

SNACRM exits with a return code of 0 upon successful completion.

Examples

Following is an example of the SNACRM command:

```
SNACRM 0 //myhost:5587 GROUP2 /dev/null>std.out 2>std.err &
```

When you start SNACRM from the UNIX command line, the following SNARCM command Line Console appears:

```
$ SNACRM -t 0 //myhost:5587 GROUP2
    BEA Connect SNA Resource Manager started Thu Dec 11
    18:40:49.098 1997
    [SNACRM]
```

```
Console active. Enter commands
?>
da => Display active tasks
dl => Display remote links
ds => Display link statistics
dt => Display trace status
st => Start all links
sh => Stop all links and terminate
si => Terminate immediately (no quiesce)
```

To launch SNARCM with the console running in the background:

```
$ SNACRM -t0 //myhost:5587 GROUP2 <dev/null>std.out 2>std.err &
```

To launch SNARCM with detailed tracing and APPC Stack API tracing turned on from the command line using the host/port address, type:

```
SNARCM -t2 -s //myhost:5587
```

When using the DMINIT server to launch the SNARCM, you must specify the CLOPT option in UBCONFIG.CFG as follows:

```
CLOPT="-- -f filename"
```

Where the filename is the name of a shell script containing the start-up command line for one or more SNARCM processes.

See Also

dmadmin, dmconfig, and xsnacrm

xsnacrm

xsnacrm: X/Motif real-time monitor for running the SNACRM (not available on Microsoft NT platforms)

Synopsis

```
xsnacrm [ X overrides ] address [ address . . . ]
```

(See syntax examples.)

Description

The `xsnacrm` program provides real-time monitoring of running SNACRMs and displays information describing the activity occurring in each SNACRM. The `xsnacrm` utility is intended to be used by administrators and system operators only. Therefore, usage may be restricted by the installation (by setting the execute permissions). `xsnacrm` requires Motif libraries.

Command Line Options

`xsnacrm` supports the standard X Toolkit command line arguments (see X(1)). The following additional arguments are supported as well.

Trace Options

You can enter one of the following `xsnacrm` trace levels:

- ◆ `0`—No tracing. Setting this level effectively disables SNACRM tracing and closes the trace file if there is one. If tracing is subsequently restarted, a new file will be created with an incremented numerical suffix.
- ◆ `1`—Minimum tracing. At this level, the SNACRM traces only major events and is sufficient only to determine the sequence of application conversations.
- ◆ `2`—Medium tracing. At this level, SNACRM also traces all I/O buffers.
- ◆ `3`—Maximum tracing. At this level, SNACRM also traces all APPC verbs.

The APPC Protocol Stack API trace is either **enabled** or **disabled**. If enabled, it generally shows the parameters and results of all API calls. Depending on the Stack being used, other options (such as vendor-specified environment variables) may have to be activated for `SNACRM` to enable the trace.

General Options

The following general option is available:

address

Specifies the host name and port number of a `SNACRM` to monitor. This value must match the corresponding parameter on the command line used to start the `SNACRM` you wish to monitor.

There must be at least one address specified. Any number of `SNACRM`s may be monitored by specifying all their associated addresses.

The format of an address consists of two forward slashes (`//`) followed by a host name or address, a colon (`:`), and a service name or decimal port number (containing no spaces).

If a host name is used, it should be an entry in the file `/etc/hosts`. If a host address is used, it should be specified in the format `nnn.nnn.nnn.nnn` where each group of `nnn` represents a decimal number between 1 and 255. This host should identify the computer where the `SNACRM` you wish to monitor is running, ***not*** the host where `xsnacrm` is to run.

If a service name is used, it should be an entry in the file `/etc/services`. If a decimal port number is used, it should be a decimal number in the range 4000 - 32767. This number must match the corresponding port number on the command line used to start the `SNACRM` you want to monitor. (If the `SNACRM` was started automatically, the address is specified in the `DMCONFIG` file).

xsnacrm Window

`xsnacrm` displays a single window consisting of the following sections from top to bottom:

- ◆ Title Frame

Displays the application title “*BEA Connect SNA CRM Status*”

◆ Menu Bar

Displays the menu items “File” and “Trace.” The File menu consists of a single “Exit” button that terminates `xsnacrm`. The `xsnacrm` window may also be terminated by selecting “close” on the X/Motif system menu for the window.

The Trace menu contains two sections that send commands to the currently selected SNACRM to change it’s own tracing function, and the tracing function of the APPC Protocol Stack the SNACRM is using, respectively. To change either current tracing option, select the corresponding menu button (For more information on tracing, please refer to the “Trace Options” section).

◆ BEA Logo

Displays the BEA Logo.

◆ SNACRM Select Pane

Displays the list of SNACRM’s specified on the command line. The list consists of a set of radio buttons. The selected button determines which SNACRM’s data is displayed in the other panes below.

The phrase “**not active or invalid address**” means that `xsnacrm` is unable to connect to the INET address specified, because the:

- ◆ Address is incorrect
- ◆ SNACRM is not monitoring the address (probably because it is not running)
- ◆ Path to SNACRM is not available (perhaps due to a network problem)

◆ Trace Status Pane

Displays the current trace options for the selected SNACRM.

◆ Link Status Pane

Displays the current status of all remote links for the selected SNACRM. The text may be scrolled if it is not entirely visible. Possible status values are:

Ins = The link is In Service
Acq = The link connection has been acquired
Xok = The link connection has been acquired and is OK

◆ Link Statistics Pane

Displays the current statistics for all remote links for the selected SNACRM. The text may be scrolled if it is not entirely visible.

◆ Message Line

Displays messages showing the results of either automatic attempts by `xsnacrm` to connect to the specified SNACRM or commands issued to change the trace options.

The space in the window allocated to each of the four panes can be adjusted by dragging the sashes (little rectangles) located on the dividers between them.

Examples

The default geometry for `xsnacrm` is 630x480+150+150. This places an appropriately sized window for the default font in approximately the center of a 1024x768 Xterm. The following command places this window in the lower-right corner at start-up:

```
xsnacrm -geometry 630x480-0-0 //somehost:4999 //otherhost:6666
```

The following command starts `xsnacrm` as an icon:

```
xsnacrm -iconic //252.148.37.16:5555
```

The following command changes the name of the trace menu to *Commands* and uses the service name *snacrm* for the port number:

```
xsnacrm -xrm "*tracemenu.labelString: Commands" //myhost:snacrm
```

Customizing X Resources

The default X resources for `xsnacrm` correspond to the distributed contents of the associated file `xsnacrm`. To customize the application, copy the `xsnacrm` file to your home directory and edit it.

Widgets

The widget structure of the `xsnacrm` window is given in the text of the `xsnacrm` file as follows:

```
! English US resource file for xsnacrm program
!
!   "@(#)ISC Devel SNACRM Xsnacrm 1.1 97/08/12 17:49:57";
!
! The values shown below are the fallback resource values
!
! The widget hierarchy is:
```

```

!
! Xsnacrm                      App Shell
!   mainWindow                 Main Window
!     logo                     Frame
!       logobitmap             Label
!   menubar                    Row/Column
!     filemenu                  Pull-down Menu
!       quit                    Push Button
!     tracemenu                 Pull-down Menu
!       tracebutton0            Push Button
!       tracebutton1            Push Button
!       tracebutton2            Push Button
!       tracebutton3            Push Button
!       traceSep                Separator
!       tracebuttonY            Push Button
!       tracebuttonN            Push Button
!   mainpane                   Paned Window
!     selectFrame               Frame
!       selectFrameLabel        Label
!       selectRadioBox          Row/Column
!       selectButton<n>         Toggle Button
!     traceFrame                Frame
!       traceFrameLabel         Label
!       traceData                Label
!     statusFrame               Frame
!       statusFrameLabel        Label
!       stusScroll              Scrolled Window
!       stusScrollData          Label
!     statisticsFrame           Frame
!       statFrameLabel          Label
!       statScroll              Scrolled Window
!       statScrollData          Label
!   mainmessage                 Label
!   quitDialog                  Message Dialog
!
!
*title:                      BEA Connect SNA CRM Status
*geometry:                    630x480+150+150
*foreground:                  white
*background:                  purple
*fontList:                    *courier-medium-r-normal--12*
*filemenu.labelString:       File
*quitDialog.okLabelString:    Exit
*quitDialog.messageString:    Exit SNA CRM Status Display now?
*quit.labelString:            Exit
*tracemenu.labelString:       Trace
*traceButton0.labelString:    Stop CRM Trace
*traceButton1.labelString:    Set Minimum CRM Trace
*traceButton2.labelString:    Set Medium CRM Trace

```

```
*traceButton3.labelString: Set Maximum CRM Trace  
*traceButtonY.labelString: Start APPC Stack Trace  
*traceButtonN.labelString: Stop APPC Stack Trace
```

See Also

xsnacrm and SNACRM

B ATMI to CPI-C Function Mapping

ATMI Calls Mapped to CPI-C Verbs

This appendix lists the most common ATMI function calls and shows how their parameters map to CPIC verbs. The mappings are shown in the following order:

- ◆ tpcall
- ◆ tpacall with or without reply
- ◆ tpgetrply
- ◆ tpservice
- ◆ tpreturn
- ◆ tpcancel
- ◆ tpconnect
- ◆ tpsend
- ◆ tprecv
- ◆ tpdicon
- ◆ tpforward

B

The tables on the following pages show the parameters of the ATMI call, what the content or meaning of the parameters is, and notes that indicate the usage with the CPIC verbs.

Table B-1 tpcall

tpcall()	Parameters	Contents	CPIC Notes
svc		Service Name	Used in CMALLC to identify the CICS transaction to be invoked.
idata		User data	This data is sent in CMSENDS until completely transmitted
len		Length of User data	0 < data <= 32K
odata		Reply data	CMRCV receives the data until it has been completely transmitted (data_received is set to CM_COMPLETE_DATA_RECEIVED) and return code is set to CM_OK or CM_DEALLOCATE_NORMAL
olen		Reply data length	0 < data < 32K
flags	TPNOTRAN	Not part of a transaction	
	TPNOCHANGE	N/A	Local
	TPNOBLOCK	N/A	Local
	TPNOTIME	N/A	Local
	TPSIGRSTRT	N/A	Local

Table B-2 tpacall

tpacall()	Parameter	Contents	CPIC Notes
svc		Service Name	Used in CMALLC to identify the CICS transaction to be invoked.
data		User data	This data is sent in CMSENDS until completely transmitted

Table B-2 tpacall

tpacall()	Parameter	Contents	CPIC Notes
len		Length of user data	0 < data <= 32K
flags	TPNOREPLY	false	The last data is sent with a CMSEND with send_type set to CMSEND_AND_PREP_TO_RECEIVE. This changes the state of the conversation to receive and a CMRCV is issued to await the reply
		true	Since no reply is expected, a CMDEAL deallocates the conversation after all data has been received
	TPNOTRAN	Not part of a transaction	Sync level 2 not supported in this release, therefore the service call should not be in transaction mode
	TPNOBLOCK	N/A	Local
	TPNOTIME	N/A	Local
	TPSIGRSTRT	N/A	Local

Table B-3 tpgetrply

tpgetrply()	Parameters	Contents	CPIC Notes
cd		call descriptor	The call descriptor is mapped to the CONVID returned by the CMINIT when the LU6.2 was initiated
data		User data	Data received from CMRCV if WHAT_RECEIVED set to DATA_COMPLETE
len		Length of user data	0 < data <= 32K

B

Table B-3 tpgetrply

tpgetrply()	Parameters	Contents	CPIC Notes
flags	TPGETANY	If true, data is returned from any conversation. If false, data is returned from conversation associated with the <code>cd</code>	Data available on any conversation is returned to the requestor
	TPNOCHANGE	Local to the requestor	Limited buffer types supported.
	TPNOBLOCK	N/A	Local
	TPNOTIME	N/A	Local
	TPSIGRSTRT	N/A	Local

Table B-4 tpservice

tpservice()	Parameters	Contents	CPIC Notes
svcinfo		Service information and data	User Data captured from a CMRCV populates the TPSVCINFO structure user data area. Service characteristics are obtained from the service attributes in the DMCONFIG and UBBCONFIG files.
name		Service name	The service name associated with the 8 character RNAME sent from CICS.
data		User data	Data captured from CMRCV
len		Length of user data	0 < data <= 32K Length of data received
cd		call descriptor	The call descriptor associated with the CONVID returned by the CMINIT when the LU6.2 was initiated
appkey		32-bit key (if used)	For security
cltid		set by BEA TUXEDO	For security

Table B-4 tpservice

tpservice()	Parameters	Contents	CPIC Notes
flags	TPCONV	If true, service is conversational	
	TPTRAN	N/A	Sync level 2 not supported in this release, therefore the service cannot be called in transaction mode
	TPNOREPLY	If true, requestor not expecting a reply	The conversation is terminated with a CMDEAL normal
	TPSENDONLY	N/A	If set, the CPIC conversation in CICS should be in receive state. If not set, the CICS CPIC conversation state will be in send state.
	TPRECVONLY	N/A	If set, the CPIC conversation in CICS remains in send state.

Table B-5 tpretreturn

tpretreturn()	Parameters	Contents	CPIC Notes
rval		TPSUCCESS	Set to TPSUCCESS when conversation terminates with a normal deallocation.
		TPSVCERR	Set to TPESVCERR when the conversation has terminated with a non-normal deallocation type or other error.
rcode		Set by the application	N/A
data		User data	Data is returned to the CICS transaction from a successful CMRCV with data received set to CM_DATA_COMPLETE and return code of CM_DEALLOCATE_NORMAL. If the service fails, no data is returned to the caller and the conversation is deallocated abnormally.
len		Length of data returned	0 < data <= 32K
flags		N/A	N/A

B

Table B-6 tpcancel

tpcancel()	Parameters	Contents	CPIC Notes
cd		The connection descriptor on which a <code>tpgetreply()</code> is waiting.	CMDEAL abnormal is issued on the conversation with CONVID mapped from call descriptor

Table B-7 tpconnect

tpconnect()	Parameters	Contents	CPIC Notes
svc		The local service name representing the service to be invoked. in CICS	The name is used to find the RNAME. The RNAME should match the TPName in CICS and will be used by CMINIT and CMALLC to initiate and allocate the conversation
data		User data	This data is sent in CMSENDs until completely transmitted
len		Length of User data	0 < data <= 32K
flags	TPNOTRAN	True	Sync level 2 not supported in this release, therefore the service call should not be in transaction mode
	TPSENDONLY	If true, the conversation stays in or changes to send state	The conversation remains in send state. This is the default.
	TPRECVONLY	If true, the conversation stays in or changes to receive state	Immediately after the allocate BEA TUXEDO sends a CMSEND with no data and send_type set to CM_SEND_AND_PREP_TO_RECEIVE
	TPNOBLOCK	N/A	Local
	TPNOTIME	N/A	Local
	TPSIGRSTRT	N/A	Local

Table B-8 tpsend

tpsend()	Parameters	Contents	CPIC Notes
cd		The connection descriptor	This locally assigned connection descriptor has been mapped to the CONVID returned in the CMINIT and CMALLC on behalf of the <code>tpconnect()</code>
data		User data	ASCII/EBCDIC conversion may be required before sending to CICS. See Chapter 5 “Buffers”
len		Length of User data	$0 < \text{data} \leq 32\text{K}$
flags	TPRECVONLY	If true, the conversation changes to receive state	The state of the conversation changes from send to receive. A CMSEND is sent with <code>send_type</code> set to <code>CM_SEND_AND_PREP_TO_RECEIVE</code>
	TPNOBLOCK	N/A	Local
	TPNOTIME	N/A	Local
	TPSIGRSTRT	N/A	Local
revent	TPEV_DISCONIMM	If set, the LU6.2 conversation has been terminated abnormally	If the return code from a CMRCV is <code>deallocate_abnormal</code> , the conversation is terminated. A disconnect event is sent to the sending process.
	TPEV_SVCERR	If set, the LU6.2 conversation has been terminated abnormally	Any return code other than <code>CM_OK</code> or <code>CM_DEALLOCATE_NORMAL</code> is treated as a <code>TPEV_SVCERR</code>
	TPEV_SVCFAIL	If set, the LU6.2 conversation has been terminated abnormally	If the return code from CMRCV is <code>CM_TP_NOT_AVAIL_NO_RETRY</code> or <code>CM_TP_RESOURCE_FAILURE_NO_RETRY</code> , <code>revent</code> is set to <code>TPEV_SVCFAIL</code>

B

Table B-9 tprecv

tprecv()	Parameters	Contents	CPIC Notes
cd		The connection descriptor	This locally assigned connection descriptor has been mapped to the CONVID returned in the CMINIT and CMALLC issued by the initiator of this conversation
data		User data	Date to be received using a CMRCV_immediate and returned to the BEA TUXEDO service
len		Length of User data	0 < data <= 32K
flags	TPNOCHANGE	Local	Must be a supported buffer type
	TPNOBLOCK	N/A	Local
	TPNOTIME	N/A	Local
	TPSIGRSTRT	N/A	Local
revent	TPEV_DISCONIMM	If set, the LU6.2 conversation has been terminated abnormally	If the return code from a CMSEND is deallocate_abnormal, the conversation is terminated. A disconnect event is sent to the sending process.
	TPEV_SENDOONLY	If set, the LU6.2 conversation changes to send if partner allows it	The sending partner has sent a CMSEND with send_type set to CM_SEND_AND_PREP_TO_RECEIVE
	TPEV_SVCERR	If set, the LU6.2 conversation has been terminated abnormally	Any return code other than CM_OK or CM_DEALLOCATE_NORMAL is treated as a TPEV_SVCERR
	TPEV_SVCFAIL		If the return code from CMRCV is CM_TP_NOT_AVAIL_NO_RETRY or CM_TP_RESOURCE_FAILURE_NO_RETRY, revent is set to TPEV_SVCFAIL
	TPEV_SVCSUCC	If set, the conversation has completed normally	The return code from CMRCV was set to CM_DEALLOCATE_NORMAL. This indicates that the sending TP has completed and deallocated the conversation normally.

Table B-10 tpdicon

tpdiscon()	Parameters	Contents	CPIC Notes
cd		The connection descriptor	This connection descriptor is mapped to the CONVID returned from CMINIT or CMACCP to the originator of the conversation

Table B-11 tpforward

tpforward ()	Parameters	Contents	CPIC Notes
svc		Service name	tpforward() is treated as if it were a tpacall(). A CMINIT and subsequent CMALLC are issued to initialize and allocate a session for a conversation. ClientID must be propagated to the CICS transaction in a TPSVCINFO record
data		User data	Data is sent using CMSEND. The last CMSEND is sent with send_type of deallocate_normal
len		Length of data returned	0 < data <= 32K
flags		Refer to tpacall()	

C CPI-C Parameters and Values

CPI-C Verbs

The following table shows the parameters required for each CPI-C verb and the permissible values when used with BEA eLink for Mainframe SNA software.

Table C-1 CMINIT

Parameter	In/Out	Value	Usage
conversation_ID	Output	Returned by the SNA Stack	Used on every other call
sym_dest_name	Input	Symbolic name that represents the partner LU, the modename, and the TP (TUXEDO service)	If blank, SET calls must be made to initialize conversation parameters
return_code	Output	See list of CPI-C return codes	If not CM_OK, conversation fails.

Table C-2 CMALLC

Parameter	In/Out	Value	Usage
conversation_ID	Input	Value returned from CMINIT	
return_code	Output	See list of CPI-C return codes	If not CM_OK, or CM_ALLOCATION_FAILURE_RETRY, conversation fails

C

Table C-3 CMRCV

Parameter	In/Out	Value	Usage
conversation_ID	Input	Value returned from CMINIT	
buffer	Input	Name of variable to be populated by data received	
requested_length	Input	Name of variable where amount of data to be received is posted	0 <= requested_length < 32K
data_received	Output	CM_COMPLETE CM_INCOMPLETE	Indicates enough data in LU buffer to satisfy requested length Another CMRCV must be issued to get enough data to satisfy the requested length
received-length	Output	Name of variable where amount of data returned is posted	Returned data may be shorter than requested amount including zero
status_received	Output	CM_NO_STATUS CM_SEND_RECEIVED	No state change. State of the conversation is changed to send
request_to_send_received	Output	CM_REQ_TO_SEND_RECEIVED CM_REQ_TO_SEND_NOT_RECEIVED	Receiver enters send state. Partner has not requested a state change
return_code	Output	See list of CPI-C return codes	If not CM_OK or CM_DEALLOCATE_NORMAL, the conversation is deallocated.

Table C-4 CMSEND

Parameter	In/Out	Value	Usage
conversation_ID	Input	Value returned from CMINIT	
buffer	Input	Name of buffer area containing data to be sent	

Table C-4 CMSEND

Parameter	In/Out	Value	Usage
send_length	Input	Length of data in buffer to be sent	0 <= data < 32K
req_to_send_received	Output	The name of the variable that contains the indication that indicates CM_REQ_TO_SEND_RECEIVED	Partner request to change state to send
		CM_REQ_TO_SEND_NOT_RECEIVED	Partner has not requested a state change
return_code	Output	See list of CPI-C return codes	If not CM_OK, the conversation is deallocated

Table C-5 CMACCP

Parameter	In/Out	Value	Usage
conversation_ID	Output	Returned from the LU	
return_code	Output	See list of CPI-C return codes	If not CM_OK, the accept fails and no conversation is started

D Error Messages

The following messages are logged to the USERLOG file from an SNA Domains Instance (GWSNAX) and/or the SNA Communications Resource Manager (SNACRM).

1118:INFO	A BLOCKING timeout has occurred on an outbound request
DESCRIPTION	A blocking time out has occurred on a request to the host.
ACTION	Examine the ULOG for more information concerning the reason for the failure. Check configuration and increase the BLOCKTIME value, if needed.
1121:ERROR	Bad action state
DESCRIPTION	An internal error has been detected processing the action.
ACTION	Contact BEA Customer Support.
1122:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected, gw_nw_acall has returned a failure.
ACTION	Contact BEA Customer Support.
1600:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected, gw_nw_connect has returned a failure.
ACTION	Contact BEA Customer Support.

D

1602:ERROR	Cannot open SNA connection
DESCRIPTION	Unable to allocate a network context. gw_nw_AllocNwCtx failed.
ACTION	See previously printed ULOG message for cause.
1604:ERROR	Initialization of environment failed
DESCRIPTION	Unable to initialize the conversation environment.
ACTION	See previously printed ULOG message for cause.
1621:ERROR	Bad action state
DESCRIPTION	An internal error has been detected processing the action.
ACTION	Contact BEA Customer Support.
1622:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected, gw_nw_convsend has returned a failure.
ACTION	Contact BEA Customer Support.
1625:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected, gw_nw_disconnect has returned a failure.
ACTION	Contact BEA Customer Support.
1630:ERROR	Unable to send data on sna_conv_idx %d
DESCRIPTION	A network error has occurred while while processing a send to the SNACRM. gw_nw_convsend failed.
ACTION	Determine if SNACRM is still active. Look for other ULOG messages that specify a reason for this failure.

1992:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected, gw_nw_decode has returned a failure.
ACTION	Contact BEA Customer Support.
1993:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected, gw_nw_encode has returned a failure.
ACTION	Contact BEA Customer Support.
1994:ERROR	Context data incorrect - null context index
DESCRIPTION	An internal error has been detected, gw_nw_decode has returned a failure.
ACTION	Contact BEA Customer Support.
1995:ERROR	Context data incorrect - null context index
DESCRIPTION	An internal error has been detected, gw_nw_encode has returned a failure.
ACTION	Contact BEA Customer Support.
2200:ERROR	Cannot malloc sna structures
DESCRIPTION	An internal error has been detected, gw_nw_init was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.
2203:ERROR	Cannot malloc remote domain structure
DESCRIPTION	An internal error has been detected, gw_nw_init was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.

D

2204:ERROR	Cannot malloc local SNA structure
DESCRIPTION	An internal error has been detected, gw_nw_init was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.
2205:ERROR	Unable to obtain local snadom information from shmem
DESCRIPTION	An internal error has been detected, gw_nw_init was unable to get needed information from shared memory.
ACTION	Contact BEA Customer Support.
2206:ERROR	Cannot malloc remote service structure
DESCRIPTION	An internal error has been detected, gw_nw_init was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.
2207:ERROR	Cannot malloc remote SNA structure
DESCRIPTION	An internal error has been detected, gw_nw_init was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.
2210:ERROR	Can't create listener for this GATEWAY
DESCRIPTION	An internal error has been detected, gw_nw_init was unable to create a listener.
ACTION	Contact BEA Customer Support.
2211:WARNING	NO SNA conversations waiting for startup
DESCRIPTION	No conversations are waiting at startup.
ACTION	No action needs to be taken.

2214:ERROR	Unable to set APPC_GATEWAY environment variable
DESCRIPTION	An internal error has been detected, _gp_get_nodename failed.
ACTION	Contact BEA Customer Support.
2220:ERROR	Memory Allocation Failure
DESCRIPTION	An internal error has been detected, gw_nw_init was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.
2221:ERROR	Memory Allocation Failure
DESCRIPTION	An internal error has been detected, gw_nw_init was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.
2222:ERROR	Memory Allocation Failure for RDOM table
DESCRIPTION	An internal error has been detected, gw_nw_init was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.
2223:ERROR	Memory Allocation Failure for SNALINK table
DESCRIPTION	An internal error has been detected, gw_nw_init was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.
2224:ERROR	Memory Allocation Failure for SNACRM table
DESCRIPTION	An internal error has been detected, gw_nw_init was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.

D

2225:ERROR	Memory Allocation Failure for SNASTACK table	
	DESCRIPTION	An internal error has been detected, gw_nw_init was unable to allocate memory needed.
	ACTION	Contact BEA Customer Support.
2226:ERROR	Unable to access SNALINK information from memory	
	DESCRIPTION	An internal error has been detected, gw_nw_init was unable to get needed information from shared memory.
	ACTION	Contact BEA Customer Support.
2227:ERROR	Unable to access SNACRM information from memory	
	DESCRIPTION	An internal error has been detected, gw_nw_init was unable to get needed information from shared memory.
	ACTION	Contact BEA Customer Support.
2228:ERROR	Unable to convert SNACRM network address for %s	
	DESCRIPTION	An error has occurred while trying to contact the SNACRM during startup.
	ACTION	Examine the ULOG for more information concerning the reason for the failure. Probably due to a configuration problem.
2229:ERROR	Unable to access SNASTACK information from memory	
	DESCRIPTION	An internal error has been detected, gw_nw_init was unable to get needed information from shared memory.
	ACTION	Contact BEA Customer Support.

2230:ERROR	Unable to build internal network tables
DESCRIPTION	An internal error has been detected, gw_nw_build_nwtbls failed.
ACTION	Examine the ULOG for more information concerning the reason for the failure. Probably due to a configuration problem.
2231:ERROR	Unable to connect to SNACRM %s
DESCRIPTION	An error has occurred while trying to contact the SNACRM during startup.
ACTION	<p>Examine the ULOG for more information concerning the reason for the failure. Possible reasons are:</p> <ol style="list-style-type: none"> 1. The SNACRM server was not configured in the UBBCONFIG. 2. The //host:port parameters as specified in the DMCONFIG and the SNACRM command line parameters in the UBBCONFIG do not agree
2232:ERROR	Unable to SIGNON to SNACRM %s
DESCRIPTION	An error has occurred while signing on to the SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
2233:ERROR	Unable to send STACK %s configuration to SNACRM %s
DESCRIPTION	An error has occurred while sending the stack configuration to the SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure.

D

2234:ERROR	Unable to send SNALINK %s configuration to SNACRM %s
DESCRIPTION	An error has occurred while sending the link configuration to the SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
2235:ERROR	Unable to send START message to SNACRM %s
DESCRIPTION	An error has occurred while sending the START command to the SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
2236:ERROR	Unable to send SHUTDOWN message to SNACRM %s
DESCRIPTION	An error has occurred while sending the SHUTDOWN command to the SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
2237:ERROR	STATE ERROR occurred during initialization, SHUTTING DOWN
DESCRIPTION	An internal state error has occurred start up.
ACTION	Contact BEA Customer Support.
2238:ERROR	Unknown message type received from SNACRM during initialization
DESCRIPTION	An unknown message has been received from SNACRM.
ACTION	Contact BEA Customer Support.
2239:ERROR	GATEWAY FAILS to complete connection to the SNACRM during initialization
DESCRIPTION	Connection to SNACRM is incomplete.
ACTION	Examine the ULOG for more information concerning the reason for the failure.

2240:ERROR	Unable to send SHUTDOWN message to SNACRM %s
DESCRIPTION	GWSNAX is unable to send the SHUTDOWN command to SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure. The SNACRM process has probably already terminated.
2241:ERROR	Unable to access codepage table [%s], reason=%s (%d)
DESCRIPTION	<p>GWSNAX is unable to find the file for the listed codepage for the reason specified. If reason is "Error 0", the (%d) value is the return code from the codepage read routine.</p> <p>2 - Can't read from file 3 - Can't allocate memory 4 - Null/invalid pointer 5 - Invalid parameter 10 - Syntax error 11 - Unsupported format version 12 - Unsupported item</p>
ACTION	Examine the DMCONFIG to determine if the CODEPAGE for a remote domain is specified incorrectly. Correct and retry.
2302:ERROR	Unable to complete initialization with SNACRM
DESCRIPTION	Connection to SNACRM is incomplete.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
2509:ERROR	Unable to obtain new convid id for this request
DESCRIPTION	An internal error has been detected, gw_nw_getnxt_cd has returned a failure.
ACTION	Contact BEA Customer Support.

D

2561:ERROR	Action data incorrect - null action index
DESCRIPTION	An internal error has been detected in gw_nw_recv.
ACTION	Contact BEA Customer Support.
2601:ERROR	Unable to send data on sna_conv_idx %d
DESCRIPTION	An error has occurred while sending reply data (gw_nw_reply) to the SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
2800:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected in gw_nw_clr_convld.
ACTION	Contact BEA Customer Support.
2801:ERROR	Invalid conversation id
DESCRIPTION	An internal error has been detected in gw_nw_clr_convld.
ACTION	Contact BEA Customer Support.
2802:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected in gw_nw_getnxt_cd.
ACTION	Contact BEA Customer Support.
2805:ERROR	Unable to obtain remote domain info from shared memory
DESCRIPTION	An internal error has been detected, gw_nw_init_env was unable to get needed information from shared memory.
ACTION	Contact BEA Customer Support.

2806:ERROR	Unable to obtain snadom info from rdom
DESCRIPTION	An internal error has been detected, gw_nw_init_env was unable to get needed information from shared memory.
ACTION	Contact BEA Customer Support.
2808:ERROR	Cannot realloc sna structures
DESCRIPTION	An internal error has been detected, gw_nw_AllocNwCtx was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.
2816:ERROR	Memory allocation failure
DESCRIPTION	An internal error has been detected, gw_nw_empty_sndbuf was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.
2847:ERROR	SECURITY: Unable to get remote username from shared memory using local principal name %s
DESCRIPTION	A security error has occurred, the user is not authorized to access the remote host.
ACTION	Contact your local security administrator.
2848:ERROR	SECURITY: Unable to get local principal name from shared memory using appkey
DESCRIPTION	A security error has occurred, the user is not authorized to access the remote host.
ACTION	Contact your local security administrator.
2849:ERROR	SECURITY: Unable to extract password from shared memory
DESCRIPTION	A security error has occurred, the user is not authorized to access the remote host.
ACTION	Contact your local security administrator.

D

2850:ERROR	SECURITY: Unable to get security schedule
DESCRIPTION	A security error has occurred, the user is not authorized to access the remote host.
ACTION	Contact your local security administrator.
2853:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected in gw_nw_mk_error.
ACTION	Contact BEA Customer Support.
2854:ERROR	Context data incorrect - null context index for action %d
DESCRIPTION	An internal error has been detected in gw_nw_mk_error.
ACTION	Contact BEA Customer Support.
2860:ERROR	SECURITY: Unable to get remote user from shared memory
DESCRIPTION	A security error has occurred, the remote user is not authorized to access the local TUXEDO host.
ACTION	Contact your local security administrator.
2935:ERROR	Too many unrecoverable errors occurred - deleting action
DESCRIPTION	An error has occurred in gw_nw_mk_error.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
2938:ERROR	SECURITY: Unable to get appkey for this outbound request
DESCRIPTION	A security error has occurred, the user is not authorized to access the remote host.
ACTION	Contact your local security administrator.

2939:ERROR	Deleting the action with the invalid context, %d
	DESCRIPTION An internal error has been detected in gw_nw_snd failure.
	ACTION Contact BEA Customer Support.
3028:ERROR	Can't find transaction node for Network TMS event!
	DESCRIPTION An internal error has been detected in gw_nw_TransCommon.
	ACTION Contact BEA Customer Support.
3029:WARNING	Shutting down GWSNAX!
	DESCRIPTION A severe error such as a protocol error or memory corruption has occurred and has already been logged. The GWSNAX process will shutdown.
	ACTION Examine the ULOG for more information concerning the reason for the failure.
3030:ERROR	Unknown input transactional event(%d)!
	DESCRIPTION An internal error has been detected in gw_nw_TransCvtMsgEvt2TranEvt.
	ACTION Contact BEA Customer Support.
3031:ERROR	Invalid input object pointer!
	DESCRIPTION An internal error has been detected in gw_nw_BindStateObject.
	ACTION Contact BEA Customer Support.
3032:ERROR	Invalid input object initial state!
	DESCRIPTION An internal error has been detected in gw_nw_BindStateObject.
	ACTION Contact BEA Customer Support.

3033:ERROR	Invalid input object type!
DESCRIPTION	An internal error has been detected in gw_nw_BindStateObject.
ACTION	Contact BEA Customer Support.
3034:ERROR	Invalid input state object event(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_StateObjectTestEvent.
ACTION	Contact BEA Customer Support.
3035:ERROR	Event %s is not allowed for state %s!
DESCRIPTION	An internal error has been detected in gw_nw_StateObjectTestEvent.
ACTION	Contact BEA Customer Support.
3036:ERROR	Invalid object event test metric with value %d for %s!
DESCRIPTION	An internal error has been detected in gw_nw_StateObjectTestEvent.
ACTION	Contact BEA Customer Support.
3037:ERROR	Invalid input trace object pointer!
DESCRIPTION	An internal error has been detected in gw_nw_InitEventTrace.
ACTION	Contact BEA Customer Support.
3038:ERROR	Invalid input trace object pointer!
DESCRIPTION	An internal error has been detected in gw_nw_AddEventTrace.
ACTION	Contact BEA Customer Support.

3039:ERROR	Input event %d out of range %d!
DESCRIPTION	An internal error has been detected in gw_nw_AddEventTrace.
ACTION	Contact BEA Customer Support.
3040:ERROR	Invalid input trace object pointer!
DESCRIPTION	An internal error has been detected in gw_nw_QueryEventTrace.
ACTION	Contact BEA Customer Support.
3041:ERROR	Invalid input trace object pointer!
DESCRIPTION	An internal error has been detected in gw_nw_PrintEventTrace.
ACTION	Contact BEA Customer Support.
3042:ERROR	Invalid input event identification(%d)!
DESCRIPTION	An internal error has been detected in gw_nw_EventToString.
ACTION	Contact BEA Customer Support.
3043:ERROR	Memory allocation failure
DESCRIPTION	An internal error has been detected in gw_nw_CreateNodeTable.
ACTION	Contact BEA Customer Support.
3044:WARNING	Transaction table already exists!
DESCRIPTION	An attempt has been made to create the node table and it already exists.
ACTION	No action needs to be taken.

D

3045:ERROR	Invalid input parameters!
DESCRIPTION	An internal error has been detected in gw_nw_AssociateTranByTXID.
ACTION	Contact BEA Customer Support.
3046:ERROR	Requires SNACRM id to create transaction!
DESCRIPTION	An internal error has been detected in gw_nw_AssociateTranByTXID.
ACTION	Contact BEA Customer Support.
3047:ERROR	Cannot associate with network transaction!
DESCRIPTION	An internal error has been detected in gw_nw_AssociateTranByTXID.
ACTION	Contact BEA Customer Support.
3048:ERROR	Invalid input transaction context!
DESCRIPTION	An internal error has been detected in gw_nw_AssociateTranByTCTXT.
ACTION	Contact BEA Customer Support.
3049:ERROR	Invalid input transaction event(%d)!
DESCRIPTION	An internal error has been detected in gw_nw_AssociateTranByTCTXT.
ACTION	Contact BEA Customer Support.
3050:ERROR	Invalid input transaction context pointer!
DESCRIPTION	An internal error has been detected in gw_nw_TransCreateTCTXT.
ACTION	Contact BEA Customer Support.

3051:ERROR	Exceeded local transaction limit(%d)!
DESCRIPTION	Number of concurrent transactions using this domain gateway exceeded the configured limit.
ACTION	Examine the DMCONFIG file for the MAXTRAN parameter, this number is the limit. If MAXTRAN is not specified, then examine the ubbconfig file for the MAXGTT parameter. In the later case MAXGTT is the limit. Modify the limit if necessary.
3052:ERROR	Can not create shared memory nettxid!
DESCRIPTION	An internal error has been detected in gw_nw_TransCreateTCTXT.
ACTION	Contact BEA Customer Support.
3053:ERROR	Create transaction tree node failed!
DESCRIPTION	gw_nw_TransCreateTCTXT failed to create the transaction tree node object. This can be caused by reaching the configured transaction limit or by a memory allocation failure.
ACTION	Examine the ULOG for more information concerning the reason for the failure. If the cause is the limit being reached, update the configuration. If the cause is a memory allocation failure, update the system and/or the system configuration.
3054:ERROR	Invalid input transaction handle!
DESCRIPTION	An internal error has been detected in gw_nw_TransGetTCTXT.
ACTION	Contact BEA Customer Support.
3055:ERROR	Invalid input transaction handle!
DESCRIPTION	An internal error has been detected in gw_nw_TransGetTXID.
ACTION	Contact BEA Customer Support.

D

3056:ERROR	Invalid input parameter!
DESCRIPTION	An internal error has been detected in gw_nw_TransProcessEvent.
ACTION	Contact BEA Customer Support.
3057:ERROR	Unable to calculate transaction handle!
DESCRIPTION	An internal error has been detected in gw_nw_TransProcessEvent.
ACTION	Contact BEA Customer Support.
3058:ERROR	Input Gateway event not transactional!
DESCRIPTION	The service request inbound from a remote host is transactional but the GWSNAX is not configured as a transactional gateway.
ACTION	The MAXSYNCLVL specified in the DMCONFIG must be 2 if transactional requests are to be processed.
3059:ERROR	Transaction does not exist!
DESCRIPTION	An internal error has been detected in gw_nw_TransProcessEvent.
ACTION	Contact BEA Customer Support.
3060:ERROR	Invalid input transaction handle!
DESCRIPTION	An internal error has been detected in gw_nw_TransProcessEvent.
ACTION	Contact BEA Customer Support.
3061:ERROR	Invalid Gateway action identification!
DESCRIPTION	An internal error has been detected in gw_nw_TransSetUpExtTmsEvent.
ACTION	Contact BEA Customer Support.

3062:ERROR	Decoding input transaction message failed!
DESCRIPTION	An internal error has been detected in gw_nw_TransetUpExtTmsEvent.
ACTION	Contact BEA Customer Support.
3063:ERROR	SNACRM verb %d is not for TMS event!
DESCRIPTION	An internal error has been detected in gw_nw_TransetUpExtTmsEvent.
ACTION	Contact BEA Customer Support.
3064:ERROR	Invalid input transaction context!!
DESCRIPTION	An internal error has been detected in gw_nw_TransetRelease.
ACTION	Contact BEA Customer Support.
3065:ERROR	Transaction for context(%d) not found!
DESCRIPTION	The specified context for the transaction to be released could not be found by gw_nw_TransetRelease.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
3066:ERROR	Cannot disassociate with network transaction!
DESCRIPTION	An error has been returned by gw_tx_end.
ACTION	Examine the ULOG for more information concerning the reason for the failure.

3067:ERROR	Cannot set remote domain for transaction!
DESCRIPTION	<p>An error has been returned by gw_tx_set_rdom. Several possibilities exist for this failure.</p> <ol style="list-style-type: none">1. The process is unable to obtain the shared memory lock.2. The configured limit for the number of remote domains that can be involved in the same transaction has been reached. This limit is specified in the MAXRDTRAN in the DMCONFIG.
ACTION	<p>Examine the DMCONFIG and compare with the number of remote domains which might become involved in the same transaction. Update the DMCONFIG if necessary. Also examine the ULOG for more information concerning possible reasons for the failure.</p>
3068:ERROR	Invalid input transaction handle!
DESCRIPTION	<p>An internal error has been detected in gw_nw_TransGetNodePtr.</p>
ACTION	<p>Contact BEA Customer Support.</p>
3069:ERROR	Transaction handle not in use!
DESCRIPTION	<p>An internal error has been detected in gw_nw_TransGetNodePtr.</p>
ACTION	<p>Contact BEA Customer Support.</p>
3070:ERROR	Transaction processing not yet initialize!
DESCRIPTION	<p>An internal error has been detected in gw_nw_TransGetNodePtr.</p>
ACTION	<p>Contact BEA Customer Support.</p>

3071:ERROR	Defined transaction limit %d reached!
DESCRIPTION	The number of concurrent transactions using this domain gateway has exceeded the limit.
ACTION	Examine the DMCONFIG file for the MAXTRAN parameter, this number is the limit. If MAXTRAN is not specified, then examine the ubbconfig file for the MAXGTT parameter. In the later case MAXGTT is the limit. Modify the limit if necessary.
3072:ERROR	Allocate SNACRM branch structure failed!
DESCRIPTION	An internal error has been detected in gw_nw__gw_nw_AllocateNode.
ACTION	Contact BEA Customer Support.
3073:ERROR	Unable to bind outbound node state object!
DESCRIPTION	A failure was returned by gw_nw_BindStateObject.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
3074:ERROR	Unable to bind inbound node state object!
DESCRIPTION	A failure was returned by gw_nw_BindStateObject.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
3075:ERROR	Unable to bind recover node state object!
DESCRIPTION	A failure was returned by gw_nw_BindStateObject.
ACTION	Examine the ULOG for more information concerning the reason for the failure.

3076:ERROR	Invalid event %s to create transaction tree node!
DESCRIPTION	An internal error has been detected in _gw_nw_AllocateNode.
ACTION	Contact BEA Customer Support.
3077:ERROR	Memory allocation failure!
DESCRIPTION	An internal error has been detected in gw_nw_AllocBranch.
ACTION	Contact BEA Customer Support.
3078:ERROR	Event(%s) is not allowed to create SNACRM branch!
DESCRIPTION	An internal error has been detected in gw_nw_AllocBranch.
ACTION	Contact BEA Customer Support.
3079:ERROR	Free more branch than transaction tree node has!
DESCRIPTION	An internal error has been detected in gw_nw_FreeBranch.
ACTION	Contact BEA Customer Support.
3080:ERROR	Protocol violation, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_3.
ACTION	Contact BEA Customer Support.
3081:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_4.
ACTION	Contact BEA Customer Support.

3082:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_5.
ACTION	Contact BEA Customer Support.
3083:ERROR	Branch in a bad state(%s) to issue prepare!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_5.
ACTION	Contact BEA Customer Support.
3084:WARNING	Inconsistent branch state for prepare(%d, %d)!
DESCRIPTION	The transaction branch is in an inconsistent state for issuing a prepare. It will be assumed that they are all prepared.
ACTION	No action needs to be taken.
3085:INFO	Transaction node is deallocated because of ABEND!
DESCRIPTION	Informational message. GWSNAX detected an ABEND condition or received an ABEND event from the SNACRM which caused the node object to be destroyed.
ACTION	No action needs to be taken.
3086:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_7.
ACTION	Contact BEA Customer Support.
3087:ERROR	Branch in a bad state(%s) to issue prepare!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_7.
ACTION	Contact BEA Customer Support.

D

3088:WARNING	Inconsistent branch state for rollback(%d, %d)!
DESCRIPTION	The transaction branch was in an inconsistent state for issuing a rollback. It will be assumed that they are all rolled back.
ACTION	No action needs to be taken.
3089:WARNING	Inconsistent branch accounting for rollback(%d, %d, %d)!
DESCRIPTION	The transaction branch accounting was inconsistent while issuing a rollback.
ACTION	No action needs to be taken.
3090:WARNING	Incorrect branch accounting for rollback(%d)!
DESCRIPTION	The transaction branch accounting was incorrect while issuing a rollback.
ACTION	No action needs to be taken.
3091:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_8.
ACTION	Contact BEA Customer Support.
3092:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_9.
ACTION	Contact BEA Customer Support.
3093:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_10.
ACTION	Contact BEA Customer Support.

3094:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_11.
ACTION	Contact BEA Customer Support.
3095:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_12.
ACTION	Contact BEA Customer Support.
3096:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_13.
ACTION	Contact BEA Customer Support.
3097:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_14.
ACTION	Contact BEA Customer Support.
3098:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_15.
ACTION	Contact BEA Customer Support.
3099:ERROR	Retired node method!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_Retired.
ACTION	Contact BEA Customer Support.

3100:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_16.
ACTION	Contact BEA Customer Support.
3101:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_17.
ACTION	Contact BEA Customer Support.
3102:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_18.
ACTION	Contact BEA Customer Support.
3103:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_19.
ACTION	Contact BEA Customer Support.
3104:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_20.
ACTION	Contact BEA Customer Support.
3105:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_21.
ACTION	Contact BEA Customer Support.

3106:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_22.
ACTION	Contact BEA Customer Support.
3107:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_23.
ACTION	Contact BEA Customer Support.
3108:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_24.
ACTION	Contact BEA Customer Support.
3109:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_25.
ACTION	Contact BEA Customer Support.
3110:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_26.
ACTION	Contact BEA Customer Support.
3111:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_27.
ACTION	Contact BEA Customer Support.

3112:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!	
	DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_28.
	ACTION	Contact BEA Customer Support.
3113:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!	
	DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_29.
	ACTION	Contact BEA Customer Support.
3114:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!	
	DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_30.
	ACTION	Contact BEA Customer Support.
3115:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!	
	DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_31.
	ACTION	Contact BEA Customer Support.
3116:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!	
	DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_32.
	ACTION	Contact BEA Customer Support.
3117:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!	
	DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_33.
	ACTION	Contact BEA Customer Support.

3118:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_39.
ACTION	Contact BEA Customer Support.
3119:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_40.
ACTION	Contact BEA Customer Support.
3120:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_42.
ACTION	Contact BEA Customer Support.
3121:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_43.
ACTION	Contact BEA Customer Support.
3122:ERROR	Encoding transaction message for verb(%d) failed!
DESCRIPTION	A failure was returned by snacrm_tx_msg.
ACTION	Contact BEA Customer Support.
3123:ERROR	SNACRM(%d) in bad state(%s) to issue verb(%d)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeSendToBranch.
ACTION	Contact BEA Customer Support.

D

3124:ERROR	Send verb %d to snacrm failed!	
	DESCRIPTION	A failure has been detected while sending the specified verb to the SNACRM.
	ACTION	Examine the ULOG for more information concerning the reason for the failure. Determine if the SNACRM process is still active.
3125:ERROR	Encoding transactional message for verb(%d) failed!	
	DESCRIPTION	A failure was returned by snacrm_tx_msg.
	ACTION	Contact BEA Customer Support.
3126:ERROR	SNACRM(%d) in bad state(%s) to issue verb(%d)!	
	DESCRIPTION	An internal error has been detected in gw_nw_NodeSendToSubordinate.
	ACTION	Contact BEA Customer Support.
3127:ERROR	Send verb(%d) to SNACRM failed!	
	DESCRIPTION	A failure has been detected while sending the specified verb to the SNACRM.
	ACTION	Examine the ULOG for more information concerning the reason for the failure. Determine if the SNACRM process is still active.
3128:ERROR	Encoding transactional message for verb(%d) failed!	
	DESCRIPTION	A failure was returned by snacrm_tx_msg.
	ACTION	Contact BEA Customer Support.
3129:ERROR	SNACRM(%d) in bad state(%s) to issue verb(%d)!	
	DESCRIPTION	An internal error has been detected in gw_nw_NodeSendToSubordinate.
	ACTION	Contact BEA Customer Support.

3130:ERROR	Send verb(%d) to SNACRM failed!
DESCRIPTION	A failure has been detected while sending the specified verb to the SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure. Determine if the SNACRM process is still active.
3131:ERROR	Protocol violation, branch id[%d] at state(%s) receive event(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_BranchMethod_1.
ACTION	Contact BEA Customer Support.
3132:ERROR	Memory allocation error!
DESCRIPTION	An internal error has been detected in gw_nw_TransRestart.
ACTION	Contact BEA Customer Support.
3133:ERROR	Unable to get shared memory semaphore lock!
DESCRIPTION	An internal error has been detected in gw_nw_TransRestart.
ACTION	Contact BEA Customer Support.
3134:ERROR	Unable to find transaction on GTT!
DESCRIPTION	An internal error has been detected in gw_nw_TransRestart.
ACTION	Contact BEA Customer Support.
3135:ERROR	SNAX group is not participating the transaction!
DESCRIPTION	An internal error has been detected in gw_nw_TransRestart.
ACTION	Contact BEA Customer Support.

D

3136:ERROR	Unable to setup transaction recovery!
DESCRIPTION	A failure was returned by gw_nw_TransRecover.
ACTION	Contact BEA Customer Support.
3137:ERROR	Unable to setup transaction recovery!
DESCRIPTION	A failure was returned by gw_nw_TransRecover.
ACTION	Contact BEA Customer Support.
3138:ERROR	Unable to create recovery action!
DESCRIPTION	A failure was returned by gw_new_action.
ACTION	Contact BEA Customer Support.
3139:ERROR	Unable to create recovery action!
DESCRIPTION	A failure was returned by gw_chld_action.
ACTION	Contact BEA Customer Support.
3140:ERROR	Unable to setup transaction recovery!
DESCRIPTION	A failure was returned by gw_nw_TransRecover.
ACTION	Contact BEA Customer Support.
3141:ERROR	Unable to create recovery action!
DESCRIPTION	A failure was returned by gw_new_action.
ACTION	Contact BEA Customer Support.
3142:ERROR	Unable to create recovery action!
DESCRIPTION	A failure was returned by gw_chld_action.
ACTION	Contact BEA Customer Support.
3143:ERROR	Unable to setup transaction recovery!
DESCRIPTION	A failure was returned by gw_nw_TransRecover.
ACTION	Contact BEA Customer Support.

3144:ERROR	Unable to setup transaction recovery!
DESCRIPTION	A failure was returned by gw_nw_TransRecover.
ACTION	Contact BEA Customer Support.
3145:ERROR	Unable to release shared memory lock!
DESCRIPTION	A failure was returned by _gw_shmunlock.
ACTION	Contact BEA Customer Support.
3146:ERROR	Unable to find SNACRM for superior remote domain(%s)!
DESCRIPTION	Failed to find the remote domain definition in the configuration in order to get the SNACRM identification.
ACTION	Examine the DMCONFIG for changes between the boots that would modify or remove the remote definition. If no such change has occurred, contact BEA Customer Support.
3147:ERROR	Could not find Remote Domain(%s) to do recovery!
DESCRIPTION	An internal error has been detected in gw_nw_TransRecover.
ACTION	Contact BEA Customer Support.
3148:ERROR	Could not find Remote Domain to do recovery!
DESCRIPTION	An internal error has been detected in gw_nw_TransRecover.
ACTION	Contact BEA Customer Support.

3149:ERROR	Could not create transaction tree structure!
DESCRIPTION	Unable to allocate a transaction tree node structure to represent the transaction recovery object.
ACTION	Examine the configuration to determine if there has been a change of MAXTRAN in DMCONFIG and/or a change of MAXGTT in UBBCONFIG. This condition may occur if there is a decrease in the number of transactions allowed between boots while many transactions must be recovered. If no changes have been made, contact BEA Customer Support.
3150:ERROR	Unable to create SNACRM branch structure!
DESCRIPTION	A failure was returned by _gw_nw_AllocBranch.
ACTION	Contact BEA Customer Support.
3151:ERROR	Unable to create SNACRM branch structure!
DESCRIPTION	A failure was returned by _gw_nw_AllocBranch.
ACTION	Contact BEA Customer Support.
3152:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_44.
ACTION	Contact BEA Customer Support.
3153:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_45.
ACTION	Contact BEA Customer Support.
3154:ERROR	Invalid Gateway action, receive event(%s) at state(%s)!
DESCRIPTION	An internal error has been detected in gw_nw_NodeMethod_46.
ACTION	Contact BEA Customer Support.

3155:ERROR	Invalid transaction context(%d) from SNACRM!
DESCRIPTION	An internal error has been detected in gw_nw_TransetUpExtTmsEvent.
ACTION	Contact BEA Customer Support.
3156:WARNING	Undefined instrumentation register %d specification, ignored!
DESCRIPTION	An internal error has been detected in gw_nw_SetUpInstrumentation.
ACTION	Contact BEA Customer Support.
3157:INFO	CONNECTED TO SNACRM
DESCRIPTION	The GWSNAX process has successfully started the gateway connection to the SNACRM process.
ACTION	No action needs to be taken.
3158:WARNING	SNACRM Link %s Inoperable
DESCRIPTION	The specified link did not start up correctly.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
3159:ERROR	INVALID STARTTYPE (%s) - calling shutdown
DESCRIPTION	The STARTTYPE specified in the DMCONFIG must be AUTO or COLD.
ACTION	Correct the value specified in the DMCONFIG and restart.
3500:ERROR	Unable to find remote service definition link
DESCRIPTION	An internal error has been detected in gw_nw_decode.
ACTION	Contact BEA Customer Support.

3501:ERROR	Unable to find local service definition link	
	DESCRIPTION	An internal error has been detected in gw_nw_decode.
	ACTION	Contact BEA Customer Support.
3502:ERROR	Buffer type (%s,%s) not defined in the buffer type switch!	
	DESCRIPTION	The buffer type associated with the inbound message is not specified in the type switch.
	ACTION	Examine the application and the configuration to determine which buffer type is being used. GWSNAX only supports standard TUXEDO buffer types over the domain gateway. If the buffer type is VIEW, VIEW32, then also examine the environment variables VIEWDIR, VIEWFILES, VIEW32DIR, or VIEW32FILES.
3503:ERROR	Failed to tmalloc() STRING buffer of size %ld	
	DESCRIPTION	No buffer of type STRING was returned by tmalloc for the size specified.
	ACTION	If the size specified is 1, then a length of zero was received. Check the application to determine if it has an error, otherwise contact BEA Customer Support.
3504:ERROR	Failed to tmalloc() CARRAY/X_OCTET buffer of size %ld	
	DESCRIPTION	No buffer of type CARRAY or X_OCTET was returned by tmalloc for the size specified.
	ACTION	If the size specified is 1, then a length of zero was received. Check the application to determine if it has an error, otherwise contact BEA Customer Support.

3505:ERROR	Input buffer too big(%ld)!
	DESCRIPTION The buffer received of the size specified, exceeded the maximum allowed of 32767.
	ACTION Check the application to determine if it has an error, otherwise contact BEA Customer Support.
3506:ERROR	Missing subtype specification for %s
	DESCRIPTION The buffer type specified of VIEW, VIEW32, X_C_TYPE, or X_COMMON requires that a subtype be specified.
	ACTION Examine the application and the DMCONFIG and correct the problem.
3507:ERROR	Malloc temporary buffer of size(%ld) failed!
	DESCRIPTION An internal error has been detected in gw_nw_decode .
	ACTION Contact BEA Customer Support.
3508:ERROR	Convert buffer type(%s,%s) failed, convert failure!
	DESCRIPTION The conversion of the buffer received from the remote host was unsuccessful.
	ACTION Examine the application to determine if it has an error, examine the DMCONFIG definition for any errors in the buffer type specification. If no errors are found, contact BEA Customer Support.
3509:ERROR	Convert buffer type(%s,%s) failed, length too big!
	DESCRIPTION The conversion of the buffer received from the remote host was unsuccessful due to the resulting size exceeding the maximum of 32767.
	ACTION Examine the application to determine if it has an error, examine the DMCONFIG definition for any errors in the buffer type specification. If no errors are found, contact BEA Customer Support.

D

3510:ERROR	Failed to tmalloc() buffer (%s,%s) of size %ld	
	DESCRIPTION	No buffer was returned by tmalloc for the size specified to hold the converted buffer data.
	ACTION	Examine the application to determine if it has an error, otherwise contact BEA Customer Support.
3511:ERROR	Missing subtype for FML type buffer!	
	DESCRIPTION	The buffer type specified of FML requires that a subtype be specified.
	ACTION	Examine the application and the configuration to determine which buffer type is being used. GWSNAX only supports standard TUXEDO buffer types over the domain gateway. If the buffer type is VIEW, VIEW32, then also examine the environment variables VIEWDIR, VIEWFILES, VIEW32DIR, or VIEW32FILES.
3512:ERROR	Malloc temporary buffer of size(%ld) failed!	
	DESCRIPTION	An internal error has been detected in gw_nw_decode.
	ACTION	Contact BEA Customer Support.
3513:ERROR	Malloc failed, unable to convert!	
	DESCRIPTION	The conversion of the buffer received from the remote host was unsuccessful.
	ACTION	Examine the application to determine if it has an error, examine the DMCONFIG definition for any errors in the buffer type specification. If no errors are found, contact BEA Customer Support.
3514:ERROR	Failed to malloc temporary buffer of size %ld	
	DESCRIPTION	An internal error has been detected in gw_nw_decode.
	ACTION	Contact BEA Customer Support.

3515:ERROR	Convert buffer type(%s,%s) failed, convert failure!
DESCRIPTION	The conversion of the buffer received from the remote host was unsuccessful.
ACTION	Examine the application to determine if it has an error, examine the DMCONFIG definition for any mistakes in the buffer type specification. If no errors are found, contact BEA Customer Support.
3516:ERROR	Failed to tmalloc() buffer (%s,%s) of size %ld
DESCRIPTION	No buffer was returned by tmalloc for the size specified to hold the converted buffer data.
ACTION	Check the application to determine if it has an error, otherwise contact BEA Customer Support.
3517:ERROR	Missing subtype definition for FML32 buffer type!
DESCRIPTION	The buffer type specified of FML32 requires that a subtype be specified.
ACTION	Correct the DMCONFIG definition.
3518:ERROR	Malloc temporary of size(%ld) failed!
DESCRIPTION	An internal error has been detected in gw_nw_decode.
ACTION	Contact BEA Customer Support.
3519:ERROR	Convert FML32 buffer type(%s,%s) failed, convert failure!
DESCRIPTION	The conversion of the buffer received from the remote host was unsuccessful.
ACTION	Examine the application to determine if it has an error, examine the DMCONFIG definition for any errors in the buffer type specification. If no errors are found, contact BEA Customer Support.

3520:ERROR	Malloc temporary buffer of size(%ld) failed!
DESCRIPTION	An internal error has been detected in gw_nw_decode.
ACTION	Contact BEA Customer Support.
3521:ERROR	Convert FML32 buffer with subtype(%s) failed!
DESCRIPTION	The conversion of the buffer received from the remote host was unsuccessful.
ACTION	Examine the application to determine if it has an error, examine the DMCONFIG definition for any errors in the buffer type specification. If no errors are found, contact BEA Customer Support.
3522:ERROR	Failed to tmalloc() FML32 buffer of size %d for %s!
DESCRIPTION	An internal error has been detected in gw_nw_decode.
ACTION	Contact BEA Customer Support.
3523:ERROR	Fail to convert for FML buffer(%s), exceeding limit!
DESCRIPTION	Failed to convert the FML buffer; the buffer size required to process the conversion exceeds the limit.
ACTION	Examine the application and the view for this buffer for any errors. If no errors are found, contact BEA Customer Support.
3524:ERROR	Fail to convert for FML32 buffer(%s), exceeding limit!
DESCRIPTION	Failed to convert the FML32 buffer; the buffer size required to process the conversion exceeds the limit.
ACTION	Examine the application and the view for this buffer for any errors. If no errors are found, contact BEA Customer Support.

3525:ERROR	Fail to retrieve remote service definition!
DESCRIPTION	Unable to find the remote service definition in shared memory.
ACTION	Examine the DMCONFIG remote service definitions. Correct any errors found. If no error is found, contact BEA Customer Support.
3526:ERROR	Fail to retrieve local service definition!
DESCRIPTION	Unable to find the local service definition in shared memory.
ACTION	Examine the DMCONFIG local service definitions. Correct any errors found. If no error is found, contact BEA Customer Support.
3527:ERROR	Must specify subtype for %s
DESCRIPTION	The buffer type specified of VIEW, VIEW32, X_C_TYPE, or X_COMMON requires that a subtype be specified.
ACTION	Correct any errors in the DMCONFIG buffer type definitions. If no errors are found, contact BEA Customer Support.
3528:ERROR	Malloc temporary buffer of size(%d) failed!
DESCRIPTION	An internal error has been detected in gw_nw_encode.
ACTION	Contact BEA Customer Support.
3529:ERROR	Convert buffer type %s with subtype %s failed(rc=%d)!
DESCRIPTION	The conversion of the buffer received from TUXEDO was unsuccessful.
ACTION	Examine the application to determine if it has an error, examine the DMCONFIG definition for any errors in the buffer type specification. If no errors are found, contact BEA Customer Support.

3530:ERROR	Convert buffer type %s with subtype %s failed(rc=%d)!
DESCRIPTION	The conversion of the buffer received from TUXEDO was unsuccessful due to the resulting size exceeding the maximum of 32767.
ACTION	Examine the application to determine if it has an error, examine the DMCONFIG definition for any errors in the buffer type specification. If no errors are found, contact BEA Customer Support.
3531:ERROR	Malloc temporary buffer of size(%d) failed!
DESCRIPTION	An internal error has been detected in gw_nw_encode.
ACTION	Contact BEA Customer Support.
3532:ERROR	FML buffer type requires subtype to be specified!
DESCRIPTION	The buffer type specified of FML requires that a subtype be specified.
ACTION	Correct the DMCONFIG definition.
3533:ERROR	Malloc temporary buffer of size(%d) failed!
DESCRIPTION	An internal error has been detected in gw_nw_encode.
ACTION	Contact BEA Customer Support.
3534:ERROR	Convert FML buffer with subtype %s failed(Error=%d)!
DESCRIPTION	The conversion of the FML buffer received from TUXEDO was unsuccessful. Error is the return code from the FML conversion routine.
ACTION	Examine the application to determine if it has an error, examine the DMCONFIG definition for any errors in the buffer type specification. If no errors are found, contact BEA Customer Support.

3535:ERROR	Malloc temporary buffer of size(%d) failed!
DESCRIPTION	An internal error has been detected in gw_nw_encode.
ACTION	Contact BEA Customer Support.
3536:ERROR	Convert FML buffer with subtype %s failed(Error=%d)!
DESCRIPTION	The conversion of the FML buffer received from TUXEDO was unsuccessful. Error is the return code from the FML conversion routine.
ACTION	Examine the application to determine if it has an error, examine the DMCONFIG definition for any errors in the buffer type specification. If no errors are found, contact BEA Customer Support.
3537:ERROR	Malloc buffer of size(%d) failed!
DESCRIPTION	An internal error has been detected in gw_nw_encode.
ACTION	Contact BEA Customer Support.
3538:ERROR	FML32 buffer type requires subtype to be specified!
DESCRIPTION	The buffer type specified of FML32 requires that a subtype be specified.
ACTION	Correct the DMCONFIG definition.
3539:ERROR	Malloc temporary buffer of size(%d) failed!
DESCRIPTION	An internal error has been detected, gw_nw_Alloc was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.

D

3540:ERROR	Convert FML32 buffer with subtype %s failed(Error=%d)!	
	DESCRIPTION	The conversion of the FML32 buffer received from TUXEDO was unsuccessful. Error is the return code from the FML conversion routine.
	ACTION	Examine the application to determine if it has an error, examine the DMCONFIG definition for any errors in the buffer type specification. If no errors are found, contact BEA Customer Support.
3541:ERROR	Malloc temporary buffer of size(%d) failed!	
	DESCRIPTION	An internal error has been detected, gw_nw_Alloc was unable to allocate memory needed.
	ACTION	Contact BEA Customer Support.
3542:ERROR	Convert FML32 buffer with subtype %s failed(Error=%d)!	
	DESCRIPTION	The conversion of the FML32 buffer received from TUXEDO was unsuccessful. Error is the return code from the FML conversion routine.
	ACTION	Examine the application to determine if it has an error, examine the DMCONFIG definition for any errors in the buffer type specification. If no errors are found, contact BEA Customer Support.
4000:ERROR	GP_SEND flow controlled for GPND %d	
	DESCRIPTION	An internal error has been detected, gw_nw_proto_flow has detected a flow control callback from gp_send.
	ACTION	Contact BEA Customer Support.
4100:ERROR	Maximum number of pointers exceeded	
	DESCRIPTION	An internal error has been detected. The maximum number of pointers has exceeded 500.
	ACTION	Contact BEA Customer Support.

4124:ERROR	Unable to format snacrm_acall
DESCRIPTION	An internal error has been detected, snacrm_acall has returned an error.
ACTION	Contact BEA Customer Support.
4125:ERROR	Unable to send data on sna_conv_idx %d, gpnd = %d
DESCRIPTION	An error has occurred while sending acall data (gw_nw_acall) to the SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
4126:ERROR	Unable to format snacrm_connect
DESCRIPTION	An internal error has been detected, snacrm_connect has returned an error.
ACTION	Contact BEA Customer Support.
4127:ERROR	Unable to send data on sna_conv_idx %d, gpnd = %d
DESCRIPTION	An error has occurred while sending connect data (gw_nw_connect) to the SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
4128:ERROR	Unable to format snacrm_send_data
DESCRIPTION	An internal error has been detected, snacrm_send has returned an error.
ACTION	Contact BEA Customer Support.
4130:ERROR	Unable to format snacrm_connect
DESCRIPTION	An internal error has been detected, snacrm_connect_rsp has returned an error.
ACTION	Contact BEA Customer Support.

5019:ERROR	Send event for RRCORR(%ld) failed!
DESCRIPTION	An internal error has been detected, gw_nw_SendEvent has returned an error.
ACTION	Contact BEA Customer Support.
5020:ERROR	Encode ACALL_RSP failed, RRCORR(%ld)!
DESCRIPTION	An internal error has been detected, snacrm_acall_rsp has returned an error.
ACTION	Contact BEA Customer Support.
5021:ERROR	Encode reply failed!
DESCRIPTION	An error was detected while attempting to encode the reply message data destined for the remote host.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
5022:ERROR	Invalid network descriptor(%d)!
DESCRIPTION	The network descriptor this context is invalid.
ACTION	Examine the ULOG for more information concerning the reason for the failure.

5023:ERROR	Could not get transaction
DESCRIPTION	<p>Failed to associate a transactional ACALL service request to a transaction object. The most likely reasons for this failure are:</p> <ol style="list-style-type: none"> 1. The locally configured limit has been exceeded, or 2. Memory allocation has failed to create the transaction object.
ACTION	<p>Determine if the application is licensed to do transactions. Examine the DMCONFIG file for the MAXTRAN parameter, this number is the limit. If MAXTRAN is not specified, then examine the ubbconfig file for the MAXGTT parameter. In the later case MAXGTT is the limit. Modify the limit if necessary. Verify that the remote domain MAXSYNCLVL is set to 2.</p>
5024:ERROR	Could not get API
DESCRIPTION	<p>An internal error has been detected. The API information is invalid.</p>
ACTION	<p>Contact BEA Customer Support.</p>
5025:ERROR	Could not get transaction
DESCRIPTION	<p>Failed to associate a transactional CONNECT service request to a transaction object. The most likely reasons for this failure are:</p> <ol style="list-style-type: none"> 1. The locally configured limit has been exceeded, or 2. Memory allocation has failed to create the transaction object
ACTION	<p>Determine if the application is licensed to do transactions. Examine the DMCONFIG file for the MAXTRAN parameter, this number is the limit. If MAXTRAN is not specified, then examine the ubbconfig file for the MAXGTT parameter. In the later case MAXGTT is the limit. Modify the limit if necessary. Verify that the remote domain MAXSYNCLVL is set to 2.</p>

5026:ERROR	Could not get API
DESCRIPTION	An internal error has been detected. The API information is invalid.
ACTION	Contact BEA Customer Support.
5027:ERROR	Could not get API
DESCRIPTION	An internal error has been detected. The API information is invalid.
ACTION	Contact BEA Customer Support.
5028:ERROR	Protocol violation, shutdown gateway!
DESCRIPTION	An internal error has been detected by gw_nw_crmrcv.
ACTION	Contact BEA Customer Support.
5029:ERROR	Link status down for remote domain %s
DESCRIPTION	The link status returned by the SNACRM is LINK_DOWN.
ACTION	Determine if the stack is active and check that the session between the stack provider and the remote host is active.
5030:ERROR	Link status pending for remote domain %s
DESCRIPTION	The link status returned by the SNACRM is LINK_PENDING. Transaction recovery for the link is still in progress following a restart. Only non-transactional requests may be sent to this link.
ACTION	Wait until recovery is complete before requesting transactional services on this link.

5031:ERROR	Transaction not allowed, request rejected!
DESCRIPTION	Failed to send a transactional ACALL request to the remote domain because MAXSYNCLVL is not 2.
ACTION	Determine the following things: <ul style="list-style-type: none"> 1. GWSNAX is licensed for transactions, and 2. DMCONFIG specifies MAXSYNCLVL=2 for the link.
5032:ERROR	Transaction not allowed, request rejected!
DESCRIPTION	Failed to send a transactional CONNECT request to the remote domain because MAXSYNCLVL is not 2.
ACTION	Determine the following things: <ul style="list-style-type: none"> 1. GWSNAX is licensed for transactions, and 2. DMCONFIG specifies MAXSYNCLVL=2 for the link.
5033:ERROR	Protocol violation, shutdown gateway!
DESCRIPTION	An internal error has been detected by gw_nw_crmrcv.
ACTION	Contact BEA Customer Support.
5034:ERROR	Allocate context failed!
DESCRIPTION	An internal error has been detected. An error was returned by gw_nw_AllocNwCtx.
ACTION	Contact BEA Customer Support.
5035:ERROR	Enter shutdown
DESCRIPTION	An internal error has been detected by gw_nw_crmrcv.
ACTION	Contact BEA Customer Support.

D

5036:ERROR	Invalid conversation identification, shutdown gateway!
DESCRIPTION	An internal error has been detected by gw_nw_convsend.
ACTION	Contact BEA Customer Support.
5037:ERROR	Unknown message type, shutdown gateway!
DESCRIPTION	An internal error has been detected by gw_nw_crmrcv.
ACTION	Contact BEA Customer Support.
5038:ERROR	LINK_STATUS state error, shutdown gateway!
DESCRIPTION	An internal error has been detected by gw_nw_crmrcv.
ACTION	Contact BEA Customer Support.
5039:ERROR	Protocol violation, shutdown gateway!
DESCRIPTION	An internal error has been detected by gw_nw_crmrcv.
ACTION	Contact BEA Customer Support.
5040:ERROR	Enter shutdown
DESCRIPTION	An internal error has been detected, an error was returned by gw_nw_getsncrm_idx.
ACTION	Contact BEA Customer Support.
5041:ERROR	Trans Event Error shutdown
DESCRIPTION	An internal error has been detected, an error was returned by gw_nw_TransetUpExtTmsEvent.
ACTION	Contact BEA Customer Support.

5042:WARNING	SIGNON identify failed, shutdown gateway!
DESCRIPTION	SNACRM returned an error to the SIGNON request by GWSNAX.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
5043:ERROR	Trans Event Error
DESCRIPTION	An internal error has been detected. An error was returned by gw_nw_AssociateTranBy.
ACTION	Contact BEA Customer Support.
5044:ERROR	SIGNON state error, shutdown gateway!
DESCRIPTION	An internal error has been detected, an error was returned by _gw_nw_snacrm_nextop.
ACTION	Contact BEA Customer Support.
5045:ERROR	STARTUP state error, shutdown gateway!
DESCRIPTION	An internal error has been detected, an error was returned by _gw_nw_snacrm_nextop.
ACTION	Contact BEA Customer Support.
5046:WARNING	LINK_STATUS decode error, shutdown gateway!
DESCRIPTION	An internal error has been detected. An error was returned by snacrm_linkstatus_rcv.
ACTION	Contact BEA Customer Support.
5047:WARNING	LINK_STATUS status error, shutdown gateway!
DESCRIPTION	An internal error has been detected by gw_nw_crmrcv.
ACTION	Contact BEA Customer Support.

5048:WARNING	LINK_CONFIG state error, shutdown gateway!
DESCRIPTION	An internal error has been detected, an error was returned by _gw_nw_snacrm_nextop.
ACTION	Contact BEA Customer Support.
5049:WARNING	STACK_CONFIG state error, shutdown gateway!
DESCRIPTION	An internal error has been detected, an error was returned by _gw_nw_snacrm_nextop.
ACTION	Contact BEA Customer Support.
5050:WARNING	SHUTDOWN message received, shutdown gateway!
DESCRIPTION	GWSNAX has received a SHUTDOWN request from the SNACRM and will shut down immediately.
ACTION	Examine the ULOG for more information concerning the reason for the shutdown.
5051:ERROR	LOG_DATA decode error, shutdown gateway!
DESCRIPTION	An internal error has been detected. An error was returned by snacrm_log_data_rcv.
ACTION	Contact BEA Customer Support.
5052:ERROR	LOG_DATA state error(%d), shutdown gateway!
DESCRIPTION	An internal error has been detected by gw_nw_crmrcv.
ACTION	Contact BEA Customer Support.
5053:ERROR	Protocol violation, shutdown gateway!
DESCRIPTION	An internal error has been detected by gw_nw_crmrcv. Inbound ACALL request contained SEND_INVITE for function DPL.
ACTION	Contact BEA Customer Support.

5054:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected by gw_nw_InBoundConnectRqst.
ACTION	Contact BEA Customer Support.
5055:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected by gw_nw_OutBoundConnectRsp.
ACTION	Contact BEA Customer Support.
5056:ERROR	Protocol violation, shutdown gateway!
DESCRIPTION	An internal error has been detected by gw_nw_crmrcv.
ACTION	Contact BEA Customer Support.
5057:ERROR	SEND_DATA decode error, shutdown gateway!
DESCRIPTION	An internal error has been detected by gw_nw_crmrcv.
ACTION	Contact BEA Customer Support.
5058:ERROR	Cannot create action to send remote disconnect
DESCRIPTION	An internal error has been detected, an error was returned by gw_new_action.
ACTION	Contact BEA Customer Support.
5059:ERROR	ACALL decode error, shutdown gateway!
DESCRIPTION	An internal error has been detected by gw_nw_crmrcv.
ACTION	Contact BEA Customer Support.

5060:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected by gw_nw_InBoundAcallRqst.
ACTION	Contact BEA Customer Support.
5061:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected by gw_nw_OutBoundAcallRsp.
ACTION	Contact BEA Customer Support.
5062:ERROR	Failed to find local service(%s) definition!
DESCRIPTION	Unable to find the local service definition for the inbound request.
ACTION	Examine the DMCONFIG local service definitions. Correct any errors found. If no error is found, contact BEA Customer Support.
5063:ERROR	Invalid link index
DESCRIPTION	An internal error has been detected, an error was returned by _gw_nw_set_link_idx.
ACTION	Contact BEA Customer Support.
5064:ERROR	Invalid query_rsp index
DESCRIPTION	An internal error has been detected by gw_nw_QueryProcess.
ACTION	Contact BEA Customer Support.
5065:ERROR	Enter shutdown
DESCRIPTION	A failure has been detected while sending the SNACRM_QSVC_RSP verb to the SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure. Determine if the SNACRM process is still active.

5066:ERROR	Encode SEND_DATA failed, RRCORR(%ld)!
DESCRIPTION	An internal error has been detected by gw_nw_reply.
ACTION	Contact BEA Customer Support.
5067:ERROR	Decode inbound ACALL request failed!
DESCRIPTION	An error has occurred while decoding an inbound ACALL request in gw_nw_decode.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
5068:ERROR	Could not get FUNC
DESCRIPTION	An internal error has been detected by gw_nw_acall.
ACTION	Contact BEA Customer Support.
5069:ERROR	Could not get FUNC
DESCRIPTION	An internal error has been detected by gw_nw_connect.
ACTION	Contact BEA Customer Support.
5070:ERROR	SECURITY: Failed in security checking for RRCORR(%lx)!
DESCRIPTION	Security checking failed for the inbound ACALL request. An error was returned by gw_nw_SetSecurity.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
5071:ERROR	BAD Transaction ID shutdown
DESCRIPTION	An internal error has been detected by gw_nw_SendData.
ACTION	Contact BEA Customer Support.

D

5072:ERROR	BAD Transaction ID shutdown
DESCRIPTION	An internal error has been detected by gw_nw_OutBoundAcallRsp.
ACTION	Contact BEA Customer Support.
5073:ERROR	Could not get API
DESCRIPTION	An internal error has been detected by gw_nw_QueryProcess.
ACTION	Contact BEA Customer Support.
5074:ERROR	Decode outbound ACALL response failed, RRCORR(%lx)!
DESCRIPTION	An error has occurred while decoding the response from the host application to an outbound ACALL.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
5075:ERROR	Invalid query_rsp index
DESCRIPTION	An internal error has been detected by gw_nw_QueryProcessError.
ACTION	Contact BEA Customer Support.
5076:ERROR	Invalid connect_resp index
DESCRIPTION	An internal error has been detected by gw_nw_ConnectError.
ACTION	Contact BEA Customer Support.
5077:ERROR	Enter shutdown
DESCRIPTION	A failure has been detected while sending the SNACRM_QSVC_RSP verb to the SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure. Determine if the SNACRM process is still active.

5078:ERROR	Enter shutdown
DESCRIPTION	A failure has been detected while sending the SNACRM_CONNECT_RSP verb to the SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure. Determine if the SNACRM process is still active.
5079:ERROR	BAD Transaction ID shutdown
DESCRIPTION	An internal error has been detected by gw_nw_InBoundAcallRqst.
ACTION	Contact BEA Customer Support.
5080:ERROR	Decode inbound connect request failed, RRCORR(%lx)!
DESCRIPTION	An error has occurred while decoding an inbound connect request in gw_nw_InBoundConnectRqst.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
5081:ERROR	SECURITY: Inbound connect request security check failed, RRCORR(%lx)!
DESCRIPTION	Security checking failed for the inbound CONNECT request. An error was returned by gw_nw_SetSecurity.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
5082:ERROR	Decode SEND_DATA failed, RRCORR(%lx)!
DESCRIPTION	An error has occurred while decoding an outbound send data request in gw_nw_SendData.
ACTION	Examine the ULOG for more information concerning the reason for the failure.

5083:ERROR	Invalid buffer type, encode failed!
DESCRIPTION	The buffer type specified for the outbound message was invalid. GWSNAX only supports standard TUXEDO buffer types over the domain gateway.
ACTION	Correct the DMCONFIG definition.
5084:ERROR	Outbound ACALL encode failed!
DESCRIPTION	An error has occurred while encoding an outbound ACALL request in gw_nw_encode.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
5085:ERROR	BAD SNACRM_IDX shutdown
DESCRIPTION	An internal error has been detected by gw_nw_InBoundAcallRqst.
ACTION	Contact BEA Customer Support.
5086:ERROR	BAD Context shutdown
DESCRIPTION	An internal error has been detected by gw_nw_InBoundAcallRqst.
ACTION	Contact BEA Customer Support.
5087:ERROR	Invalid buffer type, decode failed!
DESCRIPTION	The buffer type specified for the inbound message was invalid. GWSNAX only supports standard TUXEDO buffer types over the domain gateway.
ACTION	Correct the DMCONFIG definition.
5088:ERROR	Unable to get RDOM
DESCRIPTION	An internal error has been detected by gw_nw_init_env.
ACTION	Contact BEA Customer Support.

5089:ERROR	BAD SNACRM_IDX shutdown
DESCRIPTION	An internal error has been detected by gw_nw_InBoundConnectRqst.
ACTION	Contact BEA Customer Support.
5090:ERROR	Outbound CONNECT encode failed!
DESCRIPTION	An error has occurred while encoding an outbound CONNECT request in gw_nw_encode.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
5091:ERROR	Outbound CONVSEND encode failed!
DESCRIPTION	An error has occurred while encoding an outbound CONVSEND request in gw_nw_encode.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
5093:ERROR	Bad Connect
DESCRIPTION	An internal error has been detected by gw_nw_crmrcv.
ACTION	Contact BEA Customer Support.
5094:ERROR	Unable to send data on sna_conv_idx %d, gpnd = %d
DESCRIPTION	An error has occurred while sending a connect response to the SNACRM.
ACTION	Examine the ULOG for more information concerning the reason for the failure.
5095:ERROR	BAD Transaction ID shutdown
DESCRIPTION	An internal error has been detected by gw_nw_InBoundConnectRqst.
ACTION	Contact BEA Customer Support.

D

5096:ERROR	Unable to obtain socket id
DESCRIPTION	An internal error has been detected by gw_nw_link_gp.
ACTION	Contact BEA Customer Support.
5097:ERROR	Unable to get RDOM
DESCRIPTION	An internal error has been detected by gw_nw_link_gp.
ACTION	Contact BEA Customer Support.
5098:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected by gw_nw_link_gp.
ACTION	Contact BEA Customer Support.
5099:ERROR	Allocate context failed!
DESCRIPTION	An internal error has been detected, an error was returned by gw_nw_AllocNwCtx.
ACTION	Contact BEA Customer Support.
5100:ERROR	Unable to obtain socket id
DESCRIPTION	An internal error has been detected by gw_nw_init_env.
ACTION	Contact BEA Customer Support.
5101:ERROR	Unable to find view file for %s %s
DESCRIPTION	Failed to find the view file for the FML buffer type specified in the INBUFTYPE for an inbound request.
ACTION	Examine the environment variables VIEWDIR, VIEWFILES, VIEW32DIR, and VIEW32FILES to determine if the requested view is present.

5102:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected by gw_nw_reply.
ACTION	Contact BEA Customer Support.
5103:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected by gw_nw_reply.
ACTION	Contact BEA Customer Support.
5104:ERROR	Invalid action index
DESCRIPTION	An internal error has been detected by gw_nw_QueryProcess.
ACTION	Contact BEA Customer Support.
5105:ERROR	Invalid buffer pointer
DESCRIPTION	An internal error has been detected by gw_nw_encode.
ACTION	Contact BEA Customer Support.
5106:ERROR	Allocate send buffer failed!
DESCRIPTION	An internal error has been detected, an error was returned by gw_nw_empty_sndbuf.
ACTION	Contact BEA Customer Support.
5107:ERROR	Unable to get appkey for this outbound request
DESCRIPTION	An internal error has been detected, gw_shm_getbylink returned an error while getting the remote domain entry.
ACTION	Examine the DMCONFIG remote domain definitions and its security setting. Correct any errors found. If no error is found, contact BEA Customer Support.

D

5108:ERROR	Enter shutdown
DESCRIPTION	An internal error has been detected by gw_nw_SendEvent.
ACTION	Contact BEA Customer Support.
5109:ERROR	Unable to find view file for %s %s
DESCRIPTION	Failed to find the view file for encoding outbound FML data as specified in the OUTBUFTYPE.
ACTION	Examine the environment variables VIEWDIR, VIEWFILES, VIEW32DIR, and VIEW32FILES to determine if the requested view is present.
5110:ERROR	Unable to find view file for %s %s
DESCRIPTION	Failed to find the view file for encoding outbound FML32 data as specified in the OUTBUFTYPE.
ACTION	Examine the environment variables VIEWDIR, VIEWFILES, VIEW32DIR, and VIEW32FILES to determine if the requested view is present.
5111:ERROR	BAD Context shutdown caused at transaction associate
DESCRIPTION	An internal error has been detected, an error was returned by gw_nw_AssociateTranByTCTXT.
ACTION	Contact BEA Customer Support.
5112:ERROR	System full, can't create action, Enter shutdown
DESCRIPTION	Failed to create GWSNAX gateway internal scheduled event to handle failure ore disconnect.
ACTION	Either memory allocation failed or a system limit was reached. Contact BEA Customer Support.
5113:ERROR	Realloc buffer of size(%d) failed!
DESCRIPTION	An internal error has been detected, gw_nw_Realloc was unable to allocate memory needed.
ACTION	Contact BEA Customer Support.

5114:ERROR	Invalid network descriptor(%d)!	
	DESCRIPTION	An internal error has been detected by gw_nw_acall.
	ACTION	Contact BEA Customer Support.
6000:ERROR	YOUR CONNECT SNA LICENSE IS EITHER INVALID OR EXPIRED	
	DESCRIPTION	The eLink for Mainframe SNA v3.1 license is missing from the lic.txt file in \$TUXDIR/udataobj or it has expired.
	ACTION	Look in the \$TUXDIR/udataobj/lic.txt file for a section labeled CONNECT_SNA 3.1 and if present, check the expiration date.
6001:WARNING	YOUR CONNECT SNA LICENSE IS NOT ENABLED FOR SYNCLEVEL 2, FORCED TO SYNCLEVEL 1	
	DESCRIPTION	The eLink for Mainframe SNA v3.1 license does not include the license to run requests at synclevel 2 (transactional).
	ACTION	MAXSYNCLVL has been specified as 2 in the DMCONFIG DM_SNALINKS section. This level requires an additional license. Look in the \$TUXDIR/udataobj/lic.txt file for a section labeled CONNECT_SNA_TX 3.1 and if present, check the expiration date.

9001:ERROR	<taskname> timed out with failCode <failcode>
DESCRIPTION	<p>A conversation has timed out in the SNACRM with the stack return code of <failcode>. A timer event set to watch a conversation has expired.</p> <p><taskname> may appear as:</p> <p>OB-Conversation #<i>nn</i> (<linkref>) tx #<i>m</i> <tranname>, or</p> <p>IB-Conversation #<i>nn</i> (<linkref>) tx #<i>m</i> <tranname></p> <p>where:</p> <p><i>nn</i> is an internal APPC conversation number.</p> <p><i>m</i> is the transaction context where -1 signifies non-transactional.</p>
ACTION	<p>Examine stderr and the ULOG for additional information concerning the failure.</p>
9002:ERROR	Server (<stackref>) Creation Failed
DESCRIPTION	<p>SNACRM was unable to instantiate the stack object due to an error.</p>
ACTION	<p>Check for additional messages in stderr. Could be that the shared library for the stack or the stack interface could not be loaded due to an incorrect library path.</p>
9003:ERROR	Server Failed (<stackref>), Code = <returncode>
DESCRIPTION	<p>SNACRM received a bad return code from the stack start-up.</p>
ACTION	<p>The <returncode> is the value returned by the SNA Stack software. Check the status of the stack and the configuration of the stack and the DMCONFIG.</p> <p>Note: Unless you started the SNACRM as a TUXEDO server, you must manually kill the SNACRM process.</p>

9004:ERROR	Configuration change on link <linkref> requires cold start
	DESCRIPTION Attempting to do a warm start after changing the domain configuration.
	ACTION Change start type to "COLD" and restart.
9005:WARNING	Unrecovered transaction, ID=<tctxt>, blob dropped. Transaction presumed forgotten.
	DESCRIPTION An attempt was made by TUXEDO to recover the specified transaction which was unknown by the SNACRM. It is presumed that it was already committed or aborted prior to the recovery attempt.
	ACTION None. This message for information only.
9006:ERROR	Unable to start the recovery task for link <linkref>
	DESCRIPTION An error occurred during the warm start of TUXEDO.
	ACTION Cold start the TUXEDO application.
9008:WARNING	Unknown tranid dropped, id=<tctxt>
	DESCRIPTION Recovery was requested by TUXEDO on a transaction that was already forgotten by the SNACRM.
	ACTION None. This message for information only.
9009:ERROR	No blob with recovery request. Transaction dropped, id=<tctxt>
	DESCRIPTION Attempting to warm start after the SNACRM's BLOBLOG has been modified.
	ACTION Change start type to "COLD" and restart.

9010:ERROR <taskname> failed with failCode <failcode>	
DESCRIPTION	<p>A conversation has failed with the stack return code of <failcode>.</p> <p><taskname> may appear as:</p> <p>OB-Conversation #<i>nn</i> (<linkref>) tx #<i>m</i> <tranname>, or</p> <p>IB-Conversation #<i>nn</i> (<linkref>) tx #<i>m</i> <tranname></p> <p>where:</p> <p><i>nn</i> is an internal APPC conversation number.</p> <p><i>m</i> is the transaction context where -1 signifies non-transactional.</p> <p>Possible values for the <failcode> are:</p> <ol style="list-style-type: none">1. Communications - unable to create the APPCserver object.2. MemoryAllocation - internal error allocating memory.3. InvalidObject - a SNACRM object could not be created or has been made invalid by some previous error.4. InputOutput - error occurred during file I/O or an unexpected APPC return code was received.5. Registration - internal task cannot be registered.
ACTION	<p>Examine stderr and the ULOG for additional information concerning the failure. For failcode InputOutput, verify that the user starting the SNACRM process has the proper file permissions for the BLOBLOG and RSTRTLOG. If no apparent error is found, contact BEA Customer Support.</p>

9011:ERROR	Attempt to connect as second master refused!	
	DESCRIPTION	A second GWSNAX is attempting to connect to the SNACRM as a master gateway. Only one master gateway is allowed.
	ACTION	Ensure that multiple TUXEDO configurations do not use the same SNACRM address.
9012:ERROR	Attempt to connect as master in autonomous mode refused!	
	DESCRIPTION	An attempt to connect to the SNACRM as a master gateway was made when the SNACRM was running in autonomous mode.
	ACTION	Ensure that multiple TUXEDO configurations do not use the same SNACRM address.
9013:ERROR	Attempt to connect with incorrect group name (<groupname>) refused!	
	DESCRIPTION	The group name in the DMCONFIG file does not match the group name specified in the SNACRM command line.
	ACTION	Correct the group name that is in error and restart.
9014:ERROR	INTERNAL ERROR: memory allocation failed [for new context data buffer]	
	DESCRIPTION	Internal error allocating memory.
	ACTION	Contact BEA Customer Support.
9015:ERROR	INTERNAL ERROR: server registration failed	
	DESCRIPTION	Internal error registering the APPC server.
	ACTION	Contact BEA Customer Support.
9016:ERROR	Link refers to undefined APPC stack (<stackref>)! 	
	DESCRIPTION	The stackref in the link configuration is incorrect.
	ACTION	Correct the stackref that is in error, run dmloadcf, and restart.

9017:ERROR	INTERNAL ERROR: link registration failed
DESCRIPTION	Internal error registering the link.
ACTION	Contact BEA Customer Support.
9018:ERROR	Invalid Transition <additional information>
DESCRIPTION	An internal state table failure has occurred. The <additional information> will be one of the following: <ol style="list-style-type: none">1. From <oldstate> to <newstate> for <dir>-bound transaction #<tid>2. To <newstate> for in-bound transaction #<tid>3. To <newstate> for out-bound transaction #<tid>
ACTION	Contact BEA Customer Support.
9019:ERROR	Unknown Service Correlator = <correlator>, message dropped
DESCRIPTION	Internal error assigning service correlator values.
ACTION	Contact BEA Customer Support.
9020:ERROR	Duplicate Service Correlator = <correlator>
DESCRIPTION	Internal error assigning service correlator values.
ACTION	Contact BEA Customer Support.
9021:ERROR	Invalid Remote Link Name <linkref>
DESCRIPTION	The remote link name in a request does not match any defined link name.
ACTION	Correct the DMCONFIG and restart.
9022:ERROR	Invalid transaction context = <tctx>
DESCRIPTION	Internal error assigning transaction context values.
ACTION	Contact BEA Customer Support.

9023:ERROR	Unknown Service Correlator = <correlator>, message dropped
	DESCRIPTION Internal error assigning service correlator values.
	ACTION Contact BEA Customer Support.
9024:ERROR	Invalid initial syncpoint received from subordinate, tx#<tid>
	DESCRIPTION Syncpoint processing protocol violation. Subordinate member of conversation attempted to initiate a syncpoint.
	ACTION Contact BEA Customer Support.
9025:ERROR	Invalid Input Message Discarded
	DESCRIPTION Internal error, bad message sent between GWSNAX and SNACRM.
	ACTION Contact BEA Customer Support.
9026:ERROR	CNOS Notification Received for unknown partner <partnerLU>
	DESCRIPTION Multiple instances of the SNACRM may be using the same local LU.
	ACTION Ensure that multiple TUXEDO configurations do not use the same local LU.
9027:WARNING	Remote Stop Received for <linkref>
	DESCRIPTION The remote host has issued a stop for the specified link.
	ACTION None. This message for information only.
9028:WARNING	Remote Start Received for <linkref>
	DESCRIPTION The remote host has issued a start for the specified link.
	ACTION None. This message for information only.

9029:ERROR	Undefined Remote LU on link <linkref>
DESCRIPTION	The remote LU does not exist as defined.
ACTION	Check the DMCONFIG file and the stack configuration and correct the mis-match.
9030:ERROR	Unable to start session on link <linkref>. Reason=<reason>
DESCRIPTION	Link activation failure due to SNA error.
ACTION	<reason> is the description of the stack return code. Determine the cause and correct.
9031:ERROR	Unable to initialize link <linkref>. Reason=<reason>
DESCRIPTION	Link initialization failure due to SNA error.
ACTION	<reason> is the description of the stack return code. Determine the cause and correct.
9032:ERROR	No Available Session on link <linkref> for context <correlator>
DESCRIPTION	Max sessions has been exceeded.
ACTION	Check session limits in DMCONFIG, stack configuration, CICS or VTAM. Increase if necessary.
9033:ERROR	Requested Synclevel not supported by link <linkref> for context <correlator> (synclevel <level>)
DESCRIPTION	Attempted to issues a request at sync level <level> on a link that does not support that level.
ACTION	Correct application or DMCONFIG.
9034:ERROR	Service Request at SyncLevel=2 Rejected on PENDING link <linkref> for context <correlator>
DESCRIPTION	An attempt to start a new sync level 2 request has been received and the Link is currently processing recovery information.
ACTION	Wait until recovery is complete to request sync level 2 services.

9035:ERROR	Inbound Request Transform Failed (<status>) for context <correlator>	
	DESCRIPTION	An error has occurred while processing the CICS transform for an inbound DPL request. This normally occurs when the API entry in the DMCONFIG for the local service specifies CICS instead of ATMI.
	ACTION	Check DMCONFIG for incorrect specification of local service API entry.
9036:ERROR	Inbound Response Transform Failed (<status>) for context <correlator>	
	DESCRIPTION	An error has occurred while processing the CICS transform for an inbound DPL response. This normally occurs when the API entry in the DMCONFIG for the local service specifies CICS instead of ATMI.
	ACTION	Check DMCONFIG for incorrect specification of local service API entry.
9037:ERROR	Outbound Request Transform Failed (<status>) for context <correlator>	
	DESCRIPTION	An error has occurred while processing the CICS transform for an outbound DPL request. This normally occurs when the API entry in the DMCONFIG for the remote service specifies CICS instead of ATMI.
	ACTION	Check DMCONFIG for incorrect specification of local service API entry.

9038:ERROR	Outbound Response Transform Failed (<status>) for context <correlator>
DESCRIPTION	An error has occurred while processing the CICS transform for an outbound DPL response. This normally occurs when the API entry in the DMCONFIG for the remote service specifies CICS instead of ATMI.
ACTION	Check DMCONFIG for incorrect specification of local service API entry.
9039:ERROR	Conversation terminated without confirm for context <correlator>
DESCRIPTION	Sync level 2 conversation was terminated with out confirm.
ACTION	Check application program and correct.
9040:ERROR	Inbound Confirm not supported
DESCRIPTION	Host application is requesting an inbound confirm. This is not supported.
ACTION	Check host application program and correct.
9041:ERROR	Inbound Confirm for multi-ISRT not supported
DESCRIPTION	Host IMS application is requesting an inbound confirm and using multiple ISRT commands. This is not supported.
ACTION	Check host application program and correct.
9043:ERROR	Missing send last from host (ATMI request/response) for context <correlator>
DESCRIPTION	Host application did not issue send last during an out-bound request/response service. The host application may have abended.
ACTION	Check application program and correct.

9044:INFO	DPL program abended with CICS code <abendcode>, program=<progname>
DESCRIPTION	The specified host DPL program has abended with the code specified.
ACTION	None. This message is for information only.
9045:INFO	DPL program failed with CICS rcode <eibrcode>, program=<progname>
DESCRIPTION	The specified host DPL program has failed with the eibrcode specified.
ACTION	None. This message is for information only.
9046:ERROR	Invalid combination for Service Context <correlator>, <combination>
DESCRIPTION	The specified <combination> is invalid. It will be one of the following: <ul style="list-style-type: none"> 1. Sync-Level, function, and API 2. Function and API
ACTION	Examine the DMCONFIG and make corrections.
9047:ERROR	Sequence number error for Service Context <correlator>, seqno <seqno>
DESCRIPTION	There has been a sequence number failure for the specified context.
ACTION	Contact BEA Customer Support.
9048:ERROR	Invalid conversation task for Service Context <correlator>, task=<task>
DESCRIPTION	The conversation has already been terminated.
ACTION	Contact BEA Customer Support.

D

9049:ERROR	Invalid task switch for Service Context <correlator>, from <task1> to <task2>
DESCRIPTION	An internal protocol violation has occurred.
ACTION	Contact BEA Customer Support.
9050:ERROR	Transformer creation failed for in-bound transaction <trancode>
DESCRIPTION	An internal error has occurred.
ACTION	Contact BEA Customer Support.
9051:ERROR	Transformer failed for in-bound transaction <trancode>
DESCRIPTION	An internal error has occurred. Resource name is not present.
ACTION	Contact BEA Customer Support.
9052:WARNING	Inter-task Message dropped (<verbname>), parm=<parm> From: <task1> to <task2>
DESCRIPTION	An internal message between two tasks has been dropped.
ACTION	None. This message is for information only.
9053:ERROR	Attempt to send <nnnnn> bytes (> 32767)
DESCRIPTION	The length of a send request exceeded 32767 (including overhead).
ACTION	Check application program and correct.
9054:ERROR	Allocation Failure for <trancode> on <remotesysid>: <error>
DESCRIPTION	An Allocation error occurred.
ACTION	The reason for the failure is described by <error>. Correct problem with configuration or application.

9055:ERROR	Invalid Exchange Logs GDS variable received from <remotesysid>	
	DESCRIPTION	The log files for the SNACRM have been incorrectly modified.
	ACTION	Run CRMLOGS to examine the SNACRM log file. Cold start the TUXEDO application.
9056:ERROR	Invalid cold start received from <remotesysid>. Unrecovered local transactions are pending.	
	DESCRIPTION	Attempting to cold start host while warm starting TUXEDO.
	ACTION	Run CRMLOGS to examine the SNACRM log file. Cold start the TUXEDO application.
9057:ERROR	Invalid warm start received from <remotesysid>. Unknown log name.	
	DESCRIPTION	The log files for the SNACRM have been incorrectly modified.
	ACTION	Run CRMLOGS to examine the SNACRM log file. Cold start the TUXEDO application.
9058:ERROR	Invalid Compare States GDS variable received from <remotesysid>	
	DESCRIPTION	The log files for the SNACRM have been incorrectly modified.
	ACTION	Run CRMLOGS to examine the SNACRM log file. Cold start the TUXEDO application.
9059:ERROR	Mixed Heuristic on link <linkref> for <unitofwork> Correlator [<correlator>]	
	DESCRIPTION	One side has reported committed while the other side has reported aborted.
	ACTION	Check the ULOG for any additional messages.

9060:WARNING	Inbound Exchange Logs Rejected for <remotesysid>
DESCRIPTION	Link not configured for sync level 2.
ACTION	None. This message is for information only.
9061:WARNING	Link <linkref> not configured for synclevel 2
DESCRIPTION	Link specified by <linkref> is not configured for sync level 2.
ACTION	None. This message is for information only.
9062:ERROR	Exchange Logs Rejected for <remotesysid>, Restart Type or Log Name Mismatch
DESCRIPTION	The log files for the SNACRM have been incorrectly modified.
ACTION	Run CRMLOGS to examine the SNACRM log file. Cold start the TUXEDO application.
9063:ERROR	Exchange Logs failed with <linkref>
DESCRIPTION	An error occurred during the exchange logs process.
ACTION	Run CRMLOGS to examine the SNACRM log file. Cold start the TUXEDO application.

E Sample VTAM Configurations

Introduction

This appendix provides sample environments showing how BEA eLink for Mainframe SNA software can be configured for use with an Ethernet LAN and an APPN system 390. Considerations for token ring and subarea-style configurations are included. It is assumed that hardware and operating system installation have been completed.

An environment properly configured for the BEA eLink for Mainframe SNA system involves two general components, a local environment and a remote environment.

Local Environment

A local environment is a UNIX-based machine running BEA eLink for Mainframe SNA software. BEA eLink for Mainframe SNA is a fully bi-directional program, supporting the local system as either a client or server. This environment consists of the following components:

- ◆ Hardware
 - ◆ Any workstation and network interface supported by the required software.
- ◆ Platform operating systems with protocol stacks (PU servers)
 - ◆ AIX 4.3.2 with IBM Comm Server 5.0
 - ◆ HP-UX 10.20 with HP SNAplus2 6.1

- ◆ HP-UX 11.00 with HP SNAPPlus2 6.11
 - ◆ Solaris 2.6 with Brixton 4.1 *
 - ◆ Solaris 2.6 with DCL SNAP-IX 6.0
 - ◆ Solaris 2.6 with SUN Link 9.1*
 - ◆ Solaris 7 with Brixton 4.1*
 - ◆ Solaris 7 with SUN Link 9.1*
 - ◆ Windows NT with IBM CommServer 5.0 or 6.0
 - ◆ TUXEDO 6.5 or WebLogic Enterprise 4.0
- * Sync-level 2 not supported.

Remote Environment

A remote environment is an IBM mainframe that may or may not be on the same local network. As in the local environment, BEA eLink for Mainframe SNA is a fully bi-directional program, supporting the remote system as either a client or server. This environment consists of the following components:

- ◆ Hardware
 - ◆ Any workstation and network interface supported by the required software.
- ◆ Software
 - ◆ CICS 3.3 or higher
 - ◆ IMS/ESA DC 5.1 (optional)
 - ◆ MVS 5.22 9510 or higher, including OS/390 through 1.3
 - ◆ VSE/ESA 2.3
 - ◆ VTAM 4.3 or higher
 - ◆ Support software for a P390 or R390 (optional)

Sample Environments

Samples of each environment are provided to illustrate a starting point when first configuring your system. These samples are not intended to be used without modifications. Any similarity between them and any actual system is coincidental.

Machine Attributes (LAN Descriptions)

The attributes of the sample environment machines are listed below for reference. The sample configurations refer to these attributes as required.

10BaseT carrying SNA/DLC (IEEE 802.3) and TCP/IP (DIX) traffic.

Table E-1 SPARCstation 5

Name	Attribute
OS	Solaris 2.5.1 or 2.6
SNA	Brixton/CNT 4.1
APP	Tuxedo 6.4
MAC	08:00:20:7C:47:50
IP	206.189.43.14
NAME	beasun2

Table E-2 SPARCstation 5

Name	Attribute
OS	Solaris 2.5.1 or 2.6 (SunOS 5.5.1)
SNA	SunLink 9.1
APP	Tuxedo 6.4
MAC	08:00:20:87:47:2d
IP	206.189.43.54
NAME	dalsun4

Table E-3 HP 9000/847

Name	Attribute
OS	HP-UX B.10.20 or 11.00 (patches:PHNE_9663,9761,9889)
SNA	HPSNAPlus2 5.1 or 6.0
APP	Tuxedo 6.4
MAC	08:00:09:30:24:77
IP	206.189.43.13
NAME	dalhp10

Table E-4 P390 Server 500

Name	Attribute
OS	MVS 5.22 9510
SNA	VTAM 4.3
APP	CICS 4.1 / IMS DC 5.1
MAC	10:00:5a:d4:3e:8e
IP	206.189.43.98
NAME	beavs

Table E-5 P390 Server 500

Name	Attribute
OS	OS/390 1.2
SNA	VTAM 4.3
APP	CICS 4.1
MAC	10:00:5a:d4:c1:e0
IP	206.189.43.96
NAME	dalvs2

Local Environment Configuration

(For future reference.) HPSNAPPlus2 configurations are usually setup using the HP xSnapAdmin utility, resulting in the configuration text file `/etc/opt/sna/sna_node.cfg`. This file can be manually created and/or maintained using a text editor, however, using the HP xSnapAdmin utility is recommended. The example below is the `sna_node.cfg` file for the sample environment.

HPSNAPPlus2 Configuration

```
[define_node_config_file]
major_version = 5
minor_version = 1
update_release = 1
revision_level = 116

[define_node]
node_name = dalhp10
description = snacrm development
node_type = END_NODE
fqcp_name = BEALAN.DALHP10
cp_alias = dalhp10
mode_to_cos_map_supp = NO
mds_supported = YES
node_id = <05ffffff>
max_locates = 100
dir_cache_size = 255
max_dir_entries = 0
locate_timeout = 60
reg_with_nn = YES
reg_with_cds = YES
mds_send_alert_q_size = 100
cos_cache_size = 24
tree_cache_size = 40
tree_cache_use_limit = 40
max_tdm_nodes = 0
max_tdm_tgs = 0
max_isr_sessions = 1000
isr_sessions_upper_threshold = 900
isr_sessions_lower_threshold = 800
isr_max_ru_size = 16384
isr_rcv_pac_window = 8
store_endpt_rscvs = NO
store_isr_rscvs = NO
store_dlur_rscvs = NO
dlur_support = YES
pu_conc_support = NO
nn_rar = 128
ptf_flags = NONE

[define_ethernet_dlc]
dlc_name = ETHER0
description = ""
neg_ls_supp = YES
initially_active = NO
adapter_number = 0
```

```
[define_ethernet_port]
port_name = ethl0
description = 1st ethernet adapter
dlc_name = ETHER0
port_type = PORT_SATF
port_number = 1
max_rcv_btu_size = 1033
tot_link_act_lim = 64
inb_link_act_lim = 0
out_link_act_lim = 0
ls_role = LS_NEG
act_xid_exchange_limit = 9
nonact_xid_exchange_limit = 5
ls_xmit_rcv_cap = LS_TWS
max_ifrm_rcvd = 7
target_pacing_count = 7
max_send_btu_size = 1033
mac_address = <000000000000>
lsap_address = 0x08
implicit_cp_cp_sess_support = NO
implicit_limited_resource = NO
implicit_deact_timer = 0
effect_cap = 3993600
connect_cost = 0
byte_cost = 0
security = SEC_NONSECURE
prop_delay = PROP_DELAY_LAN
user_def_parm_1 = 0
user_def_parm_2 = 0
user_def_parm_3 = 0
initially_active = YES
test_timeout = 5
test_retry_limit = 2
xid_timeout = 5
xid_retry_limit = 2
tl_timeout = 5
tl_retry_limit = 5

[define_ethernet_ls]
ls_name = P390HP10
description = P390 - beavs
port_name = ethl0
adj_cp_name = P390.USS3270
adj_cp_type = LEARN_NODE
mac_address = <0020af543176>
lsap_address = 0x08
auto_act_supp = NO
tg_number = 0
```

```
limited_resource = NO
solicit_sscp_sessions = NO
pu_name = <0000000000000000>
disable_remote_act = NO
default_nn_server = NO
dspu_services = NONE
dspu_name = <0000000000000000>
dlus_name = <00000000000000000000000000000000>
bkup_dlus_name = <00000000000000000000000000000000>
link_deact_timer = 0
use_default_tg_chars = YES
ls_attributes = SNA
adj_node_id = <00000000>
local_node_id = <00000000>
cp_cp_sess_support = YES
effect_cap = 3993600
connect_cost = 0
byte_cost = 0
security = SEC_NONSECURE
prop_delay = PROP_DELAY_LAN
user_def_parm_1 = 0
user_def_parm_2 = 0
user_def_parm_3 = 0
target_pacing_count = 7
max_send_btu_size = 1033
ls_role = USE_PORT_DEFAULTS
initially_active = NO
react_timer = 30
react_timer_retry = 65535
test_timeout = 5
test_retry_limit = 2
xid_timeout = 5
xid_retry_limit = 2
t1_timeout = 5
t1_retry_limit = 5

[define_local_lu]
lu_name = LUHP10A
description = Test LU #1
lu_alias = LUHP10A
nau_address = 0
syncpt_support = YES
lu_session_limit = 0
default_pool = NO
pu_name = <0000000000000000>
sys_name = ""
timeout = -1
back_level = NO
```

```
[define_local_lu]
lu_name = LUHP10B
description = Test LU #2
lu_alias = LUHP10B
nau_address = 0
syncpt_support = YES
lu_session_limit = 0
default_pool = NO
pu_name = <0000000000000000>
sys_name = ""
timeout = -1
back_level = NO
```

```
[define_local_lu]
lu_name = LUHP10C
description = Test LU #3
lu_alias = LUHP10C
nau_address = 0
syncpt_support = YES
lu_session_limit = 0
default_pool = NO
pu_name = <0000000000000000>
sys_name = ""
timeout = -1
back_level = NO
```

```
[define_partner_lu]
description = APPC MVS LU for IMS
fqplu_name = P390.MVSLU01
plu_alias = MVSLU01
plu_un_name = MVSLU01
max_mc_ll_send_size = 32767
conv_security_ver = NO
parallel_sess_supp = YES
```

```
[define_partner_lu]
description = backend cics #1
fqplu_name = P390.C410XB01
plu_alias = C410XB01
plu_un_name = C410XB01
max_mc_ll_send_size = 32767
conv_security_ver = NO
parallel_sess_supp = YES
```

```
[define_partner_lu]
description = Second backend cics
fqplu_name = P390.C410XB02
plu_alias = CICS2
plu_un_name = C410XB02
```

```
max_mc_ll_send_size = 32767
conv_security_ver = NO
parallel_sess_supp = YES

[define_mode]
mode_name = SMSNA100
description = Sessions: 10 -- 5,5
max_ru_size_upp = 1024
receive_pacing_win = 4
default_ru_size = YES
max_neg_sess_lim = 256
plu_mode_session_limit = 10
min_conwin_src = 5
cos_name = #CONNECT
cryptography = NONE
auto_act = 0
```

Remote Environment Configurations

You must involve your mainframe system support personnel early in the process. In a large shop there will most likely be separate individuals responsible for MVS, VTAM, and CICS. Make sure everyone is involved. Hopefully most of the configuration for your mainframe has already been done.

These samples are provided for illustration. Mainframe technical support is not trivial, and this is not intended to train you in all of the possible configurations. These samples represent one way a P390 can be configured to work in an APPN LAN environment.

ATCSTRxx VTAM Start List

The example below is the VTAM start list for the BEAVS P390 machine. It supports both the subarea and APPN environments.

```
* -----*
* VTAM START LIST FOR SYS1 *
* -----*
BN=YES,
BNDYN=FULL,
XNETALS=YES,
SSCPID=06,NOPROMPT,
CONFIG=00,MAXSUBA=31,SUPP=NOSUP,
SSCPNAME=USS3270,
NETID=P390,
```

```

NODETYPE=NN,
HOSTSA=6,
CRPLBUF=(208,,15,,1,16),
IOBUF=(100,512,19,,1,20),
LFBUF=(104,,0,,1,1),
LPBUF=(64,,0,,1,1),
SFBUF=(163,,0,,1,1)

```

XCA Major Node Defines the LAN Adapter for SYS1

This definition is set up for use with a 3172 (emulated) for connecting an APPN network node to another APPN node. Note that it is for an Ethernet LAN and the SAPADDR specified must be the same as the LSap specified for the local link station.

```

*****
*   Emulated 3172 XCA MAJOR NODE FOR HOST beavs
*****
XETH2LP1 VBUILD TYPE=XCA ** EXTERNAL COMMUNICATION ADAPT**
PORTE2   PORT  ADAPNO=1,      ** 3172 RELATIVE ADAPTER NUMBER**
          CUADDR=E22,        ** CHANNEL UNIT ADDRESS          **
          MEDIUM=CSMACD,     ** LAN TYPE=ETHERNET            **
          SAPADDR=8,          ** SERVICE ACCESS POINT ADDRESS**
          TIMER=120           ** CHANNEL ACTIVATE RESP TIME   **
*
G1ETH2   GROUP DIAL=YES,      ** YES required for putype 2   **
          DYNPU=YES,
          CALL=INOUT,
          ANSWER=ON,
          ISTATUS=ACTIVE
LETH20   LINE
PETH20   PU
LETHE3   LINE
PETHE3   PU
LETHF3   LINE
PETHF3   PU

```

Switched Network (SWNET) Definitions

The three switched network definition examples in this section specify the VTAM PU, representing the local link stations that expect to connect with the host machine. The 10BLK and IDNUM definitions are provided to support 3270 traffic and must be unique, as well as match the values specified in the local link definition.

SWNET Major Node (DALHP10)

```

SWNETHHP      VBUILD  TYPE=SWNET,MAXNO=3,MAXGRP=3
P390HP10      PU      ADDR=02,
                  IDBLK=05F,
                  IDNUM=FFFFF,
                  PUTYPE=2,
                  NETID=BEALAN,
                  CPNAME=DALHP10,
                  MAXPATH=3,
                  DWACT=YES,
                  CONNTYPE=APPN,
                  CPCP=YES,
                  DYNLU=YES

* -----
* SNA SAP & HP10 MAC ADDRESS BIT REVERSED FOR TRFMT
* -----
PATHHP        PATH  DIALNO=00041000900C24EE,
                  GRPNM=G1ETH2
LUHP10A      LU      LOCADDR=0
LUHP10B      LU      LOCADDR=0
LUHP10C      LU      LOCADDR=0

```

SWNET Major Node (SUN2)

```

SWNETH2       VBUILD  TYPE=SWNET,MAXNO=3,MAXGRP=3
P390ETH2      PU      ADDR=04,
                  IDBLK=019,
                  IDNUM=10092,
                  PUTYPE=2,
                  NETID=BEALAN,
                  CPNAME=SUN2,
                  MAXPATH=3,
                  DWACT=YES,
                  CONNTYPE=APPN,
                  CPCP=YES,
                  DYNLU=YES

* -----
* SNA SAP & SUN2 MAC ADDRESS BIT REVERSED FOR TRFMT
* -----
PATH01        PATH  DIALNO=00081000043EE20A,
                  GRPNM=G1ETH2
LUSUN2A      LU      LOCADDR=0
LUSUN2B      LU      LOCADDR=0
LUSUN2C      LU      LOCADDR=0

```

SWNET Major Node ((SUN4)

```

SWNESUN4  VBUILD  TYPE=SWNET ,MAXNO=3 ,MAXGRP=3
P390ETH4  PU   ADDR=03 ,
           IDBLK=018 ,
           IDNUM=10092 ,
           PUTYPE=2 ,
           NETID=BEALAN ,
           CPNAME=SUN4 ,
           MAXPATH=3 ,
           DWACT=YES ,
           CONNTYPE=APPN ,
           CPCP=YES ,
           DYNLU=YES
* -----
* SNA SAP & SUN4 MAC ADDRESS BIT REVERSED FOR TRFMT
* -----
PATHSL4   PATH DIALNO=0008100002E1E2B4 ,
           GRPNM=G1ETH2
LUSUN4A   LU   LOCADDR=0
LUSUN4B   LU   LOCADDR=0
LUSUN4C   LU   LOCADDR=0

```

VTAM Application Major Nodes for CICS Regions

These examples represent the partner LU definitions to be accessed from the local environment. The APPL names must match those specified in the partner LU definitions on the local machine.

```

BEACICS VBUILD TYPE=APPL                      APPLICATION MAJOR NODE
* APPL DEFINITION STATEMENTS FOR CICS
* CICS 4.10 BACKEND REGION #1 SYSID=B41A
C410XB01 APPL EAS=64 ,                        ESTIMATED CONCURRENT SESSIONS
           MODETAB=ISTINCLM ,                 MAKE SURE DEFAULT MODETAB
           PARSESS=YES ,
           AUTH=(ACQ,BLOCK,PASS) CICS CAN ACQUIRE & PASS TMLS
                                   CICS CAN REQUEST BLOCKED INPUT

C410XB02 APPL EAS=64 ,                        ESTIMATED CONCURRENT SESSIONS
           MODETAB=ISTINCLM ,                 MAKE SURE DEFAULT MODETAB
           PARSESS=YES ,
           AUTH=(ACQ,BLOCK,PASS) CICS CAN ACQUIRE & PASS TMLS
                                   CICS CAN REQUEST BLOCKED INPUT

C410XB03 APPL EAS=64 ,                        ESTIMATED CONCURRENT SESSIONS
           MODETAB=ISTINCLM ,                 MAKE SURE DEFAULT MODETAB
           PARSESS=YES ,
           AUTH=(ACQ,BLOCK,PASS) CICS CAN ACQUIRE & PASS TMLS

```

CICS CAN REQUEST BLOCKED INPUT

```
* #####
* END OF BEACICS APPL DEF
* #####
```

CICS Resource Definition Entries (RDO)

CICS connection and session definitions map the VTAM path definitions for the CICS application. Each connection represents one local LU definition in the local SNA configuration, therefore, the names must match.

CICS session definitions associate a VTAM mode with the LU specified in the connection. The mode names and session count characteristics must match those specified in the mode definitions for the local SNA configuration. Note that these definitions set AUTOCONNECT to “YES,” allowing automatic session acquisition for a CICS client application.

```
LIST GROUP(BEAHP10) OBJECTS
GROUP NAME: BEAHP10
-----
CONNECTIONS:          FHPA      FHPB      FHPC
SESSION              FHPA      FHPB      FHPC

CONNECTION(FHPA)          GROUP(BEAHP10)
DESCRIPTION(1ST HP SNAP2+ CONNECTION)
CONNECTION-IDENTIFIERS
  NETNAME(LUHP10A)          INDSYS( )
REMOTE-ATTRIBUTES
  REMOTESYSTEM( )  REMOTENAME( )  REMOTESYSNET( )
CONNECTION-PROPERTIES
  ACCESSMETHOD(VTAM)          PROTOCOL(APPC)  CONNTYPE( )
  SINGLEESS(NO)              DATASTREAM(USER)  RECORDFORMAT(U)
  QUEUELIMIT(NO)             MAXQTIME(NO)
OPERATIONAL-PROPERTIES
  AUTOCONNECT(NO)            INSERVICE(YES)
SECURITY
  SECURITYNAME( )            ATTACHSEC(LOCAL)  BINDSECURITY(NO)
  USEDFLTUSER(NO)
RECOVERY
  PSRECOVERY(SYSDEFAULT)

CONNECTION(FHPB)          GROUP(BEAHP10)
DESCRIPTION(2ND HP SNA+ 2 CONNECTION)
CONNECTION-IDENTIFIERS
  NETNAME(LUHP10B)          INDSYS( )
REMOTE-ATTRIBUTES
  REMOTESYSTEM( )            REMOTENAME( )  REMOTESYSNET( )
```

```

CONNECTION-PROPERTIES
  ACCESSMETHOD(VTAM)          PROTOCOL(APPC)      CONNNTYPE( )
  SINGLESESS(NO)              DATASTREAM(USER)  RECORDFORMAT(U)
  QUEUELIMIT(NO)              MAXQTIME(NO)
OPERATIONAL-PROPERTIES
  AUTOCONNECT(YES)            INSERVICE(YES)
SECURITY
  SECURITYNAME( )              ATTACHSEC(LOCAL)  BINDSECURITY(NO)
  USEDFLTUSER(NO)
RECOVERY
  PSRECOVERY(SYSDEFAULT)

```

```

CONNECTION(FHPC)          GROUP(BEAHP10)
DESCRIPTION(3RD HP SNA+ 2 CONNECTION)
CONNECTION-IDENTIFIERS
  NETNAME(LUHP10C)            INDSYS( )
REMOTE-ATTRIBUTES
  REMOTESYSTEM( )             REMOTENAME( )      REMOTESYSNET( )
CONNECTION-PROPERTIES
  ACCESSMETHOD(VTAM)          PROTOCOL(APPC)      CONNNTYPE( )
  SINGLESESS(NO)              DATASTREAM(USER)  RECORDFORMAT(U)
  QUEUELIMIT(NO)              MAXQTIME(NO)
OPERATIONAL-PROPERTIES
  AUTOCONNECT(NO)             INSERVICE(YES)
SECURITY
  SECURITYNAME( )              ATTACHSEC(LOCAL)  BINDSECURITY(NO)
  USEDFLTUSER(NO)
RECOVERY
  PSRECOVERY(SYSDEFAULT)

```

```

SESSIONS(FHPA)          GROUP(BEAHP10)
DESCRIPTION(1ST HP SNAP2+ SESSION)
SESSION-IDENTIFIERS
  CONNECTION(FHPA)            SESSNAME( )        NETNAMEQ( )
  MODENAME(SMSNA100)
SESSION-PROPERTIES
  PROTOCOL(APPC)              MAXIMUM(32,16)      RECEIVEPFX( )
  RECEIVECOUNT( )            SENDPFX( )           SENDCOUNT( )
  SENDSIZE(4096)              RECEIVESIZE(4096)  SESSPRIORITY(0)
PRESET-SECURITY
  USERID( )
OPERATIONAL-PROPERTIES
  AUTOCONNECT(NO)              BUILDCHAIN(YES)     USERAREALEN(0)
  IOAREALEN(0,0)              RELREQ(NO)           DISCREQ(NO)
  NEPCCLASS(0)
RECOVERY
  RECOPTION(SYSDEFAULT)

```

```

SESSIONS(FHPB)          GROUP(BEAHP10)

```

DESCRIPTION(2ND HP SNAP2+ SESSION)		
SESSION-IDENTIFIERS		
CONNECTION(FHPB)	SESSNAME()	NETNAMEQ()
MODENAME(SMSNA100)		
SESSION-PROPERTIES		
PROTOCOL(APPC)	MAXIMUM(32,16)	RECEIVEPFX()
RECEIVECOUNT()	SENDPFX()	SENDCOUNT()
SENDSIZE(4096)	RECEIVESIZE(4096)	SESSPRIORITY(0)
PRESET-SECURITY		
USERID()		
OPERATIONAL-PROPERTIES		
AUTOCONNECT(YES)	BUILDCHAIN(YES)	USERAREALEN(0)
IOAREALEN(0,0)	RELREQ(NO)	DISCREQ(NO)
NEPCLASS(0)		
RECOVERY		
RECOVOPTION(SYSDEFAULT)		

SESSIONS(FHPC)	GROUP(BEAHP10)	DESCRIPTION(3RD HPSNAP2+ SESSION)
SESSION-IDENTIFIERS		
CONNECTION(FHPC)	SESSNAME()	NETNAMEQ()
MODENAME(SMSNA100)		
SESSION-PROPERTIES		
PROTOCOL(APPC)	MAXIMUM(10,5)	RECEIVEPFX()
RECEIVECOUNT()	SENDPFX()	SENDCOUNT()
SENDSIZE(4096)	RECEIVESIZE(4096)	SESSPRIORITY(0)
PRESET-SECURITY		
USERID()		
OPERATIONAL-PROPERTIES		
AUTOCONNECT(YES)	BUILDCHAIN(YES)	USERAREALEN(0)
IOAREALEN(0,0)	RELREQ(NO)	DISCREQ(NO)
NEPCLASS(0)		
RECOVERY		
RECOVOPTION(SYSDEFAULT)		

F Code Page Translation Tables

This section demonstrates the Code Page Translation Tables provided with BEA eLink for Mainframe SNA software. The files actually containing these tables are located in the following sub-directory on your product CDROM:

`$TUXDIR/udataobj/codepage`

Modifying a Code Page Translation Table

The tables provide conversions between the ASCII Latin-1 character set and representative national language EBCDIC character sets. In most cases, you do not have to modify them. Simply choose the appropriate translation table for a selected language and enter its file name in the CODEPAGE specification, as explained in “Code Page Translation Tables.”

However, if you must modify a translation table to suit your purpose, be aware of the following:

- ◆ It is assumed you have character mapping information; that is, you know which code represents a given character. This information is available from a number of sources and is not provided in this documentation. A good source is the *IBM National Language Support Reference Manual*.
- ◆ If you modify a character code in an outbound table, you must also modify its inbound counterpart.
- ◆ It is not recommended that you build tables from scratch.

- ◆ The tables have a common format that contains comment lines and required lines. The format must be maintained to ensure proper table operation. Comment lines begin with the # character. ***Do not alter*** the following required lines:
 - ◆ `version (100)` specifies the format of the rest of the file.
 - ◆ `table (256)` specifies the size of the table and the min/max number of bytes composing each character code.

To modify a table, perform the following steps:

1. With the text editor of your choice, open the file you want to modify, for example:

```
edit $TUXDIR/udataobj/codepage/00819x00273
```

The text editor opens the file, in this example the translation tables for Germany (00819x00273).
2. Using the editor functions, modify the character code in the outbound table.
3. Using the editor functions, modify the counterpart character code in the inbound table.
4. Repeat Steps 2 and 3 until you have completed the modifications.
5. Using the editor functions, save the file. Be sure to give it a name other than the original. ***Do not save modifications to any of the original files*** provided with your product CDROM.
6. Exit the editor.
7. To use the file you modified for code page translations, make sure you specify its name using the `CODEPAGE` option in the `DM_REMOTE_DOMAINS` section of the gateway `DMCONFIG` file.

Default TUXEDO

```
#=====
# tuxedo
#Default Tuxedo ASCII/EBCDIC character translation tables.
#
# Local:      "TUXEDO-ASCII"
# Remote:     "TUXEDO-EBCDIC"
# Built:      1999-04-13 22:12:00 UT
#
# @(#) $Id: tuxedo,v 1.1 1999/04/16 20:08:09 david Exp $
#-----

# Header
version 100;

# Outbound (local -> remote) table
table 256 1 1;
  00 01 02 03 37 2D 2E 2F 16 05 25 0B 0C 0D 0E 0F # 00-0F
  10 11 12 13 3C 3D 32 26 18 19 3F 27 1C 1D 1E 1F # 10-1F
  40 5A 7F 7B 5B 6C 50 7D 4D 5D 5C 4E 6B 60 4B 61 # 20-2F
  F0 F1 F2 F3 F4 F5 F6 F7 F8 F9 7A 5E 4C 7E 6E 6F # 30-3F
  7C C1 C2 C3 C4 C5 C6 C7 C8 C9 D1 D2 D3 D4 D5 D6 # 40-4F
  D7 D8 D9 E2 E3 E4 E5 E6 E7 E8 E9 AD E0 BD 5F 6D # 50-5F
  79 81 82 83 84 85 86 87 88 89 91 92 93 94 95 96 # 60-6F
  97 98 99 A2 A3 A4 A5 A6 A7 A8 A9 C0 6A D0 A1 07 # 70-7F
  20 21 22 23 24 15 06 17 28 29 2A 2B 2C 09 0A 1B # 80-8F
  30 31 1A 33 34 35 36 08 38 39 3A 3B 04 14 3E E1 # 90-9F
  41 42 43 44 45 46 47 48 49 51 52 53 54 55 56 57 # A0-AF
  58 59 62 63 64 65 66 67 68 69 70 71 72 73 74 75 # B0-BF
  76 77 78 80 8A 8B 8C 8D 8E 8F 90 9A 9B 9C 9D 9E # C0-CF
  9F A0 AA AB AC 4A AE AF B0 B1 B2 B3 B4 B5 B6 B7 # D0-DF
  B8 B9 BA BB BC 4F BE BF CA CB CC CD CE CF DA DB # E0-EF
  DC DD DE DF EA EB EC ED EE EF FA FB FC FD FE FF # F0-FF
```

```
# Inbound (remote -> local) table
table 256 1 1;
00 01 02 03 9C 09 86 7F 97 8D 8E 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 9D 85 08 87 18 19 92 8F 1C 1D 1E 1F # 10-1F
80 81 82 83 84 0A 17 1B 88 89 8A 8B 8C 05 06 07 # 20-2F
90 91 16 93 94 95 96 04 98 99 9A 9B 14 15 9E 1A # 30-3F
20 A0 A1 A2 A3 A4 A5 A6 A7 A8 D5 2E 3C 28 2B E5 # 40-4F
26 A9 AA AB AC AD AE AF B0 B1 21 24 2A 29 3B 5E # 50-5F
2D 2F B2 B3 B4 B5 B6 B7 B8 B9 7C 2C 25 5F 3E 3F # 60-6F
BA BB BC BD BE BF C0 C1 C2 60 3A 23 40 27 3D 22 # 70-7F
C3 61 62 63 64 65 66 67 68 69 C4 C5 C6 C7 C8 C9 # 80-8F
CA 6A 6B 6C 6D 6E 6F 70 71 72 CB CC CD CE CF D0 # 90-9F
D1 7E 73 74 75 76 77 78 79 7A D2 D3 D4 5B D6 D7 # A0-AF
D8 D9 DA DB DC DD DE DF E0 E1 E2 E3 E4 5D E6 E7 # B0-BF
7B 41 42 43 44 45 46 47 48 49 E8 E9 EA EB EC ED # C0-CF
7D 4A 4B 4C 4D 4E 4F 50 51 52 EE EF F0 F1 F2 F3 # D0-DF
5C 9F 53 54 55 56 57 58 59 5A F4 F5 F6 F7 F8 F9 # E0-EF
30 31 32 33 34 35 36 37 38 39 FA FB FC FD FE FF # F0-FF

# End
```

United States (00819x00037)

```
#=====
# 00819x00037
#Character code page mapping tables for US (USA).
#
# Local:      "IBM-CP00819", ISO-8859-1 Latin-1
# Remote:     "IBM-CP00037", EBCDIC Latin-1, US
# Built:      1999-04-16 19:50:00 UT
#
# @(#) $Id: 00819x00037,v 1.3.2.1 1999/04/29 13:03:56 cmadm Exp $
#-----

# Header
version 100;

# Outbound (local -> remote) table
table 256 1 1;
  00 01 02 03 37 2D 2E 2F 16 05 15 0B 0C 0D 0E 0F # 00-0F
  10 11 12 13 3C 3D 32 26 18 19 3F 27 1C 1D 1E 1F # 10-1F
  40 5A 7F 7B 5B 6C 50 7D 4D 5D 5C 4E 6B 60 4B 61 # 20-2F
  F0 F1 F2 F3 F4 F5 F6 F7 F8 F9 7A 5E 4C 7E 6E 6F # 30-3F
  7C C1 C2 C3 C4 C5 C6 C7 C8 C9 D1 D2 D3 D4 D5 D6 # 40-4F
  D7 D8 D9 E2 E3 E4 E5 E6 E7 E8 E9 BA E0 BB B0 6D # 50-5F
  79 81 82 83 84 85 86 87 88 89 91 92 93 94 95 96 # 60-6F
  97 98 99 A2 A3 A4 A5 A6 A7 A8 A9 C0 4F D0 A1 07 # 70-7F
  04 06 08 09 0A 14 17 1A 1B 20 21 22 23 24 25 28 # 80-8F
  29 2A 2B 2C 30 31 33 34 35 36 38 39 3A 3B 3E FF # 90-9F
  41 AA 4A B1 9F B2 6A B5 BD B4 9A 8A 5F CA AF BC # A0-AF
  90 8F EA FA BE A0 B6 B3 9D DA 9B 8B B7 B8 B9 AB # B0-BF
  64 65 62 66 63 67 9E 68 74 71 72 73 78 75 76 77 # C0-CF
  AC 69 ED EE EB EF EC BF 80 FD FE FB FC AD AE 59 # D0-DF
  44 45 42 46 43 47 9C 48 54 51 52 53 58 55 56 57 # E0-EF
  8C 49 CD CE CB CF CC E1 70 DD DE DB DC 8D 8E DF # F0-FF
```

```
# Inbound (remote -> local) table
table 256 1 1;
00 01 02 03 80 09 81 7F 82 83 84 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 85 0A 08 86 18 19 87 88 1C 1D 1E 1F # 10-1F
89 8A 8B 8C 8D 8E 17 1B 8F 90 91 92 93 05 06 07 # 20-2F
94 95 16 96 97 98 99 04 9A 9B 9C 9D 14 15 9E 1A # 30-3F
20 A0 E2 E4 E0 E1 E3 E5 E7 F1 A2 2E 3C 28 2B 7C # 40-4F
26 E9 EA EB E8 ED EE EF EC DF 21 24 2A 29 3B AC # 50-5F
2D 2F C2 C4 C0 C1 C3 C5 C7 D1 A6 2C 25 5F 3E 3F # 60-6F
F8 C9 CA CB C8 CD CE CF CC 60 3A 23 40 27 3D 22 # 70-7F
D8 61 62 63 64 65 66 67 68 69 AB BB F0 FD FE B1 # 80-8F
B0 6A 6B 6C 6D 6E 6F 70 71 72 AA BA E6 B8 C6 A4 # 90-9F
B5 7E 73 74 75 76 77 78 79 7A A1 BF D0 DD DE AE # A0-AF
5E A3 A5 B7 A9 A7 B6 BC BD BE 5B 5D AF A8 B4 D7 # B0-BF
7B 41 42 43 44 45 46 47 48 49 AD F4 F6 F2 F3 F5 # C0-CF
7D 4A 4B 4C 4D 4E 4F 50 51 52 B9 FB FC F9 FA FF # D0-DF
5C F7 53 54 55 56 57 58 59 5A B2 D4 D6 D2 D3 D5 # E0-EF
30 31 32 33 34 35 36 37 38 39 B3 DB DC D9 DA 9F # F0-FF

# End
```

Germany (00819x00273)

```
#=====
# 00819x00273
#Character code page mapping tables for Germany (Deutschland).
#
# Local:      "IBM-CP00819", ISO-8859-1 Latin-1
# Remote:     "IBM-CP00273", EBCDIC Latin-1, Germany
# Built:      1999-04-16 21:00:00 UT
#
# @(#) $Id: 00819x00273,v 1.4.2.1 1999/04/29 13:04:18 cmadm Exp $
#-----

# Header
version 100;

# Outbound (local -> remote) table
table 256 1 1;
  00 01 02 03 37 2D 2E 2F 16 05 15 0B 0C 0D 0E 0F # 00-0F
  10 11 12 13 3C 3D 32 26 18 19 3F 27 1C 1D 1E 1F # 10-1F
  40 4F 7F 7B 5B 6C 50 7D 4D 5D 5C 4E 6B 60 4B 61 # 20-2F
  F0 F1 F2 F3 F4 F5 F6 F7 F8 F9 7A 5E 4C 7E 6E 6F # 30-3F
  B5 C1 C2 C3 C4 C5 C6 C7 C8 C9 D1 D2 D3 D4 D5 D6 # 40-4F
  D7 D8 D9 E2 E3 E4 E5 E6 E7 E8 E9 63 EC FC 5F 6D # 50-5F
  79 81 82 83 84 85 86 87 88 89 91 92 93 94 95 96 # 60-6F
  97 98 99 A2 A3 A4 A5 A6 A7 A8 A9 43 BB DC 59 07 # 70-7F
  04 06 08 09 0A 14 17 1A 1B 20 21 22 23 24 25 28 # 80-8F
  29 2A 2B 2C 30 31 33 34 35 36 38 39 3A 3B 3E FF # 90-9F
  41 AA B0 B1 9F B2 CC 7C BD B4 9A 8A BA CA AF BC # A0-AF
  90 8F EA FA BE A0 B6 B3 9D DA 9B 8B B7 B8 B9 AB # B0-BF
  64 65 62 66 4A 67 9E 68 74 71 72 73 78 75 76 77 # C0-CF
  AC 69 ED EE EB EF E0 BF 80 FD FE FB 5A AD AE A1 # D0-DF
  44 45 42 46 C0 47 9C 48 54 51 52 53 58 55 56 57 # E0-EF
  8C 49 CD CE CB CF 6A E1 70 DD DE DB D0 8D 8E DF # F0-FF
```

```
# Inbound (remote -> local) table
table 256 1 1;
00 01 02 03 80 09 81 7F 82 83 84 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 85 0A 08 86 18 19 87 88 1C 1D 1E 1F # 10-1F
89 8A 8B 8C 8D 8E 17 1B 8F 90 91 92 93 05 06 07 # 20-2F
94 95 16 96 97 98 99 04 9A 9B 9C 9D 14 15 9E 1A # 30-3F
20 A0 E2 7B E0 E1 E3 E5 E7 F1 C4 2E 3C 28 2B 21 # 40-4F
26 E9 EA EB E8 ED EE EF EC 7E DC 24 2A 29 3B 5E # 50-5F
2D 2F C2 5B C0 C1 C3 C5 C7 D1 F6 2C 25 5F 3E 3F # 60-6F
F8 C9 CA CB C8 CD CE CF CC 60 3A 23 A7 27 3D 22 # 70-7F
D8 61 62 63 64 65 66 67 68 69 AB BB F0 FD FE B1 # 80-8F
B0 6A 6B 6C 6D 6E 6F 70 71 72 AA BA E6 B8 C6 A4 # 90-9F
B5 DF 73 74 75 76 77 78 79 7A A1 BF D0 DD DE AE # A0-AF
A2 A3 A5 B7 A9 40 B6 BC BD BE AC 7C AF A8 B4 D7 # B0-BF
E4 41 42 43 44 45 46 47 48 49 AD F4 A6 F2 F3 F5 # C0-CF
FC 4A 4B 4C 4D 4E 4F 50 51 52 B9 FB 7D F9 FA FF # D0-DF
D6 F7 53 54 55 56 57 58 59 5A B2 D4 5C D2 D3 D5 # E0-EF
30 31 32 33 34 35 36 37 38 39 B3 DB 5D D9 DA 9F # F0-FF

# End
```

Finland/Sweden (00819x00278)

```
#=====
# 00819x00278
#Character code page mapping tables for Finland/Sweden.
#
# Local:      "IBM-CP00819", ISO-8859-1 Latin-1
# Remote:     "IBM-CP00278", EBCDIC Latin-1, Finland/Sweden
# Built:      1999-04-16 19:50:00 UT
#
# @(#) $Id: 00819x00278,v 1.4.2.1 1999/04/29 13:04:01 cmadm Exp $
#-----

# Header
version 100;

# Outbound (local -> remote) table
table 256 1 1;
00 01 02 03 37 2D 2E 2F 16 05 15 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 3C 3D 32 26 18 19 3F 27 1C 1D 1E 1F # 10-1F
40 4F 7F 63 67 6C 50 7D 4D 5D 5C 4E 6B 60 4B 61 # 20-2F
F0 F1 F2 F3 F4 F5 F6 F7 F8 F9 7A 5E 4C 7E 6E 6F # 30-3F
EC C1 C2 C3 C4 C5 C6 C7 C8 C9 D1 D2 D3 D4 D5 D6 # 40-4F
D7 D8 D9 E2 E3 E4 E5 E6 E7 E8 E9 B5 71 9F 5F 6D # 50-5F
51 81 82 83 84 85 86 87 88 89 91 92 93 94 95 96 # 60-6F
97 98 99 A2 A3 A4 A5 A6 A7 A8 A9 43 BB 47 DC 07 # 70-7F
04 06 08 09 0A 14 17 1A 1B 20 21 22 23 24 25 28 # 80-8F
29 2A 2B 2C 30 31 33 34 35 36 38 39 3A 3B 3E FF # 90-9F
41 AA B0 B1 5A B2 CC 4A BD B4 9A 8A BA CA AF BC # A0-AF
90 8F EA FA BE A0 B6 B3 9D DA 9B 8B B7 B8 B9 AB # B0-BF
64 65 62 66 7B 5B 9E 68 74 E0 72 73 78 75 76 77 # C0-CF
AC 69 ED EE EB EF 7C BF 80 FD FE FB FC AD AE 59 # D0-DF
44 45 42 46 C0 D0 9C 48 54 79 52 53 58 55 56 57 # E0-EF
8C 49 CD CE CB CF 6A E1 70 DD DE DB A1 8D 8E DF # F0-FF
```

F

```
# Inbound (remote -> local) table
table 256 1 1;
00 01 02 03 80 09 81 7F 82 83 84 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 85 0A 08 86 18 19 87 88 1C 1D 1E 1F # 10-1F
89 8A 8B 8C 8D 8E 17 1B 8F 90 91 92 93 05 06 07 # 20-2F
94 95 16 96 97 98 99 04 9A 9B 9C 9D 14 15 9E 1A # 30-3F
20 A0 E2 7B E0 E1 E3 7D E7 F1 A7 2E 3C 28 2B 21 # 40-4F
26 60 EA EB E8 ED EE EF EC DF A4 C5 2A 29 3B 5E # 50-5F
2D 2F C2 23 C0 C1 C3 24 C7 D1 F6 2C 25 5F 3E 3F # 60-6F
F8 5C CA CB C8 CD CE CF CC E9 3A C4 D6 27 3D 22 # 70-7F
D8 61 62 63 64 65 66 67 68 69 AB BB F0 FD FE B1 # 80-8F
B0 6A 6B 6C 6D 6E 6F 70 71 72 AA BA E6 B8 C6 5D # 90-9F
B5 FC 73 74 75 76 77 78 79 7A A1 BF D0 DD DE AE # A0-AF
A2 A3 A5 B7 A9 5B B6 BC BD BE AC 7C AF A8 B4 D7 # B0-BF
E4 41 42 43 44 45 46 47 48 49 AD F4 A6 F2 F3 F5 # C0-CF
E5 4A 4B 4C 4D 4E 4F 50 51 52 B9 FB 7E F9 FA FF # D0-DF
C9 F7 53 54 55 56 57 58 59 5A B2 D4 40 D2 D3 D5 # E0-EF
30 31 32 33 34 35 36 37 38 39 B3 DB DC D9 DA 9F # F0-FF

# End
```

Spain (00819x00284)

```
#=====
# 00819x00284
#Character code page mapping tables for Spain (España).
#
# Local:      "IBM-CP00819", ISO-8859-1 Latin-1
# Remote:     "IBM-CP00284", EBCDIC Latin-1, Spain
# Built:      1999-04-16 19:50:00 UT
#
# @(#) $Id: 00819x00284,v 1.4.2.1 1999/04/29 13:04:22 cmadm Exp $
#-----

# Header
version 100;

# Outbound (local -> remote) table
table 256 1 1;
00 01 02 03 37 2D 2E 2F 16 05 15 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 3C 3D 32 26 18 19 3F 27 1C 1D 1E 1F # 10-1F
40 BB 7F 69 5B 6C 50 7D 4D 5D 5C 4E 6B 60 4B 61 # 20-2F
F0 F1 F2 F3 F4 F5 F6 F7 F8 F9 7A 5E 4C 7E 6E 6F # 30-3F
7C C1 C2 C3 C4 C5 C6 C7 C8 C9 D1 D2 D3 D4 D5 D6 # 40-4F
D7 D8 D9 E2 E3 E4 E5 E6 E7 E8 E9 4A E0 5A BA 6D # 50-5F
79 81 82 83 84 85 86 87 88 89 91 92 93 94 95 96 # 60-6F
97 98 99 A2 A3 A4 A5 A6 A7 A8 A9 C0 4F D0 BD 07 # 70-7F
04 06 08 09 0A 14 17 1A 1B 20 21 22 23 24 25 28 # 80-8F
29 2A 2B 2C 30 31 33 34 35 36 38 39 3A 3B 3E FF # 90-9F
41 AA B0 B1 9F B2 49 B5 A1 B4 9A 8A 5F CA AF BC # A0-AF
90 8F EA FA BE A0 B6 B3 9D DA 9B 8B B7 B8 B9 AB # B0-BF
64 65 62 66 63 67 9E 68 74 71 72 73 78 75 76 77 # C0-CF
AC 7B ED EE EB EF EC BF 80 FD FE FB FC AD AE 59 # D0-DF
44 45 42 46 43 47 9C 48 54 51 52 53 58 55 56 57 # E0-EF
8C 6A CD CE CB CF CC E1 70 DD DE DB DC 8D 8E DF # F0-FF
```

F

```
# Inbound (remote -> local) table
table 256 1 1;
00 01 02 03 80 09 81 7F 82 83 84 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 85 0A 08 86 18 19 87 88 1C 1D 1E 1F # 10-1F
89 8A 8B 8C 8D 8E 17 1B 8F 90 91 92 93 05 06 07 # 20-2F
94 95 16 96 97 98 99 04 9A 9B 9C 9D 14 15 9E 1A # 30-3F
20 A0 E2 E4 E0 E1 E3 E5 E7 A6 5B 2E 3C 28 2B 7C # 40-4F
26 E9 EA EB E8 ED EE EF EC DF 5D 24 2A 29 3B AC # 50-5F
2D 2F C2 C4 C0 C1 C3 C5 C7 23 F1 2C 25 5F 3E 3F # 60-6F
F8 C9 CA CB C8 CD CE CF CC 60 3A D1 40 27 3D 22 # 70-7F
D8 61 62 63 64 65 66 67 68 69 AB BB F0 FD FE B1 # 80-8F
B0 6A 6B 6C 6D 6E 6F 70 71 72 AA BA E6 B8 C6 A4 # 90-9F
B5 A8 73 74 75 76 77 78 79 7A A1 BF D0 DD DE AE # A0-AF
A2 A3 A5 B7 A9 A7 B6 BC BD BE 5E 21 AF 7E B4 D7 # B0-BF
7B 41 42 43 44 45 46 47 48 49 AD F4 F6 F2 F3 F5 # C0-CF
7D 4A 4B 4C 4D 4E 4F 50 51 52 B9 FB FC F9 FA FF # D0-DF
5C F7 53 54 55 56 57 58 59 5A B2 D4 D6 D2 D3 D5 # E0-EF
30 31 32 33 34 35 36 37 38 39 B3 DB DC D9 DA 9F # F0-FF

# End
```

Great Britain (00819x00285)

```
#=====
# 00819x00285
#Character code page mapping tables for Great Britain (UK).
#
# Local:      "IBM-CP00819", ISO-8859-1 Latin-1
# Remote:     "IBM-CP00285", EBCDIC Latin-1, UK
# Built:      1999-04-16 19:50:00 UT
#
# @(#) $Id: 00819x00285,v 1.5.2.1 1999/04/29 13:04:04 cmadm Exp $
#-----

# Header
version 100;

# Outbound (local -> remote) table
table 256 1 1;
00 01 02 03 37 2D 2E 2F 16 05 15 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 3C 3D 32 26 18 19 3F 27 1C 1D 1E 1F # 10-1F
40 5A 7F 7B 4A 6C 50 7D 4D 5D 5C 4E 6B 60 4B 61 # 20-2F
F0 F1 F2 F3 F4 F5 F6 F7 F8 F9 7A 5E 4C 7E 6E 6F # 30-3F
7C C1 C2 C3 C4 C5 C6 C7 C8 C9 D1 D2 D3 D4 D5 D6 # 40-4F
D7 D8 D9 E2 E3 E4 E5 E6 E7 E8 E9 B1 E0 BB BA 6D # 50-5F
79 81 82 83 84 85 86 87 88 89 91 92 93 94 95 96 # 60-6F
97 98 99 A2 A3 A4 A5 A6 A7 A8 A9 C0 4F D0 BC 07 # 70-7F
04 06 08 09 0A 14 17 1A 1B 20 21 22 23 24 25 28 # 80-8F
29 2A 2B 2C 30 31 33 34 35 36 38 39 3A 3B 3E FF # 90-9F
41 AA B0 5B 9F B2 6A B5 BD B4 9A 8A 5F CA AF A1 # A0-AF
90 8F EA FA BE A0 B6 B3 9D DA 9B 8B B7 B8 B9 AB # B0-BF
64 65 62 66 63 67 9E 68 74 71 72 73 78 75 76 77 # C0-CF
AC 69 ED EE EB EF EC BF 80 FD FE FB FC AD AE 59 # D0-DF
44 45 42 46 43 47 9C 48 54 51 52 53 58 55 56 57 # E0-EF
8C 49 CD CE CB CF CC E1 70 DD DE DB DC 8D 8E DF # F0-FF
```

F

```
# Inbound (remote -> local) table
table 256 1 1;
00 01 02 03 80 09 81 7F 82 83 84 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 85 0A 08 86 18 19 87 88 1C 1D 1E 1F # 10-1F
89 8A 8B 8C 8D 8E 17 1B 8F 90 91 92 93 05 06 07 # 20-2F
94 95 16 96 97 98 99 04 9A 9B 9C 9D 14 15 9E 1A # 30-3F
20 A0 E2 E4 E0 E1 E3 E5 E7 F1 24 2E 3C 28 2B 7C # 40-4F
26 E9 EA EB E8 ED EE EF EC DF 21 A3 2A 29 3B AC # 50-5F
2D 2F C2 C4 C0 C1 C3 C5 C7 D1 A6 2C 25 5F 3E 3F # 60-6F
F8 C9 CA CB C8 CD CE CF CC 60 3A 23 40 27 3D 22 # 70-7F
D8 61 62 63 64 65 66 67 68 69 AB BB F0 FD FE B1 # 80-8F
B0 6A 6B 6C 6D 6E 6F 70 71 72 AA BA E6 B8 C6 A4 # 90-9F
B5 AF 73 74 75 76 77 78 79 7A A1 BF D0 DD DE AE # A0-AF
A2 5B A5 B7 A9 A7 B6 BC BD BE 5E 5D 7E A8 B4 D7 # B0-BF
7B 41 42 43 44 45 46 47 48 49 AD F4 F6 F2 F3 F5 # C0-CF
7D 4A 4B 4C 4D 4E 4F 50 51 52 B9 FB FC F9 FA FF # D0-DF
5C F7 53 54 55 56 57 58 59 5A B2 D4 D6 D2 D3 D5 # E0-EF
30 31 32 33 34 35 36 37 38 39 B3 DB DC D9 DA 9F # F0-FF

# End
```

France (00819x00297)

```
#=====
# 00819x00297
#Character code page mapping tables for France.
#
# Local:      "IBM-CP00819", ISO-8859-1 Latin-1
# Remote:     "IBM-CP00297", EBCDIC Latin-1, France
# Built:      1999-04-16 23:30:00 UT
#
# @(#) $Id: 00819x00297,v 1.4.2.1 1999/04/29 13:04:27 cmadm Exp $
#-----

# Header
version 100;

# Outbound (local -> remote) table
table 256 1 1;
00 01 02 03 37 2D 2E 2F 16 05 15 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 3C 3D 32 26 18 19 3F 27 1C 1D 1E 1F # 10-1F
40 4F 7F B1 5B 6C 50 7D 4D 5D 5C 4E 6B 60 4B 61 # 20-2F
F0 F1 F2 F3 F4 F5 F6 F7 F8 F9 7A 5E 4C 7E 6E 6F # 30-3F
44 C1 C2 C3 C4 C5 C6 C7 C8 C9 D1 D2 D3 D4 D5 D6 # 40-4F
D7 D8 D9 E2 E3 E4 E5 E6 E7 E8 E9 90 48 B5 5F 6D # 50-5F
A0 81 82 83 84 85 86 87 88 89 91 92 93 94 95 96 # 60-6F
97 98 99 A2 A3 A4 A5 A6 A7 A8 A9 51 BB 54 BD 07 # 70-7F
04 06 08 09 0A 14 17 1A 1B 20 21 22 23 24 25 28 # 80-8F
29 2A 2B 2C 30 31 33 34 35 36 38 39 3A 3B 3E FF # 90-9F
41 AA B0 7B 9F B2 DD 5A A1 B4 9A 8A BA CA AF BC # A0-AF
4A 8F EA FA BE 79 B6 B3 9D DA 9B 8B B7 B8 B9 AB # B0-BF
64 65 62 66 63 67 9E 68 74 71 72 73 78 75 76 77 # C0-CF
AC 69 ED EE EB EF EC BF 80 FD FE FB FC AD AE 59 # D0-DF
7C 45 42 46 43 47 9C E0 D0 C0 52 53 58 55 56 57 # E0-EF
8C 49 CD CE CB CF CC E1 70 6A DE DB DC 8D 8E DF # F0-FF
```

F

```
# Inbound (remote -> local) table
table 256 1 1;
00 01 02 03 80 09 81 7F 82 83 84 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 85 0A 08 86 18 19 87 88 1C 1D 1E 1F # 10-1F
89 8A 8B 8C 8D 8E 17 1B 8F 90 91 92 93 05 06 07 # 20-2F
94 95 16 96 97 98 99 04 9A 9B 9C 9D 14 15 9E 1A # 30-3F
20 A0 E2 E4 40 E1 E3 E5 5C F1 B0 2E 3C 28 2B 21 # 40-4F
26 7B EA EB 7D ED EE EF EC DF A7 24 2A 29 3B 5E # 50-5F
2D 2F C2 C4 C0 C1 C3 C5 C7 D1 F9 2C 25 5F 3E 3F # 60-6F
F8 C9 CA CB C8 CD CE CF CC B5 3A A3 E0 27 3D 22 # 70-7F
D8 61 62 63 64 65 66 67 68 69 AB BB F0 FD FE B1 # 80-8F
5B 6A 6B 6C 6D 6E 6F 70 71 72 AA BA E6 B8 C6 A4 # 90-9F
60 A8 73 74 75 76 77 78 79 7A A1 BF D0 DD DE AE # A0-AF
A2 23 A5 B7 A9 5D B6 BC BD BE AC 7C AF 7E B4 D7 # B0-BF
E9 41 42 43 44 45 46 47 48 49 AD F4 F6 F2 F3 F5 # C0-CF
E8 4A 4B 4C 4D 4E 4F 50 51 52 B9 FB FC A6 FA FF # D0-DF
E7 F7 53 54 55 56 57 58 59 5A B2 D4 D6 D2 D3 D5 # E0-EF
30 31 32 33 34 35 36 37 38 39 B3 DB DC D9 DA 9F # F0-FF

# End
```

Belgium (00819x00500)

```
#=====
# 00819x00500
#Character code page mapping tables for Belgium (Belgique).
#
# Local:      "IBM-CP00819", ISO-8859-1 Latin-1
# Remote:     "IBM-CP00500", EBCDIC Latin-1, Belgium
# Built:      1999-04-16 19:50:00 UT
#
# @(#) $Id: 00819x00500,v 1.4.2.1 1999/04/29 13:04:09 cmadm Exp $
#-----

# Header
version 100;

# Outbound (local -> remote) table
table 256 1 1;
00 01 02 03 37 2D 2E 2F 16 05 15 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 3C 3D 32 26 18 19 3F 27 1C 1D 1E 1F # 10-1F
40 4F 7F 7B 5B 6C 50 7D 4D 5D 5C 4E 6B 60 4B 61 # 20-2F
F0 F1 F2 F3 F4 F5 F6 F7 F8 F9 7A 5E 4C 7E 6E 6F # 30-3F
7C C1 C2 C3 C4 C5 C6 C7 C8 C9 D1 D2 D3 D4 D5 D6 # 40-4F
D7 D8 D9 E2 E3 E4 E5 E6 E7 E8 E9 4A E0 5A 5F 6D # 50-5F
79 81 82 83 84 85 86 87 88 89 91 92 93 94 95 96 # 60-6F
97 98 99 A2 A3 A4 A5 A6 A7 A8 A9 C0 BB D0 A1 07 # 70-7F
04 06 08 09 0A 14 17 1A 1B 20 21 22 23 24 25 28 # 80-8F
29 2A 2B 2C 30 31 33 34 35 36 38 39 3A 3B 3E FF # 90-9F
41 AA B0 B1 9F B2 6A B5 BD B4 9A 8A BA CA AF BC # A0-AF
90 8F EA FA BE A0 B6 B3 9D DA 9B 8B B7 B8 B9 AB # B0-BF
64 65 62 66 63 67 9E 68 74 71 72 73 78 75 76 77 # C0-CF
AC 69 ED EE EB EF EC BF 80 FD FE FB FC AD AE 59 # D0-DF
44 45 42 46 43 47 9C 48 54 51 52 53 58 55 56 57 # E0-EF
8C 49 CD CE CB CF CC E1 70 DD DE DB DC 8D 8E DF # F0-FF
```

F

```
# Inbound (remote -> local) table
table 256 1 1;
00 01 02 03 80 09 81 7F 82 83 84 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 85 0A 08 86 18 19 87 88 1C 1D 1E 1F # 10-1F
89 8A 8B 8C 8D 8E 17 1B 8F 90 91 92 93 05 06 07 # 20-2F
94 95 16 96 97 98 99 04 9A 9B 9C 9D 14 15 9E 1A # 30-3F
20 A0 E2 E4 E0 E1 E3 E5 E7 F1 5B 2E 3C 28 2B 21 # 40-4F
26 E9 EA EB E8 ED EE EF EC DF 5D 24 2A 29 3B 5E # 50-5F
2D 2F C2 C4 C0 C1 C3 C5 C7 D1 A6 2C 25 5F 3E 3F # 60-6F
F8 C9 CA CB C8 CD CE CF CC 60 3A 23 40 27 3D 22 # 70-7F
D8 61 62 63 64 65 66 67 68 69 AB BB F0 FD FE B1 # 80-8F
B0 6A 6B 6C 6D 6E 6F 70 71 72 AA BA E6 B8 C6 A4 # 90-9F
B5 7E 73 74 75 76 77 78 79 7A A1 BF D0 DD DE AE # A0-AF
A2 A3 A5 B7 A9 A7 B6 BC BD BE AC 7C AF A8 B4 D7 # B0-BF
7B 41 42 43 44 45 46 47 48 49 AD F4 F6 F2 F3 F5 # C0-CF
7D 4A 4B 4C 4D 4E 4F 50 51 52 B9 FB FC F9 FA FF # D0-DF
5C F7 53 54 55 56 57 58 59 5A B2 D4 D6 D2 D3 D5 # E0-EF
30 31 32 33 34 35 36 37 38 39 B3 DB DC D9 DA 9F # F0-FF

# End
```

Portugal (00819x00860)

```
#=====
# 00819x00860
#Character code page mapping tables for Portugal.
#
# Local:      "IBM-CP00819", ISO-8859-1 Latin-1
# Remote:     "IBM-CP00860", ASCII IBM-PC graphics, Portugal
# Built:      1999-04-20 00:03:00 UT
#
# Caveats
#The mapping between the two code pages is inexact, because some
#characters do not exist in both code sets.
#
# @(#) $Id: 00819x00860,v 1.4 1999/04/20 20:19:20 david Exp $
#-----

# Header
version 100;

# Outbound (local -> remote) table
table 256 1 1;
00 01 02 03 04 05 06 07 08 09 0A 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 9E B0 16 17 18 19 1A 1B 1C 1D 1E 1F # 10-1F
20 21 22 23 24 25 26 27 28 29 2A 2B 2C 2D 2E 2F # 20-2F
30 31 32 33 34 35 36 37 38 39 3A 3B 3C 3D 3E 3F # 30-3F
40 41 42 43 44 45 46 47 48 49 4A 4B 4C 4D 4E 4F # 40-4F
50 51 52 53 54 55 56 57 58 59 5A 5B 5C 5D 5E 5F # 50-5F
60 61 62 63 64 65 66 67 68 69 6A 6B 6C 6D 6E 6F # 60-6F
70 71 72 73 74 75 76 77 78 79 7A 7B 7C 7D 7E 7F # 70-7F
B1 B2 B3 B4 B5 B6 B7 B8 B9 BA BB BC BD BE BF C0 # 80-8F
C1 C2 C3 C4 C5 C6 C7 C8 C9 CA CB CC CD CE CF D0 # 90-9F
FF AD 9B 9C D1 D2 D3 15 D4 D5 A6 AE AA D6 D7 D8 # A0-AF
F8 F1 FD D9 DA E6 14 FA DB DC A7 AF AC AB DD A8 # B0-BF
91 86 8F 8E DE DF E0 80 92 90 89 E2 98 8B E3 E4 # C0-CF
E5 A5 A9 9F 8C 99 E7 E9 E8 9D 96 EA 9A EC EE E1 # D0-DF
85 A0 83 84 EF F0 F2 87 8A 82 88 F3 8D A1 F4 F5 # E0-EF
EB A4 95 A2 93 94 F7 F6 ED 97 A3 F9 81 FB FC FE # F0-FF
```

```
# Inbound (remote -> local) table
table 256 1 1;
00 01 02 03 04 05 06 07 08 09 0A 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 B6 A7 16 17 18 19 1A 1B 1C 1D 1E 1F # 10-1F
20 21 22 23 24 25 26 27 28 29 2A 2B 2C 2D 2E 2F # 20-2F
30 31 32 33 34 35 36 37 38 39 3A 3B 3C 3D 3E 3F # 30-3F
40 41 42 43 44 45 46 47 48 49 4A 4B 4C 4D 4E 4F # 40-4F
50 51 52 53 54 55 56 57 58 59 5A 5B 5C 5D 5E 5F # 50-5F
60 61 62 63 64 65 66 67 68 69 6A 6B 6C 6D 6E 6F # 60-6F
70 71 72 73 74 75 76 77 78 79 7A 7B 7C 7D 7E 7F # 70-7F
C7 FC E9 E2 E3 E0 C1 E7 EA CA E8 CD D4 EC C3 C2 # 80-8F
C9 C0 C8 F4 F5 F2 DA F9 CC D5 DC A2 A3 D9 14 D3 # 90-9F
E1 ED F3 FA F1 D1 AA BA BF D2 AC BD BC A1 AB BB # A0-AF
15 80 81 82 83 84 85 86 87 88 89 8A 8B 8C 8D 8E # B0-BF
8F 90 91 92 93 94 95 96 97 98 99 9A 9B 9C 9D 9E # C0-CF
9F A4 A5 A6 A8 A9 AD AE AF B3 B4 B8 B9 BE C4 C5 # D0-DF
C6 DF CB CE CF D0 B5 D6 D8 D7 DB F0 DD F8 DE E4 # E0-EF
E5 B1 E6 EB EE EF F7 F6 B0 FB B7 FD FE B2 FF A0 # F0-FF

# End
```

Latin-1 – (00819x01047)

```
#=====
# 00819x01047
#Character code page mapping tables.
#
# Local:      "IBM-CP00819", ISO-8859-1 Latin-1
# Remote:     "IBM-CP01047", EBCDIC Latin-1
# Built:      1999-04-22 23:40:00 UT
#
# @(#) $Id: 00819x01047,v 1.1.2.1 1999/04/29 13:04:13 cmadm Exp $
#-----

# Header
version 100;

# Outbound (local -> remote) table
table 256 1 1;
  00 01 02 03 37 2D 2E 2F 16 05 15 0B 0C 0D 0E 0F # 00-0F
  10 11 12 13 3C 3D 32 26 18 19 3F 27 1C 1D 1E 1F # 10-1F
  40 5A 7F 7B 5B 6C 50 7D 4D 5D 5C 4E 6B 60 4B 61 # 20-2F
  F0 F1 F2 F3 F4 F5 F6 F7 F8 F9 7A 5E 4C 7E 6E 6F # 30-3F
  7C C1 C2 C3 C4 C5 C6 C7 C8 C9 D1 D2 D3 D4 D5 D6 # 40-4F
  D7 D8 D9 E2 E3 E4 E5 E6 E7 E8 E9 AD E0 BD 5F 6D # 50-5F
  79 81 82 83 84 85 86 87 88 89 91 92 93 94 95 96 # 60-6F
  97 98 99 A2 A3 A4 A5 A6 A7 A8 A9 C0 4F D0 A1 07 # 70-7F
  04 06 08 09 0A 14 17 1A 1B 20 21 22 23 24 25 28 # 80-8F
  29 2A 2B 2C 30 31 33 34 35 36 38 39 3A 3B 3E FF # 90-9F
  41 AA 4A B1 9F B2 6A B5 BB B4 9A 8A B0 CA AF BC # A0-AF
  90 8F EA FA BE A0 B6 B3 9D DA 9B 8B B7 B8 B9 AB # B0-BF
  64 65 62 66 63 67 9E 68 74 71 72 73 78 75 76 77 # C0-CF
  AC 69 ED EE EB EF EC BF 80 FD FE FB FC BA AE 59 # D0-DF
  44 45 42 46 43 47 9C 48 54 51 52 53 58 55 56 57 # E0-EF
  8C 49 CD CE CB CF CC E1 70 DD DE DB DC 8D 8E DF # F0-FF
```

```
# Inbound (remote -> local) table
table 256 1 1;
00 01 02 03 80 09 81 7F 82 83 84 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 85 0A 08 86 18 19 87 88 1C 1D 1E 1F # 10-1F
89 8A 8B 8C 8D 8E 17 1B 8F 90 91 92 93 05 06 07 # 20-2F
94 95 16 96 97 98 99 04 9A 9B 9C 9D 14 15 9E 1A # 30-3F
20 A0 E2 E4 E0 E1 E3 E5 E7 F1 A2 2E 3C 28 2B 7C # 40-4F
26 E9 EA EB E8 ED EE EF EC DF 21 24 2A 29 3B 5E # 50-5F
2D 2F C2 C4 C0 C1 C3 C5 C7 D1 A6 2C 25 5F 3E 3F # 60-6F
F8 C9 CA CB C8 CD CE CF CC 60 3A 23 40 27 3D 22 # 70-7F
D8 61 62 63 64 65 66 67 68 69 AB BB F0 FD FE B1 # 80-8F
B0 6A 6B 6C 6D 6E 6F 70 71 72 AA BA E6 B8 C6 A4 # 90-9F
B5 7E 73 74 75 76 77 78 79 7A A1 BF D0 5B DE AE # A0-AF
AC A3 A5 B7 A9 A7 B6 BC BD BE DD A8 AF 5D B4 D7 # B0-BF
7B 41 42 43 44 45 46 47 48 49 AD F4 F6 F2 F3 F5 # C0-CF
7D 4A 4B 4C 4D 4E 4F 50 51 52 B9 FB FC F9 FA FF # D0-DF
5C F7 53 54 55 56 57 58 59 5A B2 D4 D6 D2 D3 D5 # E0-EF
30 31 32 33 34 35 36 37 38 39 B3 DB DC D9 DA 9F # F0-FF

# End
```

Latin-2 – (00912x00870)

```
#=====
# 00912x00870
#Character code page mapping tables for Latin-2 character sets.
#
# Local:      "IBM-CP00912", ISO-8859-2 Latin-2
# Remote:     "IBM-CP00870", EBCDIC Latin-2
# Built:      1999-04-16 19:50:00 UT
#
# @(#) $Id: 00912x00870,v 1.3.2.1 1999/04/29 13:04:32 cmadm Exp $
#-----

# Header
version 100;

# Outbound (local -> remote) table
table 256 1 1;
00 01 02 03 37 2D 2E 2F 16 05 15 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 3C 3D 32 26 18 19 3F 27 1C 1D 1E 1F # 10-1F
40 4F 7F 7B 5B 6C 50 7D 4D 5D 5C 4E 6B 60 4B 61 # 20-2F
F0 F1 F2 F3 F4 F5 F6 F7 F8 F9 7A 5E 4C 7E 6E 6F # 30-3F
7C C1 C2 C3 C4 C5 C6 C7 C8 C9 D1 D2 D3 D4 D5 D6 # 40-4F
D7 D8 D9 E2 E3 E4 E5 E6 E7 E8 E9 4A E0 5A 5F 6D # 50-5F
79 81 82 83 84 85 86 87 88 89 91 92 93 94 95 96 # 60-6F
97 98 99 A2 A3 A4 A5 A6 A7 A8 A9 C0 6A D0 A1 07 # 70-7F
04 06 08 09 0A 14 17 1A 1B 20 21 22 23 24 25 28 # 80-8F
29 2A 2B 2C 30 31 33 34 35 36 38 39 3A 3B 3E FF # 90-9F
41 B1 80 BA 9F 77 AA B5 BD BC AF FD B9 CA B8 B4 # A0-AF
90 A0 9E 9A BE 57 8A 70 9D 9C 8F DD B7 64 B6 B2 # B0-BF
ED 65 62 66 63 78 69 68 67 71 72 73 DA 75 76 FA # C0-CF
AC BB AB EE EB EF EC BF AE 74 FE FB FC AD B3 59 # D0-DF
CD 45 42 46 43 58 49 48 47 51 52 53 DF 55 56 EA # E0-EF
8C 9B 8B CE CB CF CC E1 8E 54 DE DB DC 8D 44 B0 # F0-FF
```

```
# Inbound (remote -> local) table
table 256 1 1;
00 01 02 03 80 09 81 7F 82 83 84 0B 0C 0D 0E 0F # 00-0F
10 11 12 13 85 0A 08 86 18 19 87 88 1C 1D 1E 1F # 10-1F
89 8A 8B 8C 8D 8E 17 1B 8F 90 91 92 93 05 06 07 # 20-2F
94 95 16 96 97 98 99 04 9A 9B 9C 9D 14 15 9E 1A # 30-3F
20 A0 E2 E4 FE E1 E3 E8 E7 E6 5B 2E 3C 28 2B 21 # 40-4F
26 E9 EA EB F9 ED EE B5 E5 DF 5D 24 2A 29 3B 5E # 50-5F
2D 2F C2 C4 BD C1 C3 C8 C7 C6 7C 2C 25 5F 3E 3F # 60-6F
B7 C9 CA CB D9 CD CE A5 C5 60 3A 23 40 27 3D 22 # 70-7F
A2 61 62 63 64 65 66 67 68 69 B6 F2 F0 FD F8 BA # 80-8F
B0 6A 6B 6C 6D 6E 6F 70 71 72 B3 F1 B9 B8 B2 A4 # 90-9F
B1 7E 73 74 75 76 77 78 79 7A A6 D2 D0 DD D8 AA # A0-AF
FF A1 BF DE AF A7 BE BC AE AC A3 D1 A9 A8 B4 D7 # B0-BF
7B 41 42 43 44 45 46 47 48 49 AD F4 F6 E0 F3 F5 # C0-CF
7D 4A 4B 4C 4D 4E 4F 50 51 52 CC FB FC BB FA EC # D0-DF
5C F7 53 54 55 56 57 58 59 5A EF D4 D6 C0 D3 D5 # E0-EF
30 31 32 33 34 35 36 37 38 39 CF DB DC AB DA 9F # F0-FF
# End
```

Glossary

A

Access Control Lists (ACL)

A Tuxedo security feature that controls client access to services by means of lists that are automatically checked each time a service is requested.

ACID Properties

The essential characteristic of transaction processing systems:

Atomicity: All changes that a transaction makes to a database are made permanent, or else are nullified.

Consistency: A successful transaction transforms a database from a previous valid state to a new valid state.

Isolation: Changes that a transaction makes to a database are not visible to other operations until the transaction completes its work.

Durability: Changes that a transaction makes to a database survive future system or media failures.

Application

A BEA TUXEDO System/T *application* is bounded by the environment described in a single TUXCONFIG file. In /Domain, a BEA TUXEDO System/T application can communicate with another application via a domain gateway group.

Application Domain

When used alone, the term *Domain* can mean a number of things. In order to avoid confusion, the term *application domain* is used to refer to a BEA TUXEDO application bounded by the configuration of a `tmconfig` file. This application domain can be restricted to a single platform, or shared memory (SHM) environment, or could be scaled across multiple machines in a multiple processor (MP) environment.

Application Programming Interface (API)

1) The verbs and environment that exist at the application level to support a particular system software product. 2) A set of code that enables a developer to initiate and complete client/server requests within an application. 3) A set of calling conventions that define how to invoke a service. A set of well-defined programming interfaces (entry points, calling parameters, and return values) by which one software program utilizes the services of another

Application Program-to-Program Communication (APPC)

An interface to LU6.2 services; provides a set of primitives to conduct conversations in LU6.2 sessions.

Application-Transaction Monitor Interface (ATMI)

The Application Programming Interface (API) to Tuxedo that includes transaction routines, message handling routines, service interface routines, and buffer management routines.

C

Client

A program designed to request information from a server.

CNOS

CNOS are service programs implemented as part of an LU6.2. The *CNOS* programs negotiate session limits between the two communication LU's.

Common Programming Interface for Communications (CPI-C)

An interface to LU6.2 services. It is a simpler set of primitives than the APPC interface and is intended for use in program-to-program communications.

Conversation

In this guide *conversation* has two meanings; the context determines which meaning is intended. In BEA TUXEDO System/T, conversation identifies a mode of communication between processes in which a connection is opened and stays open until brought down. Communication is achieved through sends and receives. This is distinguished from the request/response model in which communication is achieved through calls and replies. In SNA terms, a conversation uses a session as long as the conversation continues. In an SNA conversation, communication can

be either the BEA TUXEDO System/T conversation or request/response model. Each SNA conversation is assigned a CONVID (Conversation ID) at the time it is initialized by the LU. SNA conversations can be *mapped* or *basic*:

Conversation, Mapped

Conversations that allow programmers to send and receive buffers without having to worry about the sizes of underlying request units (RUs) used for communication. The LU takes the buffer and divides it, if necessary, into appropriate Logical Records with associated length fields and data type fields. This is the style supported for applications by BEA eLink for Mainframe SNA software.

Conversation, Basic

Conversations in which logical records with appropriate type and length fields must be formatted for transmission and parsed on receipt. The service transaction programs in an LU use basic conversations to communicate.

Customer Information Control System/Extended System Architecture (CICS/ESA)

An operating environment devised by IBM that provides a foundation upon which to write customer applications programs. Several facilities useful for programming are supplied by the CICS environment, including basic mapping services (BMS), transient data queues (TD), temporary storage files (TS), memory services, etc. Customer applications are built as separate transaction programs, and are invoked as transactional tasks. CICS/ESA is a trademark of International Business Machines (IBM), Inc.

D

Distributed Program Link (DPL)

Function of CICS ISC that supports LINK requests between CICS regions, and is similar to a BEA TUXEDO request/response.

Distributed Transaction Processing (DTP)

A CICS intercommunication in which processing is distributed among transactions that communicate synchronously over intersystem or inter-region links. It is roughly equivalent to BEA TUXEDO conversations.

Domain

A *domain* can be another BEA TUXEDO System/T application that is independently administered, an application that is under the control of another transaction processing system, or an application in a remote CICS/ESA region. Domains can be local or remote.

Domain Gateway

A BEA TUXEDO System/T process that provides connectivity to remote BEA TUXEDO application environments, such as OSI, MVS/APPC, CICS/MVS, and IMS operating environments. BEA eLink for Mainframe OSI TP, BEA eLink SNA, and BEA eLink TCP/IP are domain gateways.

Domain Gateway Group

A *Domain Gateway Group* is a collection of domain gateway processes that provide communication services with other domains.

E

ESA

(ESA) Enterprise Systems Architecture is the conceptual structure and functional behavior of IBM's latest range of mainframe computers. ESA/370 is the fourth step in an evolution of which the first three steps were System/360, System/370, and System/370 extended architecture (370-XA).

F

Field Manipulation Language (FML)

A set of C language functions for defining and manipulating storage structures called field buffers. Cooperating processes can send and receive data in fielded buffers.

FML Buffer

A buffer of self-describing data items accessed through the Field Manipulation Language API.

G

Graphical Administrative Interface

A Tuxedo System component that enables an authorized user to configure and control an application through a Motif-based set of screens and icons.

I

Inbound

A generic term referring to request message direction relative to the server, or response message direction relative to the client.

Information Management System (IMS)

A database manager used by CICS/ESA to allow access to data. IMS provides for the arrangement of data in an hierarchical structure and a common access approach in application programs that manipulate IMS databases.

InterSystem Communications (ISC)

Communication between separate systems by means of SNA networking facilities or by means of the application-to-application facilities. ISC links CICS systems to other systems, and may be used for communication between user applications, or to transparently execute CICS functions on a remote CICS system.

J

Job Control Language (JCL)

Control language used to describe a job and its requirements to an operating system.

L

Local Domain

A *Local Domain* is a part of an application (set or subset of services) that is available to other domains. A Local Domain is always represented by a Domain Gateway Group, and the terms are used interchangeably.

Local Service

A *Local Service* is a service of a local domain that is made available to remote domains through a Domain Gateway Group.

Logical Unit (LU)

In SNA, a port through which a user gains access to the services of a network. Also, see System Network Architecture (SNA).

LU6.2

LU6.2 is a particular SNA logical unit that identifies a specific set of services for program to program communication. Services include syncpoint, mapping of buffers into records, message confirmation, and security.

M

MODENAME

MODENAME is a configuration parameter that names a set of characteristics for a group of BEA eLink for Mainframe SNA sessions. In the CICS region, the mode is defined in VTAM and referenced in CIC and the DMCONFIG file.

mirror task

CICS/ESA task that services incoming requests that specify a *mirror transaction* (CSMI, CSM1, CSM2, CSM3, CSM5, CPMI, CVMI, or a user-defined mirror transaction identifier).

mirror transaction

CICS/ESA transaction that recreates a request that is function shipped from one system to another, issues the request on the second system, and passes the acquired data back to the first system.

Mirror Transaction Identifier Support

BEA eLink for Mainframe SNA feature which enables BEA TUXEDO clients to invoke host CICS/ESA programs and, conversely, CICS/ESA client programs to invoke BEA TUXEDO services. Based on the IBM CICS/ESA mirror transaction.

Multiple Virtual Storage (MVS)

An operating system for processing systems consisting of one or more mainframe processors.

O

Outbound

A generic term referring to request message direction relative to the client, or response message direction relative to the server.

P

Partitioned Data Set (PDS).

A CICS/ESA data set in direct access storage that is divided into partitions called members. A member can contain a program or data. Program libraries are held in partitioned data sets.

R

re-entrant

The attribute of a program or routine that allows the same copy of the program or routine to be used concurrently by two or more tasks.

Remote Domain

A *Remote Domain* is a part of an application accessed through a Domain Gateway Group. The remote domain may be another BEA TUXEDO System/T application, an application running under another TP system, or a BEA eLink for Mainframe SNA application.

Remote Service

A *Remote Service* is a service of a remote domain that is made available to the local application through a Domain Gateway Group.

Resource Definition Online (RDO)

The recommended method of defining resources to CICS/ESA. Resource definitions are created interactively by a CEDA transaction, or by the DFHCSDUP utility. Both methods store definition in the CICS/ESA system definition data set (CSD). At CICS initialization, CSD definitions are selectively installed as CICS system tables controlled by a user-supplied list of definitions. CEDA-defined resource definitions can be installed while CICS is active and used immediately.

S

Server

A computer or program that is dedicated to providing information in response to external requests.

Session

When two LU's bind with each other, that is, when they have successfully negotiated how they will communicate, they are said to be in *session*. SNA has fixed limits on the number of sessions configurable for an LU type.

Stack

Platform vendor-supplied software that provides connectivity to an SNA network.

Synchronization Level (sync level)

The level of synchronization (0, 1, or 2) established for an APPC session between intercommunicating CICS/ESA transactions. Level 0 gives no synchronization support, level 1 allows the exchange of private synchronization requests, and level 2 gives full CICS/ESA synchronization support, with backout of all updates to recoverable resources if failure occurs.

System Definition Data Set (CSD)

A VSAM KSDS cluster that contains a resource definition record for every resource defined to CICS using resource definition online (RDO).

SNA Communication Resource Manager (SNACRM)

A process that provides all of the sync-level two logic for an SNA domain gateway and directly communicates with the PU2.1 server.

SYM_DEST_NAME

A symbolic name for a combination of Partner LUNAME, MODENAME and TPNAME that uniquely identifies the destination for a conversation start-up request.

System Network Architecture (SNA)

A seven-layer networking protocol. Each layer of the protocol has a set of associated data communication services. The services of the uppermost layer are embodied in a Logical Unit (LU). Each LU type defined in SNA has its own specific set of services available to an end user for communicating. The end user may be a terminal device, or an application program. The SNA structure enables the end user to operate independently, unaffected by the specific facilities used for information exchange.

T

Transaction

- 1) A complete unit of work that transforms a database from one consistent state to another. In DTP, a transaction can include multiple units of work performed on one or more systems.
- 2) A logical construct through which applications perform work on shared resources (e.g., databases). The work done on behalf of the transaction conforms to the four ACID Properties: atomicity, consistency, isolation, and durability.

Transaction Processing (TP)

A form of immediate data processing in which user requests are entered directly to the terminal and on-line programs satisfy the requests; for example, by updating database files and displaying output messages.

Typed Buffer

A buffer for message communication involving data of a specific data type.

V

Virtual Telecommunications Access Method (VTAM)

A set of programs that control communication across a network between terminals and application programs.

